

CUPS on FreeBSD

Chess Griffin

chess@chessgriffin.com

**\$FreeBSD: head/en_US.ISO8859-1/articles/cups/article.xml 41645 2013-05-17
18:49:52Z gabor \$**

**\$FreeBSD: head/en_US.ISO8859-1/articles/cups/article.xml 41645 2013-05-17
18:49:52Z gabor \$**

FreeBSD is a registered trademark of the FreeBSD Foundation.

Many of the designations used by manufacturers and sellers to distinguish their products are claimed as trademarks. Where those designations appear in this document, and the FreeBSD Project was aware of the trademark claim, the designations have been followed by the “™” or the “®” symbol.

An article about configuring CUPS on FreeBSD.

1 An Introduction to the Common Unix Printing System (CUPS)

CUPS, the Common UNIX Printing System, provides a portable printing layer for UNIX®-based operating systems. It has been developed by Easy Software Products to promote a standard printing solution for all UNIX vendors and users.

CUPS uses the Internet Printing Protocol (IPP) as the basis for managing print jobs and queues. The Line Printer Daemon (LPD), Server Message Block (SMB), and AppSocket (aka JetDirect) protocols are also supported with reduced functionality. **CUPS** adds network printer browsing and PostScript Printer Description (PPD) based printing options to support real-world printing under UNIX. As a result, **CUPS** is ideally-suited for sharing and accessing printers in mixed environments of FreeBSD, Linux®, Mac OS® X, or Windows®.

The main site for **CUPS** is <http://www.cups.org/>.

2 Installing the CUPS Print Server

CUPS can be installed from ports or by using a precompiled binary package. To install **CUPS** from ports, issue the following command from a root terminal:

```
# cd /usr/ports/print/cups && make install clean
```

To install **CUPS** using a precompiled binary, issue the following command from a root terminal:

```
# pkg_add -r cups
```

Other optional, but recommended, ports or packages are `print/gutenprint-cups` and `print/hplip`, both of which add drivers and utilities for a variety of printers. Once installed, the **CUPS** configuration files can be found in the directory `/usr/local/etc/cups`.

3 Configuring the CUPS Print Server

After installation, a few files must be edited in order to configure the **CUPS** server. First, create or modify, as the case may be, the file `/etc/devfs.rules` and add the following information to set the proper permissions on all potential printer devices and to associate printers with the `cups` user group:

```
[system=10]
add path 'unlpt*' mode 0660 group cups
add path 'ulpt*' mode 0660 group cups
add path 'lpt*' mode 0660 group cups
add path 'usb/X.Y.Z' mode 0660 group cups
```

Note: Note that `x`, `y`, and `z` should be replaced with the target USB device listed in the `/dev/usb` directory that corresponds to the printer. To find the correct device, examine the output of `dmesg(8)`, where `ugenX.Y` lists the printer device, which is a symbolic link to a USB device in `/dev/usb`.

Next, add two lines to `/etc/rc.conf` as follows:

```
cupsd_enable="YES"
devfs_system_ruleset="system"
```

These two entries will start the **CUPS** print server on boot and invoke the local `devfs` rule created above, respectively.

In order to enable **CUPS** printing under certain Microsoft® Windows clients, the line below should be uncommented in `/usr/local/etc/cups/mime.types` and `/usr/local/etc/cups/mime.convs`:

```
application/octet-stream
```

Once these changes have been made, the `devfs(8)` and **CUPS** systems must both be restarted, either by rebooting the computer or issuing the following two commands in a root terminal:

```
# /etc/rc.d/devfs restart
# /usr/local/etc/rc.d/cupsd restart
```

4 Configuring Printers on the CUPS Print Server

After the **CUPS** system has been installed and configured, the administrator can begin configuring the local printers attached to the **CUPS** print server. This part of the process is very similar, if not identical, to configuring **CUPS** printers on other UNIX-based operating systems, such as a Linux distribution.

The primary means for managing and administering the **CUPS** server is through the web-based interface, which can be found by launching a web browser and entering `http://localhost:631` in the browser's URL bar. If the **CUPS** server is on another machine on the network, substitute the server's local IP address for `localhost`. The **CUPS** web interface is fairly self-explanatory, as there are sections for managing printers and print jobs, authorizing users, and

more. Additionally, on the right-hand side of the Administration screen are several check-boxes allowing easy access to commonly-changed settings, such as whether to share published printers connected to the system, whether to allow remote administration of the **CUPS** server, and whether to allow users additional access and privileges to the printers and print jobs.

Adding a printer is generally as easy as clicking “Add Printer” at the Administration screen of the **CUPS** web interface, or clicking one of the “New Printers Found” buttons also at the Administration screen. When presented with the “Device” drop-down box, simply select the desired locally-attached printer, and then continue through the process. If one has added the `print/gutenprint-cups` or `print/hplip` ports or packages as referenced above, then additional print drivers will be available in the subsequent screens that might provide more stability or features.

5 Configuring CUPS Clients

Once the **CUPS** server has been configured and printers have been added and published to the network, the next step is to configure the clients, or the machines that are going to access the **CUPS** server. If one has a single desktop machine that is acting as both server and client, then much of this information may not be needed.

5.1 UNIX® Clients

CUPS will also need to be installed on your UNIX clients. Once **CUPS** is installed on the clients, then **CUPS** printers that are shared across the network are often automatically discovered by the printer managers for various desktop environments such as **GNOME** or **KDE**. Alternatively, one can access the local **CUPS** interface on the client machine at `http://localhost:631` and click on “Add Printer” in the Administration section. When presented with the “Device” drop-down box, simply select the networked **CUPS** printer, if it was automatically discovered, or select `ipp` or `http` and enter the IPP or HTTP URI of the networked **CUPS** printer, usually in one of the two following syntaxes:

```
ipp://server-name-or-ip/printers/printername
http://server-name-or-ip:631/printers/printername
```

If the **CUPS** clients have difficulty finding other **CUPS** printers shared across the network, sometimes it is helpful to add or create a file `/usr/local/etc/cups/client.conf` with a single entry as follows:

```
ServerName server-ip
```

In this case, `server-ip` would be replaced by the local IP address of the **CUPS** server on the network.

5.2 Windows® Clients

Versions of Windows prior to XP did not have the capability to natively network with IPP-based printers. However, Windows XP and later versions do have this capability. Therefore, to add a **CUPS** printer in these versions of Windows is quite easy. Generally, the Windows administrator will run the Windows Add Printer wizard, select Network Printer and then enter the URI in the following syntax:

```
http://server-name-or-ip:631/printers/printername
```

If one has an older version of Windows without native IPP printing support, then the general means of connecting to a **CUPS** printer is to use `net/samba3` and **CUPS** together, which is a topic outside the scope of this chapter.

6 CUPS Troubleshooting

Difficulties with **CUPS** often lies in permissions. First, double check the devfs(8) permissions as outlined above. Next, check the actual permissions of the devices created in the file system. It is also helpful to make sure your user is a member of the cups group. If the permissions check boxes in the Administration section of the **CUPS** web interface do not seem to be working, another fix might be to manually backup the main **CUPS** configuration file located at `/usr/local/etc/cups/cupsd.conf` and edit the various configuration options and try different combinations of configuration options. One sample `/usr/local/etc/cups/cupsd.conf` to test is listed below. Please note that this sample `cupsd.conf` file sacrifices security for easier configuration; once the administrator successfully connects to the **CUPS** server and configures the clients, it is advisable to revisit this configuration file and begin locking down access.

```
# Log general information in error_log - change "info" to "debug" for
# troubleshooting...
LogLevel info

# Administrator user group...
SystemGroup wheel

# Listen for connections on Port 631.
Port 631
#Listen localhost:631
Listen /var/run/cups.sock

# Show shared printers on the local network.
Browsing On
BrowseOrder allow,deny
#BrowseAllow @LOCAL
BrowseAllow 192.168.1.* # change to local LAN settings
BrowseAddress 192.168.1.* # change to local LAN settings

# Default authentication type, when authentication is required...
DefaultAuthType Basic
DefaultEncryption Never # comment this line to allow encryption

# Allow access to the server from any machine on the LAN
<Location />
    Order allow,deny
    #Allow localhost
    Allow 192.168.1.* # change to local LAN settings
</Location>

# Allow access to the admin pages from any machine on the LAN
<Location /admin>
    #Encryption Required
    Order allow,deny
    #Allow localhost
    Allow 192.168.1.* # change to local LAN settings
</Location>

# Allow access to configuration files from any machine on the LAN
<Location /admin/conf>
```

```

AuthType Basic
Require user @SYSTEM
Order allow,deny
#Allow localhost
Allow 192.168.1.* # change to local LAN settings
</Location>

# Set the default printer/job policies...
<Policy default>
  # Job-related operations must be done by the owner or an administrator...
  <Limit Send-Document Send-URI Hold-Job Release-Job Restart-Job Purge-Jobs \
Set-Job-Attributes Create-Job-Subscription Renew-Subscription Cancel-Subscription \
Get-Notifications Reprocess-Job Cancel-Current-Job Suspend-Current-Job Resume-Job \
CUPS-Move-Job>
    Require user @OWNER @SYSTEM
    Order deny,allow
  </Limit>

  # All administration operations require an administrator to authenticate...
  <Limit Pause-Printer Resume-Printer Set-Printer-Attributes Enable-Printer \
Disable-Printer Pause-Printer-After-Current-Job Hold-New-Jobs Release-Held-New-Jobs \
Deactivate-Printer Activate-Printer Restart-Printer Shutdown-Printer Startup-Printer \
Promote-Job Schedule-Job-After CUPS-Add-Printer CUPS-Delete-Printer CUPS-Add-Class \
CUPS-Delete-Class CUPS-Accept-Jobs CUPS-Reject-Jobs CUPS-Set-Default>
    AuthType Basic
    Require user @SYSTEM
    Order deny,allow
  </Limit>

  # Only the owner or an administrator can cancel or authenticate a job...
  <Limit Cancel-Job CUPS-Authenticate-Job>
    Require user @OWNER @SYSTEM
    Order deny,allow
  </Limit>

  <Limit All>
    Order deny,allow
  </Limit>
</Policy>

```

7 Fine Tuning CUPS-Related Ports

If **CUPS** is going to serve as the primary printing system, then one may choose to optionally add certain knobs to `/etc/make.conf` that will emphasize **CUPS** over other printing options. Some of these “knobs” that one may want to add are:

```

WITH_CUPS=YES
CUPS_OVERWRITE_BASE=YES
WITHOUT_LPR=YES

```

The first knob, `WITH_CUPS`, adds **CUPS** support to ports where applicable. The second knob, `CUPS_OVERWRITE_BASE`, will fix certain symlinks and paths that would otherwise apply to the default FreeBSD printing system, **LPR**, and will prevent these fixes from being reverted upon the next `buildworld` system upgrade. The third knob, `WITHOUT_LPR`, will prevent **LPR** support from being added to ports where applicable.