

CICS[®] Transaction Server for
OS/390[®]



CICS Trace Entries

Release 3

CICS[®] Transaction Server for OS/390[®]



CICS Trace Entries

Release 3

Second edition (November 2000)

This edition applies to Release 3 of CICS Transaction Server for OS/390, program number 5655-147, and to all subsequent versions, releases, and modifications until otherwise indicated in new editions. Make sure you are using the correct edition for the level of the product.

The changes for this release of CICS Transaction Server for OS/390, are indicated by a vertical bar to the left of a change.

This edition replaces and makes obsolete the previous edition, SC34-5446-00. Changes since that edition are indicated by a # sign to the left of a change. Any vertical lines in the left margin indicate a change made between Version 1 Release 2 and Version 1 Release 3 of CICS Transaction Server for OS/390.

Order publications through your IBM representative or the IBM branch office serving your locality. Publications are not stocked at the address given below.

At the back of this publication is a page entitled "Sending your comments to IBM". If you want to make comments, but the methods described are not available to you, please address them to:

IBM United Kingdom Laboratories, Information Development,
Mail Point 095, Hursley Park, Winchester, Hampshire, England, SO21 2JN.

When you send information to IBM, you grant IBM a nonexclusive right to use or distribute the information in any way it believes appropriate without incurring any obligation to you.

© Copyright International Business Machines Corporation 1989, 2000. All rights reserved.

US Government Users Restricted Rights – Use, duplication or disclosure restricted by GSA ADP Schedule Contract with IBM Corp.

Contents

Notices	v
Trademarks	vi

Preface	vii
What this book is about	vii
Who this book is for	vii
What you need to know to understand this book	vii
Determining if a publication is current	vii
Book structure	vii

Bibliography	ix
CICS Transaction Server for OS/390	ix
CICS books for CICS Transaction Server for OS/390	ix
CICSplex SM books for CICS Transaction Server for OS/390	ix
Other CICS books	x

Chapter 1. AP domain trace points – ‘old style’ **1**

Format of REQ, FIELD A, FIELD B, and RESOURCE fields	1	#
Contents of the trace entry resource field	1	
Data conversion for CICS OS/2® ISC	2	
CAVM services	3	
Dynamic transaction backout	7	
Basic mapping support	7	
Recovery control	7	
Basic mapping support	8	
LU6.2 services manager	8	
Development Management System/CICS/VS	8	
Allocation program	8	
Data interchange	10	
Abnormal condition program	11	
Subtask management program	12	
Intersystem program	13	
Message processor	13	
EXEC interface	14	
CSD parameter utility program	14	
System spooling interface	15	
Terminal control	17	
Allocation management program	19	
Definition management program	21	
Terminal object resolution	23	
Interval control	24	
Temporary storage	26	
Basic mapping support	27	
Built-in function	30	
Terminal control	30	
Trace control	33	

Chapter 2. Domain trace points	35
AP domain trace points – ‘new style’	35
XPI trace put	35

Trace points in common subroutines	35
DBCTL and DL/I trace points	36
File control	38
Transaction manager	45
Transaction attach	48
JAVA/IIOP	48
AP domain recovery	49
LU6.2 transaction routing	50
DM gate service module	53
XRF takeover	54
Data tables	55
File control	58
Common Programming Interface	67
DFHCRxx	79
CICS OS/2 mirror program	81
Autoinstall terminal model manager	82
Partner resource manager	82
Front end programming interface (FEPI)	83
Transaction initiation	95
Surrogate terminal interface	101
Application language interface	101
Java virtual machine	113
Java hot-pooling	114
Program control	116
Signon	116
Bridge facility management	120
C++ and JAVA	122
File control	197
RMI trace entries	213
DFHCRRSY trace entries	215
LU6.1 Resynchronization	218
Bridge facility management 2	220
Connection to quiesce processing	221
Server support for CICS Clients	222
RDO for RCT	227
Web trace points	235
User exit routines	246
Cancel start requests	249
Syncpoint program	250
Function shipping data transformation	250
AP domain statistics gathering	251
Transaction routing data transformation	255
IRC commands	256
EXEC interface	261
Security	263
Table Management Program	264
Transaction manager	264
Storage control SM interface	265
Program control	265
Interval control	266
Dump control	266
Transient data	267
Temporary storage	270
Event manager trace points	271
TCPIP SPI	271
Journaling	272

Document handler AP trace points	272	Monitoring domain trace points	416
Autoinstall for APPC sessions	272	Enqueue domain trace points	422
VTAM.	276	Parameter manager domain trace points	427
Terminal control	288	Program manager domain trace points	428
Terminal control (intersystem communication)	296	Recovery Manager	440
Terminal control (LU6.2 application requests)	299	RRMS domain trace points	464
Business application manager trace points	304	Scheduler domain trace points.	467
CICS catalog domain trace points	312	Storage manager domain trace points	470
Directory domain trace points	314	Socket domain	482
Document handler trace points	317	Statistics domain trace points	492
Domain manager domain trace points	322	Timer domain trace points	495
Dispatcher domain trace points	326	Trace domain trace points	496
Dump domain trace points	334	Temporary storage domain trace points	497
Event Manager	340	User domain trace points	501
External CICS interface trace points	341	Web domain trace points	505
ONC/RPC trace points	353	Transaction manager domain trace points	507
Kernel domain trace points.	366	Security manager trace points	521
Loader domain trace points	369		
Log manager trace points	379		
Lock manager domain trace points	411		
Message domain trace points	412		
		Sending your comments to IBM	525

Notices

This information was developed for products and services offered in the U.S.A. IBM may not offer the products, services, or features discussed in this document in other countries. Consult your local IBM representative for information on the products and services currently available in your area. Any reference to an IBM product, program, or service is not intended to state or imply that only that IBM product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any IBM intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any non-IBM product, program, or service.

IBM may have patents or pending patent applications covering subject matter described in this document. The furnishing of this document does not give you any license to these patents. You can send license inquiries, in writing, to:

IBM Director of Licensing
IBM Corporation
North Castle Drive
Armonk, NY 10504-1785
U.S.A.

For license inquiries regarding double-byte (DBCS) information, contact the IBM Intellectual Property Department in your country or send inquiries, in writing, to:

IBM World Trade Asia Corporation
Licensing
2-31 Roppongi 3-chome, Minato-ku
Tokyo 106, Japan

The following paragraph does not apply in the United Kingdom or any other country where such provisions are inconsistent with local law:

INTERNATIONAL BUSINESS MACHINES CORPORATION PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE. Some states do not allow disclaimer of express or implied warranties in certain transactions, therefore this statement may not apply to you.

This publication could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. IBM may make improvements and/or changes in the product(s) and/or the program(s) described in this publication at any time without notice.

Licensees of this program who wish to have information about it for the purpose of enabling: (i) the exchange of information between independently created programs and other programs (including this one) and (ii) the mutual use of the information which has been exchanged, should contact IBM United Kingdom Laboratories, MP151, Hursley Park, Winchester, Hampshire, England, SO21 2JN. Such information may be available, subject to appropriate terms and conditions, including in some cases, payment of a fee.

The licensed program described in this document and all licensed material available for it are provided by IBM under terms of the IBM Customer Agreement, IBM International Programming License Agreement, or any equivalent agreement between us.

Trademarks

The following terms are trademarks of International Business Machines Corporation in the United States, or other countries, or both:

ACF/VTAM	CICS/MVS	IMS
AIX	COBOL/2	MVS/ESA
CICS	C/370	RACF
CICS OS/2	DB2	VSE/ESA
CICS/ESA	IBM	VTAM

Java and all Java-based trademarks and logos are trademarks or registered trademarks of Sun Microsystems Inc, in the United States, or other countries, or both.

Other company, product, and service names may be trademarks or service marks of others.

Preface

What this book is about

This book contains CICS[®] trace information. It consists of tables that you can use to interpret trace entries, as described in the *CICS Problem Determination Guide*.

Who this book is for

This book is for:

- System programmers
 - CICS or system operators
 - Application programmers.
-

What you need to know to understand this book

You need to have a good understanding of how CICS works. This assumes familiarity with most, if not all, of the books in the CICS library, together with adequate practical experience of running a CICS system.

Determining if a publication is current

IBM regularly updates its publications with new and changed information. When first published, both hardcopy and BookManager softcopy versions of a publication are usually in step. However, due to the time required to print and distribute hardcopy books, the BookManager version is more likely to have had last-minute changes made to it before publication.

Subsequent updates will probably be available in softcopy before they are available in hardcopy. This means that at any time from the availability of a release, softcopy versions should be regarded as the most up-to-date.

For CICS Transaction Server books, these softcopy updates appear regularly on the *Transaction Processing and Data Collection Kit* CD-ROM, SK2T-0730-xx. Each reissue of the collection kit is indicated by an updated order number suffix (the -xx part). For example, collection kit SK2T-0730-06 is more up-to-date than SK2T-0730-05. The collection kit is also clearly dated on the cover.

Updates to the softcopy are clearly marked by revision codes (usually a “#” character) to the left of the changes.

Book structure

This book lists CICS trace entries alphanumerically. There are two slightly different types of trace entry formats. One (“old-style”) resembles the format used in earlier releases of CICS, and gives FIELD A and FIELD B values. The other (“new-style”) uses a different format.

“Chapter 1. AP domain trace points – ‘old style’” on page 1 contains the trace interpretation tables for “old-style” trace entries.

“Chapter 2. Domain trace points” on page 35 contains the trace interpretation tables for “new-style” trace entries.

Trace entries added for this release of CICS and not previously published are indicated by a vertical bar to the left of the new information.

Bibliography

CICS Transaction Server for OS/390

<i>CICS Transaction Server for OS/390: Planning for Installation</i>	GC33-1789
<i>CICS Transaction Server for OS/390 Release Guide</i>	GC34-5352
<i>CICS Transaction Server for OS/390 Migration Guide</i>	GC34-5353
<i>CICS Transaction Server for OS/390 Installation Guide</i>	GC33-1681
<i>CICS Transaction Server for OS/390 Program Directory</i>	GI10-2506
<i>CICS Transaction Server for OS/390 Licensed Program Specification</i>	GC33-1707

CICS books for CICS Transaction Server for OS/390

General

<i>CICS Master Index</i>	SC33-1704
<i>CICS User's Handbook</i>	SX33-6104
<i>CICS Transaction Server for OS/390 Glossary (softcopy only)</i>	GC33-1705

Administration

<i>CICS System Definition Guide</i>	SC33-1682
<i>CICS Customization Guide</i>	SC33-1683
<i>CICS Resource Definition Guide</i>	SC33-1684
<i>CICS Operations and Utilities Guide</i>	SC33-1685
<i>CICS Supplied Transactions</i>	SC33-1686

Programming

<i>CICS Application Programming Guide</i>	SC33-1687
<i>CICS Application Programming Reference</i>	SC33-1688
<i>CICS System Programming Reference</i>	SC33-1689
<i>CICS Front End Programming Interface User's Guide</i>	SC33-1692
<i>CICS C++ OO Class Libraries</i>	SC34-5455
<i>CICS Distributed Transaction Programming Guide</i>	SC33-1691

<i>CICS Business Transaction Services</i>	SC34-5268
---	-----------

Diagnosis

<i>CICS Problem Determination Guide</i>	GC33-1693
<i>CICS Messages and Codes</i>	GC33-1694
<i>CICS Diagnosis Reference</i>	LY33-6088
<i>CICS Data Areas</i>	LY33-6089
<i>CICS Trace Entries</i>	SC34-5446
<i>CICS Supplementary Data Areas</i>	LY33-6090

Communication

<i>CICS Intercommunication Guide</i>	SC33-1695
<i>CICS Family: Interproduct Communication</i>	SC33-0824
<i>CICS Family: Communicating from CICS on System/390</i>	SC33-1697
<i>CICS External Interfaces Guide</i>	SC33-1944
<i>CICS Internet Guide</i>	SC34-5445

Special topics

<i>CICS Recovery and Restart Guide</i>	SC33-1698
<i>CICS Performance Guide</i>	SC33-1699
<i>CICS IMS Database Control Guide</i>	SC33-1700
<i>CICS RACF Security Guide</i>	SC33-1701
<i>CICS Shared Data Tables Guide</i>	SC33-1702
<i>CICS Transaction Affinities Utility Guide</i>	SC33-1777
<i>CICS DB2 Guide</i>	SC33-1939

CICSplex SM books for CICS Transaction Server for OS/390

General

<i>CICSplex SM Master Index</i>	SC33-1812
<i>CICSplex SM Concepts and Planning</i>	GC33-0786

<i>CICSplex SM User Interface Guide</i>	SC33-0788
<i>CICSplex SM View Commands Reference Summary</i>	SX33-6099
Administration and Management	
<i>CICSplex SM Administration</i>	SC34-5401
<i>CICSplex SM Operations Views Reference</i>	SC33-0789
<i>CICSplex SM Monitor Views Reference</i>	SC34-5402
<i>CICSplex SM Managing Workloads</i>	SC33-1807
<i>CICSplex SM Managing Resource Usage</i>	SC33-1808
<i>CICSplex SM Managing Business Applications</i>	SC33-1809
Programming	
<i>CICSplex SM Application Programming Guide</i>	SC34-5457
<i>CICSplex SM Application Programming Reference</i>	SC34-5458
Diagnosis	
<i>CICSplex SM Resource Tables Reference</i>	SC33-1220
<i>CICSplex SM Messages and Codes</i>	GC33-0790
<i>CICSplex SM Problem Determination</i>	GC33-0791

Other CICS books

<i>CICS Application Programming Primer (VS COBOL II)</i>	SC33-0674
<i>CICS Application Migration Aid Guide</i>	SC33-0768
<i>CICS Family: API Structure</i>	SC33-1007
<i>CICS Family: Client/Server Programming</i>	SC33-1435
<i>CICS Family: General Information</i>	GC33-0155
<i>CICS 4.1 Sample Applications Guide</i>	SC33-1173
<i>CICS/ESA 3.3 XRF Guide</i>	SC33-0661

If you have any questions about the CICS Transaction Server for OS/390 library, see *CICS Transaction Server for OS/390: Planning for Installation* which discusses both hardcopy and softcopy books and the ways that the books can be ordered.

Chapter 1. AP domain trace points – ‘old style’

Trace entries with point IDs in the range AP 0000 through AP 00C2 are user trace entries, the numeric part of the point ID being defined in the application making the trace call. AP domain system trace entries have point IDs in the range AP 00C3 through AP FFFF. Not all the values are used.

Where descriptions are given of the specific contents of the REQ field, FIELD A, FIELD B, and the RESOURCE field, byte positions are numbered from left to right, starting at 0.

Format of REQ, FIELD A, FIELD B, and RESOURCE fields

Field	Contents
REQ Byte 0 and byte 1, bits 0–3	For system entries, byte 0 and byte 1 (bits 0–3) usually contain the request code relating to the type of CICS management involved. For user entries, these bits are not used.
REQ Byte 1, bits 4–7	These bits indicate the type of entry, as follows: X'2' User entry X'3' LIFO system entry X'4' System entry X'5' LIFO response/return X'D' Trace on/off entry
FIELD A Bytes 0–3	Data relevant to this entry
FIELD B Bytes 0–3	Data relevant to this entry
RESOURCE Bytes 0–7	When provided, this is usually the name of a resource associated with the request being traced. Details are given below.

Contents of the trace entry resource field

ID	Program	Request Types	Resource
AP 00C4	DFHWMS	Entry	Bytes 0–3: instance number (WMSINSTN) Bytes 4–7: version number (WMSVERN)/ queue name (WMSQNAME)
AP 00D6	Allocation program	X'17' allocate	Modename
AP 00E3	System spooling interface	Where appropriate	Data set ID token
AP 00EA	Table management program	Where appropriate	Resource name
AP 00F3	Interval control	Where appropriate X'90' RETRY X'F0' CANCEL	Transid Request ID Request ID
AP 00F7	Temporary storage	Where appropriate	Queue name

Resource field

Data conversion for CICS OS/2[®] ISC

Table 1. AP 00C3, DFHCCNV trace entries

Point ID	Byte	Value	Contents
AP 00C3	Byte 1, bits 4-7	X'4'	System trace
DFHCCNV	Byte 0	X'01'	TS resource
AP Lvl 1	Field A, bytes 0-1		Reserved
	bytes 2-3		TS data length
	Field B		TS data address
	Byte 0	X'02'	TS resource
	Field A, byte 0		Reserved
	byte 1 1...	Match key template
	1..	Match on select compare
	1.	Match on select default
	1	Match on resource name
	bytes 2-3		TS template length
	Field B		TS template address
	Byte 0	X'03'	TD resource
	Field A, bytes 0-1		Reserved
	bytes 2-3		TD data length
	Field B		TD data address
	Byte 0	X'04'	TD resource
	Field A, byte 0		Reserved
	byte 1 1...	Match key template
	1..	Match on select compare
	1.	Match on select default
		Match on resource name
	bytes 2-3		TD template length
	Field B		TD template address
	Byte 0	X'05'	FC resource
	Field A, bytes 0-1		Reserved
	bytes 2-3		FC data length
	Field B		FC data address
	Byte 0	X'06'	FC resource
	Field A, byte 0		Reserved
	byte 1 1...	Match key template
	1..	Match on select compare
	1.	Match on select default
		Match on resource name
	bytes 2-3		FC template length
	Field B		FC template address
	Byte 0	X'07'	FC resource

Table 1. AP 00C3, DFHCCNV trace entries (continued)

Point ID	Byte	Value	Contents
	Field A, bytes 0-1		Reserved
	bytes 2-3		FC key length
	Field B		FC key address
	Byte 0 Field A, bytes 0-1	X'08'	FC resource Reserved
	bytes 2-3		FC key template length
	Field B		FC key template address
	Byte 0 Field A, bytes 0-1	X'09'	IC resource Reserved
	bytes 2-3		IC data length
	Field B		IC data address
	Byte 0 Field A, byte 0	X'0A'	IC resource Reserved
	byte 1 1...	Match key template
	1..	Match on select compare
	1.	Match on select default
		Match on resource name
	bytes 2-3		IC template length
	Field B		IC template address
	Byte 0 Field A	X'0B'	Exit Resource name
	Field B		Resource name
	Byte 0 Field A, byte 0	X'0C'	Entry Reserved
	byte 1	X'02'	ASCII to EBCDIC request
		X'04'	EBCDIC to ASCII request
	bytes 2-3		ARG0 bytes 1 and 2 (FNCODE)
	Field B		ARG0 bytes 3-6

CAVM services

Table 2. AP 00C4, DFHWMS trace entries

Point ID	Byte	Value	Contents
AP 00C4	Byte 1, bits 4-7	X'3'	Entry
DFHWMS	Field A		Message manager request ID (WMSREQID)
AP Lvl 1	Field B		Data area address (WMSDATAD)
	Byte 1, bits 4-7	X'5'	Exit
	Field A		Message manager return code (WMSRC)
	Field B, bytes 0-1		Data area size (WMSDATSZ)

Resource field

Table 2. AP 00C4, DFHWMS trace entries (continued)

Point ID	Byte	Value	Contents
	bytes 2-3		Data length (WMSDATLN)

Table 3. AP 00C5, DFHXRCR trace entries

Point ID	Byte	Value	Contents
AP 00C5	Byte 0	X'00'	Entry
DFHXRCR	Byte 1	X'04'	
AP Lvl 1	Field A		Reserved
	Field B		Reserved
	Byte 0	X'01'	Exit
	Field A		Reserved
	Field B		Reserved
	Byte 0	X'02'	Resumption of DFHXRCR
	Field A		Reserved
	Field B		Reserved
	Byte 0	X'03'	Suspension of DFHXRCR
	Field A		Reserved
	Field B		Reserved
	Byte 0	X'04'	CIB prefix
	Field A, byte 0		CIBVERB
	byte 1		CIBLEN
	bytes 2-3		CIBASID
	Field B		CIB console ID (CIBCONID or CIBXCNID)
	Byte 0	X'05'	CIB data for modify command
	Field A		CIB data bytes 0-3
	Field B		CIB data bytes 4-7
	Byte 0	X'06'	CIB data for modify command - continuation 1
	Field A		CIB data bytes 8-11
	Field B		CIB data bytes 12-15
	Byte 0	X'07'	CIB data for modify command - continuation 2
	Field A		CIB data bytes 16-19
	Field B		CIB data bytes 20-23

Table 4. AP 00C6 DFHXRSP trace entries

Point ID	Byte	Value	Contents
AP 00C6	Byte 0	X'00'	Entry
DFHXRSP	Byte 1	X'04'	
AP Lvl 1	Field A		Reserved
	Field B		Reserved
	Byte 0	X'01'	Exit
	Field A		Reserved
	Field B		Reserved
	Byte 0	X'02'	Resumption of DFHXRSP
	Field A		Reserved

Table 4. AP 00C6 DFHXRSR trace entries (continued)

Point ID	Byte	Value	Contents
	Field B		Reserved
	Byte 0	X'03'	Suspension of DFHXRSR
	Field A		Reserved
	Field B		Reserved
	Byte 0	X'04'	Work element
	Field A, byte 0	X'01'	Signon
	(XRWERQ)	X'02'	Signoff normal
		X'03'	Signoff abnormal
		X'07'	Clock difference changed
		X'08'	Status data changed
		X'09'	Surveillance signal overdue
		X'0A'	Surveillance signal resumed
		X'0F'	Takeover requested
		X'10'	Post IA (incipient active) ECB
		X'11'	Post TC (takeover complete) ECB
		X'12'	Post SS (synchronized with respect to signoff) ECB
		X'13'	Post ST (synchronized with respect to termination) ECB
		X'18'	CAVM failed
		X'19'	Invalidated
	byte 1, bit 0		XRWERQM, implicit request, (SIGNON/SIGNOFFNORM)
	byte 1, bit 1		XRWERQM, DUMP=YES (takeover requested)
	bytes 2-3		Reserved
	Field B		A(work element)
	Byte 0	X'05'	Work element - continuation 1
	Field A		XRWEINS instance number
	Field B		XRWEVER version number
	Byte 0	X'06'	Work element - continuation 2
	For sign-on:		
	Field A		APPLID- first four characters
	Field B		APPLID - second four characters
	For clock diff changed:		
	Field A		Lower bound for difference in seconds
	Field B		Upper bound for difference in seconds
	For surveillance signal overdue:		
	Field A		Number of seconds overdue
	For CAVM failed:		
	Field A		Abend code
	Any other event:		
	Field A		Reserved
	Byte 1	X'07'	Abend imminent
	Field A		Abend code

Resource field

Table 4. AP 00C6 DFHXRSR trace entries (continued)

Point ID	Byte Field B	Value	Contents Reserved
----------	--------------	-------	-------------------

Table 5. AP 00C7, DFHXRA trace entries

Point ID	Byte	Value	Contents
AP 00C7	Byte 1 bits 4-7	X'3'	Entry
DFHXRA	Field A, byte 0	X'01'	DFHXR CTYPE=INITIALIZE
AP Lvl 1	(XRRQTR)	X'02'	DFHXR CTYPE=TERMINATE
		X'03'	DFHXR CTYPE=SIGNON
		X'04'	DFHXR CTYPE=SIGNOFF
		X'05'	DFHXR CTYPE=QUERY-TAKEOVER-INIT
		X'06'	DFHXR CTYPE=SET-TAKEOVER-INIT
		X'07'	DFHXR CTYPE=WAIT-TAKEOVER-INIT
		X'08'	DFHXR CTYPE=QUERY-TAKEOVER-COMP
		X'08'	DFHXR CTYPE=QUERY-TAKEOVER COMP
		X'09'	DFHXR CTYPE=SET-TAKEOVER-COMP
		X'0A'	DFHXR CTYPE=WAIT-TAKEOVER-COMP
		X'0B'	DFHXR CTYPE=QUERY-RSD-AVAIL
		X'0C'	DFHXR CTYPE=SET-RSD-AVAIL
		X'0D'	DFHXR CTYPE=WAIT-RSD-AVAIL
		X'0E'	DFHXR CTYPE=QUERY-SYNC-SIGNOFF
		X'0F'	DFHXR CTYPE=SET-SYNC-SIGNOFF
		X'10'	DFHXR CTYPE=WAIT-SYNC-SIGNOFF
		X'11'	DFHXR CTYPE=QUERY-SYNC-TERM
		X'12'	DFHXR CTYPE=SET-SYNC-TERM
		X'13'	DFHXR CTYPE=WAIT-SYNC-TERM
		X'18'	DFHXR CTYPE=INIT-SURVEILLANCE
		X'19'	DFHXR CTYPE=TERM-SURVEILLANCE
		X'1A'	DFHXR CTYPE=INIT-CONSOLE-COMM
		X'1B'	DFHXR CTYPE=TERM-CONSOLE-COMM
		X'1C'	DFHXR CTYPE=SET-HEALTH-DATA
	Byte 1 bits 4-7	X'5'	Exit
	Field A, byte 0		See entry trace XRRQTR immediately above
	byte 3 (XRRQRC)		
	For DFHXR CTYPE=xxx		
		X'00'	Normal response
		X'08'	Invalid request
	For DFHXR CTYPE=SIGNON		
		X'14'	Retry possible
		X'1C'	Rejected by CAVM
	For DFHXR CTYPE=SIGNOFF		
		X'24'	Dump requested
		X'2C'	Rejected by CAVM

Table 5. AP 00C7, DFHXRA trace entries (continued)

Point ID	Byte	Value	Contents
	For DFHXR CTYPE=SET- TAKEOVER- INIT		
		X'34'	Takeover in progress
		X'35'	Shutdown in progress
		X'3C'	Rejected by CAVM
	For DFHXR CTYPE=WAIT-RSD-AVAIL		
		X'44'	Restart data set not available

Dynamic transaction backout

Table 6. AP 00CB DFHDBP trace entries

Point ID	Byte	Value	Contents
X'00CB'	Bytes 0-1		Reserved
DFHDBP	Field A		Saved DWE chain address, TCADWASV
AP Lvl 1	Field B		Address of first DWE, TCADWLBA

Basic mapping support

Table 7. AP 00CD BMS trace entries

Point ID	Byte	Value	Contents
X'00CD'	Bytes 0-1		Reserved
BMS	Field A		First four bytes of temporary storage key
BM Lvl 1	Field B		Next four bytes of temporary storage key

Note: See also trace point AP 00FA.

Recovery control

Table 8. AP 00CE, DFHRCP trace entries

Point ID	Byte	Value	Contents
AP 00CE	Byte 1, bits 4-7	X'3'	Entry
DFHRCP	Field A, byte 0	X'01'	OPEN
AP Lvl 1	(request type)	X'02'	CLOSE
		X'03'	CONNECT
		X'04'	DISCONNECT
		X'05'	STARTBROWSE
		X'06'	ENDBROWSE
		X'07'	GETNEXT
		X'08'	WRITE
		X'09'	READ
		X'0A'	DELETE
		X'0B'	PURGE
		X'0C'	LOG
		X'0D'	INITIALIZE
		X'0E'	WAITINIT
		X'0F'	RESTART TASK
	byte 1		RCRQRM

Resource field

Table 8. AP 00CE, DFHRCP trace entries (continued)

Point ID	Byte	Value	Contents
	bytes 2-3		Reserved
	Field B		Addr of parm list except when byte 8 is X'0F' - it is then reserved.
	Byte 1, bits 4-7	X'5'	Exit
	Field A, byte 0		
	(request type)		Same as on entry trace
	bytes 1-2		Reserved
	byte 3		Response code, RCRQRC
	Field B		Reserved

Basic mapping support

Table 9. AP 00CF, BMS trace entries

Point ID	Byte	Value	Contents
AP 00CF	Bytes 0-1		Reserved
DFHMCP	Field A		Same as for AP 00FA with byte 1, bits 4-7=X'5'
BM Lvl 1			

Note: This trace occurs when an application program issues an EXEC CICS PAGE with RELEASE before the BMS module issues a DFHPC TYPE=RETURN macro to exit from the calling program.

LU6.2 services manager

Table 10. AP 00D3, DFHLUP trace entries

Point ID	Byte	Value	Contents
AP 00D3	Bytes 0-1		Reserved
DFHLUP	Field A		Reserved
TC Lvl 1	Field B		Reserved

Development Management System/CICS/VS

Byte 0 - X'D4': DMS trace entry, see the *Development Management System/CICS/VS: Problem Determination Manual*.

Allocation program

Table 11. AP 00D6, DFHALP trace entries

Point ID	Byte	Value	Contents
AP 00D6	Byte 1, bits 4-7	X'03'	Entry
DFHALP	Byte 0	X'01'	Unchain
KC Lvl 1	Byte 0 Field A	X'02'	BMS TPQ call 2 MCRID
	Byte 0 Field A	X'05'	BMS TPR call 2 Address of AID
	Byte 0 Field A	X'06'	CRS call 1 Reserved

Table 11. AP 00D6, DFHALP trace entries (continued)

Point ID	Byte	Value	Contents
	Field B		System ID
	Byte 0 Field A Field B	X'07'	CRS call 2 Tranid Termid
	Byte 0 Field A Field B	X'08'	ICP call 1 Reserved Reserved
	Byte 0 Field A Field B	X'09'	ICP call 2 Address of AID Reserved
	Byte 0 Field A Field B	X'0A'	BMS TPQ call 1 Normal threshold Adjusted threshold
	Byte 0 Field A Field B	X'0C'	BMS TPQ call 3 Msg ID Reserved
	Byte 0 Field A Field B	X'0D'	BMS TPR call 1 (Supplied AID) Addr of TCTTE
	Byte 0 Field A Field B	X'0E'	CRQ call 1 Normal threshold Adjusted threshold
	Byte 0 Field A Field B	X'12'	Schedule Tranid Termid
	Byte 0 Field A Field B	X'14'	Avail Termid Terminal address
	Byte 0 Field A Field B	X'15'	Unavail Termid Terminal address
	Byte 0 Field A Field B	X'16'	Release Termid Terminal address
	Byte 0 Field A Field B	X'17'	Allocate Tranid System address
	Byte 0 Field A Field B	X'18'	Release abnormal Termid Terminal address

Resource field

Table 11. AP 00D6, DFHALP trace entries (continued)

Point ID	Byte	Value	Contents
	Byte 0, bits 4-7	X'05'	Exit
	Field A		Reserved
	Field B, byte 0	X'00'	Normal return
		X'04'	Error return
	byte 1	X'01'	BMS TPQ call 1, no AIDs found
	Secondary error code	X'02'	BMS TPQ call 2, no AIDs found
		X'03'	BMS TPQ call 3, no AIDs found
		X'04'	ICP call 1, no AIDs found
		X'05'	ICP call 1, AID found but does not match
		X'06'	No AID found for generalized locate function
	byte 0	X'0C'	Error return
		X'31'	Error return

Data interchange

Table 12. AP 00D7, DFHDIP trace entries

Point ID	Byte	Value	Contents
AP 00D7	Byte 1, bits 4-7	X'03'	Entry
DFHDIP DI Lvl 1	Byte 0	X'01'	ADD
		X'02'	ERASE
		X'03'	REPLACE
		X'04'	ABORT
		X'05'	QUERY
		X'06'	END
		X'07'	RECEIVE
		X'08'	NOTE
		X'09'	DETACH
		X'0A'	ATTACH
		X'0B'	SEND
		X'0C'	WAIT
	Byte 1, bits 0-3	X'1'	DSN not specified
		X'2'	Profile specified
		X'4'	SELECT
		X'8'	VOLADDR
	Field A, byte 0	X'01'	WAIT
		X'08'	KEYNUMB
		X'10'	RRNADDR
		X'20'	KEYADDR
		X'40'	TYPE=SAVE
		X'80'	DEFRESP=YES
	byte 1		Reserved
	byte 2		Value of NUMREC (valid for ADD, ERASE, and REPLACE)
	Field B		TIOA address, TCTTEDA
	Byte 1, bits 4-7	X'05'	Exit

Table 12. AP 00D7, DFHDIP trace entries (continued)

Point ID	Byte	Value	Contents
	Field A, bytes 0-1		Return code, TCADIRC
	bytes 2-3		Deferred return code (set by next call to DFHDIP if nonzero)
	Field B, bytes 0-1		System sense code from DFHZNAC
	bytes 2-3		User sense code from DFHZNAC

Abnormal condition program

Table 13. AP 00DC, DFHACP trace entries

Point ID	Byte	Value	Contents
AP 00DC	Byte 1, bits 4-7	X'3'	Entry
DFHACP AP Lvl 1	byte 0	X'00'	Abend or invalid transaction
		X'81'	Invalid transaction ID
		X'82'	Transaction disabled
		X'83'	End user not authorized - security violation
		X'84'	Invalid tranid during system quiesce
		X'85'	Transaction not executable on requested terminal
		X'86'	Invalid remote transaction ID
		X'87'	ZNAC detected error
		X'88'	I/O error when starting session
		X'89'	Normal termination for DFHACP
		X'8A'	Console not defined
		X'8B'	Program not available
		X'8C'	Terminal profile not available
		X'8D'	XRF recovery process is active
		X'8E'	Remote system out of service
		X'8F'	Dynamic route system not available
		X'90'	All remote sessions are busy
		X'91'	Invalid PIP received with ATTACH
		X'92'	Requested transaction does not support GDS
		X'93'	Invalid conversation type in ATTACH
		X'94'	Invalid SBA in ATTACH
		X'95'	Requested syncpoint level not supported
		X'96'	Invalid syncpoint in ATTACH
		X'97'	Invalid ACC in ATTACH
		X'98'	Invalid UOW in ATTACH
		X'99'	Invalid FMH length
		X'9A'	Conversation restart not supported
		X'9C'	Invalid access security subfield length
		X'9D'	Password required but not supplied in FMH
		X'9E'	Invalid ATTACH parameter
		X'9F'	Partner LU security protocol violation
		X'C2'	Invalid non-terminal transaction
		X'C3'	End user not signed on - security violation
		X'C4'	Insufficient resource to start transaction
	Field A		Current transaction
	Field B		Abend code
	Byte 1, bits 4-7	X'5'	Exit
	byte 0	X'00'	Invalid transaction entered at terminal

Resource field

Table 13. AP 00DC, DFHACP trace entries (continued)

Point ID	Byte	Value	Contents
		X'05'	Transaction abended
		X'06'	Transaction abended, resource backout successful
		X'07'	Resource backout failed
		X'08'	Resource backout abended
		X'10'	Restart rejected - backout had failed
		X'11'	Restart rejected due to abend code
		X'12'	Restart rejected due to terminal I/O
		X'13'	Restart rejected due to prior syncpoint
		X'14'	Restart rejected at request of user code
		X'81' - X'9F'	As entry trace
		X'C2' - X'C4'	As entry trace
	Field A		Current transaction
	Field B		Abend code

Subtask management program

Table 14. AP 00DE, DFHSKP trace entries

Point ID	Byte	Value	Contents
AP 00DE	Byte 1, bits 4-7	X'3'	Entry
DFHSKP	Field A, byte 0	X'01'	PERFORM
AP Lvl 1	(request type)	X'02'	WAIT
		X'03'	RETURN
		X'04'	TERMINATE
		X'05'	DWE PROCESS
	byte 1 (request modifier)1	AUTH=YES
	1.	CLASS=I/O
	1..	SAVAREA
	 1...	SYNC=YES
	bytes 2-3		Reserved
	Field B		Address of exit routine if byte 8=X'01', otherwise reserved
	Byte 1, bits 4-7	X'5'	Exit
	Field A, byte 0	X'01'	PERFORM
	(request type)	X'02'	WAIT
		X'03'	RETURN
		X'04'	TERMINATE
		X'05'	DWE PROCESS
	bytes 1-2		Reserved
	byte 3 (response code)	X'00'	Normal response
		X'04'	User code failed
		X'08'	Subtask code failed
		X'0C'	Unable to perform request
		X'10'	Request never completed
		X'14'	Invalid request

Table 14. AP 00DE, DFHSKP trace entries (continued)

Point ID	Byte	Value	Contents
		X'18'	Invalid ECB address
		X'1C'	User task canceled
	Field B		Addr of parm list

Intersystem program

Table 15. AP 00DF, DFHISP trace entries

Point ID	Byte	Value	Contents
AP 00DF	Byte 1, bits 4-7	X'3'	Entry
DFHISP	Field A, byte 0	X'03'	Shut down
IS Lvl 1		X'04'	Converse
	bytes 1-2		Reserved
	Field B		TCTSE name
	Byte 1, bits 4-7	X'5'	Exit
	Field A, byte 0	X'00'	Successful
	(ISCRQTR)	X'04'	Retry possible
		X'08'	Permanent error
		X'0C'	Terminal out of service
	bytes 1-3		Reserved
	Field B		Reserved

Message processor

Table 16. AP 00E0, DFHMGP trace entries

Point ID	Byte	Value	Contents
AP 00E0	Byte 1, bits 4-7	X'3'	Entry
DFHMGP	Field A, byte 0	X'01'	
AP Lvl 1	byte 1	X'01'	CSCS (TD queue)
		X'02'	TIOA to be used
		X'04'	No number to be used
		X'08'	Return the message
		X'10'	Output to console
		X'20'	Output to terminal
		X'40'	CSTL (TD queue)
		X'80'	CSMT (TD queue)
	bytes 2-3		Message number in binary
	Field B		TCTTE address
	Byte 1, bits 4-7	X'5'	Exit
	Field A, byte 0	X'01'	
	byte 1	X'01'	CSCS (TD queue)
	Field B		TCTTE address
	Field A, byte 1	X'02'	TIOA to be used
	Field B		TIOA address

Resource field

Table 16. AP 00E0, DFHMGP trace entries (continued)

Point ID	Byte	Value	Contents
	Field A, byte 1	X'04'	No number to be used
		X'08'	Return the message
		X'10'	Output to console
		X'20'	Output to terminal
		X'40'	CSTL (TD queue)
		X'80'	CSMT (TD queue)
	bytes 2-3		Message number in binary
	Field B		TCTTE address

EXEC interface

Table 17. AP 00E1, DFHEIP trace entries

Point ID	Byte	Value	Contents
AP 00E1	Byte 0		Reserved
DFHEIP	Byte 1, bits 0-3	X'0'	Entry
EI Lvl 1	Field A		Value of Register 13: PL/I - DSA Assembler - DFHEISTG COBOL - TGT
	Field B, byte 0		Current execution key
	byte 1		Reserved
	bytes 2-3		Command code, EIBFN
	Byte 0		EIBGDI
	Byte 1, bits 0-3	X'F'	Exit
	Field A		Secondary response, EIBRESP2
	Field B, bytes 0-1		Condition number, EIBRESP (zero indicates normal return)
	bytes 2-3		Command code, EIBFN

Note: See the *CICS User's Handbook* for the values and meanings of RESP, RESP2, and EIBFN fields. Trace entries with an EIBFN byte 0 value greater than X'80' are CICS internal trace entries.

CSD parameter utility program

Table 18. AP 00E2, DFHPUP trace entries

Point ID	Byte	Value	Contents
AP 00E2	Byte 0		Reserved
DFHPUP	Byte 1, bits 4-7	X'3'	Entry
AP Lvl 1	Field A, bytes 0-1		Function code
		X'F001'	Flatten
		X'F002'	Unflatten
		X'F003'	Trancase
		X'F004'	Backtrans
		X'F005'	Compare
	Field B		Reserved

Table 18. AP 00E2, DFHPUP trace entries (continued)

Point ID	Byte	Value	Contents
	Byte 1, bits 4-7	X'5'	Exit
	Field A, byte 3		Response code
		X'00'	Normal response
		X'04'	Warning
		X'08'	Error
		X'0C'	Severe error
		X'10'	Terminating
		X'FC'	Inform
	Field B, bytes 0-3	X'00'	

System spooling interface

Table 19. AP 00E3, DFHPSP trace points

Point ID	Byte	Value	Contents
AP 00E3 DFHPSP	Note: RESP and RESP2 codes are explained in the <i>CICS User's Handbook</i> .		
AP Lvl 1	Byte 0	X'A0'	Entry
	Field A		Address of DFHPS parameter list
	Field B		Reserved
	Byte 0	X'A1'	Response
	Field A		Address of DFHPS parameter list
	Field B		Reserved
	Byte 0	X'A2'	Unsupported function
	Field A		Address of DFHPS parameter list
	Field B		RESP return code

The following trace entries are provided only if the system spooling interface trace facility has been activated (by means of the SPOOLFE option of the CSFE transaction), or if an abnormal response is given:

Byte 0	X'10'	DFHEPS SPOOLCLOSE response
Field A		RESP return code
Field B		RESP2 return code
Byte 0	X'11'	DFHEPS SPOOLCLOSE DELETE
Field A		Reserved
Field B		Reserved
Byte 0	X'14'	DFHEPS SPOOLCLOSE PRINT
Field A		Reserved
Field B		Reserved
Byte 0	X'20'	DFHEPS SPOOLREAD response
Field A		RESP return code
Field B		RESP2 return code
Byte 0	X'21'	DFHEPS SPOOLREAD STANDARD
Field A		Reserved
Field B		Reserved

Resource field

Table 19. AP 00E3, DFHPSP trace points (continued)

Point ID	Byte	Value	Contents
	Byte 0 Field A Field B	X'22'	DFHEPS SPOOLWRITE response RESP return code RESP2 return code
	Byte 0 Field A Field B	X'28'	DFHEPS SPOOLWRITE STANDARD Reserved Reserved
	Byte 0 Field A Field B	X'40'	DFHEPS SPOOLOPEN response RESP return code RESP2 return code
	Byte 0 Field A Field B	X'41'	DFHEPS SPOOLOPEN OUTPUT Reserved Reserved
	Byte 0 Field A Field B	X'42'	DFHEPS SPOOLOPEN INPUT Reserved Reserved
	Byte 0 Field A Field B	X'88'	DFHEPS SPOOLOPEN STANDARD Reserved Reserved
	Byte 0 Field A Field B	X'B0'	DFHPSPCK entry Reserved Reserved
	Byte 0 Field A Field B	X'B1'	DFHPSPCK invalid request RESP return code Reserved
	Byte 0 Field A Field B	X'B2'	DFHPSPCK interface halting RESP return code Reserved
	Byte 0 Field A Field B	X'B3'	DFHPSPCK interface disable Reserved Reserved
	Byte 0 Field A Field B	X'B4'	DFHPSPCK interface terminate Reserved Reserved
	Byte 0 Field A Field B	X'E0'	DFHPSPST entry Address of DFHPS parameter list Reserved
	Byte 0 Field A Field B	X'E1'	DFHPSPST open input response Address of DFHPS parameter list Spool data block address
	Byte 0	X'E2'	DFHPSPST open output response

Table 19. AP 00E3, DFHPSP trace points (continued)

Point ID	Byte	Value	Contents
	Field A		Address of DFHPS parameter list
	Field B		Spool data block address
	Byte 0	X'E3'	DFHPSPST read response
	Field A		Address of DFHPS parameter list
	Field B		Spool data block address
	Byte 0	X'E4'	DFHPSPST write response
	Field A		Address of DFHPS parameter list
	Field B		Spool data block address
	Byte 0	X'E5'	DFHPSPST close response
	Field A		Address of DFHPS parameter list
	Field B		Reserved
	Byte 0	X'E6'	DFHPSPST interface halting
	Field A		Address of DFHPS parameter list
	Field B		RESP return code
	Byte 0	X'E7'	DFHPSPST invalid request
	Field A		Address of DFHPS parameter list
	Field B		Reserved
	Byte 0	X'E8'	DFHPSPST invalid open request
	Field A		Address of DFHPS parameter list
	Field B		RESP return code
	Byte 0	X'E9'	DFHPSPST invalid read request
	Field A		Address of DFHPS parameter list
	Field B		RESP return code
	Byte 0	X'EA'	DFHPSPST invalid write request
	Field A		Address of DFHPS parameter list
	Field B		RESP return code
	Byte 0	X'EB'	DFHPSPST invalid close request
	Field A		Address of DFHPS parameter list
	Field B		RESP return code

Terminal control

Table 20. AP 00E6, DFHTCP trace entries

Point ID	Byte	Value	Contents
AP 00E6	Byte 1, bits 4-7	X'4'	System trace
DFHTCP	Byte 0	X'01'	TCATRID1
TC Lvl 2	Field A		TCTLE address
	Field B		TCTTE address
	This trace occurs during line scan.		
	Byte 0	X'02'	TCATRID1
	Field A, byte 0		TCTLESI, line status

Resource field

Table 20. AP 00E6, DFHTCP trace entries (continued)

Point ID	Byte	Value	Contents
	byte 1		TCTLEMI, access method flags
	bytes 2-3		TCTLEAL, input area length
	Field B		TCTLEECB, event control block
	This trace occurs during line scan.		
	Byte 0	X'03'	TCATRIDI
	Field A		TCTLE address
	Field B, bytes 0-1		TCTLETOP, type of operation
		X'0000'	Write break
		X'0000'	Init image
		X'0001'	Read initial
		X'0002'	Write initial
		X'0003'	Read continue
		X'0004'	Write continue
		X'0005'	Read conv
		X'0006'	Write conv
		X'0006'	Write erase alternate
		X'0008'	Write structured field
		X'0008'	Write +ve ack
		X'0009'	Read inquiry monitor
		X'000A'	Write -ve ack
		X'000A'	Write reset
		X'000A'	Write disconnect
		X'000B'	Write reset monitor
		X'000B'	Read buffer
		X'000C'	Write at line address
		X'000C'	Write initial transparent block
		X'000D'	Write initial conv
		X'000E'	Write erase
		X'000E'	Write continue transparent block
		X'000F'	Write cont conv
		X'000F'	Read with ID exch
		X'0010'	Write disconnect
		X'0011'	Read modified
		X'0011'	Read connect
		X'0012'	Write initial transparent
		X'0012'	Write unprotected erase
		X'0014'	Write continue transparent
		X'0015'	Read inquiry
		X'0016'	Write inquiry
		X'001A'	Write wait before transmitting
		X'001B'	Read interrupt
		X'001C'	Write connect
		X'0080'	Init with reset
		X'0081'	Read init with reset
		X'0082'	Write init with reset
		X'0086'	Write conv with reset
	bytes 2-3		TCTLEIOL, I/O data length
	This trace occurs at I/O event initiation.		
	Byte 0	X'04'	TCATRIDI
	Field A		See definition of field A for byte 0=X'02'
	Field B		Reserved

Table 20. AP 00E6, DFHTCP trace entries (continued)

Point ID	Byte	Value	Contents
DFHTACP	Byte 1, bits 4-7	X'4'	System trace
TC Lvl 2	Byte 0 Field A, bytes 0-1 byte 2 byte 3 Field B	X'10'	TCATRID1 Op code, TCTLETOP TP code, TCTLETPO Action flags, TCTLEECB+1 (set by DFHTACP) Terminal ID
	This trace occurs in DFHTACP just prior to transferring control to DFHTEP.		
	Byte 0 Field A, byte 0 byte 1 byte 2 byte 3 Field B, byte 0 byte 1 byte 2 byte 3	X'20'	TCATRID1 Completion code, TCTLEECB BTAM return code, TCTLEECB+3 Error flags, TCTLEPFL Action flags, TCTLEECB+1 (set by DFHTACP) Completion code, TCTLECC Status byte, TCTLESF Sense byte, TCTLESB Sense byte, TCTLESB+1
	This trace occurs in DFHTACP just after returning from DFHTEP.		

Allocation management program

Table 21. AP 00EB, DFHAMP trace entries

Point ID	Byte	Value	Contents
AP 00EB	Byte 0		Reserved
DFHAMP	Byte 1, bits 4-7	X'3'	Entry
AP Lvl 1	Field A, bytes 0-1		Function code
		X'A001'- X'A019'	Alter
		X'A041'- X'A059'	Define
		X'A060' X'A064'	Copy Rename
		X'A068' X'A070'	Delete Append
		X'A078' X'A07A'	Remove Add
		X'A080' X'A084'	Lock Append
		X'A08A' X'A090'	Check Install
		X'A094' X'A098'	Begin End
		X'A099' X'A0A0'	Install list Expand group
		X'A0A8' X'A0AA'	Display Expand list

Resource field

Table 21. AP 00EB, DFHAMP trace entries (continued)

Point ID	Byte	Value	Contents
	Field B		Reserved
	Byte 1, bits 4-7	X'5'	Exit
		For function code X'A099'	
	Field A, bytes 1, 3	00,00	Normal response
		00,04	Some installs failed
		00,08	Install errors
		01,08	Bad list - retry
		00,0C	Severe errors, unable to cont inue
	Field B	X'00'	Reason
		For function code other than X'A099'	
	Field A, byte 3	X'00'	Normal response
		X'01'	DISPLAY, EXPAND already active
		X'02'	CSD accessing error
		X'03'	Duplicate resource or group
		X'04'	End of display
		X'08'	INSTALL failed
		X'09'	Invalid keyword
		X'0A'	Conflicting keywords
		X'0B'	List is group
		X'0C'	Group or list is locked
		X'0D'	No keyword specified
		X'0E'	After, before group not in list
		X'0F'	DISPLAY, EXPAND not active
		X'10'	GROUP, LIST, RESOURCE not found
		X'11'	DEFINE REPLACE TIMESTAMP conflict
		X'12'	Not allowed
	Field B, byte 3		Reason
		X'00'	No error
		X'01'	AFTER name invalid
		X'02'	BEFORE name invalid
		X'03'	CSD control record corrupt
		X'04'	CSD disabled
		X'05'	Data set ID error
		X'06'	CSD full
		X'07'	CSD READ WRITE error
		X'08'	Cannot CONNECT to CSD
		X'09'	Insufficient function in FCP
		X'0A'	Insufficient function in FCT entry
		X'0B'	CSD not OPEN
		X'0C'	VSAM share options
		X'0D'	VSAM STRNO limit exceeded
		X'0E'	Cannot OPEN CSD

Table 21. AP 00EB, DFHAMP trace entries (continued)

Point ID	Byte	Value	Contents
		X'0F'	DISPLAY command not active
		X'10'	EXPAND command active
		X'11'	Group not found
		X'12'	DEFINE created a new group
		X'13'	Groupname invalid
		X'14'	IBM protected
		X'15'	BROWSE, START commands inconsistent
		X'17'	List not found
		X'18'	ADD created a new list
		X'19'	Listname in error
		X'1A'	Group not in list
		X'1B'	Resource not found
		X'1C'	Resource name invalid
		X'1D'	Resource type invalid
		X'1E'	Locked internally by command in progress
		X'1F'	Group or list locked to you
		X'20'	Group or list not locked
		X'21'	Locked to another user

Definition management program

Table 22. AP 00EC, DFHDMP trace entries

Point ID	Byte	Value	Contents
AP 00EC	Byte 1, bits 4-7	X'3'	Entry
DFHDMP	Byte 0	X'00'	Router
AP Lvl 1	Field A, bytes 0-1		Function code
		X'D001'	Connect
		X'D002'	Disconnect
		X'D003'	Build key
		X'D004'	Read
		X'D005'	Write
		X'D006'	Delete
		X'D007'	Lock
		X'D008'	Unlock
		X'D009'	Set browse
		X'D00A'	End browse
		X'D00B'	Get next
		X'D00C'	Create set
		X'D00E'	Query set
		X'D00F'	Erase set
		X'D010'	Release KWA
	bytes 2-3		Reserved
	Field B		Reserved
	Byte 0	X'01'	Connect
		X'02'	Disconnect
		X'03'	Write
		X'04'	Read
		X'05'	Delete
		X'06'	(Un)lock
		X'08'	Start browse

Resource field

Table 22. AP 00EC, DFHDMP trace entries (continued)

Point ID	Byte	Value	Contents
		X'09'	Get next
		X'0A'	End browse
		X'0B'	Create set
		X'0D'	Query set
		X'0F'	Access primary control record
		X'10'	Build KWA
		X'11'	Release KWA
		X'12'	Tokenize key
		X'13'	Free tokens
		X'15'	Generic qualify
		X'16'	Seq ordered set
		X'17'	Verify KWA
		X'63'	Adapter
	Field A, bytes 0-1		Function code
		X'D201'	GETMAIN
		X'D202'	FREEMAIN
		X'D203'	FREEFWA
		X'D204'	Get
		X'D205'	Set browse
		X'D206'	Get next
		X'D207'	Get previous
		X'D208'	End browse
		X'D209'	Put
		X'D20A'	Delete
		X'D20B'	Query CSD
		X'D20C'	Gettime
		X'D20D'	Gettls
		X'D20E'	Wait
		X'D20F'	Load
		X'D210'	Open
		X'D211'	Close
		X'D215'	Freetls
		X'D216'	Unload
	bytes 2-3		Reserved
	Field B		Reserved
	Byte 1, bits 4-7	X'5'	Exit
	Field A, byte 3		Response
		X'00'	Normal response
		X'04'	Warning
		X'08'	Error
		X'0C'	Severe error
		X'0C'	Terminating
	Field B, byte 3		Reason
		X'01'	CSD empty or not initialized
		X'02'	Invalid request
		X'03'	CSD cannot be connected
		X'04'	Set locked to another user
		X'05'	Set is ordered
		X'06'	Set is unordered

Table 22. AP 00EC, DFHDMP trace entries (continued)

Point ID	Byte	Value	Contents
		X'07'	Object not found in CSD
		X'09'	CSD is full
		X'0A'	DMP logic error
		X'0B'	Invalid KWA
		X'0C'	Key invalid in set type
		X'0D'	Key invalid in object type
		X'0E'	Key invalid in set name
		X'0F'	Key invalid in object name
		X'10'	Key invalid in set and object names
		X'11'	Generic in set name
		X'12'	Generic in object name
		X'13'	Generic in set and object names
		X'14'	Set invalid, generic in object name
		X'15'	Object invalid, generic in set name
		X'16'	KWA generic direct, should be alternative
		X'17'	In browse sequence
		X'18'	Getmain failed
		X'19'	After setbrowse with generic set
		X'1A'	After disconnect without updates
		X'1B'	Primary control record overwritten
		X'1C'	FCT entry for CSD disabled
		X'1D'	No more sequence numbers available
		X'1E'	No more RPL threads available
		X'33'	Invalid request returned from adaptor
		X'34'	CICS error
		X'35'	No FCT entry for CSD
		X'36'	Record not found in CSD
		X'37'	Insufficient function in FCP
		X'38'	Insufficient function in FCT
		X'39'	I/O error
		X'3A'	CSD not OPEN
		X'3B'	Illogic returned from FCP
		X'3C'	Invalid flattened parameter list
		X'3F'	DUPREC returned from FCP
		X'46'	Key length of CSD is invalid
		X'47'	Record length of CSD is invalid
		X'48'	CSD is read only

Terminal object resolution

Table 23. AP 00EF, DFHTOR trace entries

Point ID	Byte	Value	Contents
AP 00EF	Byte 1, bits 4-7	X'3'	Entry
DFHTOR	Byte 0	X'01'	Main program
AP Lvl 1	Field A, bytes 0-1		Function code
		X'E301'	Add
		X'E302'	End lcr
		X'E304'	End luw
		X'E305'	End lu6
		X'E314'	End luw commit
		X'E324'	End luw cancel

Resource field

Table 23. AP 00EF, DFHTOR trace entries (continued)

Point ID	Byte	Value	Contents
	bytes 2-3		Reserved
	Field B		Reserved
	Byte 0	X'02'	Add nonpooled terminal
		X'03'	Add pooled terminal
		X'04'	Add TYPETERM
		X'05'	Add connection
		X'06'	Add sessions
		X'07'	End group event 1
		X'08'	End group event 2
		X'09'	DWE commit
		X'0A'	DWE cancel
		X'0B'	Utility 1
		X'0C'	Utility 2
		X'10'	Model retrieval
		X'11'	Create terminal BPS
		X'12'	Recovery program
	Byte 1, bits 4-7	X'5'	Exit
	Field A, byte 3		Response
		X'00'	Normal response
		X'04'	Warning
		X'08'	Error
		X'0C'	Severe error
		X'0C'	Terminating
	Field B, bytes 2-3		Reason
		X'0000'	No error
		X'000D'	Invalid request
		X'00C8'	Start luw
		X'00C9'	Add connection
		X'00CA'	Add pooled terminal
		X'00CB'	Add session
		X'00CC'	Add terminal
		X'00CD'	Add typeterm
		X'00CE'	End lcr
		X'00CF'	End lui
		X'00D0'	End luw cancel
		X'00D1'	End luw commit
		X'0130'	Error

Interval control

Table 24. AP 00F3, DFHICP trace entries

Point ID	Byte	Value	Contents
AP 00F3	Byte 1, bits 4-7	X'3'	Entry
DFHICP	Byte 0	0001 00..	GETIME
IC Lvl 1	Field A		Return time to user address, TCAICDA
	Field B		Reserved

Table 24. AP 00F3, DFHICP trace entries (continued)

Point ID	Byte	Value	Contents
	Byte 0	0001 ...0	Binary format
		0001 ...1	Packed format
		0001 ..0.	Refresh CSA time only
		0001 ..1.	Return time to user
	Byte 0	0010 ...0	WAIT
		0011 ...0	POST
Field A			INTERVAL or TIME value, TCAICRT
Field B			Reserved
	Byte 0	0010 .00.	No request ID provided
		001. .01.	Request ID prefix in TCAICQPX
		001. .10.	Request ID in TCAICQID
		001. 0...	INTERVAL specified
		001. 1...	TIME specified
	Byte 0	0100	INITIATE
		0101	PUT
		0110	INITIATE
		0111	PUT
Field A			INTERVAL or TIME value, TCAICRT
Field B			Reserved
	Byte 0	01.. ...0	Nonterminal dest
		01.. ...1	Terminal dest
		01.. .00.	No request ID supplied
		01.. .01.	Request ID prefix in TCAICQPX
		01.. .10.	Request ID in TCAICQID
		01.. 0...	INTERVAL supplied
01.. 1...	TIME supplied		
	Byte 0	1000 00..	GET
			User-provided data address
			Reserved
	Byte 0	1000 ...1	RELEASE=NO
		1000 ..0.	Data address specified
		1000 ..1.	Return address to user
		1000 1...	WAIT specified
		1001 000.	RETRY
		1001 ...1	RELEASE=NO
	Byte 0	1010 0000	RESET
		1011 0000	SCHEDULE
		1100	EXPIRY ANALYSIS
		1101	RECOVERY CALL
Field A			Reserved
Field B			Reserved
	Byte 0	1110	Use extended function code
			Function
		X'01'	SEARCH
		X'02'	RESUME_GET_WAITS

Resource field

Table 24. AP 00F3, DFHICP trace entries (continued)

Point ID	Byte Field B	Value	Contents
			Reserved
	Byte 0	1111 0.00	CANCEL
		1111 .0..	No request ID provided
		1111 .1..	Request ID specified
	Byte 1, bits 4-7	X'5'	Exit
	Byte 0		Return code
		X'00'	NORESP
		X'01'	ENDDATA
		X'04'	IOERROR
		X'08'	FOUND
		X'11'	TRNIDER
		X'12'	TRMIDER
		X'14'	TSINVLD
		X'20'	EXPIRD
		X'40'	NOT_FOUND (search)
		X'81'	NOTFND
		X'FF'	INVREQ

Temporary storage

Table 25. AP 00F7, DFHTSP trace entries

Point ID	Byte	Value	Contents
AP 00F7	Byte 1	X'03'	Application request
	Byte 0		TCATSTR
		0000 0010	FLUSH
		0010 00..	RELEASE
		010.	PUT
		10.. ..0.	GET
	Fields A and B		Data identification, TCATSDI
	Byte 1	X'13'	Start of DWE logic
		X'23'	Start of cancel logic
	Byte 1	X'05'	Appl response
	Byte 0	X'0'	NORESP
		X'01'	ENERROR
		X'02'	IDERROR
		X'04'	IOERROR
		X'08'	NOSPACE
		X'20'	INVREQ
	Field A		Reserved
	Field B		Reserved
	Byte 1	X'15'	End of DWE logic
	Byte 1	X'25'	End of cancel logic

Basic mapping support

Table 26. AP 00FA, DFHBMS trace entries

Point ID	Byte	Value	Contents	
AP 00FA	Byte 0	X'00'		
BMS	Byte 1, bits 4-7	X'3'	Entry	
BM Lvl 1	Field A, byte 0	X'01'	OPCLASS=operator class	
		X'02'	LIST=symbolic address	
		X'04'	LIST=ALL	
		X'08'	TIME=numeric	
		X'10'	INTERVAL=numeric	
		X'20'	ERRTERM=termid	
		X'40'	ERRTERM=ORIG	
		X'80'	TYPE=ROUTE	
		byte 1	X'01'	TYPE=PURGE
			X'04'	Send partition set
			X'08'	IOTYPE=IMMED
	X'10'		LDC=mnemonic or YES	
	X'20'		REQID=alphanum.	
	X'40'		PROPT=NLEOM	
	X'80'		TITLE=symbolic address	
	byte 2		X'01'	MAPSET=map set name
			X'02'	MSETADR=symbolic address
			X'04'	MAP=map name
		X'08'	CTRL=any 3270 WCC	
		X'10'	CURSOR=number	
		X'20'	TYPE=TEXT	
		X'40'	Receive partition set	
	byte 3	X'80'	TYPE=LAST	
		X'01'	TYPE=IN	
		X'02'	TYPE=ERASE	
		X'04'	TYPE=MAP	
		X'08'	TYPE=WAIT	
		X'10'	MAPADR=symbolic address	
		X'20'	TYPE=SAVE	
		X'40'	DATA=NO	
		X'C0'	DATA=YES	
		Field B, byte 0	X'01'	TYPE=RETURN
	X'02'		TYPE=STORE	
	X'04'		TYPE=OUT	
	X'20'		TYPE=ERASEAUP	
	X'40'		OFLOW=symbolic address	
	X'80'		TYPE=PAGEBLD	
	byte 1		X'01'	EODPURG=OPER
			X'02'	WRBRK=ALL
			X'04'	WRBRK=CURRENT
			X'08'	CTRL=RELEASE
			X'10'	CTRL=RETAIN
			X'20'	CTRL=PAGE
			X'40'	CTRL=AUTOPAGE
X'80'			TYPE=PAGEOUT	
byte 2			X'01'	TYPE=NOEDIT
			X'04'	Active partition

Resource field

Table 26. AP 00FA, DFHBMS trace entries (continued)

Point ID	Byte	Value	Contents
		X'08'	Out partition
		X'10'	JUSTIFY specified
		X'20'	TRAILER=symbolic address
		X'40'	HEADER=symbolic address
		X'80'	TYPE=TEXTBLD
	byte 3	X'01'	Control
		X'04'	WRBRK=symbolic address
		X'08'	RDATT=symbolic address
		X'10'	FMHPARM=YES or parameter
		X'20'	Request by EXEC interface
		X'40'	Magnetic stripe reader
		X'80'	In partition
	Byte 1, bits 4-7	X'5'	Exit
	Field A, byte 0	X'00'	Normal response
		X'01'	Invalid request
		X'02'	Page returned
		X'04'	I/O area cannot be mapped
		X'08'	Map too large
		X'20'	Invalid error terminal
		X'40'	Route worked, some resolutions
		X'80'	Route failed, no resolutions
	byte 1	X'02'	Partition fail
		X'04'	Invalid partition
		X'08'	Invalid partition set
		X'10'	Invalid LDC mnemonic
		X'80'	Temporary storage I/O error
	byte 2	X'01'	PAGEBLD overflow
		X'02'	Inbound FMH in last input
		X'04'	End-of-data-set in last input
		X'08'	End-of-chain in last input
		X'10'	Specified REQID ignored
	byte 3		Terminal code from TCAMSRI1 when byte 0=X'08'
	Field B		Reserved unless field A indicates PAGEBLD overflow when:
	bytes 0-1		Current page number (TCAMSPGN)
	bytes 2-3		Overflow control number (TCAMSOCN)
	Byte 0	X'01'	DFHRLR entry
	Field A		Addr(OSPWA)
	Field B		Addr(TCTTE)

Table 26. AP 00FA, DFHBMS trace entries (continued)

Point ID	Byte	Value	Contents
	Byte 0 Field A Field B	X'02'	DFHPBP entry Addr(TTP) Addr(TIOA)
	Byte 0 Field A Field B	X'03'	DFHM32 entry Addr(TTP) Addr(TIOA)
	Byte 0 Field A Field B	X'04'	DFHML1 entry Addr(TTP) Addr(TIOA)
	Byte 0 Field A Field B	X'05'	DFHDSB entry Addr(TTP) Addr(TIOA)
	Byte 0 Field A Field B	X'06'	DFHTPP entry Addr(TTP) Addr(TIOA)
	Byte 0 Field A Field B	X'07'	DFHIIP entry Addr(TTP) Addr(TIOA)
	Byte 0 Field A Field B	X'41'	DFHRLR exit Addr(OSPWA) Addr(TIOA)
	Byte 0 Field A Field B	X'42'	DFHPBP exit Addr(TTP) Addr(TIOA)
	Byte 0 Field A Field B	X'43'	DFHM32 exit Addr(TTP) Addr(TIOA)
	Byte 0 Field A Field B	X'44'	DFHML1 exit Addr(TTP) Addr(TIOA)
	Byte 0 Field A Field B	X'45'	DFHDSB exit Addr(TTP) Addr(TIOA)
	Byte 0 Field A Field B	X'46'	DFHTPP exit Addr(TTP) Addr(TIOA)
	Byte 0 Field A Field B	X'47'	DFHIIP exit Addr(TTP) Addr(TIOA)
	Byte 0	X'81'	Query entry 1

Resource field

Table 26. AP 00FA, DFHBMS trace entries (continued)

Point ID	Byte	Value	Contents
	Field A, byte 0		TCTE32EF
	byte 1		TCTE32E2
	byte 2		TCTE32E3
	byte 3		TCTE32SF
	Field B, bytes 0-1		TCTEASCZ
	byte 2		TCTEASCL
	byte 3		TCTEASCC
	Byte 0	X'82'	Query entry 2
	Field A, byte 0		TCTETXTF
	byte 1		TCTTEFMB
	bytes 2-3		Reserved
	Field B, bytes 0-1		TCTECSG1
	bytes 2-3		TCTECSG2

Built-in function

Table 27. AP 00FB, DFHEBF trace entries

Point ID	Byte	Value	Contents
AP 00FB	Byte 0	X'02'	DEEDIT
DFHEBF	Field A, bytes 0-1		Field length
BF Lvl 1	bytes 2-3		Reserved
	Field B		Field address

Terminal control

Table 28. AP 00FC, Terminal control

Point ID	Byte	Value	Contents
AP 00FC	Byte 0	X'CA'	DFHTRZCP build terminal BPS
DFHZCP	Field A, bytes 0-1		Response
FC Lvl 1	bytes 2-3		Reason
	Field B, bytes 0-1		BPS_RTC
	bytes 2-3		BPS_SUBTYPE
	Byte 0	X'CB'	DFHTRZXP build connection BPS
	Field A, bytes 0-1		Response
	bytes 2-3		Reason
	Field B, bytes 0-1		BPS_RTC
	bytes 2-3		BPS_SUBTYPE
	Byte 0	X'CC'	DFHTRZIP build sessions BPS
	Field A, bytes 0-1		Response
	bytes 2-3		Reason

Table 28. AP 00FC, Terminal control (continued)

Point ID	Byte	Value	Contents
	Field B, bytes 0-1		BPS_RTC
	bytes 2-3		BPS_SUBTYPE
Byte 0	Field A, bytes 0-1	X'CD'	DFHTRZYP build type BPS Response
	bytes 2-3		Reason
	Field B, bytes 0-1		BPS_RTC
	bytes 2-3		BPS_SUBTYPE
Byte 0	Field A, bytes 0-1	X'CE'	DFHTRZPP build pool BPS Response
	bytes 2-3		Reason
	Field B, bytes 0-1		BPS_RTC
	bytes 2-3		BPS_SUBTYPE
Byte 0	Field A, bytes 0-1	X'CF'	DFHTRZZP merge terminal and type BPS Response
	bytes 2-3		Reason
	Field B, bytes 0-1		BPS_RTC
	bytes 2-3		BPS_SUBTYPE
Byte 0	Field A	X'D3'	DFHZXSTS set logon
	Field B		Reserved
Byte 0	Field A, byte 0	X'D5'	DFHTRCRPS
	byte 1	'S'	Schedule action
		'M'	Give ZXQ0 an error message for display purposes
		0	Response code
		1	XQ0_RSP_NORMAL
		4	XQ0_RSP_SCHEDULE
	Field B		XQ0_RSP_ERROR
			Address of token used to correlate the initiated action and its completion (done by ZNAC)
Byte 0	Field A, byte 0	X'D6'	DFHTRRPC
	byte 1	'S'	Schedule action
		'M'	Give ZXQ0 an error message for display purposes
		0	Response code
		1	XQ0_RSP_NORMAL
		>4	XQ0_RSP_SCHEDULE
	Field B		Error code returned by ZCP RECOVER
			Address of token used to correlate the initiated action and its completion (done by ZNAC)

Resource field

Table 28. AP 00FC, Terminal control (continued)

Point ID	Byte	Value	Contents
	Byte 0	X'D7'	DFHZXRE0 valid on the return/exit trace
	Field A, byte 0		Passnumber
	byte 1		Number of unbound entries
	byte 2		Number of standby-bound entries
	byte 3		Number with TCTEXRE set in error
	Field B		Address of last TCTTE processed if error
	Byte 0	X'D8'	DFHZXQ0 exit trace
	Field A, byte 0		XQ0-REQCODE
		'I'	Initialize
		'A'	Add action
		'P'	Post
		'D'	Drain
	bytes 2-3		XQ0-RESPONSE
		0	Complete
		1	Scheduled
		3	Queued
		4	GMU
		8	Invreq
	Field B		Addr(action)
	Byte 0	X'D9'	DFHZXST exit trace
	Field A, byte 0	X'00'	BIND complete in active
		X'01'	Logon data free in active
		X'02'	UNBIND complete in active
		X'03'	BOUND catch-up in active
		X'05'	UNBOUND catch-up in active
	Field B		Addr(TCTTE)
	Field A, byte 0	X'FC'	Set logon start and modify USERVAR
	Field A, byte 0	X'FD'	Drain session tracking and modify USERVAR
	Field B		Reserved
	Field A, byte 0	X'FE'	REQCODE session tracking in alternate
	byte 1		RESPCODE
		X'0'	Complete
		X'1'	Scheduled
		X'4'	Error
	byte 2		XTR-ST-REQUEST
		X'1'	BIND
		X'2'	Free LOGON data
		X'3'	UNBIND
	byte 3		XTR-ST-FLAGS-1
		1... ..	XRF-capable
	Field B		XTR-XT-SESS-NAME netname

Table 28. AP 00FC, Terminal control (continued)

Point ID	Byte	Value	Contents
	Field A, byte 0	X'FF'	Action complete in alternate
	Field B		Addr(TCTTE)
	Byte 0	X'DA'	DFHZXTR put/get header
		X'DB'	DFHZXTR put/get key
		X'DC'	DFHZXTR put/get data
	Field A, bytes 0-1	X'0000'	Normal
		X'0401'	XRF inactive
		X'0402'	End of data
		X'0403'	Backup signed off
		X'0801'	Invalid request
		X'0802'	Service closed
		X'0803'	Task canceled
		X'0804'	Length error
		X'0805'	Overlap
		X'0806'	No destination
		X'0807'	Queue busy
		X'0808'	Program check
		X'0809'	Abend
		X'080A'	I/O error
		X'080B'	Format error
		X'080C'	Sequence number error
		X'080D'	System not active
	bytes 2-3		Data length
	Field B, bytes 0-1		Record ID
	byte 2		Type
		X'C3'	Contents
		X'E2'	Status
	byte 3		Request ID
		X'01'	Put message
		X'02'	Get message
		X'03'	Put request
		X'02'	Put response

Trace control

Table 29. AP 00FE, trace control

Point ID	Byte	Value	Contents
AP 00FE	Byte 1, bits 4-7	X'D'	On/off entry
Trace turned on	Byte 0		Reserved
	Byte 1, bits 0-3	X'0'	
	Field A		Images before trace request as follows:
	byte 8		CSATRMF1
	byte 9		CSATRMF2
	byte 10		CSATRMF3
	byte 11		CSATRMF4

Resource field

Table 29. AP 00FE, trace control (continued)

Point ID	Byte	Value	Contents
	Field B		Images before trace request as follows:
	byte 12		TCATRTR
	byte 13		TCATRID
	byte 14		TCATRMF
	byte 15		TCATRID1
	Byte 1, bits 0-3	X'1'	
	Field A		Images before trace request as follows:
	byte 8		CSATRMF1
	byte 9		CSATRMF2
	byte 10		CSATRMF3
	byte 11		CSATRMF4
	Field B		Images after trace request as follows:
	byte 12		CSATRMF1
	byte 13		CSATRMF2
	byte 14		CSATRMF3
	byte 15		CSATRMF4

Table 30. AP 00FF, trace control

Point ID	Byte	Value	Contents
AP 00FF	Bytes 0 thru 14		As for X'FE'
	Trace turned off		

Chapter 2. Domain trace points

AP domain trace points – ‘new style’

XPI trace put

Trace point IDs in the range AP 0100 through AP 01FF are reserved for users of the XPI TRACE PUT function.

Trace points in common subroutines

Table 31. Trace points in common subroutines

Point ID	Module	Lvl	Type	Data	
** FF00	DFHSUWT	** 1	Entry	1	SUWT parameter list
** FF01	DFHSUWT	** 1	Exit	1	SUWT parameter list
** FF02	DFHSUWT	** 1	Before WTO MVS SVC call	1 2	WTO parameter WTO extension (WPX)
** FF03	DFHSUWT	** 1	After WTO MVS SVC call	1 2	WTO parameter list WTO extension (WPX)
** FF04	DFHSUWT	** 1	Before WTOR MVS SVC call	1	WTOR parameter list
** FF05	DFHSUWT	** 1	After WTOR MVS SVC call	1	WTOR parameter list
** FF06	DFHSUWT	Exc	WTO operator message exceeded maximum length	1	SUWT parameter list
** FF07	DFHSUWT	Exc	WTOR operator message exceeded maximum length	1	SUWT parameter list
** FF08	DFHSUWT	Exc	Reply area not allocated	1	SUWT parameter list
** FF09	DFHSUWT	Exc	DS call error	1	DSSR parameter list
** FF0A	DFHSUWT	Exc	Unformatted message	1	SUWT parameter list
** FF0B	DFHSUWT	Exc	Invalid route code	1	SUWT parameter list
** FF0C	DFHSUWT	Exc	Invalid descriptor code	1	SUWT parameter list
** FF0D	DFHSUWT	Exc	Line formatting error	1	SUWT parameter list
** FF0F	DFHSUWT	Exc	Recovery	1 2 3	SUWT parameter list Kernel error data WTO parameter list
** FF30	SUME	** 1	Entry	1	SUME parameter list
** FF31	SUME	** 1	Exit	1	SUME parameter list
** FF32	SUME	Exc	Invalid format	1	SUME parameter list
** FF33	SUME	Exc	Invalid function	1	SUME parameter list

Table 31. Trace points in common subroutines (continued)

Point ID	Module	Lvl	Type	Data	
** FF34	SUME	Exc	Missing message	1	SUME parameter list
** FF35	MEFO	** 1	Entry	1	MEFO parameter list
** FF36	MEFO	** 1	Exit	1	MEFO parameter list
** FF37	MEFO	Exc	Invalid DBCS format	1	MEFO parameter list
** FF38	MEFO	Exc	Invalid input string	1	MEFO parameter list
** FF39	MEFO	Exc	Emergency format used	1	MEFO parameter list
** FF40	MEWS	** 1	Entry	1	CDURUN parameter list
** FF41	MEWS	** 1	Exit	1	CDURUN parameter list
** FF42	MEWS	Exc	Invalid format	1	CDURUN parameter list
** FF43	MEWS	Exc	Invalid function	1	CDURUN parameter list
** FF44	MEWS	** 2	Good return from SYMREC	1 2 3	Symptom record Return code Reason code
** FF45	MEWS	Exc	Bad return from SYMREC	1 2 3	Symptom record Return code Reason code
** FF50	NQIE	** 1	Entry	1	NQIQ parameter list
** FF51	NQIE	** 1	Exit	1	NQIQ parameter list
** FF52	NQIE	Exc	Recovery	1 2	NQIQ parameter list Kernel error data
** FF53	NQIE	Exc	Invalid format	1	Invalid parameter list
** FF54	NQIE	Exc	Invalid function	1	NQIQ parameter list
** FF55	NQIE	Exc	Invalid pool token	1 2	NQIQ parameter list Storage addressed by token
** FF56	NQIE	Exc	Invalid enqueue	1 2	NQIE parameter list NQPL control block

Note: ** Component is either AP, ME, or LM

DBCTL and DL/I trace points

Table 32. DBCTL and DL/I trace points

Point ID	Module	Lvl	Type	Data	
AP 0302	DFHDLIDP	FC 2	Before RMCALL to DBCTL	1	DSB parameter list
AP 0303	DFHDLIDP	FC 2	After RMCALL to DBCTL	1	DSB parameter list

Table 32. DBCTL and DL/I trace points (continued)

Point ID	Module	Lvl	Type	Data	
AP 0304	DFHDBSPX	FC 1	DFHDBSPX about to wait	1	DSB request type
AP 0305	DFHDBSPX	FC 1	DFHDBSPX has been posted	1 2	DSB request type TCADLII
AP 0306	DFHDBCT	FC 1	DFHDBCT has been posted	1	Control work area chain
AP 030E	DFHDXCT	FC 1	DBCT XRF message put	1	Message text
AP 030F	DFHDBCR	FC 1	Message received from XRF active	1 2 3	Return code Reason code Message data
AP 0310	DFHDBAT	FC 2	Entry	1	ERM request type
AP 0311	DFHDBAT	FC 1	Before invoking DRA thread request	1 2	Recovery token DRA request type
AP 0312	DFHDBAT	FC 1	After invoking DRA thread request	1 2	Recovery token DRA return code
AP 0313	DFHDBAT	FC 2	Exit	1	DFHDBAT response code (R15)
AP 0314	DFHDBAT	FC 1	After loading router	1	LOAD response code (R15)
AP 0315	DFHDBAT	FC 1	Before invoking DRA interface request	1	DRA request type
AP 0316	DFHDBAT	FC 1	After invoking DRA interface request	1	DRA return code
AP 0320	DFHDXSTM	FC 1	Entry	1	DXSTM parameter list
AP 0321	DFHDXSTM	FC 1	Exit	1	DXSTM parameter list
AP 0322	DFHDXSTM	FC 2	MVS subtask attach	1 2	Queue element Subtask storage
AP 0323	DFHDXSTM	FC 2	MVS subtask detach	1 2	Queue element Subtask storage
AP 0324	DFHDXSTM	FC 2	MVS subtask retrieve	1 2	DXSTM parameter list Returned parameters
AP 0325	DFHDBREX	RI 2	DFHDBREX has posted ECB	1	DFHDSB (without fields DSBMONI and DSBGTRACE)

Table 32. DBCTL and DL/I trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 0328	DFHDLI	FC 1	Entry	<p>Data</p> <p>1 DL/I 4-character function code</p> <p>2 If data1 'PCB ', Addr(PSB) If data1 'TERM' or 'T', Reserved If data1 database access call, Addr(PCB) If data1 AIB format call, Addr(AIB)</p> <p>3 8 bytes of data at data2 address</p>
AP 0329	DFHDLI	FC 1	Exit	<p>PCB format</p> <p>1 UIB return codes (TCADLRC and TCADLTR) shown as 4 hex characters</p> <p>2 DL/I status code, 2 characters (if any). Non-alphameric values are printed as 4 hexadecimal characters. If the UIB return code is 0805 (that is, the response code is 'PSB schedule failure') and the PSB is local to this CICS system, the DL/I status code is the PSTSCHDF field from the IMS™ PST control block.</p> <p>3 DL/I function code 4 characters</p> <p>AIB Format</p> <p>1 AIB return code shown as 8 hex chars.</p> <p>1 AIB reason code shown as 8 hex chars.</p> <p>3 UIB return codes (TCADLRC and TCADLTR) shown as 4 hex characters</p> <p>4 DL/I status code, 2 characters (if any). Non-alphameric characters are printed as 4 hexadecimal characters.</p> <p>5 DL/I function code 4 characters</p>
AP 0330	DFHDLIDP	FC 1	Entry	
AP 0331	DFHDLIDP	FC 1	Exit	2 Address of ECB
AP 0348	DFHDLIRP	FC 1	Entry	
AP 0349	DFHDLIRP	FC 1	Exit	

File control

Table 33. File control trace points

Point ID	Module	Lvl	Type	Data
AP 0400	DFHAFMT	FC 1	Entry	1 AFMT parameter list

Table 33. File control trace points (continued)

Point ID	Module	Lvl	Type	Data	
AP 0401	DFHAFMT	FC 1	Exit	1	AFMT parameter list
AP 0402	DFHAFMT	FC 2	Exit	1	FCT entry
AP 0403	DFHAFMT	Exc	Invalid response	1 2	AFMT parameter list Reason for error
AP 0404	DFHAFMT	Exc	Recovery	1 2	AFMT parameter list Kernel error data
AP 0410	DFHFCMT	FC 1	Entry	1	FCMT parameter list
AP 0411	DFHFCMT	FC 1	Exit	1	FCMT parameter list
AP 0412	DFHFCMT	FC 2	Exit	1	FCT entry
AP 0413	DFHFCMT	Exc	Invalid response	1 2	FCMT parameter list Reason for error
AP 0414	DFHFCMT	Exc	Recovery	1 2	FCMT parameter list Kernel error data
AP 0415	DFHFCMT	Exc	Purged	1	FCMT parameter list
AP 0418	DFHFCNQ	FC 1	Entry	1	Parameter list (FCCA, NQNQ)
AP 0419	DFHFCNQ	FC 1	Exit	1	Parameter list (FCCA, NQNQ)
AP 041A	DFHFCNQ	Exc	Invalid format	1	Parameter list
AP 041B	DFHFCNQ	Exc	Invalid function	1	Parameter list
AP 041C	DFHFCNQ	Exc	Recovery	1	Parameter list
AP 041D	DFHFCNQ	Exc	Unrecognized pool name	1	NQNQ parameter list
AP 041E	DFHFCNQ	Exc	Short queue name	1	NQNQ parameter list
AP 0420	DFHFCRL	FC 1	Entry	1	FCRL parameter list
AP 0421	DFHFCRL	FC 1	Exit	1	FCRL parameter list
AP 0422	DFHFCRL	FC 2	Exit	1	SHRCTL block
AP 0423	DFHFCRL	Exc	Invalid response	1 2	FCRL parameter list Reason for error
AP 0424	DFHFCRL	Exc	Recovery	1 2	FCRL parameter list Kernel error data
AP 0428	DFHFCDTS	FC 1	Entry	1	FCDTS parameter list
AP 0429	DFHFCDTS	FC 1	Exit	1	FCDTS parameter list

Table 33. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 042A	DFHFCDTS	Exc	Shared data tables service failed	1 FCDTS parameter list 2 DFHDTPPS plist
AP 042B	DFHFCDTS	Exc	Invalid response	1 FCDTS parameter list 2 Reason for error
AP 042C	DFHFCDTS	Exc	Recovery	1 FCDTS parameter list 2 Kernel error data
AP 042E	DFHFCDTS	Exc	Purged	1 FCDTS parameter list
AP 0430	DFHFCST	FC 1	Entry	1 FCST parameter list
AP 0431	DFHFCST	FC 1	Exit	1 FCST parameter list
AP 0432	DFHFCST	FC 2	Exit	1 FCT entry
AP 0433	DFHFCST	Exc	Invalid response	1 FCST parameter list
AP 0434	DFHFCST	Exc	Recovery	1 FCST parameter list
AP 0435	DFHFCST	Exc	Disaster	1 FCST parameter list
AP 0436	DFHFCST	Exc	Purged	1 FCST parameter list
AP 0437	DFHFCST	Exc	No LSR pools	1 FCST parameter list
AP 0438	DFHFCST	Exc	Pool not built	1 FCST parameter list 2 Kernel error data
AP 0440	DFHFCDN	FC 1	Entry	1 FCDN parameter list
AP 0441	DFHFCDN	FC 1	Exit	1 FCDN parameter list
AP 0442	DFHFCDN	FC 2	Exit	1 DSNB entry
AP 0443	DFHFCDN	Exc	Invalid response	1 FCDN parameter list
AP 0444	DFHFCDN	Exc	Recovery	1 FCDN parameter list 2 Kernel error data
AP 0445	DFHFCDN	Exc	Disaster	1 FCDN parameter list
AP 0446	DFHFCDN	Exc	Purged	1 FCDN parameter list
AP 0447	DFHFCDN	Exc	Exception	1 FCDN parameter list
AP 0448	DFHFCDTX	FC 1	Entry	1 FCDTX parameter list
AP 0449	DFHFCDTX	FC 1	Exit	1 FCDTX parameter list
AP 044B	DFHFCDTX	Exc	Invalid response	1 FCDTX parameter list 2 Reason for error

Table 33. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 044C	DFHFCDTX	Exc	Recovery	1 FCDTX parameter list 2 Kernel error data
AP 044E	DFHFCDTX	Exc	Purged	1 FCDTX parameter list
AP 0470	DFHFCFS	FC 1	Entry	1 FCFS parameter list
AP 0471	DFHFCFS	FC 1	Exit	1 FCFS parameter list
AP 0472	DFHFCFS	FC 2	Exit	1 FCT entry
AP 0473	DFHFCFS	Exc	Invalid response	1 FCFS parameter list
AP 0474	DFHFCFS	Exc	Recovery	1 FCFS parameter list 2 Kernel error data
AP 0475	DFHFCFS	Exc	Disaster	1 FCFS parameter list
AP 0476	DFHFCFS	Exc	Purged	1 FCFS parameter list
AP 0477	DFHFCFS	Exc	DFHFCQI call failure	1 FCFS parameter list 2 FCQI parameter list
AP 0478	DFHFCFS	FC 1	Quiesce suppressed by XFCSREQ	1 FCFS parameter list 2 Dataset name
AP 0480	DFHFICRP	FC 1	Entry	1 FICRP parameter list
AP 0481	DFHFICRP	FC 1	Exit	1 FICRP parameter list
AP 0482	DFHFICRP	FC 2	Exit	1 FICRP parameter list
AP 0483	DFHFICRP	Exc	Invalid response	1 FICRP parameter list
AP 0484	DFHFICRP	Exc	Recovery	1 FICRP parameter list 2 Kernel error data
AP 0485	DFHFICRP	Exc	Disaster	1 FICRP parameter list
AP 0486	DFHFICRP	Exc	FC TE missing in catalog	1 FICRP parameter list
AP 0487	DFHFICRP	Exc	FC system transaction definition error	1 FICRP parameter list 2 XMXD parameter list
AP 0488	DFHFICRP	Exc	FC program definition error	1 FICRP parameter list 2 PGDD parameter list
AP 0489	DFHFICRP	Exc	DFHXMAT call failure	1 FICRP parameter list 2 XMAT parameter list
AP 048A	DFHFICRP	Exc	Program link to DFHRCEX error	1 FICRP parameter list 2 PGLE parameter list
AP 048B	DFHFICRP	Exc	RM set gate error	1 FICRP parameter list 2 RMCD parameter list

Table 33. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 048C	DFHFICRP	Exc	Domain manager listen request error	1 FICRP parameter list 2 DMEN parameter list
AP 048D	DFHFICRP	Exc	Unknown data set in catalogued FLLB entry	1 FICRP parameter list
AP 048E	DFHFICRP	Exc	Table manager locate DSNB failed	1 FICRP parameter list 2 Table manager return code
AP 0492	DFHFICVR	FC 2	Before VSAM call	1 RPL 2 Address of RPL
AP 0493	DFHFICVR	FC 2	After VSAM call	1 RPL 2 Address of RPL
AP 0494	DFHFICVR	Exc	Disaster	
AP 0495	DFHFICVR	Exc	Recovery	1 FCWSV parameter block 2 Kernel error data
AP 0496	DFHFICVR	Exc	Purged	
AP 04B0	DFHFICVS	FC 1	Entry	1 FICFR parameter list 2 File name. Level-2 trace is on
AP 04B1	DFHFICVS	FC 1	Exit	1 FICFR parameter list 2 File name
AP 04B2	DFHFICVS	FC 2	Exit	1 FICFR parameter list
AP 04B3	DFHFICVS	Exc	Invalid request	1 FICFR parameter list
AP 04B4	DFHFICVS	Exc	Recovery	1 FICFR parameter list 2 Kernel error data
AP 04B6	DFHFICVS	Exc	Purged	
AP 04B7	DFHFICVS	Exc	Nonzero VSAM return code	1 FICFR parameter list 2 RPL 3 RPL address 4 File name 5 Transaction name
AP 04B8	DFHFICVS	Exc	Deadlock detected	1 FICFR parameter list 2 VSWA of this task 3 Information about conflicting task: RPL address, task number, task name and FCT name 4 VSWA of conflicting task 5 FRAB involved in conflict 6 Freemained FRTE

Table 33. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 04B9	DFHFCVS	Exc	Self deadlock detected	1 FCFR parameter list 2 VSWA of this task 3 Information about conflicting task: RPL address, task number, task name and FCT name 4 VSWA of conflicting task 5 FRAB involved in conflict 6 Freemained FRTE
AP 04BA	DFHFCVS	Exc	Wait for exclusive control	1 FCFR parameter list 3 Information about conflicting task: RPL address, task number, task name and FCT name
AP 04C0	DFHFCL	FC 1	BUILD pool	1 Pool number
AP 04C1	DFHFCL	FC 1	DELETE pool	1 Pool number
AP 04C2	DFHFCL	Exc	Invalid request	1 Pool number
AP 04C3	DFHFCL	FC 1	Normal exit	1 Pool number
AP 04C4	DFHFCL	FC 1	Warning exit	1 Pool number
AP 04C5	DFHFCL	FC 1	Error exit	1 Pool number
AP 04C6	DFHFCL	FC 1	OPEN entry	
AP 04C7	DFHFCL	FC 1	CLOSE entry	
AP 04C8	DFHFCL	FC 1	Invalid request	
AP 04C9	DFHFCL	FC 1	Normal exit	
AP 04CA	DFHFCL	FC 1	Warning exit	
AP 04CB	DFHFCL	FC 1	Error exit	
AP 04CC	DFHFCL	FC 1	Disaster exit	
AP 04CD	DFHFCL	Exc	Disaster	
AP 04CE	DFHFCL	FC 1	OPEN entry	1 File name
AP 04CF	DFHFCL	FC 1	CLOSE entry	1 File name
AP 04D0	DFHFCL	FC 1	Invalid request	1 File name
AP 04D1	DFHFCL	FC 1	Normal exit	1 File name
AP 04D2	DFHFCL	FC 1	Warning exit	1 File name
AP 04D3	DFHFCL	FC 1	Error exit	1 File name
AP 04D4	DFHFCL	FC 1	Disaster exit	1 File name
AP 04D5	DFHFCL	Exc	Disaster	
AP 04D6	DFHFCL	FC 1	Dispatcher error ACB. GETMAIN detected	

Table 33. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 04D7	DFHFCL	Exc	VSAM error	1 Name of VSAM macro 2 VSAM rc from register 15 3 VSAM rc from reg 0 if macro is LOCATE 4 VSAM rc from reg 1 if macro is LOCATE
AP 04D9	DFHFCL	FC 1	Dispatcher error	
AP 04DA	DFHFVCR	FC 2	Enter UPAD	1 VSAM parameter list 2 VSWA address
AP 04DB	DFHFVCR	FC 2	Exit UPAD	1 VSAM parameter list 2 VSWA address
AP 04E0	DFHFVCR	FC 1	Entry	1 VSWA address
AP 04E1	DFHFVCR	FC 1	Exit	1 VSWA address
AP 04E2	DFHFVCR	FC 2	Exit	1 VSWA address
AP 04E3	DFHFVCR	Exc	Invalid request	1 VSWA address
AP 04E4	DFHFVCR	Exc	Recovery	1 VSWA address 2 Kernel error data
AP 04E5	DFHFVCR	Exc	Disaster	1 VSWA address
AP 04E6	DFHFVCR	Exc	Purged	1 VSWA address
AP 04E7	DFHFVCR	Exc	Recoverable request made when file control restart has failed	1 VSWA address
AP 04F0	DFHEIFC	FC 2	Entry	1 EIEI parameter list 2 EIB
AP 04F1	DFHEIFC	FC 2	Exit	1 EIEI parameter list 2 EIB
AP 04F2	DFHEIFC	Exc	Invalid request	1 EIEI parameter list
AP 04F7	DFHEIFC	Exc	Dispatcher call failed	1 EIEI parameter list 2 DSSR parameter list
AP 04F8	DFHEFRM	FC 1	Entry	1 Parameter list (RMRO, RMKP, RMDE)
AP 04F9	DFHEFRM	FC 1	Exit	1 Parameter list (RMRO, RMKP, RMDE)
AP 04FA	DFHEFRM	Exc	Invalid	1 Parameter list
AP 04FB	DFHEFRM	Exc	Recovery	1 Parameter list 2 Kernel error data

Note: For more file control trace entries, see “File control” on page 58 and “File control” on page 197.

Transaction manager

The following table shows trace entries that support the transaction manager.

Table 34. AP domain trace entries for transaction manager

Point ID	Module	Lvl	Type	Data
AP 0518	DFHXFRM	IS 1	Entry	1 Parameter list (RMRO, RMKP, RMDE)
AP 0519	DFHXFRM	IS 1	Exit	1 Parameter list (RMRO, RMKP, RMDE)
AP 051A	DFHXFRM	Exc	Recovery	1 Parameter list 2 Kernel error data
AP 0581	DFHAPSI	AP 1	Entry	1 None
AP 0582	DFHAPSI	AP 1	Exit	1 None
AP 0583	DFHAPSI	Exc	Add subpool failure	1 DFHSMAD_ARG
AP 0584	DFHAPSI	Exc	GETMAIN failure	1 DFHSMGF_ARG
AP 0585	DFHAPSI	Exc	Define program failure	1 DFHLDLD_ARG
AP 0586	DFHAPSI	Exc	Acquire program failure	1 DFHLDLD_ARG
AP 0587	DFHAPSI	Exc	Add gate failure	1 DFHKEDD_ARG
AP 0588	DFHAPSI	Exc	Add trandef failure	1 DFHXMxD_ARG
AP 0589	DFHAPSI	Exc	Abend	1 Kernel error data
AP 058A	DFHAPSI	Exc	Wait phase failure	1 DFHDMDM_ARG
AP 058B	DFHAPSI	Exc	Add program failure	1 DFHPGDD_ARG
AP 058C	DFHAPSI	Exc	RM register fail	1 RMCD parameter list
AP 0590	DFHAPXM	AP 1	Entry	1 DFHAPXM_ARG
AP 0591	DFHAPXM	AP 1	Exit	1 DFHAPXM_ARG
AP 0592	DFHAPXM	Exc	Recovery	1 DFHAPXM_ARG 2 Kernel error data
AP 0593	DFHAPXM	Exc	Invalid format	1 DFHAPXM_ARG
AP 0594	DFHAPXM	Exc	Invalid function	1 DFHAPXM_ARG
AP 0595	DFHAPXM	Exc	TCA GETMAIN failure	1 DFHSMGF_ARG
AP 0596	DFHAPXM	Exc	User GETMAIN failure	1 DFHSMGF_ARG
AP 0597	DFHAPXM	Exc	TCA FREEMAIN failure	1 DFHSMGF_ARG
AP 0598	DFHAPXM	Exc	UOWAT FREEMAIN failure	1 DFHSMGF_ARG

Table 34. AP domain trace entries for transaction manager (continued)

Point ID	Module	Lvl	Type	Data	
AP 0599	DFHAPXM	AP 1	Dump control block to trace	1	DFHSMGF_ARG
AP 059A	DFHAPXM	Exc	GETMAIN failure	1	TCA
AP 059B	DFHAPXM	Exc	LE/370 GETMAIN failure	1	DFHSMGF_ARG
AP 05A8	DFHAPRC	SP 1	Entry	1	Parameter list (RMRO, RMKP, RMDE, ROIN)
AP 05A9	DFHAPRC	SP 1	Exit	1	Parameter list (RMRO, RMKP, RMDE, ROIN)
AP 05AA	DFHAPRC	Exc	Recovery	1 2	Parameter list Kernel error data
AP 05AB	DFHAPRC	Exc	Invalid format	1	Parameter list
AP 05AC	DFHAPRC	Exc	Invalid function	1	Parameter list
AP 05B0	DFHTDXM	AP 1	Entry	1	DFHTDXM_ARG
AP 05B1	DFHTDXM	AP 1	Exit	1	DFHTDXM_ARG
AP 05B2	DFHTDXM	Exc	Recovery	1 2	DFHTDXM_ARG Kernel error data
AP 05B3	DFHTDXM	Exc	Invalid format	1	None
AP 05B4	DFHTDXM	Exc	Invalid function	1	None
AP 05B5	DFHTDXM	Exc	Invalid environment	1	None
AP 05B6	DFHTDXM	Exc	XMIQ failure	1	DFHXMIQ_ARG
AP 05B7	DFHTDXM	Exc	XMAT failure	1	DFHXMAT_ARG
AP 05B8	DFHTDXM	Exc	Unexpected USXM failure	1	USXM parameter list
AP 05C0	DFHICXM	AP 1	Entry	1	DFHICXM_ARG
AP 05C1	DFHICXM	AP 1	Exit	1	DFHICXM_ARG
AP 05C2	DFHICXM	Exc	Recovery	1 2	DFHICXM_ARG Kernel error data
AP 05C3	DFHICXM	Exc	Invalid format	1	None
AP 05C4	DFHICXM	Exc	Invalid function	1	None
AP 05C5	DFHICXM	Exc	Invalid environment	1	None
AP 05C6	DFHICXM	Exc	XMIQ failure	1	DFHXMIQ_ARG
AP 05C7	DFHICXM	Exc	XMAT failure	1	DFHXMAT_ARG

Table 34. AP domain trace entries for transaction manager (continued)

Point ID	Module	Lvl	Type	Data
AP 05C8	DFHICXM	Exc	SMGF failure	1 DFHSMGF_ARG
AP 05C9	DFHICXM	Exc	Unexpected USXM failure	1 USXM parameter list
AP 05CA	DFHICXM	Exc	Unexpected USAD failure	1 USAD parameter list
AP 05D0	DFHAPNT	AP 1	Entry	1 DFHXMNT_ARG
AP 05D1	DFHAPNT	AP 1	Exit	1 DFHXMNT_ARG
AP 05D2	DFHAPNT	Exc	Recovery	1 DFHXMNT_ARG 2 Kernel error data
AP 05D3	DFHAPNT	Exc	Invalid format	1 None
AP 05D8	DFHAPDN	AP 1	Entry	1 DFHXMDN_ARG
AP 05D9	DFHAPDN	AP 1	Exit	1 DFHXMDN_ARG
AP 05DA	DFHAPDN	Exc	Recovery	1 DFHXMDN_ARG 2 Kernel error data
AP 05DB	DFHAPDN	Exc	Invalid format	1 None
AP 05DC	DFHAPDN	AP 2	Before token	1 DFHAPXDC
AP 05DD	DFHAPDN	AP 2	After token	1 DFHAPXDC
AP 05DE	DFHAPDN	Exc	SMGF failure	1 DFHSMGF_ARG
AP 05DF	DFHAPDN	Exc	KCSC failure	1 DFHKCSC_ARG
AP 05E0	DFHAPATT	AP 1	Entry	1 None
AP 05E1	DFHAPATT	AP 1	Exit	1 None
AP 05E7	DFHMIRS	Exc	Recovery	1 Kernel error data
AP 05E8	DFHAPXME	AP 1	Entry	1 DFHXMER_ARG if error occurs during transaction initialization, or 1 DFHXMPP_ARG if force purge request is issued
AP 05E9	DFHAPXME	AP 1	Exit	1 DFHXMER_ARG if error occurs during transaction initialization, or 1 DFHXMPP_ARG if force purge request is issued
AP 05EA	DFHAPXME	Exc	Invalid format	1 CDURUN input parameter list
AP 05EB	DFHAPXME	Exc	Invalid function	1 CDURUN input parameter list

Table 34. AP domain trace entries for transaction manager (continued)

Point ID	Module	Lvl	Type	Data
AP 05EC	DFHAPXME	Exc	Invalid message	1 DFHXMER_ARG
AP 05ED	DFHAPXME	Exc	Recovery	1 CDURUN input parameter list 2 Kernel error data
AP 05EF	DFHAPXME	Exc	PGLK error	1 DFHPGLK_ARG

Transaction attach

Table 35. Transaction attach trace points

Point ID	Module	Lvl	Type	Data
AP 0651	DFHALXM	AP 1	Entry	1 ALXM parameter list
AP 0652	DFHALXM	AP 1	Exit	1 ALXM parameter list
AP 0653	DFHALXM	Exc	Recovery	1 ALXM parameter list
AP 0654	DFHALXM	Exc	Invalid format	1 None
AP 0655	DFHALXM	Exc	Invalid function	1 None
AP 0656	DFHALXM	Exc	RMWT failure	1 None

JAVA/IIOF

Table 36. JAVA/IIOF trace points

Point ID	Module	Lvl	Type	Data
AP 0680	DFHIIOP	AP 1	Data	1 Session token
AP 0681	DFHIIOP	AP 2	Data	1 First 32 bytes of COMMAREA
AP 0682	DFHIIOP	AP 1	Data	1 Record length 2 First 16 bytes of message
AP 0683	DFHIIOP	AAP 1	Data	1 RQM pattern
AP 0686	DFHIIOP	Exc	Exc	1 Pointer to shared memory 2 Program name 3 Program status word
AP 0687	DFHIIOP	AP 1	Data	1 XMAT request block
AP 0690	DFHIPXM	Exc	Invalid function	None
AP 0691	DFHIPXM	Exc	USAD failure	1 USAD parameter list
AP 0692	DFHIPXM	Exc	USXM failure	1 USXM parameter list
AP 0693	DFHIPXM	AP 1	Entry	1 IPXM parameter list
AP 0694	DFHIPXM	Exc	Invalid format	None
AP 0695	DFHIPXM	AP 1	Exit	1 IPXM parameter list

Table 36. JAVA/IIO trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 0696	DFHIPXM	Exc	Invalid environment	None
AP 0697	DFHIPXM	Exc	Recovery	1 XMAC parameter list 2 Kernel error data

AP domain recovery

Table 37. System recovery trace points

Point ID	Module	Lvl	Type	Data
AP 0701	DFHSRLI	AP 2	Entry	1 SRLI parameter list
AP 0702	DFHSRLI	AP 2	Exit	1 SRLI parameter list
AP 0741	DFHABAB	AP 1	Entry	1 ABAB parameter list
AP 0742	DFHABAB	AP 1	Exit	1 ABAB parameter list
AP 0743	DFHABAB	Exc	Recovery	1 ABAB parameter list 2 Kernel error data
AP 0744	DFHABAB	Exc	Invalid format	1 ABAB parameter list
AP 0745	DFHABAB	Exc	Invalid function	1 ABAB parameter list
AP 0779	DFHSRP	Exc	Abend AEYD	1 Application program name 2 Parameter address 3 ARG0
AP 0780	DFHSRP	Exc	Recovery	1 Kernel error data
AP 0781	DFHSRP	Exc	ASRA abend	1 TCASRDAT ¹ 2 TCAPCSTG ² 3 Kernel error data
AP 0782	DFHSRP	Exc	ASRB abend	1 TCASRDAT ¹ 2 TCAPCSTG ² 3 Kernel error data
AP 0783	DFHSRP	Exc	ASRD abend	1 TCASRDAT ¹ 2 TCAPCSTG ² 3 Kernel error data
AP 0790	DFHSRP	Exc	Program check	1 Kernel error data
AP 0791	DFHSRP	Exc	Operating system abend	1 Kernel error data
AP 0792	DFHSRP	Exc	Runaway task	1 Kernel error data
AP 0793	DFHSRP	Exc	Linkage error	1 Kernel error data
AP 0794	DFHSRP	Exc	Kernel error	1 Kernel error data
AP 0795	DFHSRP	Exc	Error requested	1 Kernel error data

Table 37. System recovery trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 0796	DFHSRP	Exc	Error percolate	1 Kernel error data
AP 0797	DFHSRP	Exc	Error abend requested	1 Kernel error data
AP 0798	DFHSRP	Exc	Error abend percolate	1 Kernel error data
AP 0799	DFHSRP	Exc	Other	1 Kernel error data
AP 079A	DFHSRP	Exc	Deferred abend	1 Kernel error data

Notes:

1. TCASRDAT contains:
 - a. Name of abended program
 - b. Kernel error code
 - c. Abend offset in program
 - d. Flags
2. TCAPCSTG contains indicator of storage hit.

LU6.2 transaction routing

Table 38. LU6.2 transaction routing

Point ID	Module	Lvl	Type	Data
AP 0800	DFHZXRL	IS 1	Entry	1 LUC parameter list
AP 0801	DFHZXRL	IS 2	Subroutine entry	
AP 0802	DFHZXRL	IS 2	Subroutine entry	
AP 080F	DFHZXRL	IS 1	Exit	1 LUC parameter list
AP 0810	DFHZXRL	Exc	Invalid parameter list	1 LUC parameter list
AP 0811	DFHZXRL	Exc	Specified system invalid	1 Remote system entry address 2 LUC parameter list
AP 0812	DFHZXRL	Exc	DFHTC request failed	1 Remote system entry address 2 Relay link TCTTE address 3 LUC parameter list
AP 0813	DFHZXRL	Exc	Surrogate TCTTE not built	1 Remote system entry address 2 Relay link TCTTE address 3 LUC parameter list 4 DFHIS parameter list
AP 0814	DFHZXRL	Exc	Surrogate TCTTE not freed	1 Remote system entry address 2 Relay link TCTTE address 3 Surrogate session entry address 4 LUC parameter list 5 DFHIS Parameter list
AP 0815	DFHZXRL	Exc	Bad response from ALLOCATE	1 Remote system entry address 2 LUC parameter list
AP 0816	DFHZXRL	Exc	Profile not found	1 Remote system entry address 2 LUC parameter list

Table 38. LU6.2 transaction routing (continued)

Point ID	Module	Lvl	Type	Data
AP 0817	DFHZXRL	Exc	Link session failed	1 Remote system entry address 2 LUC parameter list
AP 0818	DFHZXRL	Exc	After call to DFHRTSU	1 Address of relay link TCTTE 2 Address of surrogate TCTTE 3 DFHLUC parameter list 4 RTSU parameter list
AP 0819	DFHZXRL	Exc	Relay link not MRO orAPPC	1 Remote system entry address 2 Address of relay link TCTTE 3 DFHLUC parameter list
AP 081A	DFHZXRL	Exc	After call to DFHRTSU	1 Address of relay link TCTTE 2 Address of surrogate TCTTE 3 DFHLUC parameter list 4 RTSU parameter list
AP 081B	DFHZXRL	Exc	After call to DFHRMLN	1 Address of relay link TCTTE 2 Address of surrogate TCTTE 3 DFHLUC parameter list 4 RMLN parameter list
AP 0820	DFHZXRL	Exc	Bad response from FREE LINK	1 Relay link TCTTE address 2 Surrogate session entry address 3 LUC parameter list
AP 0821	DFHZXRL	Exc	CICS error detected	1 Relay link TCTTE address 2 Surrogate session entry address 3 LUC parameter list
AP 0822	DFHZXRL	Exc	CICS error detected	1 Relay link TCTTE address 2 Surrogate session entry address 3 LUC parameter list
AP 0823	DFHZXRL	Exc	Syncpoint or rollback failed	1 Relay link TCTTE address 2 Surrogate session entry address 3 LUC parameter list
AP 0825	DFHZXRL	Exc	CICS error detected	1 Relay link TCTTE address 2 Surrogate session entry address 3 LUC parameter list
AP 0826	DFHZXRL	Exc	CICS error detected	1 Relay link TCTTE address 2 Surrogate session entry address 3 LUC parameter list
AP 0827	DFHZXRL	Exc	Bad response from tos	1 Relay link TCTTE address 2 Surrogate session entry address 3 LUC parameter list

Table 38. LU6.2 transaction routing (continued)

Point ID	Module	Lvl	Type	Data
AP 0828	DFHZXRL	Exc	State error	1 Relay link TCTTE address 2 Surrogate session entry address 3 LUC parameter list
AP 0829	DFHZXRL	Exc	State error	1 Relay link TCTTE address 2 Surrogate session entry address 3 LUC parameter list
AP 0830	DFHZXRL	Exc	Invalid request	1 LUC parameter list
AP 0840	DFHCRT	IS 1	Entry	
AP 084F	DFHCRT	IS 1	Exit	
AP 0850	DFHZXRT	IS 1	Entry	1 Relay link TCTTE address 2 LU6.2 session TCTTE address
AP 0851	DFHZXRT	IS 2	Start of loop	1 Relay link TCTTE address 2 LU6.2 session TCTTE address 3 LUC parameter list
AP 085F	DFHZXRT	IS 1	Exit	
AP 0860	DFHZXRT	Exc	Bad response from DFHTC call	1 Relay link TCTTE address 2 LU6.2 session TCTTE address 3 LUC parameter list
AP 0861	DFHZXRT	Exc	Invalid state	1 Relay link TCTTE address 2 LU6.2 session TCTTE address 3 LUC parameter list
AP 0862	DFHZXRT	Exc	Bad response from ISSUE SIGNAL	1 Relay link TCTTE address 2 LU6.2 session TCTTE address 3 LUC parameter list
AP 0863	DFHZXRT	Exc	Bad response from DFHTC call	1 Relay link TCTTE address 2 LU6.2 session TCTTE address 3 LUC parameter list
AP 0864	DFHZXRT	Exc	Bad response from DFHTC call	1 Relay link TCTTE address 2 LU6.2 session TCTTE address 3 LUC parameter list
AP 0865	DFHZXRT	Exc	Bad response from DFHTC call	1 Relay link TCTTE address 2 LU6.2 session TCTTE address 3 LUC parameter list
AP 0866	DFHZXRT	Exc	Bad response from FREE TERMINAL TCTTE	1 Relay link TCTTE address 2 LU6.2 session TCTTE address 3 LUC parameter list
AP 0867	DFHZXRT	Exc	Bad response from FREE LINK TCTTE	1 Relay link TCTTE address 2 LU6.2 session TCTTE address 3 LUC parameter list

Table 38. LU6.2 transaction routing (continued)

Point ID	Module	Lvl	Type	Data
AP 086A	DFHZXRT	Exc	Bad response from ISSUE ABEND	1 Relay link TCTTE address 2 LU6.2 session TCTTE address 3 LUC parameter list
AP 086B	DFHZXRT	Exc	Bad response from ISSUE ABEND	1 Relay link TCTTE address 2 LU6.2 session TCTTE address 3 LUC parameter list
AP 086C	DFHZXRT	Exc	Bad response from ISSUE ERROR	1 Relay link TCTTE address 2 LU6.2 session TCTTE address 3 LUC parameter list
AP 086D	DFHZXRT	Exc	Bad response from ISSUE ERROR	1 Relay link TCTTE address 2 LU6.2 session TCTTE address 3 LUC parameter list
AP 086E	DFHZXRT	Exc	Bad response from ISSUE PREPARE	1 Relay link TCTTE address 2 LU6.2 session TCTTE address 3 LUC parameter list
AP 086F	DFHZXRT	Exc	ISSUE SIGNAL failed	1 Relay link TCTTE address 2 LU6.2 session TCTTE address 3 LUC parameter list
AP 0870	DFHZXRT	Exc	Bad rc from terminal	1 Relay link TCTTE address 2 LU6.2 session TCTTE address
AP 0871	DFHZXRT	Exc	Bad rc from terminal	1 Relay link TCTTE address 2 LU6.2 Session TCTTE address 3 LUC parameter list

DM gate service module

Table 39. DM gate service module trace points

Point ID	Module	Lvl	Type	Data
AP 0900	DFHAPDM	AP 1	Entry	1 DMDM parameter list
AP 0901	DFHAPDM DFHAPSIP DFHSIC1 DFHSIH1	AP 1	Exit	1 DMDM parameter list
AP 0902	DFHAPDM	Exc	Logic error	1 DMDM parameter list
AP 0903	DFHAPDM	Exc	Invalid function	1 DMDM parameter list
AP 0904	DFHAPSIP	Exc	Insufficient storage	1 SMGF parameter list
AP 0905	DFHAPSIP	Exc	Unable to define subpools	1 SMAD parameter list
AP 0906	DFHAPDM	Exc	Invalid format	1 DMDM parameter list
AP 0907	DFHAPDM	Exc	Recovery entered	1 DMDM parameter list 2 Kernel error data

Table 39. DM gate service module trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 0908	DFHAPDM	Exc	Already initialized	1 DMDM parameter list
AP 0909	DFHAPDM	Exc	Loader domain call failed	1 LDLD parameter list
AP 090A	DFHAPSIP	Exc	Insufficient storage for load	1 DMDM parameter list
AP 090C	DFHAPSIP	Exc	SMGF call failed	1 SMGF parameter list
AP 090D	DFHAPSIP	Exc	KEDD call failed	1 KEDD parameter list
AP 090E	DFHAPSIP	Exc	PAGP call failed	1 PAGP parameter list
AP 090F	DFHAPSIP	Exc	Insufficient storage	1 SMGF parameter list
AP 0910	DFHAPSIP	AP 1	Entry	1 APAP parameter list
AP 0911	DFHAPSIP	AP 1	Exit	1 APAP parameter list
AP 0912	DFHAPSIP	Exc	Inconsistent SIT release	1 APAP parameter list
AP 0913	DFHAPSIP	Exc	level Invalid SIT length	1 APAP parameter list
AP 0914	DFHAPSIP	Exc	Invalid function	1 APAP parameter list
AP 0915	DFHAPSIP	Exc	Invalid SIT address	1 APAP parameter list

XRF takeover

Table 40. XRF takeover—signon and signoff

Point ID	Module	Lvl	Type	Data
AP 0A00	DFHSUSX	AP 1	Entry	1 SUSX parameter list
AP 0A01	DFHSUSX	AP 1	Exit	1 SUSX parameter list
AP 0A02	DFHSUSX	Exc	Unable to produce key from TCTTE	1 ZXTR buffer 2 ZC make key response 3 TCTTE
AP 0A03	DFHSUSX	Exc	Key longer than expected	1 ZXTR buffer before sending to alternate 2 TCTTE
AP 0A04	DFHSUSX	Exc	Unsuccessful locate	1 ZXTR buffer as received by alternate
AP 0A05	DFHSUSX	AP 2	Data	1 TCTTE
AP 0A06	DFHSUSX	Exc	Unable to unlock TCTTE	1 ZXTR buffer as received by alternate
AP 0A07	DFHCSSC	AP 1	Data	1 Number of TCTTEs eligible for signoff during takeover

Data tables

Table 41. Data tables trace points

Point ID	Module	Lvl	Type	Data
AP 0B0A	DFHDTRE	Exc	Unrecognized function on call to DFHDTRE	1 DFHDTPPS parameter list
AP 0B0B	DFHDTRR	Exc	Unrecognized function on call to DFHDTRR	1 DFHDTPPS parameter list
AP 0B0C	DFHDTUP	Exc	Unrecognized function on call to DFHDTUP	1 DFHDTPPS parameter list
AP 0B0D	DFHDTST	Exc	Unrecognized function on call to DFHDTST	1 DFHDTPPS parameter list
AP 0B0E	DFHDTSS	Exc	Unrecognized function on call to DFHDTSS	1 DFHDTPPS parameter list
AP 0B0F	DFHDTRC	Exc	Unrecognized function on call to DFHDTRC	1 DFHDTPPS parameter list
AP 0B10	DFHDTLI	Exc	Error on initializing record management	1 Response and reason 2 Error code
AP 0B11	DFHDTST	Exc	Error on record manager OPEN	1 Response and reason 2 Error code
AP 0B12	DFHDTST	Exc	Error on record manager CLOSE	1 Response and reason 2 Error code
AP 0B13	DFHDTRR	FC 2	Entry	1 Function 2 Qualifier flags 3 Table connect token 4 Key address GET_DIRECT, GET_SEQUENTIAL only: 5 Record buffer address 6 Record buffer length 7 Record token if supplied
AP 0B14	DFHDTRR	FC 2	Exit	1 Function 2 Response and reason codes 3 Error code 4 Qualifier flags 5 Table connect token POINT only: 6 Output key address if supplied GET_DIRECT,GET_SEQUENTIAL only: 6 Output record length 7 Output key address if supplied
AP 0B15	DFHDTRR	Exc	Unexpected error on call to retrieval PC	1 Response and reason 2 Error code
AP 0B19	DFHDTLI	Exc	Error calling data-tables SVC	1 Response and reason 2 Error code
AP 0B1A	DFHDTRI	Exc	Error calling data-tables SVC	1 Response and reason 2 Error code

Table 41. Data tables trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 0B1B	DFHDTINS	FC 2	Entry	1 Function 2 Qualifier flags
AP 0B1C	DFHDTINS	FC 2	Exit	1 Function 2 Response and reason codes 3 Error code 4 Qualifier flags 5 Global token
AP 0B1D	DFHDTSS	FC 2	Entry	1 Function 2 Global token 3 Applid
AP 0B1E	DFHDTSS	FC 2	Exit	1 Function 2 Response and reason codes 3 Error code 4 Time-stamp address
AP 0B1F	DFHDTLA	FC 2	Entry	1 Function 2 Qualifier flags 3 Table token 4 File name for table
AP 0B20	DFHDTLA	FC 2	Exit	1 Function 2 Response and reason codes 3 Error code 4 Qualifier flags 5 Table token 6 File name for table 7 Load ID
AP 0B21	DFHDTST	FC 2	Entry	1 Function OPEN, CLOSE, STATISTICS only: 2 File name SET_ENABLEMENT only: 2 Qualifier flags 3 File name 4 Path token CLOSE, STATISTICS only: 3 Path token OPEN only: 3 Source data set name 4 Table size 5 UMT and other flags 6 Base token

Table 41. Data tables trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 0B22	DFHDTST	FC 2	Exit	<p>1 Function</p> <p>2 Response and reason codes</p> <p>3 Error code OPEN, CLOSE, STATISTICS only:</p> <p>4 Path token SET_ENABLEMENT only:</p> <p>4 Qualifier flags</p> <p>5 Path token OPEN only:</p> <p>5 Base token</p> <p>6 File name STATISTICS only:</p> <p>5 14 statistics fields</p>
AP 0B23	DFHDTRE	FC 2	Entry	<p>1 Function</p> <p>2 Qualifier flags</p> <p>3 File name for table</p> <p>4 Key GET_DIRECT, GET_SEQUENTIAL only:</p> <p>5 Record buffer address</p> <p>6 Record buffer length</p> <p>7 Record token if supplied</p>
AP 0B24	DFHDTRE	FC 2	Exit	<p>1 Function</p> <p>2 Response and reason codes</p> <p>3 Error code</p> <p>4 Qualifier flags</p> <p>5 File name for table POINT only:</p> <p>6 Output key if returned GET_DIRECT, GET_SEQUENTIAL only:</p> <p>6 Output record length</p> <p>7 Output key if returned</p>
AP 0B25	DFHDTUP	FC 2	Entry	<p>1 Function ADD, ADD RECORD, REPLACE, DELETE only:</p> <p>2 Qualifier flags</p> <p>3 File name for table</p> <p>4 Key ADD RECORD, ADD, REPLACE only:</p> <p>5 Record address</p> <p>6 Record length ADD, REPLACE only:</p> <p>7 Record token if supplied DELETE only:</p> <p>5 Record token if supplied COMMIT, BACKOUT only:</p> <p>2 UOW token END_LOAD only:</p> <p>2 File name for table</p>

Table 41. Data tables trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 0B26	DFHDTUP	FC 2	Exit	1 Function 2 Response and reason codes 3 Error code ADD, ADD RECORD, REPLACE, DELETE only: 4 Qualifier flags 5 File name for table REPLACE, DELETE only: 6 Record token if returned END_LOAD only: 4 File name of table
AP 0B27	DFHDTST	Exc	CLOSE could not find table block	1 Table block address
AP 0B28	DFHDTST	Exc	CLOSE could not find file block	1 File block address
AP 0B29	DFHDTSS	Exc	Error calling DT SVC	1 Function 2 Response and reason 3 Error code
AP 0B2A	DFHDTRC	Exc	Error calling DT SVC	1 Function 2 Response and reason 3 Error code
AP 0B2B	DFHDTUP	Exc	XDTRD exit returned invalid record length	1 length returned
AP 0B2C	DFHDTRC	Exc	Connect index exceeds maximum supported size	1 connect index
AP 0B2D	DFHDTRC	FC 2	Entry	1 Function 2 Global token CONNECT only: 3 Remote file name 4 Remote applid DISCONNECT only: 3 Table connect token
AP 0B2E	DFHDTRC	FC 2	Exit	1 Function 2 Response and reason codes 3 Error code CONNECT only: 4 Remote file name 5 Remote applid 6 Table connect token DISCONNECT only: 4 Table connect token
AP 0B2F	DFHDTLA	Exc	Disastrous error acquiring common storage to pass parameters to loading transaction	1 SM error code

File control

Table 42. File control trace points

Point ID	Module	Lvl	Type	Data
----------	--------	-----	------	------

Table 42. File control trace points (continued)

Point ID	Module	Lvl	Type	Data	
AP 0B50	DFHFHFCAT	FC 1	Entry	1	FCAT Parameter list
AP 0B51	DFHFHFCAT	FC 1	Exit	1	FCAT Parameter list
AP 0B52	DFHFHFCAT	Exc	Invalid format	1	FCAT Parameter list
AP 0B53	DFHFHFCAT	Exc	Invalid function	1	FCAT Parameter list
AP 0B54	DFHFHFCAT	Exc	Recovery routine	1	FCAT Parameter list
AP 0B55	DFHFHFCAT	Exc	Change mode failed	1	FCAT Parameter list
AP 0B56	DFHFHFCAT	Exc	Backup while open not supported	1	FCAT Parameter list
AP 0B57	DFHFHFCAT	Exc	Inquire on whether DSN is SMS-managed failed	1 2 3 4	Return code Reason code Prob determination FCAT Parameter list
AP 0B58	DFHFHFCAT	Exc	DSN not known	1	FCAT Parameter list
AP 0B59	DFHFHFCAT	Exc	Set RECOVERED error	1 2 3 4	Return code Reason code Prob determination FCAT Parameter list
AP 0B5A	DFHFHFCAT	Exc	Set recovery point error	1 2 3 4	Return code Reason code Prob determination FCAT Parameter list
AP 0B5B	DFHFHFCAT	Exc	Set BWO disabled failed	1 2 3 4	Return code Reason code Prob determination FCAT Parameter list
AP 0B5C	DFHFHFCAT	Exc	Inquire BWO enabled failed	1 2 3 4	Return code Reason code Prob determination FCAT Parameter list
AP 0B5D	DFHFHFCAT	Exc	Set BWO enabled failed	1 2 3 4	Return code Reason code Prob determination FCAT Parameter list
AP 0B5E	DFHFHFCAT	Exc	Restore and forward recovery needed	1	FCAT Parameter list
AP 0B5F	DFHFHFCAT	Exc	Forward recovery needed	1	FCAT Parameter list
AP 0B60	DFHFHFCSD	FC 1	Entry	1	FCSD Parameter list
AP 0B61	DFHFHFCSD	FC 1	Exit	1	FCSD Parameter list
AP 0B62	DFHFHFCSD	Exc	Invalid format	1	FCSD Parameter list

Table 42. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 0B63	DFHFCS D	Exc	Invalid function	1 FCSD Parameter list
AP 0B64	DFHFCS D	Exc	Recovery	1 FCSD Parameter list
AP 0B65	DFHFCS D	Exc	File close error	1 FCSD Parameter list
AP 0B66	DFHFCS D	Exc	TM get next failed	1 FCSD Parameter list
AP 0B70	DFHFCA T	Exc	DFHSM/DFDSS back level	1 FCAT Parameter list
AP 0B71	DFHFCS R	FC 2	Entry	1 FCFR parameter list
AP 0B72	DFHFCS R	FC 2	Exit	1 FCFR parameter list
AP 0B73	DFHFCS R	Exc	Recovery routine entered	1 FCFR parameter list 2 Kernel error data
AP 0B74	DFHFCS R	Exc	Purged	1 FCFR parameter list
AP 0B75	DFHFCS R	Exc	DFHDSSR call failed	1 FCFR parameter list 2 DSSR parameter list
AP 0B76	DFHFCS R	Exc	DFHRMRE call failed	1 FCFR parameter list 2 RMRE parameter list
AP 0B77	DFHFCS RV	FC 2	About to call VSAM	1 RPL 2 Address of RPL 3 IFGLUWID structure 4 (if present) key 5 (if present) data
AP 0B78	DFHFCS RV	FC 2	Return from VSAM	1 RPL 2 Address of RPL 3 IFGLUWID structure 4 (if present) key 5 (if present) data
AP 0B79	DFHFCS RV	FC 2	Enter RLSWAIT exit	1 RLSWAIT parameter list
AP 0B7A	DFHFCS RV	FC 2	Exit RLSWAIT exit	1 RLSWAIT parameter list
AP 0B7B	DFHFCS RV	Exc	VSAM detected error	1 DFHFCSFR parameter list 2 VSWA 3 Address of VSWA 4 FRTE 5 Filename 6 Transaction id 7 Key
AP 0B7C	DFHFCS RV	Exc	Recovery	1 DFHFCSFR parameter list 2 Kernel error data
AP 0B7D	DFHFCS RV	Exc	Purged	
AP 0B7E	DFHFCS RV	Exc	DFHDSSR call failed	1 DFHFCSFR parameter list 2 DFHDSSR parameter list

Table 42. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 0B80	DFHFCCA	FC 1	Entry	1 DFHFCCA parameter list 2 (if present) IFGLUWID
AP 0B81	DFHFCCA	FC 1	Exit	1 DFHFCCA parameter list
AP 0B82	DFHFCCA	Exc	Invalid format	1 Invalid parameter list
AP 0B83	DFHFCCA	Exc	Invalid function	1 DFHFCCA parameter list
AP 0B84	DFHFCCA	Exc	Recovery	1 DFHFCCA parameter list 2 Kernel error data
AP 0B85	DFHFCCA	FC 2	ACB before VSAM	1 ACB 2 Address of ACB
AP 0B86	DFHFCCA	FC 2	ACB after VSAM	1 ACB 2 Address of ACB
AP 0B87	DFHFCCA	Exc	ACB request error	1 Macro 2 VSAM return code 3 VSAM reason code 4 ACB 5 ACB address 6 Task name
AP 0B88	DFHFCCA	FC 2	RPL before VSAM	1 RPL 2 Address of RPL 3 Control ACB 4 (if quiesce) IFGQUIES 4 (otherwise) IFGLUWID 5 (if present) IFGRETNS
AP 0B89	DFHFCCA	FC 2	RPL after VSAM	1 RPL 2 Address of RPL 3 Error message area 4 IDARECOV data
AP 0B8A	DFHFCCA	Exc	VSAM detected error	1 Macro 2 Return code 3 Reason code 4 RPL 5 Address of RPL 6 Message area 7 Task name
AP 0B8B	DFHFCCA	Exc	DFHDSSR call failed	1 DFHFCCA parameter list 2 DFHDSSR parameter list
AP 0B8C	DFHFCCA	FC 2	Enter RLSWAIT exit	1 RLSWAIT parameter list
AP 0B8D	DFHFCCA	FC 2	Exit RLSWAIT exit	1 RLSWAIT parameter list
AP 0B8E	DFHFCCA	Exc	Purged	1 DFHFCCA parameter list
AP 0B8F	DFHFCCA	Exc	DFHXMAT call failed	1 DFHFCCA parameter list 2 DFHXMAT parameter list

Table 42. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 0B90	DFHFCCA	FC 2	ACB Before GENCB	1 ACB 2 ACB address
AP 0B91	DFHFCCA	FC 2	ACB After GENCB	1 ACB 2 ACB address
AP 0B92	DFHFCCA	Exc	GENCB VSAM error	1 Name of VSAM macro 2 VSAM return code 3 VSAM reason code 4 ACB 5 ACB address 6 Name of current task
AP 0B93	DFHFCCA	FC 2	ACB Before IDAREGP	1 ACB 2 ACB address
AP 0B94	DFHFCCA	FC 2	ACB After IDAREGP	1 ACB 2 ACB address
AP 0B95	DFHFCCA	FC 2	ACB Before IDAUNRP	1 ACB 2 ACB address
AP 0B96	DFHFCCA	FC 2	ACB After IDAUNRP	1 ACB 2 ACB address
AP 0B97	DFHFCCA	Exc	REG VSAM error	1 Name of VSAM macro 2 VSAM return code 3 VSAM reason code 4 VSAM error data 5 ACB 6 ACB address 7 Name of current task
AP 0B98	DFHFCCA	Exc	UNREG VSAM error	1 Name of VSAM macro 2 VSAM return code 3 VSAM reason code 4 VSAM error data 5 ACB 6 ACB address 7 Name of current task
AP 0BA0	DFHFCRO	FC 2	Entry	1 FCFS parameter list
AP 0BA1	DFHFCRO	FC 2	Exit	1 FCFS parameter list
AP 0BA2	DFHFCRO	Exc	Invalid request	1 FCFS parameter list
AP 0BA3	DFHFCRO	Exc	Recovery	1 FCFS parameter list 2 Kernel error data
AP 0BA4	DFHFCRO	Exc	Disaster	1 FCFS parameter list
AP 0BA5	DFHFCRO	Exc	Purged	1 FCFS parameter list

Table 42. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 0BA6	DFHFCRO	Exc	VSAM Error	1 Name of VSAM macro 2 ACB address 3 ACB
AP 0BA7	DFHFCRO	Exc	Getmain failed	1 SMGF parameter list 2 FCFS parameter list
AP 0BA9	DFHFCRO	FC 2	Call VSAM	1 Name of VSAM macro 2 ACB address 3 ACB
AP 0BAA	DFHFCRO	FC 2	Return from VSAM	1 Name of VSAM macro 2 ACB address 3 ACB
AP 0BAB	DFHFCRO	FC 2	Locate volume before	1 None
AP 0BAC	DFHFCRO	FC 2	Locate volume after	1 None
AP 0BB0	DFHFCIR	FC 1	Entry	1 RMDE parameter list 2 Resource ID (for DELIVER_RECOVERY only)
AP 0BB1	DFHFCIR	FC 1	Exit	1 RMDE parameter list
AP 0BB2	DFHFCIR	Exc	Invalid format	1 Supplied parameter list
AP 0BB3	DFHFCIR	Exc	Invalid function	1 RMDE parameter list
AP 0BB4	DFHFCIR	Exc	Recovery routine	1 RMDE parameter list 2 Kernel error data
AP 0BB7	DFHFCIR	Exc	Inadequate parameter list supplied	1 RMDE parameter list
AP 0BB8	DFHFCIR	Exc	Table manager locate for FCTE returned not found	1 RMDE parameter list 2 Start of FC log record
AP 0BB9	DFHFCIR	Exc	Table manager locate for FCTE returned serious error	1 RMDE parameter list 2 Table manager return code 3 Start of FC log record
AP 0BBA	DFHFCIR	Exc	Table manager unlock for FCTE returned not found	1 RMDE parameter list 2 Start of FC log record
AP 0BBB	DFHFCIR	Exc	Table manager unlock for FCTE returned serious error	1 RMDE parameter list 2 Table manager return code 3 Start of FC log record
AP 0BBC	DFHFCIR	Exc	Enqueue error on acquiring retained CICS	1 RMDE parameter list 2 NQNQ parameter list 3 Start of FC log record
AP 0BBD	DFHFCIR	Exc	Unrecognized data set type code	1 RMDE parameter list 2 Data set name block 3 Start of FC log record

Table 42. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 0BBE	DFHFCIR	Exc	DFHRMRE call failed	1 RMDE parameter list 2 RMRE parameter list
AP 0BCG	DFHFCLJ	LG 1	Buffer length error	1 FCLJ parameter list 2 LGGL parameter list
AP 0BC0	DFHFCLJ	FC 2	Entry	1 FCLJ parameter list
AP 0BC1	DFHFCLJ	FC 2	Exit	1 FCLJ parameter list 2 See "Format of data fields 2, 3, and 4 from DFHFCLJ" on page 65 3 See "Format of data fields 2, 3, and 4 from DFHFCLJ" on page 65 4 See "Format of data fields 2, 3, and 4 from DFHFCLJ" on page 65

Table 42. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
----------	--------	-----	------	------

Format of data fields 2, 3, and 4 from DFHFCLJ

Data field 1 contains the FCLJ parameter list in all cases. The contents of data fields 2, 3, and 4 depend on the function performed by DFHFCLJ:

Function

Contents of data fields

File Open

Data field 2 contains the complete tie-up record. This comprises data that is general to all log records followed by data specific to tie-up records. Data fields 3 and 4 are not used.

Dataset Copy

Data fields 2, 3, and 4 are as for File Open

File Close

Data field 2 contains the complete file close record. This comprises data general to all log records followed by data specific to file close records. Data fields 3 and 4 are not used.

Read Only

Data field 2 contains the fixed-length part of the log record. This comprises data that is general to all log records followed by data that is particular to just the records being accessed. Data field 3 contains the key of access. Data field 4 contains the first 80 bytes of the record being accessed.

Read Update

Data fields 2, 3, and 4 are as for Read Only

Write Update

Data fields 2, 3, and 4 are as for Read Only

Write Add

Data fields 2, 3, and 4 are as for Read Only

Write Add Complete

Data fields 2, 3, and 4 are as for Read Only. However, if the Write Add Complete is to an ESDS, data fields 3 and 4 are not used.

Write Delete

Data field 2 contains the fixed-length part of the log record. This comprises data that is general to all log records, followed by data that is specific to Write Delete records. Data field 3 contains the base key. Data field 4 contains the path key.

Take Keypoint

Data fields 2, 3, and 4 are not used.

Synchronize Read Update

Data fields 2, 3, and 4 are not used.

AP 0BC2	DFHFCLJ	Exc	Invalid format	1	FCLJ parameter list
AP 0BC3	DFHFCLJ	Exc	Invalid function	1	FCLJ parameter list
AP 0BC4	DFHFCLJ	Exc	Recovery	1 2	FCLJ parameter list Kernel error data
AP 0BC5	DFHFCLJ	Exc	Table manager GETNEXT failure	1	FCLJ parameter list
AP 0BC6	DFHFCLJ	Exc	Recovery manager append failure	1 2	FCLJ parameter list RMRE parameter list
AP 0BC7	DFHFCLJ	Exc	Recovery manager force failure	1 2	FCLJ parameter list RMRE parameter list

Table 42. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 0BC8	DFHFCLJ	Exc	Buffer length error	1 FCLJ parameter list 2 LGGL parameter list
AP 0BD0	DFHFCES	FC 1	Entry	1 DMEN parameter list
AP 0BD1	DFHFCES	FC 1	Exit	1 DMEN parameter list
AP 0BD2	DFHFCES	Exc	Invalid format	1 Supplied parameter list
AP 0BD3	DFHFCES	Exc	Invalid function	1 DMEN parameter list
AP 0BD4	DFHFCES	Exc	Recovery routine	1 DMEN parameter list 2 Kernel error data
AP 0BD5	DFHFCES	Exc	Disaster	1 DMEN parameter list
AP 0BD6	DFHFCES	Exc	Purged	1 DMEN parameter list
AP 0BD7	DFHFCES	Exc	Transaction environment error	1 DMEN parameter list
AP 0BE0	DFHFCRC	FC 1	Entry	1 RMRO, RMDE, or RMKP parameter list
AP 0BE1	DFHFCRC	FC 1	Exit	1 RMRO, RMDE, or RMKP parameter list
AP 0BE2	DFHFCRC	Exc	Invalid format	1 Supplied parameter list
AP 0BE3	DFHFCRC	Exc	Invalid function	1 RMRO, RMDE, or RMKP parameter list
AP 0BE4	DFHFCRC	Exc	Recovery routine	1 RMRO, RMDE, or RMKP parameter list 2 Kernel error data
AP 0BE7	DFHFCRC	Exc	Invalid log record type	1 Log record type 2 RMRO parameter list
AP 0BE8	DFHFCRC	Exc	Invalid file name in log record	1 File name from log record
AP 0BE9	DFHFCRC	Exc	Invalid LUWID	1 RMRO parameter list 2 FCCA parameter list 3 LUWID from FRAB 4 LUWID from Recovery Manager
AP 0BEA	DFHFCRC	Exc	Unretained FLAB found on unshunt	1 RMRO parameter list 2 FLAB
AP 0BEB	DFHFCRC	Exc	Release locks exception	1 RMRO parameter list 2 FCCA parameter list
AP 0BEC	DFHFCRC	Exc	Retain locks exception	1 RMRO parameter list 2 FCCA parameter list

Table 42. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 0BED	DFHFCRC	Exc	Unexpected backout failure	1 RMRO parameter list 2 FCFR parameter list
AP 0BEE	DFHFCRC	Exc	Lost locks complete error	1 RMRO parameter list 2 FCCA parameter list
AP 0BEF	DFHFCRC	Exc	Backout failure	1 RMRO parameter list 2 Type of backout failure 3 Data set name
AP 0BF0	DFHFCRC	Exc	Exception from FCFR Prepare	1 RMRO parameter list 2 FCFR parameter list
AP 0BF1	DFHFCRC	Exc	Transaction attach error	1 RMRO parameter list 2 FCFR parameter list
AP 0BF2	DFHFCRC	Exc	No work token	1 RMRO parameter list

Note: For more file control trace entries, see “File control” on page 38 and “File control” on page 197.

Common Programming Interface

Table 43. Common Programming Interface

Point ID	Module	Lvl	Type	Data
AP 0C01	DFHCPIN1	CP 1	Entry	1 CPIN parameter list
AP 0C02	DFHCPIN1	CP 1	Exit	1 CPIN parameter list
AP 0C03	DFHCPIN1	Exc	The point where failure of CPI initialization is detected	1 SSACPI 2 CPI static storage area
AP 0C05	DFHCPIN2	CP 1	Entry	1 SSACPI 2 CPI static storage area
AP 0C06	DFHCPIN2	CP 1	Exit	1 SSACPI 2 CPI static storage area
AP 0C07	DFHCPIN2	Exc	The point where failure of CPI initialization is detected	1 SSACPI 2 CPI static storage area
AP 0C0A	DFHCPI	CP 1	Immediately the copied parameter list has been established	1 Contents of R0 2 USER_PLIST 3 USER_PLIST_COPY 4 Caller’s return address, copied from R14
AP 0C0B	DFHCPI	CP 1	Immediately on return from the called CPI module	1 Contents of R0 2 USER_PLIST 3 USER_PLIST_COPY 4 Caller’s return address, copied from R14
AP 0C0C	DFHCPI	Exc	Unsupported CPI verb	1 Contents of R0
AP 0C0D	DFHCPI	Exc	Verb with more than 8 parameters	1 Contents of R0

Table 43. Common Programming Interface (continued)

Point ID	Module	Lvl	Type	Data
AP 0C0E	DFHCPI	Exc	CPI not initialized	1 Contents of R0
AP 0C20	DFHCPCRW	CP 1	Receive_and_Wait entry	1 Conversation ID 2 Buffer address 3 Requested length
AP 0C21	DFHCPCRW	CP 1	Receive_and_Wait exit	1 Data received 2 Received length 3 Status received 4 REQUEST_TO_SEND received 5 Address of CPC 6 Return code
AP 0C22	DFHCPCRI	CP 1	Receive_Immediate entry	1 Conversation ID 2 Buffer address 3 Requested length
AP 0C23	DFHCPCRI	CP 1	Receive_Immediate exit	1 Data received 2 Received length 3 Status received 4 REQUEST_TO_SEND received 5 Address of CPC 6 Return code
AP 0C24	DFHCPCN1	CP 1	Send_and_Buffer entry	1 Conversation ID 2 Buffer address 3 Send length
AP 0C25	DFHCPCN1	CP 1	Send_and_Buffer exit	1 Address of CPC 2 REQUEST_TO_SEND received 3 Return code
AP 0C26	DFHCPCN2	CP 1	Send_and_Flush entry	1 Conversation ID 2 Buffer address 3 Send length
AP 0C27	DFHCPCN2	CP 1	Send_and_Flush exit	1 Address of CPC 2 REQUEST_TO_SEND received 3 Return code
AP 0C28	DFHCPCN3	CP 1	Send_Prep_to_Receive entry	1 Conversation ID 2 Buffer address 3 Send length
AP 0C29	DFHCPCN3	CP 1	Send_Prep_to_Receive exit	1 Address of CPC 2 REQUEST_TO_SEND received 3 Return code
AP 0C2A	DFHCPCN4	CP 1	Send_Confirm entry	1 Conversation ID 2 Buffer address 3 Send length
AP 0C2B	DFHCPCN4	CP 1	Send_Confirm exit	1 Address of CPC 2 REQUEST_TO_SEND received 3 Return code

Table 43. Common Programming Interface (continued)

Point ID	Module	Lvl	Type	Data
AP 0C2C	DFHCPCN5	CP 1	Send_and_Deallocate entry	1 Conversation ID 2 Buffer address 3 Send length
AP 0C2D	DFHCPCN5	CP 1	Send_and_Deallocate exit	1 Address of CPC 2 REQUEST_TO_SEND received 3 Return code
AP 0C2E	DFHCPCOJ	CP 1	Output_Journaling entry	1 Conversation ID 2 Address of CPC 3 Buffer address 4 Send length
AP 0C2F	DFHCPCOJ	CP 1	Output_Journaling exit	
AP 0C30	DFHCPCFS	CP 2	CPI-C finite state machine entry	1 Conversation ID 2 Address of CPC 3 Call type 4 Verb name 5 Return code
AP 0C31	DFHCPCFS	CP 2	CPI-C finite state machine exit	1 Conversation ID 2 Address of CPC 3 Response 4 New state
AP 0C32	DFHCPCFS	Exc	Unrecognized CPI-C finite machine request	1 Conversation ID 2 Address of CPC 3 Call type 4 Verb name
AP 0C33	DFHCPCFS	Exc	Unrecognized CPI-C return code	1 Conversation ID 2 Address of CPC 3 Call type 4 Verb name 5 Return code
AP 0C34	DFHCPCFS	Exc	Unrecognized return code for verb	1 Conversation ID 2 Address of CPC 3 Call type 4 Verb name 5 Return code
AP 0C35	DFHCPCFS	Exc	Invalid state setting request	1 Conversation ID 2 Address of CPC 3 Call type 4 Verb name 5 Return code 6 CPC
AP 0C36	DFHCPCFS	Exc	Unrecognized state setting	1 Conversation ID 2 Address of CPC 3 Call type 4 Verb name 5 Return code 6 symbol

Table 43. Common Programming Interface (continued)

Point ID	Module	Lvl	Type	Data
AP 0C37	DFHPCPFS	Exc	Unrecognized verb	1 Conversation ID 2 Address of CPC 3 Call type 4 Verb name 5 Return code
AP 0C40	DFHCPCLC	CP 2	CPI-C/LUC interface program entry	1 Call type 2 Address of CPC 3 Buffer address 4 Buffer length
AP 0C41	DFHCPCLC	CP 2	CPI-C/LUC interface program exit	1 Received length 2 Status received 3 Complete LL received 4 REQUEST_TO_SEND received 5 Return code
AP 0C42	DFHCPCLR	CP 2	Return code conversion entry	1 DFHLUC plist 2 CPC
AP 0C43	DFHCPCLR	CP 2	Return code conversion exit	1 Return code
AP 0C46	DFHCPCLM	CP 2	Create GDS records program entry	1 Buffer address 2 Buffer length
AP 0C47	DFHCPCLM	CP 2	Create GDS records program exit	1 Send list 2 Send list length 3 LLID field 4 LL field
AP 0C48	DFHCPCLC	Exc	Invalid call type	1 Call type
AP 0C49	DFHCPCL*	Exc	Incorrect response from DFHLUC	1 DFHLUC plist 2 CPC 3 Field name in error 4 Detecting module
AP 0C4A	DFHCPCLM	Exc	Data longer than two GDS records	1 Buffer address 2 Buffer length
AP 0C4B	DFHCPCLC	Exc	Unrecognized indicator Request_To_Send_Received	1 RTSR indicator
AP 0C4C	DFHCPCLR	Exc	Conversion state error	1 DFHLUC plist 2 CPC
AP 0C4D	DFHCPCLR	Exc	Unrecognized response from DFHLUC	1 DFHLUC plist 2 CPC
AP 0C4E	DFHCPCLR	Exc	Low-level logic error detected	1 DFHLUC plist 2 CPC
AP 0C51	DFHCPCLR	Exc	Task purge detected	1 DFHLUC plist 2 CPC
AP 0C60	DFHCPCRW	Exc	input_journaling routine	1 Address of CPC 2 Conversation ID

Table 43. Common Programming Interface (continued)

Point ID	Module	Lvl	Type	Data	
AP 0C61	DFHCPCOJ	Exc	Journaling request for a BASIC conversation	1 2	Address of CPC Conversation ID
AP 0C62	DFHCPCOJ	Exc	abend_from_output_ journaling routine	1 2 3	Address of CPC Conversation ID DFHJC response
AP 0C63	DFHCPCRW	Exc	abend_from_input_ journaling	1 2 3 4	Address of CPC Routine Conversation ID DFHJC response
AP 0C64	DFHCPCRW	Exc	bad_resp_from_CPCRx routine	1 2 3 4 5 6 7	Address of CPC Requested length Data received Received length Status received REQUEST_TO_SEND received Return code
AP 0C65	DFHCPCRW	Exc	check_appl_buffer routine	1 2 3	Conversation ID Address of CPC Buffer address
AP 0C66	DFHCPCN1	Exc	check_appl_data_ addressability routine	1 2 3	Conversation ID Address of CPC Buffer address
AP 0C67	DFHCPCN2	Exc	check_appl_data_ addressability routine	1 2 3	Conversation ID Address of CPC Buffer address
AP 0C68	DFHCPCN3	Exc	check_appl_data_ addressability routine	1 2 3	Conversation ID Address of CPC Buffer address
AP 0C69	DFHCPCN4	Exc	check_appl_data_ addressability routine	1 2 3	Conversation ID Address of CPC Buffer address
AP 0C6A	DFHCPCN5	Exc	check_appl_data_ addressability routine	1 2 3	Conversation ID Address of CPC Buffer address
AP 0C6B	DFHCPCRI	Exc	input_ journaling routine	1 2	Address of CPC Conversation ID
AP 0C6C	DFHCPCRI	Exc	abend_from_input_ journaling	1 2 3	Address of CPC Conversation ID DFHJC response

Table 43. Common Programming Interface (continued)

Point ID	Module	Lvl	Type	Data
AP 0C6D	DFHCPCRI	Exc	bad_resp_from_CPCRx routine	1 Address of CPC 2 Requested length 3 Data received 4 Received length 5 Status received 6 REQUEST_TO_SEND received 7 Return code
AP 0C6E	DFHCPCRI	Exc	check_appl_buffer routine	1 Conversation ID 2 Address of CPC 3 Buffer address
AP 0C70	DFHCPARH	CP 1	Entry	1 CPCC parameter list
AP 0C71	DFHCPARH	CP 1	Exit	1 CPCC parameter list 2 Parameter 1 3 Parameter 2 4 Parameter 3 5 Parameter 4 6 Parameter 5 7 Parameter 6
AP 0C72	DFHCPCEA	CP 2	Extract_Conversation_Type entry	1 Conversation ID 2 Entry
AP 0C73	DFHCPCEA	CP 2	Extract_Conversation_Type exit	1 Address of CPC 2 Exit 3 Conversation type 4 Return code
AP 0C74	DFHCPCEB	CP 2	Extract_Mode_Name entry	1 Conversation ID
AP 0C75	DFHCPCEB	CP 2	Extract_Mode_Name exit	1 Address of CPC 2 Mode name 3 Mode name length 4 Return code
AP 0C76	DFHCPCEC	CP 2	Extract_Partner_LU_Name entry	1 Conversation ID
AP 0C77	DFHCPCEC	CP 2	Extract_Partner_LU_Name exit	1 Address of CPC 2 Partner LU name 3 Partner LU name length 4 Return code
AP 0C78	DFHCPCED	CP 2	Extract_Sync_Level entry	1 Conversation ID
AP 0C79	DFHCPCED	CP 2	Extract_Sync_Level exit	1 Address of CPC 2 Sync level 3 Return code
AP 0C7A	DFHCPCSA	CP 2	Set_Conversation_Type entry	1 Conversation ID 2 Conversation type
AP 0C7B	DFHCPCSA	CP 2	Set_Conversation_Type exit	1 Address of CPC 2 Return code

Table 43. Common Programming Interface (continued)

Point ID	Module	Lvl	Type	Data
AP 0C7C	DFHCPCSB	CP 2	Set_Deallocate_Type entry	1 Conversation ID 2 Deallocate type
AP 0C7D	DFHCPCSB	CP 2	Set_Deallocate_Type exit	1 Address of CPC 2 Return code
AP 0C7E	DFHCPCSC	CP 2	Set_Error_Direction entry	1 Conversation ID 2 Error direction
AP 0C7F	DFHCPCSC	CP 2	Set_Error_Direction exit	1 Address of CPC 2 Return code
AP 0C80	DFHCPCSD	CP 2	Set_Fill entry	1 Conversation ID 2 Fill
AP 0C81	DFHCPCSD	CP 2	Set_Fill exit	1 Address of CPC 2 Return code
AP 0C82	DFHCPCSE	CP 2	Set_Log_Data entry	1 Conversation ID 2 Log data 3 Log data length
AP 0C83	DFHCPCSE	CP 2	Set_Log_Data exit	1 Address of CPC 2 Return code
AP 0C84	DFHCPCSF	CP 2	Set_Mode_Name entry	1 Conversation ID 2 Mode name 3 Mode name length
AP 0C85	DFHCPCSF	CP 2	Set_Mode_Name exit	1 Address of CPC 2 Return code
AP 0C86	DFHCPCSG	CP 2	Set_Partner_LU_Name entry	1 Conversation ID 2 Partner LU name 3 Partner LU name length
AP 0C87	DFHCPCSG	CP 2	Set_Partner_LU_Name exit	1 Address of CPC 2 Return code
AP 0C88	DFHCPCSH	CP 2	Set_Prepare_To_Receive_ entry	1 Conversation ID 2 Prepare_to_receive type
AP 0C89	DFHCPCSH	CP 2	Set_Prepare_To_Receive_ exit	1 Address of CPC 2 Return code
AP 0C8A	DFHCPCSI	CP 2	Set_Receive_Type entry	1 Conversation ID 2 Receive type
AP 0C8B	DFHCPCSI	CP 2	Set_Receive_Type exit	1 Address of CPC 2 Return code
AP 0C8C	DFHCPCSJ	CP 2	Set_Return_Control entry	1 Conversation ID 2 Return control
AP 0C8D	DFHCPCSJ	CP 2	Set_Return_Control exit	1 Address of CPC 2 Return code

Table 43. Common Programming Interface (continued)

Point ID	Module	Lvl	Type	Data
AP 0C8E	DFHCPCSK	CP 2	Set_Send_Type entry	1 Conversation ID 2 Send type
AP 0C8F	DFHCPCSK	CP 2	Set_Send_Type exit	1 Address of CPC 2 Return code
AP 0C90	DFHCPCSL	CP 2	Set_Sync_Level entry	1 Conversation ID 2 Sync level
AP 0C91	DFHCPCSL	CP 2	Set_Sync_Level exit	1 Address of CPC 2 Return code
AP 0C92	DFHCPCSM	CP 2	Set_TP_Name entry	1 Conversation ID 2 TP name 3 TP name length
AP 0C93	DFHCPCSM	CP 2	Set_TP_Name exit	1 Address of CPC 2 Return code
AP 0C94	DFHCPCAC	CP 2	Accept_Conversation entry	1 Conversation ID 2 Address of CPC 3 Return code
AP 0C95	DFHCPCAC	CP 2	Accept_Conversation exit	
AP 0C96	DFHCPCAL	CP 2	Allocate entry	1 Conversation ID
AP 0C97	DFHCPCAL	CP 2	Allocate exit	1 Address of CPC 2 Return code
AP 0C98	DFHCPCCM	CP 2	Confirm entry	1 Conversation ID
AP 0C99	DFHCPCCM	CP 2	Confirm exit	1 Address of CPC 2 REQUEST_TO_SEND received 3 Return code
AP 0C9A	DFHCPCCD	CP 2	Confirmed entry	1 Conversation ID
AP 0C9B	DFHCPCCD	CP 2	Confirmed exit	1 Address of CPC 2 Return code
AP 0C9C	DFHCPCDE	CP 2	Deallocate entry	1 Conversation ID
AP 0C9D	DFHCPCDE	CP 2	Deallocate exit	1 Address of CPC 2 Return code
AP 0C9E	DFHCPCFL	CP 2	Clear entry	1 Conversation ID
AP 0C9F	DFHCPCFL	CP 2	Clear exit	2 Address of CPC 3 Return code
AP 0CA0	DFHCPCIC	CP 2	Initialize_Conversation entry	1 SYM_DEST name
AP 0CA1	DFHCPCIC	CP 2	Initialize_Conversation exit	1 Conversation ID 2 Address of CPC 3 Return code 4 CPC

Table 43. Common Programming Interface (continued)

Point ID	Module	Lvl	Type	Data
AP 0CA2	DFHCPCPR	CP 2	Prepare_To_Receive entry	1 Conversation ID
AP 0CA3	DFHCPCPR	CP 2	Prepare_To_Receive exit	1 Address of CPC 2 Return code
AP 0CA4	DFHCPCR	CP 2	Receive entry	1 Conversation ID 2 Buffer address 3 Requested length
AP 0CA5	DFHCPCR	CP 2	Receive exit	1 Data received 2 Received length 3 Status received 4 REQUEST_TO_SEND received 5 Address of CPC 6 Return code
AP 0CA6	DFHCPCRS	CP 2	Request_To_Send entry	1 Conversation ID
AP 0CA7	DFHCPCRS	CP 2	Request_To_Send exit	1 Address of CPC 2 Return code
AP 0CA8	DFHCPCND	CP 2	Send_Data entry	1 Conversation ID 2 Buffer address 3 Send length
AP 0CA9	DFHCPCND	CP 2	Send_Data exit	1 Address of CPC 2 REQUEST_TO_SEND received 3 Return code
AP 0CAA	DFHCPCNE	CP 2	Send_Error entry	1 Conversation ID
AP 0CAB	DFHCPCNE	CP 2	Send_Error exit	1 Address of CPC 2 REQUEST_TO_SEND received 3 Return code
AP 0CAC	DFHCPCTE	CP 2	Test_Request_To_Send_Received entry	1 Conversation ID
AP 0CAD	DFHCPCTE	CP 2	Test_Request_To_Send_Received exit	1 Address of CPC 2 REQUEST_TO_SEND received 3 Return code
AP 0CAE	DFHCPCPE	CP 2	Extract_Conversation_State entry	1 Conversation ID
AP 0CAF	DFHCPCPE	CP 2	Extract_Conversation_State exit	1 Address of CPC 2 Conversation state 3 Return code
AP 0CB0	DFHCPCRA	CP 2	Receive mapped data entry	1 Conversation ID 2 Address of CPC 3 Address of buffer 4 Requested length

Table 43. Common Programming Interface (continued)

Point ID	Module	Lvl	Type	Data
AP 0CB1	DFHCPCRA	CP 2	Receive mapped data exit	1 Conversation ID 2 Address of CPC 3 Data received 4 Received length 5 Status received 6 REQUEST_TO_SEND received 7 Return code
AP 0CB2	DFHCPCRB	CP 2	Receive GDS header entry	1 Conversation ID 2 Address of CPC 3 Call type
AP 0CB3	DFHCPCRB	CP 2	Receive GDS header exit	1 Conversation ID 2 Address of CPC 3 Concatenation indicator 4 Data length in next record 5 Status received 6 REQUEST_TO_SEND received 7 Return code
AP 0CB4	DFHCPCRC	CP 2	Receive basic data entry	1 Conversation ID 2 Address of CPC 3 Address of buffer 4 Requested length
AP 0CB5	DFHCPCRC	CP 2	Receive basic data exit	1 Conversation ID 2 Address of CPC 3 Data received 4 Received length 5 Status received 6 REQUEST_TO_SEND received 7 Return code
AP 0CB6	DFHCPCRB	Exc	Unrecognized call type	1 Conversation ID 2 Address of CPC 3 Call type
AP 0CB7	DFHCPCRB	Exc	Invalid LL received	1 Conversation ID 2 Address of CPC 3 LL
AP 0CB8	DFHCPCRB	Exc	Invalid GDS ID received	1 Conversation ID 2 Address of CPC 3 ID
AP 0CC0	DFHCPARH	Exc	Bad_CPIC_call	1 CPCC parameter list
AP 0CC1	DFHCPARH	Exc	Invalid_parm_number	1 CPCC parameter list
AP 0CC2	DFHCPIC	Exc	Bad_resp_from_CPCBA routine	1 Response 2 Detecting module
AP 0CC3	DFHCPIC	Exc	Bad_resp_from_CPCBI routine	1 Response 2 Detecting module

Table 43. Common Programming Interface (continued)

Point ID	Module	Lvl	Type	Data
AP 0CC4	DFHCPIIC	Exc	Bad_resp_from_CPCBL routine	1 Conversation ID 2 Response 3 Detecting module
AP 0CC5	DFHCPIIC	Exc	Bad_resp_from_CPCBS routine	1 Conversation ID 2 Address of CPC 3 Response 4 Detecting module
AP 0CC6	DFHCPIIC	Exc	Bad_resp_from_CPCFS routine	1 Conversation ID 2 Address of CPC 3 Response 4 Detecting module 5 CPC
AP 0CC7	DFHCPIIC	Exc	Bad_resp_from_CPCLC routine	1 Conversation ID 2 Address of CPC 3 Response block 4 Detecting module 5 CPC 6 Call type
AP 0CC8	DFHCPIIC	Exc	Unexpected_reset_state routine	1 Conversation ID 2 Address of CPC 3 Detecting module 4 CPC
AP 0CC9	DFHCPIIC	Exc	Corrupted_CPC routine	1 Conversation ID 2 Address of CPC 3 Detecting module 4 CPC
AP 0CD0	DFHCPSRH	CP 1	Entry	1 CPSP parameter list 2 DFHLUC plist 3 CPC
AP 0CD1	DFHCPSRH	CP 1	Exit	1 CPSP parameter list 2 DFHLUC plist 3 CPC
AP 0CD2	DFHCPSRH	Exc	Invalid_LUC_Parameter_list	1 DFHLUC plist
AP 0CD3	DFHCPSRH	Exc	Invalid_CPC	1 CPC
AP 0CD4	DFHCPSRH	Exc	Unexpected_ZUSR_State_error	1 DFHLUC plist 2 CPC
AP 0CDA	DFHCPIIR	CP 1	Entry	1 CPCC parameter list
AP 0CDB	DFHCPIIR	Exc	Bad_CPIIR_call	1 CPCC parameter list
AP 0CDC	DFHCPIIR	Exc	Invalid_parm_number	1 CPCC parameter list
AP 0CDD	DFHCPIIR	Exc	Bad_return_code	1 CPCC parameter list 2 Syncpoint return code

Table 43. Common Programming Interface (continued)

Point ID	Module	Lvl	Type	Data
AP 0CDE	DFHCPIR	CP 1	Exit	1 CPC parameter list 2 Response
AP 0CE0	DFHCPCBI	Exc	Blank netname	1 SYM_DEST name 2 PRFS parameter list
AP 0CE1	DFHCPCBI	Exc	Blank TP name	1 SYM_DEST name 2 PRFS parameter list
AP 0CE2	DFHCPCBI	Exc	Task purge detected	
AP 0CE3	DFHCPCBS	Exc	Invalid CPC address	1 Address of CPC
AP 0CE4	DFHCPCBS	Exc	Invalid log data length	1 Address of CPC 2 Log data length
AP 0CE5	DFHCPCBS	Exc	Task purge detected	
AP 0CE6	DFHCPCBL	Exc	CPC chain corrupted	1 Conversation ID
AP 0CE7	DFHCPCBA	Exc	Unrecognized sync level	1 Address of TCTTE 2 TCTESP
AP 0CE8	DFHCPCBA	Exc	Task purge detected	
AP 0CE9	DFHCPCBA	Exc	Incorrect response from DFHLUC	1 DFHLUC plist 2 Field name in error
AP 0CEA	DFHCPCBD	Exc	Null CPC pointer	1 Address of CPC
AP 0CED	DFHCPCBD	Exc	CPC chain for this task is empty	1 Address of CPC
AP 0CEE	DFHCPCBD	Exc	CPC chain corrupted	
AP 0CF0	DFHCPCBI	CP 2	Create_CPC initialization entry	1 SYM_DEST name
AP 0CF1	DFHCPCBI	CP 2	Create_CPC initialization exit	1 Output conversation ID 2 Address of CPC 3 Response
AP 0CF2	DFHCPCBA	CP 2	Create_CPC accept entry	
AP 0CF3	DFHCPCBA	CP 2	Create_CPC accept exit	1 Output conversation ID 2 Address of CPC 3 Response
AP 0CF4	DFHCPCBS	CP 2	Set_CPC_Log_Data entry	1 Address of CPC 2 Log data length 3 Address of log data
AP 0CF5	DFHCPCBS	CP 2	Set_CPC_Log_Data exit	1 Response
AP 0CF6	DFHCPCBL	CP 2	Locate_CPC entry	1 Input conversation ID
AP 0CF7	DFHCPCBL	CP 2	Locate_CPC exit	1 Address of CPC 2 Response
AP 0CF8	DFHCPCBD	CP 2	Delete_conversation entry	1 Address of CPC
AP 0CF9	DFHCPCBD	CP 2	Delete_conversation exit	
AP 0CFA	DFHCPCBB	CP 2	Increment_Last_conv_id entry	

Table 43. Common Programming Interface (continued)

Point ID	Module	Lvl	Type	Data
AP 0CFB	DFHCPCBB	CP 2	Increase_Last_convid exit	1 Conversation ID
AP 0CFC	DFHCPCBG	CP 2	Initialize_CPC entry	1 Address of CPC
AP 0CFD	DFHCPCBG	CP 2	Initialize_CPC exit	
AP 0CFE	DFHCPCBE	CP 2	Extract_syncpoint_rc entry	1 Address of CPC
AP 0CFF	DFHCPCBE	CP 2	Extract_syncpoint_rc exit	1 Response

DFHCRxx

Table 44. DFHCRxx

Point ID	Module	Lvl	Type	Data
AP 0D80	DFHCRIU	AP 1	Entry	1 DFHRMLKM parameter list 2 Session TCTTE address (unless RMLK_FUNCTION = RMLK_PERFORM_UNSHUNT)
AP 0D81	DFHCRIU	AP 1	Exit	1 DFHRMLKM parameter list 2 Session TCTTE address (unless RMLK_FUNCTION = RMLK_PERFORM_UNSHUNT)
AP 0D82	DFHCRIU	Exc	Recovery	1 DFHRMLKM parameter list 2 Kernel error data
AP 0D83	DFHCRIU	Exc	DFHRMUWM FUNCTION(SET_UOW) call failure	1 DFHRMLKM parameter list 2 DFHRMUWM parameter list
AP 0D84	DFHCRIU	Exc	DFHRMLNM FUNCTION(INQUIRE_LINK) call failure during PERFORM_COMMIT request	1 DFHRMLKM parameter list 2 DFHRMLNM parameter list
AP 0D85	DFHCRIU	Exc	DFHRMLNM FUNCTION(INQUIRE_ LINK) call failure during PERFORM_SHUNT request	1 DFHRMLKM parameter list 2 DFHRMLNM parameter list
AP 0D86	DFHCRIU	Exc	Failure during DFHTC TYPE=FREE call	1 DFHRMLKM parameter list
AP 0D87	DFHCRIU	Exc	Unreachable OTHERWISE clause executed during DO_COMMIT request	1 DFHRMLKM parameter list
AP 0D88	DFHCRIU	Exc	Unreachable OTHERWISE clause executed during PERFORM_PREPARE request	1 DFHRMLKM parameter list
AP 0D89	DFHCRIU	Exc	DFHTFRFM FUNCTION(RELEASE_ FACILITY) call failure	1 DFHRMLKM parameter list 2 DFHTFRFM parameter list
AP 0D8A	DFHCRIU	Exc	DFHTFRFM FUNCTION(SET_LINK) call failure	1 DFHRMLKM parameter list 2 DFHRMLNM parameter list
AP 0D90	DFHCRIU	AP 1	Entry	1 DFHCRIU parameter list 2 Session name
AP 0D91	DFHCRIU	AP 1	Exit	1 DFHCRIU parameter list 2 Session name

Table 44. DFHCRxx (continued)

Point ID	Module	Lvl	Type	Data
AP 0D92	DFHCR1U	Exc	Recovery routine	1 DFHCR1U parameter list 2 Session name
AP 0D93	DFHCR1U	Exc	After call to DFHRMUW	1 DFHCR1U parameter list 2 DFHRMUW parameter list
AP 0D94	DFHCR1U	Exc	After call to DFHRMLN	1 DFHCR1U parameter list 2 DFHRMLN parameter list
AP 0D95	DFHCR1U	Exc	After call to DFHRMLN	1 DFHCR1U parameter list 2 DFHRMLN parameter list
AP 0D96	DFHCR1U	Exc	After DFHTC TYPE=FREE	1 DFHCR1U parameter list
AP 0D97	DFHCR1U	Exc	After call to DFHTFRF	1 DFHCR1U parameter list 2 DFHTFRF parameter list
AP 0DA0	DFHCR2U	AP 1	Entry	1 DFHRMLKM parameter list 2 Session TCTTE address (unless RMLK_FUNCTION = RMLK_PERFORM_UNSHUNT)
AP 0DA1	DFHCR2U	AP 1	Exit	1 DFHRMLKM parameter list 2 Session TCTTE address (unless RMLK_FUNCTION = RMLK_PERFORM_UNSHUNT)
AP 0DA2	DFHCR2U	Exc	Recovery	1 DFHRMLKM parameter list 2 Kernel error data
AP 0DA3	DFHCR2U	Exc	DFHRMUWM FUNCTION(SET_UOW) failure	1 DFHRMLKM parameter list 2 DFHRMUWM parameter list
AP 0DA4	DFHCR2U	Exc	DFHRMLNM FUNCTION(INQUIRE_LINK) failure during PERFORM_COMMIT request	1 DFHRMLKM parameter list 2 DFHRMLNM parameter list
AP 0DA5	DFHCR2U	Exc	DFHRMLNM FUNCTION(INQUIRE_ LINK) failure during PERFORM_SHUNT request	1 DFHRMLKM parameter list 2 DFHRMLNM parameter list
AP 0DA6	DFHCR2U	Exc	DFHTC TYPE=FREE call failure	1 DFHRMLKM parameter list
AP 0DA7	DFHCR2U	Exc	DFHTFRFM RELEASE_FACILITY request returned DISASTER resp	1 DFHRMLKM parameter list 2 DFHTFRFM parameter list
AP 0DB0	DFHCRL	AP 1	Entry	1 DFHRMROM, DFHRMDEM, or DFHRMKPM parameter list
AP 0DB1	DFHCRL	AP 1	Exit	1 DFHRMROM, DFHRMDEM, or DFHRMKPM parameter list
AP 0DB2	DFHCRL	Exc	Recovery	1 DFHRMROM, DFHRMDEM, or DFHRMKPM parameter list 2 Kernel error data
AP 0DB3	DFHCRL	Exc	Invalid format	1 Domain call parameter list

Table 44. DFHCRxx (continued)

Point ID	Module	Lvl	Type	Data
AP 0DB4	DFHCRL	Exc	Invalid function	1 DFHRMROM, DFHRMDEM, or DFHRMKPM parameter list
AP 0DB5	DFHCRL	Exc	DFHRMKDM FUNCTION(KEYPOINT_ DATA) call failure during DFHRMKPM TAKE_KEYPOINT call	1 DFHRMKPM parameter list 2 DFHRMKDM parameter list
AP 0DB6	DFHCRL	Exc	DFHRMLNM FUNCTION(START_ LINK_ BROWSE) call failure during DFHRMDEM END_ DELIVERY call	1 DFHRMDEM parameter list 2 DFHRMLNM parameter list
AP 0DB7	DFHCRL	Exc	DFHRMLNM FUNCTION(GET_NEXT_ LINK) call failure during DFHRMDEM END_ DELIVERY call	1 DFHRMDEM parameter list 2 DFHRMLNM parameter list
AP 0DB8	DFHCRL	Exc	DFHRMLNM FUNCTION(END_ LINK_ BROWSE) call failure during DFHRMDEM END_ DELIVERY call	1 DFHRMDEM parameter list 2 DFHRMLNM parameter list
AP 0DB9	DFHCRL	Exc	DFHSMGFI FUNCTION(GETMAIN) for DFHCRL's anchor block failed	1 DFHRMDEM parameter list 2 DFHSMGFM parameter list
AP 0DBA	DFHCRL	Exc	DFHSMGFI FUNCTION(GETMAIN) for DFHCRL recovery record	1 DFHRMDEM parameter list 2 DFHSMGFM parameter list
AP 0DC0	DFHCRLB	AP 1	Entry	1 DFHCRLB parameter list
AP 0DC1	DFHCRLB	AP 1	Exit	1 DFHCRLB parameter list
AP 0DC2	DFHCRLB	Exc	Recovery	1 DFHCRLB parameter list 2 Kernel error data
AP 0DC3	DFHCRLB	Exc	Invalid format	1 Domain call parameter list
AP 0DC4	DFHCRLB	Exc	Invalid function	1 DFHCRLBM parameter list
AP 0DC5	DFHCRLB	Exc	DFHRMREM FUNCTION(APPEND) call failure	1 DFHCRLBM parameter list 2 DFHRMREM parameter list

CICS OS/2 mirror program

Table 45. CICS OS/2 mirror program

Point ID	Module	Lvl	Type	Data
AP 0E00	DFHCHS	IS 2	Entry	
AP 0E01	DFHCHS	IS 2	Exit	
AP 0E02	DFHCHS	IS 2	SEND REQUEST NOACK LAST	
AP 0E03	DFHCHS	IS 2	SEND RESPONSE NOACK LAST	
AP 0E04	DFHCHS	IS 2	SEND RESPONSE ACK NOT LAST	
AP 0E05	DFHCHS	IS 2	SEND NEGATIVE ACK	
AP 0E06	DFHCHS	IS 2	SEND ACK	
AP 0E07	DFHCHS	IS 2	RECV RESPONSE NOACK LAST	
AP 0E08	DFHCHS	IS 2	RECV REQUEST NOACK LAST	
AP 0E09	DFHCHS	IS 2	RECV REQUEST ACK NOT LAST	
AP 0E0A	DFHCHS	IS 2	RECV NEGATIVE ACK	
AP 0E0B	DFHCHS	IS 2	RECV ACK	

Table 45. CICS OS/2 mirror program (continued)

Point ID	Module	Lvl	Type	Data	
AP 0E10	DFHCHS	IS 2	SERF AND PLIST	1	Copy of Service Request Function (SERF) block descriptor
AP 0E11	DFHCHS	IS 2	SEND UNENCODED DATA	1	VSI header
AP 0E12	DFHCHS	IS 2	SEND ENCODED DATA	1	TIOA data beginning address
AP 0E13	DFHCHS	IS 2	RESEND ENCODED DATA	1	TIOA data beginning address
AP 0E14	DFHCHS	IS 2	RECV ENCODED DATA	1	VSI header
AP 0E15	DFHCHS	IS 2	RECV UNENCODED DATA	1	TIOA data beginning address
AP 0E20	DFHCHS	IS 2	DATA SHORT		
AP 0E21	DFHCHS	IS 2	UNKNOWN DATA ORIGIN		
AP 0E22	DFHCHS	IS 2	CHECKSUM FAILED		

Autoinstall terminal model manager

Table 46. Autoinstall terminal model manager

Point ID	Module	Lvl	Type	Data	
AP 0F01	DFHAIRP	AP 1	Entry	1	AIRP parameter list
AP 0F02	DFHAIRP	AP 1	Exit	1	AIRP parameter list
AP 0F03	DFHAIRP	Exc	Initialization failed	1	AIRP parameter list
AP 0F08	DFHAITM	AP 1	Entry	1	AITM parameter list
AP 0F09	DFHAITM	AP 1	Exit	1	AITM parameter list
AP 0F0A	DFHAITM	Exc	Catalog write failed	1	AITM parameter list
AP 0F0B	DFHAITM	Exc	Catalog delete failed	1	AITM parameter list
AP 0F10	DFHAIIN	AP 1	Entry	1	AIIN parameter list
AP 0F11	DFHAIIN	AP 1	Exit	1	AIIN parameter list
AP 0F18	DFHAIIQ	AP 1	Entry	1	AIIQ parameter list
AP 0F19	DFHAIIQ	AP 1	Exit	1	AIIQ parameter list

Partner resource manager

Table 47. Partner resource manager

Point ID	Module	Lvl	Type	Data	
AP 0F20	DFHPRIN1	AP 1	Entry	1	PRIN parameter list
AP 0F21	DFHPRIN1	AP 1	Exit	1	PRIN parameter list

Table 47. Partner resource manager (continued)

Point ID	Module	Lvl	Type	Data	
AP 0F22	DFHPRIN1	Exc	The point where failure of partner initialization is detected	1	SSAPRM
				2	Partner static storage area
AP 0F24	DFHPRIN2	AP 1	Entry	1	SSAPRM
				2	Partner static storage area
AP 0F25	DFHPRIN2	AP 1	Exit	1	SSAPRM
				2	Partner static storage area
AP 0F26	DFHPRIN2	Exc	The point where failure of partner initialization is detected	1	SSAPRM
				2	Partner static storage area
AP 0F30	DFHPRPT	AP 1	Entry	1	PRPT parameter list
AP 0F31	DFHPRPT	AP 1	Exit	1	PRPT parameter list
AP 0F32	DFHPRRP	AP 1	Entry	1	PRRP parameter list
AP 0F33	DFHPRRP	AP 1	Exit	1	PRRP parameter list
AP 0F34	DFHPRFS	AP 1	Entry	1	PRFS parameter list
AP 0F35	DFHPRFS	AP 1	Exit	1	PRFS parameter list
AP 0F36	DFHPRCM	AP 1	Entry	1	PRCM parameter list
AP 0F37	DFHPRCM	AP 1	Exit	1	PRCM parameter list

Front end programming interface (FEPI)

All FEPI trace entries are in the AP domain (X'1200' through X'16FF') and under the control of SZ level 1. Unless indicated otherwise, the trace data areas are "Internal areas"—these are object code only (OCO) control blocks.

Table 48. FEPI trace entries

Point ID	Module	Lvl	Type	Data area description	
AP 1200	DFHESZ	SZ 1	Entry	1	Static area
				2	Parameter list
				3	Static area
AP 1201	DFHESZ	SZ 1	Exit	1	Command code
				2	Return code
				3	Reason code
				4	Parameter list
				5	Static area
AP 1220	DFHEIQSZ	SZ 1	Entry	1	Command code
				2	Parameter list
				3	Static area

Table 48. FEPI trace entries (continued)

Point ID	Module	Lvl	Type	Data area description
AP 1221	DFHEIQSZ	SZ 1	Exit	1 Command code 2 Return code 3 Reason code 4 Parameter list 5 Static area
AP 1240	DFHSZATR	SZ 1	Entry	1 Command code 2 Argument list descriptor 3 Static area
AP 1241	DFHSZATR	SZ 1	Exit	1 Command code 2 Argument list descriptor 3 Response code 4 Reason code 5 Static area
AP 1242	DFHSZATR	SZ 1	Keyword error	1 Keyword Descriptor 2 Keyword value
AP 1243	DFHSZATR	SZ 1	Before RM	3 User data or 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'
AP 1244	DFHSZATR	SZ 1	After RM	3 User data or 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'
AP 1245	DFHSZATR	SZ 1	Before XSZBRQ	1 User exit parameter list
AP 1246	DFHSZATR	SZ 1	After XSZBRQ	1 User exit parameter list
AP 1247	DFHSZATR	SZ 1	Before XSZARQ	1 User exit parameter list
AP 1248	DFHSZATR	SZ 1	After XSZARQ	1 User exit parameter list
AP 1250	DFHSZATR	SZ 1	GETMAIN failure	1 Subpool token 2 SMGF parameter list 3 Return code 4 Response code
AP 1251	DFHSZATR	SZ 1	WAIT failure	1 DSSR parameter list
AP 1260	DFHSZSIP	SZ 1	Entry	1 Static area
AP 1261	DFHSZSIP	SZ 1	Exit	1 Static area
AP 1262	DFHSZSIP	SZ 1	FEPI(NO) in SIT	1 Static area
AP 1263	DFHSZSIP	SZ 1	FEPI inflight	1 Static area
AP 1264	DFHSZSIP	SZ 1	DFHSZENQRM ENQ failure	1 DFHKC return code 2 Static area

Table 48. FEPI trace entries (continued)

Point ID	Module	Lvl	Type	Data area description
AP 1265	DFHSZSIP	SZ 1	SM subpool failure	1 SP name 2 SMAD response 3 SMAD reason 4 Static area
AP 1266	DFHSZSIP	SZ 1	Stop runaway failure	1 KEDS response 2 KEDS reason 3 Static area
AP 1267	DFHSZSIP	SZ 1	Change priority failure	1 DSAT response 2 Static area
AP 1268	DFHSZSIP	SZ 1	DFHSZ TCB swap failure	1 DSAT response 2 Static area
AP 1269	DFHSZSIP	SZ 1	Termination	1 Static area
AP 126A	DFHSZSIP	SZ 1	FEPI abended	1 Static area
AP 126B	DFHSZZNG	SZ 1	Entry ZNG get session control	
AP 126C	DFHSZZNG	SZ 1	Exit ZNG get session control	
AP 126D	DFHSZZNG	SZ 1	GETMAIN SP(NB)	4 SMGF parameter list
AP 126E	DFHSZZNG	SZ 1	GETMAIN failure SP(NB)	2 SMGF parameter list
AP 126F	DFHSZZAG	SZ 1	Entry	1 ZAG Get receive any
AP 1270	DFHSZZAG	SZ 1	Exit	1 ZAG Get receive any
AP 1271	DFHSZZAG	SZ 1	GETMAIN SP(DA)	4 SMGF parameter list
AP 1272	DFHSZZAG	SZ 1	GETMAIN failure SP(DA)	2 SMGF parameter list
AP 1273	DFHSZZRG	SZ 1	Entry ZRG get RPL req block	
AP 1274	DFHSZZRG	SZ 1	Exit ZRG get RPL req block	
AP 1275	DFHSZZRG	SZ 1	GETMAIN SP(RP)	4 SMGF parameter list
AP 1276	DFHSZZRG	SZ 1	GETMAIN failure SP(RP)	2 SMGF parameter list
AP 1277	DFHSZZFR	SZ 1	Entry ZFR FREE receive any	2 VTAM™ RPL
AP 1278	DFHSZZFR	SZ 1	FREEMAIN for dynamic	3 SMGF parameter list
AP 1279	DFHSZZFR	SZ 1	FREEMAIN failure for dynamic	3 SMGF parameter list
AP 127A	DFHSZZFR	SZ 1	FREEMAIN for receive any	2 SMGF parameter list
AP 127B	DFHSZZFR	SZ 1	FREEMAIN failure for receive any	2 SMGF parameter list
AP 127C	DFHSZZFR	SZ 1	Exit ZFR FREE receive any	
AP 1400	DFHSZRPW	SZ 1	Entry RPW req preparation	2 SMGF parameter list
AP 1401	DFHSZRPW	SZ 1	Exit RPW req preparation	2 SMGF parameter list
AP 1402	DFHSZRRT	SZ 1	Entry RRT req release proc	2 SMGF parameter list

Table 48. FEPI trace entries (continued)

Point ID	Module	Lvl	Type	Data area	description
AP 1403	DFHSZRRT	SZ 1	Free request element associated with completed request	2	SMGF parameter list
AP 1404	DFHSZRRT	SZ 1	Free dynamic storage associated with request	2	SMGF parameter list
AP 1405	DFHSZRRT	SZ 1	Exit RRT req release proc	2	SMGF parameter list
AP 1406	DFHSZRQW	SZ 1	Entry RQW req queue proc		
AP 1407	DFHSZRQW	SZ 1	Queue request element to RM for processing		
AP 1408	DFHSZRQW	SZ 1	Post RM to dispatch queued request		
AP 1409	DFHSZRQW	SZ 1	Exit RQW req queue proc		
AP 140A	DFHSZRDP	SZ 1	Entry RDP dispatcher	1	Static area
AP 140B	DFHSZRDP	SZ 1	RM initialization completed		
AP 140C	DFHSZRDP	SZ 1	RM start of request processing		
AP 140D	DFHSZRDP	SZ 1	Unrecognized request type		
AP 140E	DFHSZRDP	SZ 1	The ECB in a request element has been POSTed		
AP 140F	DFHSZRDP	SZ 1	RM has entered the no-work (WAIT) state		
AP 1410	DFHSZRDP	SZ 1	Forced termination detected	1	Static area
AP 1411	DFHSZRDP	SZ 1	Error during initialization: no common area	1	Static area
AP 1412	DFHSZRDP	SZ 1	Error during initialization: no LIFO available	1	Static area
AP 1413	DFHSZRDP	SZ 1	Exit RDP dispatcher	1	Static area
AP 1414	DFHSZRNO	SZ 1	Entry RNO NOOP proc		
AP 1415	DFHSZRNO	SZ 1	Exit RNO NOOP proc		
AP 1416	DFHSZRRI	SZ 1	Entry RII install proc		
AP 1417	DFHSZRRI	SZ 1	Exit RII install proc		
AP 1418	DFHSZRID	SZ 1	Entry RID discard proc		
AP 1419	DFHSZRID	SZ 1	Exit RID discard proc		
AP 141A	DFHSZRZZ	SZ 1	Entry RZZ terminate proc		
AP 141B	DFHSZRZZ	SZ 1	Exit RZZ terminate proc		
AP 141C	DFHSZRNC	SZ 1	Entry RNC node proc		
AP 141D	DFHSZRNC	SZ 1	Exit RNC node proc		
AP 141E	DFHSZRCA	SZ 1	Entry RCA node control proc		
AP 141F	DFHSZRCA	SZ 1	FREEMAIN of NODE related resources		
AP 1420	DFHSZRCA	SZ 1	Close ACB processing performed		
AP 1421	DFHSZRCA	SZ 1	Exit RCA node control proc		
AP 1422	DFHSZRIO	SZ 1	Entry RIO ACB open proc	1	SMGF parameter list
AP 1423	DFHSZRIO	SZ 1	Unable to allocate storage for VTAM ACB	1	SMGF parameter list
AP 1424	DFHSZRIO	SZ 1	Exit RIO ACB open proc	1	SMGF parameter list
AP 1425	DFHSZRIN	SZ 1	Entry RIN install node proc	1	Node name
AP 1426	DFHSZRIN	SZ 1	Error during NODE initialization	1	Node name
AP 1427	DFHSZRIN	SZ 1	GETMAIN of NODE related storage	1	Node name

Table 48. FEPI trace entries (continued)

Point ID	Module	Lvl	Type	Data area description
AP 1428	DFHSZRIN	SZ 1	Exit RIN install node proc	1 Node name
AP 1429	DFHSZRIP	SZ 1	Entry RIP install pool proc	1 Pool name 2 Property set name
AP 142A	DFHSZRIP	SZ 1	Error during POOL initialization	1 Pool name 2 Property set name
AP 142B	DFHSZRIP	SZ 1	GETMAIN of POOL related storage	1 Pool name 2 Property set name
AP 142C	DFHSZRIP	SZ 1	Exit RIP install pool proc	1 Pool name 2 Property set name
AP 142D	DFHSZRIT	SZ 1	Entry RIT install target proc	1 Target name 2 PLU name
AP 142E	DFHSZRIT	SZ 1	Error during TARGET initialization	1 Target name 2 PLU name
AP 142F	DFHSZRIT	SZ 1	GETMAIN of TARGET related storage	1 Target name 2 PLU name
AP 1430	DFHSZRIT	SZ 1	Exit RIT install pool proc	1 Target name 2 PLU name
AP 1431	DFHSZRIS	SZ 1	Entry RIS install proc	3 Property set name
AP 1432	DFHSZRIS	SZ 1	Error during PROPERTYSET initialization	3 Property set name
AP 1433	DFHSZRIS	SZ 1	GETMAIN of PROPERTYSET related storage	3 Property set name
AP 1434	DFHSZRIS	SZ 1	Exit RIS install proc	3 Property set name
AP 1435	DFHSZRIC	SZ 1	Entry RIC define conn proc	4 Resource name 5 Pool name
AP 1436	DFHSZRIC	SZ 1	Error during CONNECTION initialization	4 Resource name 5 Pool name
AP 1437	DFHSZRIC	SZ 1	GETMAIN of CONNECTION related storage	4 Resource name 5 Pool name
AP 1438	DFHSZRIC	SZ 1	Exit RIC define conn proc	4 Resource name 5 Pool name
AP 1439	DFHSZRDC	SZ 1	Entry RDC delete conn proc	
AP 143A	DFHSZRDC	SZ 1	Entry RDC delete conn proc	
AP 143B	DFHSZRDC	SZ 1	Unrecognized POOL name specified in DISCARD	
AP 143C	DFHSZRDC	SZ 1	Exit RDC delete conn proc	
AP 143D	DFHSZRDC	SZ 1	Entry RDC delete conn proc	
AP 143E	DFHSZRDC	SZ 1	Exit RDC delete conn proc	
AP 143F	DFHSZRDS	SZ 1	Entry RDS discard prop proc	
AP 1440	DFHSZRDS	SZ 1	FREEMAIN of PROPERTYSET related storage	

Table 48. FEPI trace entries (continued)

Point ID	Module	Lvl	Type	Data area description	
AP 1441	DFHSZRDS	SZ 1	Unrecognized PROPERTYSET name in DISCARD		
AP 1442	DFHSZRDS	SZ 1	Exit RDS discard prop proc		
AP 1443	DFHSZRDN	SZ 1	Entry RDN delete node proc		
AP 1444	DFHSZRDN	SZ 1	FREEMAIN of NODE related storage		
AP 1445	DFHSZRDN	SZ 1	Unrecognized NODE name specified in DISCARD		
AP 1446	DFHSZRDN	SZ 1	Exit RDN delete node proc		
AP 1447	DFHSZRDT	SZ 1	Entry RDT discard target proc		
AP 1448	DFHSZRDT	SZ 1	FREEMAIN of TARGET related storage		
AP 1449	DFHSZRDT	SZ 1	Unrecognized TARGET name specified in DISCARD		
AP 144A	DFHSZRDT	SZ 1	Exit RDT discard target proc		
AP 144B	DFHSZRSC	SZ 1	Entry RCS connection proc	2	Pool name
				3	Node name
				4	Target name
AP 144C	DFHSZRSC	SZ 1	Unrecognized LU type (internal error)	2	Pool name
				3	Node name
				4	Target name
AP 144D	DFHSZRSC	SZ 1	Exit RCS connection proc	2	Pool name
				3	Node name
				4	Target name
AP 144E	DFHSZVQS	SZ 1	Entry VQS REQSESS dispatcher		
AP 144F	DFHSZVQS	SZ 1	Exit VQS REQSESS dispatcher		
AP 1450	DFHSZRIW	SZ 1	Entry RIW SET proc		
AP 1451	DFHSZRIW	SZ 1	Exit RIW SET proc		
AP 1452	DFHSZRIF	SZ 1	Entry RIF install free proc		
AP 1453	DFHSZRIF	SZ 1	Exit RIF install free proc		
AP 1454	DFHSZRIA	SZ 1	Entry RIA allocate proc		
AP 1459	DFHSZRIA	SZ 1	Exit RIA allocate proc		
AP 145A	DFHSZRIQ	SZ 1	Entry RIQ inquire proc		
AP 145B	DFHSZRIQ	SZ 1	Exit RIQ inquire proc		
AP 145C	DFHSZRXD	SZ 1	Entry RXD extract proc	3	User data
AP 145D	DFHSZRXD	SZ 1	Exit RXD extract proc	3	User data
AP 145E	DFHSZRRD	SZ 1	Entry RRD receive req proc	3	Data buffer or 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'
AP 145F	DFHSZRRD	SZ 1	Exit RRD receive req proc	3	Data buffer or 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'
AP 1460	DFHSZRSE	SZ 1	Entry RSE send req proc	3	Data buffer or 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'
AP 1461	DFHSZRSE	SZ 1	Exit RSE send req proc	3	Data buffer or 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'
AP 1462	DFHSZRCT	SZ 1	Entry RCT issue proc		

Table 48. FEPI trace entries (continued)

Point ID	Module	Lvl	Type	Data area description	
AP 1463	DFHSZRCT	SZ 1	Exit RCT issue proc		
AP 1464	DFHSZRID	SZ 1	FREEMAIN surrogate related storage		
AP 1465	DFHSZRIO	SZ 1	FREEMAIN ACB related storage (including 24-bit)	1	SMGF parameter list
AP 1466	DFHSZRIO	SZ 1	GETMAIN ACB related storage (including 24-bit)	1	SMGF parameter list
AP 1467	DFHSZRDC	SZ 1	FREEMAIN CONNECTION related storage		
AP 1468	DFHSZ2CP	SZ 1	Entry 2CP SLU2 flow control		
AP 1469	DFHSZ2CP	SZ 1	Exit 2CP SLU2 flow control		
AP 146A	DFHSZPCP	SZ 1	Entry PCP SLUP flow control		
AP 146B	DFHSZPCP	SZ 1	Exit PCP SLUP flow control		
AP 146C	DFHSZVRA	SZ 1	Entry VRA receive any proc		
AP 146D	DFHSZVRA	SZ 1	Exit VRA receive any proc		
AP 146E	DFHSZRIO	SZ 1	GETMAIN failure for 24-bit storage	1	SMGF parameter list
AP 146F	DFHSZRIO	SZ 1	GETMAIN of temporary 24-bit storage for OPEN parameter list	1	SMGF parameter list
AP 1470	DFHSZRIO	SZ 1	Error during GENCB processing for ACB(s)	1	SMGF parameter list
AP 1471	DFHSZRIO	SZ 1	Error during OPEN processing for ACB	1	SMGF parameter list
AP 1472	DFHSZRQR	SZ 1	Entry RQR queue for REQSESS		
AP 1473	DFHSZRQR	SZ 1	Exit RQR queue for REQSESS		
AP 1474	DFHSZRIC	SZ 1	GETMAIN storage for surrogate	4 5	Resource name Pool name
AP 1475	DFHSZRIC	SZ 1	GETMAIN storage for connection	4 5	Resource name Pool name
AP 1476	DFHSZ2SB	SZ 1	Entry 2SB SLU2 bind proc		
AP 1477	DFHSZ2SB	SZ 1	About to issue OPNSEC request (accept session)		
AP 1478	DFHSZ2SB	SZ 1	About to issue SESSIONC request (reject session)		
AP 1479	DFHSZ2SB	SZ 1	Exit 2SB SLU2 bind proc		
AP 147A	DFHSZ2SC	SZ 1	Entry 2SC SLU2 session control		
AP 147B	DFHSZ2SC	SZ 1	Exit 2SC SLU2 session control		
AP 1480	DFHSZ2SD	SZ 1	Entry 2SD SLU2 SDT proc		
AP 1481	DFHSZ2SD	SZ 1	About to respond to 'start data traffic' request	2	VTAM RPL
AP 1482	DFHSZ2SD	SZ 1	Exit 2SD SLU2 SDT proc		
AP 1483	DFHSZ2ID	SZ 1	Entry 2ID SLU2 send data proc		
AP 1484	DFHSZ2ID	SZ 1	About to issue SEND request for data	2	VTAM RPL
AP 1485	DFHSZ2ID	SZ 1	About to POST API SEND request complete		
AP 1486	DFHSZ2ID	SZ 1	Exit 2ID SLU2 send data proc		
AP 1487	DFHSZ2OA	SZ 1	Entry 2OA SLU2 send resp proc		
AP 1488	DFHSZ2OA	SZ 1	About to issue SEND for pending response		
AP 1489	DFHSZ2OA	SZ 1	Exit 2OA SLU2 send resp proc		
AP 1490	DFHSZ2OD	SZ 1	Entry 2OD SLU2 rec data proc		
AP 1491	DFHSZ2OD	SZ 1	About to issue RECEIVE(SPECIFIC) request	3	VTAM RPL

Table 48. FEPI trace entries (continued)

Point ID	Module	Lvl	Type	Data area description
AP 1492	DFHSZ2OD	SZ 1	About to POST API RECEIVE complete	
AP 1493	DFHSZ2OD	SZ 1	About to issue SEND for intermediate resp	3 VTAM RPL
AP 1494	DFHSZ2OD	SZ 1	Exit 2OD SLU2 rec data proc	
AP 1495	DFHSZ2OR	SZ 1	Entry 2OR SLU2 response proc	
AP 1496	DFHSZ2OR	SZ 1	About to POST API request complete (response pending)	
AP 1497	DFHSZ2OR	SZ 1	Exit 2OR SLU2 response proc	
AP 1498	DFHSZPSB	SZ 1	Entry PSB SLUP bind proc	
AP 1499	DFHSZPSB	SZ 1	About to issue OPNSEC request (accept session)	
AP 149A	DFHSZPSB	SZ 1	About to issue SESSIONC request (reject session)	
AP 149B	DFHSZPSB	SZ 1	Exit PSB SLUP bind proc	
AP 149C	DFHSZPSC	SZ 1	Entry PSC SLUP session control	
AP 149D	DFHSZPSC	SZ 1	Exit PSC SLUP session control	
AP 1502	DFHSZPSD	SZ 1	Entry	
AP 1503	DFHSZPSD	SZ 1	About to respond to SDT	2 VTAM RPL
AP 1504	DFHSZPSD	SZ 1	About to POST STSN related API request	
AP 1505	DFHSZPSD	SZ 1	Exit PSD SLUP SDT proc	
AP 1506	DFHSZPSS	SZ 1	Entry PSS SLUP STSN proc	
AP 1507	DFHSZPSS	SZ 1	About to respond to STSN	
AP 1508	DFHSZPSS	SZ 1	About to POST STSN related API request	
AP 1509	DFHSZPSS	SZ 1	Exit PSS SLUP STSN proc	
AP 1510	DFHSZPID	SZ 1	Entry PID SLUP send data proc	
AP 1511	DFHSZPID	SZ 1	About to issue VTAM SEND for data	2 VTAM RPL
AP 1512	DFHSZPID	SZ 1	About to POST failed API SEND request complete	
AP 1513	DFHSZPID	SZ 1	Exit PID SLUP send data proc	
AP 1514	DFHSZPOA	SZ 1	Entry POA SLUP send resp proc	
AP 1515	DFHSZPOA	SZ 1	About to issue VTAM SEND for pending resp	2 VTAM RPL
AP 1516	DFHSZPOA	SZ 1	Exit POA SLUP send resp proc	
AP 1517	DFHSZPOD	SZ 1	Entry POD SLUP rec data proc	
AP 1518	DFHSZPOD	SZ 1	About to issue VTAM RECEIVE(SPECIFIC) for data	3 VTAM RPL
AP 1519	DFHSZPOD	SZ 1	About to POST API RECEIVE request complete	
AP 1520	DFHSZPOD	SZ 1	About to issue VTAM SEND for intermediate response	3 VTAM RPL
AP 1521	DFHSZPOD	SZ 1	Exit POD SLUP rec data proc	
AP 1522	DFHSZPOR	SZ 1	Entry POR SLUP response proc	
AP 1523	DFHSZPOR	SZ 1	About to POST API request (response pending)	
AP 1524	DFHSZPOR	SZ 1	Exit POR SLUP response proc	
AP 1528	DFHSZ2SH	SZ 1	Entry 2SH SLU2 SHUTC proc	
AP 1529	DFHSZ2SH	SZ 1	About to issue SHUTDOWN COMPLETE request	
AP 1530	DFHSZ2SH	SZ 1	Exit 2SH SLU2 SHUTC proc	
AP 1531	DFHSZ2SQ	SZ 1	Entry 2SQ SLU2 QC proc	

Table 48. FEPI trace entries (continued)

Point ID	Module	Lvl	Type	Data area description	
AP 1532	DFHSZ2SQ	SZ 1	About to issue QUIESCE COMPLETE request		
AP 1533	DFHSZ2SQ	SZ 1	Exit 2SQ SLU2 QC proc		
AP 1534	DFHSZ2SR	SZ 1	Entry 2SR SLU2 RESETSR proc		
AP 1535	DFHSZ2SR	SZ 1	Exit 2SR SLU2 RESETSR proc		
AP 1536	DFHSZ2TE	SZ 1	Entry 2TE SLU2 TERMSESS proc		
AP 1537	DFHSZ2TE	SZ 1	About to issue VTAM TERMSESS request		
AP 1538	DFHSZ2TE	SZ 1	Exit 2TE SLU2 TERMSESS proc		
AP 1542	DFHSZPSH	SZ 1	Entry PSH SLUP SHUTC proc		
AP 1543	DFHSZPSH	SZ 1	About to issue SHUTDOWN COMPLETE request		
AP 1544	DFHSZPSH	SZ 1	Exit PSH SLUP SHUTC proc		
AP 1545	DFHSZPSQ	SZ 1	Entry PSQ SLUP quiesce complete		
AP 1546	DFHSZPSQ	SZ 1	About to issue QUIESCE COMPLETE request		
AP 1547	DFHSZPSQ	SZ 1	Exit PSQ SLUP quiesce complete		
AP 1548	DFHSZPSR	SZ 1	Entry PSR RESETSR proc		
AP 1549	DFHSZPSR	SZ 1	Exit PSR RESETSR proc		
AP 1550	DFHSZPTE	SZ 1	Entry PTE SLUP TERMSESS proc		
AP 1551	DFHSZPTE	SZ 1	About to issue VTAM TERMSESS request		
AP 1552	DFHSZPTE	SZ 1	Exit PTE SLUP TERMSESS proc		
AP 1553	DFHSZ2QS	SZ 1	Entry 2QS SLU2 REQSESS issuer	2	Pool name
				3	Node name
				4	Target name
AP 1554	DFHSZ2QS	SZ 1	Exit 2QS SLU2 REQSESS issuer	2	Pool name
				3	Node name
				4	Target name
AP 1555	DFHSZPQS	SZ 1	Entry PQS SLUP REQSESS issuer	2	Pool name
				3	Node name
				4	Target name
AP 1556	DFHSZPQS	SZ 1	Exit PQS SLUP REQSESS issuer	2	Pool name
				3	Node name
				4	Target name
AP 1557	DFHSZBCL	SZ 1	Entry BCL cleanup API reqs		
AP 1558	DFHSZBCL	SZ 1	About to POST pending API request complete (fail)		
AP 1559	DFHSZBCL	SZ 1	Exit BCL cleanup API reqs		
AP 1560	DFHSZBST	SZ 1	Entry BST STSN trans scheduler		
AP 1561	DFHSZBST	SZ 1	GETMAIN storage for STSN conversation		
AP 1562	DFHSZBST	SZ 1	Exit BST STSN trans scheduler		
AP 1563	DFHSZBSI	SZ 1	Entry BSI signon exit scheduler		
AP 1564	DFHSZBSI	SZ 1	GETMAIN storage for SIGNON conversation		
AP 1565	DFHSZBSI	SZ 1	Exit BSI signon exit scheduler		
AP 1566	DFHSZBUN	SZ 1	Entry BUN uns data trans sched		
AP 1567	DFHSZBUN	SZ 1	GETMAIN storage for UNSOLICITED DATA conversation		
AP 1568	DFHSZBUN	SZ 1	Exit BUN uns data trans sched		

Table 48. FEPI trace entries (continued)

Point ID	Module	Lvl	Type	Data area description	
AP 1569	DFHSZBLO	SZ 1	Entry BLO lost session reporter		
AP 1570	DFHSZBLO	SZ 1	GETMAIN storage for LOST SESSION TDQ processing		
AP 1571	DFHSZBLO	SZ 1	Exit BLO lost session reporter		
AP 1572	DFHSZVBN	SZ 1	Entry VBN copy NIB mask to real		
AP 1573	DFHSZVBN	SZ 1	Exit VBN copy NIB mask to real		
AP 1576	DFHSZRIA	SZ 1	GETMAIN storage for API conversation request		
AP 1577	DFHSZRIA	SZ 1	FREEMAIN storage for ended conversation		
AP 1578	DFHSZRIQ	SZ 1	GETMAIN storage for BROWSE processing		
AP 1579	DFHSZRIQ	SZ 1	FREEMAIN storage related to BROWSE processing		
AP 157A	DFHSZRIF	SZ 1	GETMAIN storage for FREE related processing		
AP 157B	DFHSZRIF	SZ 1	FREEMAIN storage for FREE related processing		
AP 157C	DFHSZVRI	SZ 1	Entry VRI receive any issuer		
AP 157D	DFHSZVRI	SZ 1	About to issue RECEIVE(ANY) request for node		
AP 157E	DFHSZVRI	SZ 1	Exit VRI receive any issuer		
AP 1580	DFHSZVSL	SZ 1	Entry VSL SETLOGON req issuer		
AP 1581	DFHSZVSL	SZ 1	About to issue SETLOGON request for NODE		
AP 1582	DFHSZVSL	SZ 1	Exit VSL SETLOGON req issuer		
AP 1583	DFHSZRPM	SZ 1	Entry RPM timer services		
AP 1584	DFHSZRPM	SZ 1	Exit RPM timer services		
AP 1585	DFHSZRST	SZ 1	Entry RST START req proc		
AP 1586	DFHSZRST	SZ 1	Exit RST START req proc		
AP 1587	DFHSZRTM	SZ 1	Entry RTM recovery services		
AP 1588	DFHSZRTM	SZ 1	Exit RTM recovery services		
AP 1589	DFHSZRFC	SZ 1	Entry RFC free completion proc	2	Pool name
				3	Node name
				4	Target name
AP 158A	DFHSZRFC	SZ 1	Exit RFC free completion proc	2	Pool name
				3	Node name
				4	Target name
AP 158B	DFHSZRFC	SZ 1	GETMAIN	2	Pool name
				3	Node name
				4	Target name
AP 158C	DFHSZRFC	SZ 1	FREEMAIN	2	Pool name
				3	Node name
				4	Target name
AP 158D	DFHSZBSI	SZ 1	FREEMAIN storage related to SIGNON conversation		
AP 158E	DFHSZBUN	SZ 1	FREEMAIN storage related to UNSOLDATA conversation		
AP 158F	DFHSZBST	SZ 1	FREEMAIN storage related to STSN conversation		
AP 1590	DFHSZRPM	SZ 1	FREEMAIN storage related to TDQ and IC START request		

Table 48. FEPI trace entries (continued)

Point ID	Module	Lvl	Type	Data area description	
AP 1591	DFHSZ2OD	SZ 1	GETMAIN of storage for START processing		
AP 1592	DFHSZRIC	SZ 1	EVENT	4	Resource name
				5	Pool name
AP 1593	DFHSZ2SB	SZ 1	EVENT		
AP 1594	DFHSZ2SB	SZ 1	EVENT		
AP 1595	DFHSZFSD	SZ 1	Entry FSD FORM 3270 SEND	3	Send data or 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'
AP 1596	DFHSZFSD	SZ 1	EVENT	3, 4	Send data or 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'
AP 1597	DFHSZFSD	SZ 1	Exit FSD FORM 3270 SEND	3, 4	Send data or 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'
AP 1598	DFHSZFRD	SZ 1	Entry FRD FORM 3270 RECEIVE	2	User data or 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'
				3	User data or 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'
AP 1599	DFHSZFRD	SZ 1	Exit FRD FORM 3270 RECEIVE	2	User data or 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'
AP 159A	DFHSZBFT	SZ 1	Entry BFT FREE trans reqs sched		
AP 159B	DFHSZBFT	SZ 1	GETMAIN storage for FREE conversation		
AP 159C	DFHSZBFT	SZ 1	FREEMAIN storage related to FREE conversation		
AP 159D	DFHSZBFT	SZ 1	Exit BFT FREE trans reqs sched		
AP 159E	DFHSZRPM	SZ 1	IC START failed, bad transaction name		
AP 159F	DFHSZBFT	SZ 1	Error allocating storage for FREE QE		
AP 15A0	DFHSZBSI	SZ 1	Error allocating storage for SIGNON START QE		
AP 15A1	DFHSZBSI	SZ 1	Error allocating storage for SIGNON conversation		
AP 15A2	DFHSZBST	SZ 1	Error allocating storage for STSN START QE		
AP 15A3	DFHSZBST	SZ 1	Error allocating storage for STSN conversation		
AP 15A4	DFHSZBUN	SZ 1	Error allocating storage for UNSOLDATA START QE		
AP 15A5	DFHSZBUN	SZ 1	Error allocating storage for UNSOLDATA conversation		
AP 15A6	DFHSZPSC	SZ 1	FREEMAIN of conversation related storage		
AP 15A7	DFHSZ2SC	SZ 1	FREEMAIN of conversation related storage		
AP 15A8	DFHSZRST	SZ 1	GETMAIN of storage for API START request		

Table 48. FEPI trace entries (continued)

Point ID	Module	Lvl	Type	Data area description
AP 15A9	DFHSZRIC	SZ 1	Error allocating storage for CONNECTION	4 Resource name 5 Pool name
AP 15AA	DFHSZRIO	SZ 1	GETMAIN of storage for VTAM ACB	1 SMGF parameter list
AP 15AB	DFHSZRIO	SZ 1	GETMAIN of storage for TDQ QE	1 SMGF parameter list
AP 15AC	DFHSZRDS	SZ 1	GETMAIN of storage for TDQ QE	
AP 15AD	DFHSZRDN	SZ 1	GETMAIN of storage for TDQ QE	
AP 15AE	DFHSZRDG	SZ 1	GETMAIN of storage for TDQ QE	
AP 15AF	DFHSZRDT	SZ 1	GETMAIN of storage for TDQ QE	
AP 15B0	DFHSZPOD	SZ 1	GETMAIN of storage for START processing	
AP 15B1	DFHSZRCA	SZ 1	GETMAIN of NODE related storage	
AP 15B2	DFHSZFSD	SZ 1	FREEMAIN of formatted data buffer storage	3 Send data
AP 15B3	DFHSZRIW	SZ 1	GETMAIN of storage for TDQ QE	
AP 15B4	DFHSZPOR	SZ 1	GETMAIN of storage for START processing	
AP 15B5	DFHSZ2OR	SZ 1	GETMAIN of storage for START processing	
AP 15B6	DFHSZBCS	SZ 1	Entry	1 Current work element 2 Request parm area
AP 15B7	DFHSZBCS	SZ 1	Exit	1 Current work element 2 Request parm area
AP 15B8	DFHSZBRS	SZ 1	Entry	1 Current work element 2 Request parm area
AP 15B9	DFHSZBRS	SZ 1	Exit	1 Current work element 2 Request parm area
AP 15BA	DFHSZBUS	SZ 1	Entry	1 Resource pointer: pool, SZDSR target, SZDSR conn, SZDCD
AP 15BB	DFHSZBUS	SZ 1	Exit	1 Resource pointer: pool, SZDSR target, SZDSR conn, SZDCD
AP 15BC	DFHSZBUS	Exc	GETMAIN fail	1 SMGF parameter list
AP 15C0	DFHSZIDX	SZ 1	Entry	1 Install/discard resource pointer
AP 15C1	DFHSZIDX	SZ 1	Exit	1 Install/discard resource pointer
AP 15C2	DFHSZIDX	Exc	GETMAIN fail	1 SMGF parameter list
AP 15C3	DFHSZREQ	SZ 1	Entry	1 Current work element

Table 48. FEPI trace entries (continued)

Point ID	Module	Lvl	Type	Data area description
AP 15C4	DFHSZREQ	SZ 1	Entry	1 Current work element
AP 15C5	DFHSZ2OD	SZ 1	About to SEND a negative response and enter drain processing	3 VTAM RPL
AP 15C6	DFHSZ2OD	SZ 1	About to issue a RECEIVE to purge the remainder of the good morning message	3 VTAM RPL
AP 15C7	DFHSZ2OD	SZ 1	About to SEND a positive response	3 VTAM RPL
AP 15C8	DFHSZ2OD	SZ 1	About to SEND a negative response	3 VTAM RPL
AP 15C9	DFHSZ2OD	SZ 1	About to SEND a positive response to a good morning message	3 VTAM RPL

Transaction initiation

The trace entries in the following table are related to transaction initiation.

Table 49. Transaction initiation trace entries

Point ID	Module	Lvl	Type	Data
AP 1700	DFHTFIQ	AP 1	Entry	1 DFHTFIQ parameter list
AP 1701	DFHTFIQ	AP 1	Exit	1 DFHTFIQ parameter list
AP 1702	DFHTFIQ	Exc	Recovery	1 DFHTFIQ parameter list
AP 1703	DFHTFIQ	Exc	Invalid format	1 DFHTFIQ parameter list
AP 1704	DFHTFIQ	Exc	Invalid function	1 DFHTFIQ parameter list
AP 1705	DFHTFIQ	Exc	GETMAIN failure	1 DFHTFIQ parameter list 2 DFHSMGF or DFHSMMC parameter list
AP 1710	DFHTFRF	AP 1	Entry	1 DFHTFRF parameter list 2 tcte_trace_1
AP 1711	DFHTFRF	AP 1	Exit	1 DFHTFRF parameter list 2 tcte_trace_1
AP 1712	DFHTFRF	Exc	Recovery	1 DFHTFRF parameter list 2 tcte_trace_1 3 Kernel error data
AP 1713	DFHTFRF	Exc	Invalid format	1 DFHTFRF parameter list 2 tcte_trace_1
AP 1714	DFHTFRF	Exc	Invalid function	1 DFHTFRF parameter list 2 tcte_trace_1
AP 1715	DFHTFRF	Exc	No terminal	1 DFHTFRF parameter list 2 tcte_trace_1
AP 1716	DFHTFRF	Exc	GETMAIN failed	1 DFHTFRF parameter list 2 tcte_trace_1

Table 49. Transaction initiation trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP 1717	DFHTFRF	Exc	Restart attach failure	1 DFHTFRF parameter list 2 tcte_trace_1
AP 1719	DFHTFRF	Exc	Invalid response from DFHUS	1 DFHTFRF parameter list 2 tcte_trace_1
AP 171F	DFHTFRF	Exc	Internal logic error	1 DFHTFRF parameter list 2 tcte_trace_1
AP 1730	DFHTFBBF	AP 1	Entry	1 DFHTFBBF parameter list 2 tcte_trace_1
AP 1731	DFHTFBBF	AP 1	Exit	1 DFHTFBBF parameter list 2 tcte_trace_1
AP 1732	DFHTFBBF	Exc	Recovery	1 DFHTFBBF parameter list 2 tcte_trace_1 3 Kernel error data
AP 1733	DFHTFBBF	Exc	Invalid format	1 DFHTFBBF parameter list 2 tcte_trace_1
AP 1734	DFHTFBBF	Exc	Invalid function	1 DFHTFBBF parameter list 2 tcte_trace_1
AP 1735	DFHTFBBF	Exc	No terminal	1 DFHTFBBF parameter list 2 tcte_trace_1
AP 1736	DFHTFBBF	Exc	Transaction abend	1 DFHTFBBF parameter list 2 tcte_trace_1 3 Abend code
AP 1737	DFHTFBBF	Exc	Transaction start-up failed	1 DFHTFBBF parameter list 2 tcte_trace_1 3 FMH5 4 DFHXMER parameter list
AP 1738	DFHTFBBF	Exc	Remote attach failed	1 DFHTFBBF parameter list 2 tcte_trace_1 3 Abend code 4 DFHIS parameter list
AP 1739	DFHTFBBF	Exc	Transaction start-up failed	1 DFHTFBBF parameter list 2 tcte_trace_1 3 Abend code 4 DFHUSRM parameter list
AP 1740	DFHTFBBF	Exc	LUC init call failed	1 DFHTFBBF parameter list 2 tcte_trace_1 3 Abend code 4 DFHLUC parameter list
AP 1741	DFHTFBBF	Exc	Terminal sharing profile not found	1 DFHTFBBF parameter list 2 tcte_trace_1 3 Abend code 4 DFHTM parameter list

Table 49. Transaction initiation trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP 1742	DFHTFBBF	Exc	Inbound FMH error	1 DFHTFBBF parameter list 2 tcte_trace_1 3 Abend code 4 Abend instance 5 FMH5
AP 1743	DFHTFBBF	Exc	Journal write failure	1 DFHTFBBF parameter list 2 tcte_trace_1 3 Abend code 4 Abend instance 5 JCA
AP 1744	DFHTFBBF	Exc	Purge received from SMGF	1 DFHTFBBF parameter list 2 tcte_trace_1 3 Abend code 4 SMGF parameter list
AP 1745	DFHTFBBF	Exc	Bad response recieved from SMGF	1 DFHTFBBF parameter list 2 tcte_trace_1 3 Abend code 4 SMGF parameter list
AP 1746	DFHTFBBF	Exc	Purge received from SMMC	1 DFHTFBBF parameter list 2 tcte_trace_1 3 Abend code 4 SMMC parameter list
AP 1747	DFHTFBBF	Exc	Bad response received from SMMC	1 DFHTFBBF parameter list 2 tcte_trace_1 3 Abend code 4 SMMC parameter list
AP 1748	DFHTFBBF	Exc	Purged received from USXM	1 DFHTFBBF parameter list 2 tcte_trace_1 3 Abend code 4 SMMC parameter list
AP 1749	DFHTFBBF	Exc	Bad response received from USXM	1 DFHTFBBF parameter list 2 tcte_trace_1 3 Abend code 4 SMMC parameter list
AP 1750	DFHTFBBF	Exc	Inherited UOW_ID is invalid	1 DFHTFBBF parameter list 2 tcte_trace_1 3 XMIQ parameter list
AP 1751	DFHZSUP	Exc	DFHRMLNM FUNCTION(ADD_LINK) call failure	1 DFHTFBBFM parameter list 2 tcte_trace_1 3 Abend code (AZCQ) 4 DFHRMLNM parameter list (failing call) 5 LINK id

Table 49. Transaction initiation trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP 1755	DFHTFBF	Exc	After call to DFHRTSU	1 DFHTFBF parameter list 2 Address of terminal 3 Abend code 4 DFHRTSU parameter list
AP 1790	DFHTFXM	AP 1	Entry	1 TFXM parameter list
AP 1791	DFHTFXM	AP 1	Exit	1 TFXM parameter list
AP 1792	DFHTFXM	Exc	Recovery entered	1 TFXM parameter list
AP 1793	DFHTFXM	Exc	Invalid format	1 TFXM parameter list
AP 1794	DFHTFXM	Exc	Invalid function	1 TFXM parameter list
AP 1795	DFHTFXM	Exc	RMWT failure	1 RMWT parameter list
AP 1796	DFHTFXM	Exc	Inbound FMH error	1 DFHTFXM parameter list 2 tcte_trace_1 3 Abend code 4 Abend instance 5 FMH5
AP 1797	DFHTFXM	Exc	Journal write failure	1 DFHTFXM parameter list 2 tcte_trace_1 3 Abend code 4 Abend instance 5 JCA
AP 1798	DFHTFXM	Exc	Purge received from SMGF	1 DFHTFXM parameter list 2 tcte_trace_1 3 Abend code 4 SMGF parameter list
AP 1799	DFHTFXM	Exc	Bad response recieved from SMGF	1 DFHTFXM parameter list 2 tcte_trace_1 3 Abend code 4 SMGF parameter list
AP 179A	DFHTFXM	Exc	Purge received from SMMC	1 DFHTFXM parameter list 2 tcte_trace_1 3 Abend code 4 SMMC parameter list
AP 179B	DFHTFXM	Exc	Bad response received from SMMC	1 DFHTFXM parameter list 2 tcte_trace_1 3 Abend code 4 SMMC parameter list
AP 17B0	DFHMRXM	AP 1	Entry	1 MRXM parameter list
AP 17B1	DFHMRXM	AP 1	Exit	1 MRXM parameter list
AP 17B2	DFHMRXM	Exc	Recovery entered	1 MRXM parameter list
AP 17B3	DFHMRXM	Exc	Invalid format	1 MRXM parameter list

Table 49. Transaction initiation trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP 17B4	DFHMRXM	Exc	Invalid function	1 MRXM parameter list
AP 17B5	DFHMRXM	Exc	RMWT failure	1 RMWT parameter list
AP 17B6	DFHMRXM	Exc	Remote attach failed	1 DFHMRXM parameter list 2 tcte_trace_1 3 Abend code 4 DFHIS parameter list
AP 17B7	DFHMRXM	Exc	Terminal sharing profile not found	1 DFHMRXM parameter list 2 tcte_trace_1 3 Abend code 4 DFHTM parameter list
AP 17B8	DFHMRXM	Exc	Inbound FMH error	1 DFHMRXM parameter list 2 tcte_trace_1 3 Abend code 4 Abend instance 5 FMH5
AP 17B9	DFHMXRM	Exc	Purge received from SMGF	1 DFHMXRM parameter list 2 tcte_trace_1 3 Abend code 4 SMGF parameter list
AP 17BA	DFHMRXM	Exc	Bad response recieved from SMGF	1 DFHMRXM parameter list 2 tcte_trace_1 3 Abend code 4 SMGF parameter list
AP 17BB	DFHMRXM	Exc	DFHRMLNM FUNCTION(ADD_LINK) call failure	1 DFHTMRXM parameter list 2 tcte_trace_1 3 Abend code (AZCQ) 4 DFHRMLNM parameter list (failing call) 5 LINK id
AP 17BD	DFHMRXM	Exc	After call to DFHRTSU	1 DFHMRXM parameter list 2 Address of terminal 3 Abend code 4 DFHRTSU parameter list
AP 17C0	DFH62XM	AP 1	Entry	1 62XM parameter list
AP 17C1	DFH62XM	AP 1	Exit	1 62XM parameter list
AP 17C2	DFH62XM	Exc	RMWT failure	1 RMWT parameter list
AP 17C3	DFH62XM	Exc	Invalid format	1 62XM parameter list
AP 17C4	DFH62XM	Exc	Invalid function	1 62XM parameter list
AP 17C5	DFH62XM	Exc	Recovery entered	1 62XM parameter list

Table 49. Transaction initiation trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP 17C6	DFH62XM	Exc	Transaction start-up failed	1 DFH62XM parameter list 2 tcte_trace_1 3 FMH5 4 DFHXMER parameter list
AP 17C7	DFH62XM	Exc	Remote attach failed	1 DFH62XM parameter list 2 tcte_trace_1 3 Abend code 4 DFHIS parameter list
AP 17C8	DFH62XM	Exc	Transaction start-up failed	1 DFH62XM parameter list 2 tcte_trace_1 3 Abend code 4 DFHUSRM parameter list
AP 17C9	DFH62XM	Exc	LUC init call failed	1 DFH62XM parameter list 2 tcte_trace_1 3 Abend code 4 DFHLUC parameter list
AP 17CA	DFH62XM	Exc	Terminal sharing profile not found	1 DFH62XM parameter list 2 tcte_trace_1 3 Abend code 4 DFHTM parameter list
AP 17CB	DFH62XM	Exc	Inbound FMH error	1 DFH62XM parameter list 2 tcte_trace_1 3 Abend code 4 Abend instance 5 FMH5
AP 17CC	DFH62XM	Exc	Journal write failure	1 DFH62XM parameter list 2 tcte_trace_1 3 Abend code 4 Abend instance 5 JCA
AP 17CD	DFH62XM	Exc	Purge received from SMGF	1 DFH62XM parameter list 2 tcte_trace_1 3 Abend code 4 SMGF parameter list
AP 17CE	DFH62XM	Exc	Bad response recieved from SMGF	1 DFH62XM parameter list 2 tcte_trace_1 3 Abend code 4 SMGF parameter list
AP 17CF	DFH62XM	Exc	Purge received from SMMC	1 DFH62XM parameter list 2 tcte_trace_1 3 Abend code 4 SMMC parameter list
AP 17D0	DFH62XM	Exc	Bad response received from SMMC	1 DFH62XM parameter list 2 tcte_trace_1 3 Abend code 4 SMMC parameter list

Table 49. Transaction initiation trace entries (continued)

Point ID	Module	Lvl	Type	Data	
AP 17D1	DFH62XM	Exc	DFHRMLNM FUNCTION(ADD_LINK) call failure	1	DFHT52XM parameter list
				2	tcte_trace_1
				3	Abend code (AZCQ)
				4	DFHRMLNM parameter list (failing call)
				5	LINK id
AP 17D3	DFH62XM	Exc	After call to DFHRTSU	1	DFH62XM parameter list
				2	Address of terminal
				3	Abend code
				4	DFHRTSU parameter list

Surrogate terminal interface

Table 50. Surrogate terminal interface trace points

Point ID	Module	Lvl	Type	Data	
AP 1910	DFHRTSU	1	Entry	1 DFHRTSU parameter list	
AP 1911	DFHRTSU	1	Exit	1 DFHRTSU parameter list	
AP 1912	DFHRTSU	Exc	Recovery	1	DFHRTSU parameter list
				2	Kernel parameter list
AP 1913	DFHRTSU	Exc	Invalid format	1 DFHRTSU parameter list	
AP 1914	DFHRTSU	Exc	Invalid function	1 DFHRTSU parameter list	
AP 1915	DFHRTSU	Exc	Invalid surrogate	1 DFHRTSU parameter list	
AP 1916	DFHRTSU	Exc	Invalid state	1	DFHRTSU parameter list
				2	TCTEUSRS
AP 1917	DFHRTSU	Exc	Invalid saved_state	1	DFHRTSU parameter list
				2	TCTEUSRS
				2	TCTEUSRV

Application language interface

Table 51. Language interface trace points

Point ID	Module	Lvl	Type	Data	
AP 1940	DFHAPLI	1	Entry	See Table 52 on page 102	
AP 1941	DFHAPLI	1	Exit	See Table 52 on page 102	
AP 1942	DFHAPLI	Exc	Recovery	Current parameter list (see note)	
AP 1943	DFHAPLI	Exc	Invalid format	1	DFHAPLI parameter list
AP 1944	DFHAPLI	Exc	Invalid function	1 DFHAPLI parameter list	
AP 1945	DFHAPLI	Exc	Missing parameter	1 DFHAPLI parameter list	
AP 1948	DFHAPLI	1	LE/370 call	See Table 53 on page 103	
AP 1949	DFHAPLI	1	LE/370 return	See Table 53 on page 103	
AP 194A	DFHAPLI	1	COBOL2 call	See Table 54 on page 104	

Table 51. Language interface trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 194B	DFHAPLI	1	COBOL2 return	See Table 54 on page 104
AP 194C	DFHAPLI	1	C/370™ call	See Table 55 on page 105
AP 194D	DFHAPLI	1	C/370 return	See Table 55 on page 105
AP 194E	DFHAPLI	Exc	Determine working storage failed	1 DFHAPLI parameter list
AP 1950	DFHAPLI	Exc	LE/370 error	LE/370 reason code
AP 1951	DFHAPLI	Exc	COBOL/2 error	
AP 1952	DFHAPLI	Exc	C/370 error	C/370 reason code
AP 1960	DFHAPLJ	1	Entry	1 DFHAPLI parameter list
AP 1961	DFHAPLJ	1	Exit	1 DFHAPLI parameter list
AP 1962	DFHAPLJ	Exc	Recovery	1 DFHAPLI parameter list
AP 1963	DFHAPLJ	Exc	Invalid format	1 DFHAPLI parameter list
AP 1964	DFHAPLJ	Exc	Invalid function	1 DFHAPLI parameter list
AP 1965	DFHAPLJ	Exc	Error occurred within JVM	1 DFHAPLI parameter list
# AP 1966	DFHAPLJ	Exc	Invalid URM fetch	1 DFHAPLI parameter list
# AP 1967	DFHAPLJ	Exc	Invalid URM call	1 DFHAPLI parameter list
# AP 1968	DFHAPLJ	Exc	System Exit from JVM	1 DFHAPLI parameter list

Note: The current parameter list relates to the function being performed at the time of failure, and is as shown for AP 1940 in 52. For an application problem, the function is usually Start Program.

Table 52. DFHAPLI entry/exit trace data fields

Function	Data fields for trace point AP 1940	Data fields for trace point AP 1941
Initialize languages		
Terminate languages		
Establish language	<ol style="list-style-type: none"> 1. Program name 2. Program load point 3. Program entry point 4. Program length 5. Execution key 6. Data location (above below 16 MB line) 7. User-defined language 8. Old language block 	<ol style="list-style-type: none"> 1. Language established by CICS 2. New language block 3. Abend code

Table 52. DFHAPLI entry/exit trace data fields (continued)

Function	Data fields for trace point AP 1940	Data fields for trace point AP 1941
Start program	<ol style="list-style-type: none"> 1. Program name 2. CEDF status 3. Execution set (full API or DPL subset) 4. Environment type 5. SYNCONRETURN 6. Language block 7. Parameter-list address 8. COMMAREA address and length 9. Link level 	<ol style="list-style-type: none"> 1. Abend code 2. Program name
Find program attributes	<ol style="list-style-type: none"> 1. RSA address 	<ol style="list-style-type: none"> 1. Program entry point 2. Name at entry point 3. Working storage address 4. Static storage address
Goto	<ol style="list-style-type: none"> 1. RSA address 	<ol style="list-style-type: none"> 1. Parameter list 2. RSA address 3. LE/370 entry point

Table 53. LE/370 call/return trace data fields

Function	Data fields for trace point AP 1948	Data fields for trace point AP 1949
Partition initialization	<ol style="list-style-type: none"> 1. Function 2. Parameter list 3. System use 	<ol style="list-style-type: none"> 1. Function 2. Reason code 3. LE/370 partition token 4. LE/370 Interface level 5. LE/370 thread workarea length 6. Language availability bits
Partition termination	<ol style="list-style-type: none"> 1. Function 2. Parameter list 	<ol style="list-style-type: none"> 1. Function 2. Reason code
Thread initialization	<ol style="list-style-type: none"> 1. Function 2. Parameter list 3. Program name 4. PGMINFO1 (see page Table 56 on page 106) 	<ol style="list-style-type: none"> 1. Function 2. Reason code 3. Program name 4. LE/370 Thread token
Thread termination	<ol style="list-style-type: none"> 1. Function 2. Parameter list 	<ol style="list-style-type: none"> 1. Function 2. Reason code
Run-Unit Initialization	<ol style="list-style-type: none"> 1. Function 2. Parameter list 3. Program name 4. PGMINFO1 (see page Table 56 on page 106) 	<ol style="list-style-type: none"> 1. Function 2. Reason code 3. Program name 4. LE/370 run-unit token
Run-Unit Initialization and begin invocation	<ol style="list-style-type: none"> 1. Function 2. Parameter list 3. Program name 4. PGMINFO1 (see page Table 56 on page 106) 5. and-begin 	<ol style="list-style-type: none"> 1. Function 2. Reason code 3. Program name 4. LE/370 run-unit token 5. and-begin

Table 53. LE/370 call/return trace data fields (continued)

Function	Data fields for trace point AP 1948	Data fields for trace point AP 1949
Run-unit termination	1. Function 2. Parameter list 3. Program name	1. Function 2. Reason code 3. Program name
Run-unit begin invocation	1. Function 2. Parameter list 3. Program name	1. Function 2. Reason code 3. Program name
Run-unit end invocation	1. Function 2. Parameter list 3. Program name 4. System use 5. Registers at abend	1. Function 2. Reason code 3. Program name 4. Contcode
Establish ownership type	1. Function 2. Parameter list 3. Program name 4. PGMINFO1 (see page Table 56 on page 106)	1. Function 2. Reason code 3. Program name 4. PGMINFO2 (see page Table 57 on page 107)
Determine working storage	1. Function 2. Parameter list 3. Program name	1. Function 2. Reason code 3. Program name 4. Working storage address 5. Working storage length 6. Static storage address 7. Static storage length
Perform Goto	1. Function 2. Parameter list 3. Program name	1. Function 2. Reason code 3. Program name 4. Out-of-block flag
Program check recovery	1. Function 2. Parameter list 3. Program name 4. Celinfo	1. Function 2. Return code 3. Program name 4. Reason code 5. Contcode
Note: LE/370 parameter lists are described starting on page "LE/370 parameter lists" on page 107		

Table 54. COBOL/2™ call/return trace data fields

Function	Data fields for trace point AP 194A	Data fields for trace point AP 194B
Partition initialization	1. Function 2. Parameter list 3. System flags	1. Function 2. Reason code 3. COBOL/2 partition token 4. COBOL/2 Interface level
Partition termination	1. Function 2. Parameter list	1. Function 2. Reason code
Thread initialization	1. Function 2. Parameter list 3. Program name	1. Function 2. Reason code 3. Program name 4. COBOL/2 Thread token
Thread termination	1. Function 2. Parameter list	1. Function 2. Reason code

Table 54. COBOL/2™ call/return trace data fields (continued)

Function	Data fields for trace point AP 194A	Data fields for trace point AP 194B
Run-Unit Initialization	1. Function 2. Parameter list 3. Program name	1. Function 2. Reason code 3. Program name
Run-unit termination	1. Function 2. Parameter list 3. Program name 4. Termino 5. Registers at abend	1. Function 2. Reason code 3. Program name 4. Contcode
Determine program type	1. Function 2. Parameter list 3. Program name	1. Function 2. Reason code 3. Program name 4. Program flags
Working storage locate	1. Function 2. Parameter list 3. Program name	1. Function 2. Reason code 3. Program name 4. W/S address 5. W/S length
Note: COBOL/2 parameter lists are described starting on page “COBOL2 parameter lists” on page 110		

Table 55. C/370 call/return trace data fields

Function	Data fields for trace point AP 194C	Data fields for trace point AP 194D
Partition initialization	1. Function 2. Parameter list	1. Function 2. Reason code 3. C/370 partition token 4. C/370 Interface level
Partition termination	1. Function 2. Parameter list	1. Function 2. Reason code
Thread initialization	1. Function 2. Parameter list 3. Program name	1. Function 2. Reason code 3. Program name 4. C/370 Thread token
Thread termination	1. Function 2. Parameter list	1. Function 2. Reason code
Run-Unit Initialization	1. Function 2. Parameter list 3. Program name	1. Function 2. Reason code 3. Program name 4. C/370 run-unit token
Run-unit termination	1. Function 2. Parameter list 3. Program name 4. Celinfo 5. Registers at abend	1. Function 2. Reason code 3. Program name 4. Contcode
Determine program type	1. Function 2. Parameter list 3. Program name	1. Function 2. Reason code 3. Program name 4. Program flags

Table 55. C/370 call/return trace data fields (continued)

Function	Data fields for trace point AP 194C	Data fields for trace point AP 194D
Working storage locate	<ol style="list-style-type: none"> 1. Function 2. Parameter list 3. Program name 	<ol style="list-style-type: none"> 1. Function 2. Reason code 3. Program name 4. W/S address 5. W/S length
<p>Note: C/370 parameter lists are described starting on page "C/370 parameter lists" on page 111</p>		

Table 56. PGMINFO1 structure. This structure, used for communication between CICS and LE/370, is referred to in figures 52 and 53. The structure consists of 11 fullwords.

Displacement (hex)	Fullword contents
00	Length of the structure
04	The language of the run unit (main program) as known to CICS. One of the first 6 bits is set on with the following meaning: <ol style="list-style-type: none"> 1. Assembler 2. C/370 3. Cobol/2 4. PL/I 5. RPG (not supported by CICS) 6. Not known or LE/370
08	Address of the run unit program
0C	Length of the run unit program
10	Entry point address of the run unit; bit zero of this field is set on in the case of programs running in 31-bit addressing mode.
14	Modified entry address
18	Address of the run unit work area preallocated above 16 megabytes
1A	Address of the run unit work area preallocated below 16 megabytes
20	Address of the application program argument list, which is a 2-fullword structure containing the addresses of the user EIB and COMMAREA
24	Address of the run time options string passed by CICS to LE/370.
28	Length of the run time options string
2C	Pointer to the program name

#

Table 57. PGMINFO2 structure. This structure, used for communication between CICS and LE/370, is referred to in Table 53 on page 103. Some fields are used when the language is not LE/370. The structure consists of 7 fullwords.

Displacement (hex)	Fullword contents
00	Length of the structure
04	Size of the work area required to run the program. This is used by LE/370 for storage above the 16-megabyte line, and by C/370 for all storage. For C/370 only, the first bit of this fullword is set on to indicate storage above the 16-megabyte line.
08	Size of the work area, below the 16-megabyte line, that is required to run the program (LE/370 only).
0C	The first ten bits are binary flags. The meaning of an on setting for each bit is as follows: <ol style="list-style-type: none"> 1. The program can run under LE/370. 2. LE/370 knows the language of the program (LE/370 only). 3. More than one language is used in the program (LE/370 only). 4. The program can run under LE/370, but is not compiled by an LE/370 compiler. LE/370 must run the program in compatibility mode (LE/370 only). 5. The program is executable under LE/370. 6. The program language is Assembler. 7. The program language is C/370. 8. The program language is Cobol II. 9. The program language is OS/VS Cobol. 10. The program language is PL/I.
10	Language ID number of the first executable CSECT in the program (LE/370 only)
14	Address of CEECOPT (Global LE runtime options)
18	Address of CEEVOPT (Specific LE runtime options)

LE/370 parameter lists

The parameter list passed to LE/370 varies with the function as follows.

Partition initialization:

1. Function (partition initialization)
2. Address of reason code
3. Address of system EIB
4. Address of 240-byte work-area for use by LE/370
5. Address of a double-word into which LE/370 saves its partition token
6. Address of a fullword containing the length of the EIB
7. Address of a fullword into which LE/370 saves the length of the thread work-area required for LE programs
8. Address of a fullword into which LE/370 saves the LE/370 Interface Level number
9. Address of a pointer to the CICS Get CAA module DFHGCAA
10. Address of a pointer to the CICS Set CAA module DFHSCAA
11. Address of the LANGDEF area
12. Address of the 'language availability' area set by LE/370. Flags set by LE/370 in this area that are of interest to CICS are:

```

x . . . . . ASMINIT - LE supports Assembler
. x . . . . . CINIT - LE supports C
. . x . . . . . COBINIT - LE supports COBOL2
. . . . x . . . . PLIINIT - LE supports PL/I

```

#

13. Address of the service routine vector table.

Partition termination:

1. Function (partition termination)
2. Address of reason code
3. Address of system EIB
4. Address of 240-byte work-area for use by LE/370
5. Address of LE/370 partition token.

Thread initialization:

1. Function (thread initialization)
2. Address of reason code
3. Address of system EIB
4. Address of 240-byte work-area for use by LE/370
5. Address of LE/370 partition token
6. Address of a double-word into which LE/370 saves its thread token
7. Address of LE/370 Thread Work-area
8. Address of pgminfo1
9. Address of pgminfo2.

Thread termination:

1. Function (thread termination)
2. Address of reason code
3. Address of system EIB
4. Address of 240-byte work-area for use by LE/370
5. Address of LE/370 partition token
6. address of LE/370 thread token.

Run-unit initialization/Run-unit initialization and begin invocation:

1. Function (run-unit initialization)
2. Address of reason code
3. Address of system EIB
4. Address of 240-byte work-area for use by LE/370
5. Address of LE/370 partition token
6. Address of LE/370 thread token
7. Address of LE/370 run-unit token
8. Address of pgminfo1
9. Address of pgminfo2.
10. Address of ioinfo.
11. Address of runinfo. Runinfo is a fullword containing bits:
 - bit 0 - off**
Indicates rununit initialization only
 - bit 0 - on**
Indicates combined rununit initialization and begin invocation
 - bit 1 - on**
Indicates CICSTS passing a reusable RUWA (allows LE optimization)

Run-unit begin invocation:

1. Function (run-unit begin invocation)
2. Address of reason code
3. Address of system EIB
4. Address of 240-byte work-area for use by LE/370
5. Address of LE/370 partition token

6. Address of LE/370 thread token
7. Address of LE/370 run-unit token
8. Address of pgminfo1
9. Address of pgminfo2
10. Address of ioinfo

Run-unit end invocation:

1. Function (run-unit end invocation)
2. Address of reason code
3. Address of system EIB
4. Address of 240-byte work-area for use by LE/370
5. Address of LE/370 partition token
6. Address of LE/370 thread token
7. Address of LE/370 run-unit token
8. Address of pgminfo1
9. Address of pgminfo2
10. Address of celinfo.

Program check recovery:

1. Function (program check recovery)
2. Address of reason code
3. Address of celinfo
4. Address of 240-byte work-area for use by LE/370

Run-unit termination:

1. Function (run-unit termination)
2. Address of reason code
3. Address of system EIB
4. Address of 240-byte work-area for use by LE/370
5. Address of LE/370 partition token
6. Address of LE/370 thread token
7. Address of LE/370 run-unit token.

Establish ownership type:

1. Function (establish ownership type)
2. Address of reason code
3. Address of system EIB
4. Address of 240-byte work-area for use by LE/370
5. Address of LE/370 partition token
6. Reserved
7. Reserved
8. Address of pgminfo1
9. Address of pgminfo2.

Determine working storage:

1. Function (determine working storage)
2. Address of reason code
3. Address of system EIB
4. Address of 240-byte work-area for use by LE/370
5. Address of LE/370 partition token
6. Address of LE/370 thread token for the user transaction
7. Address of LE/370 run-unit token for the user transaction
8. Address of the Language Definition bits
9. Address of the user program's register save area
10. Address of a fullword into which LE/370 saves the address of the user program's working storage

11. Address of a fullword into which LE/370 saves the length of the user program's working storage
12. Address of a fullword into which LE/370 saves the address of the user program's static storage
13. Address of a fullword into which LE/370 saves the length of the user program's static storage
14. Address of a fullword into which LE/370 saves the entry point of the program
15. Address of a fullword into which LE/370 saves the address of a character string, preceded by a length halfword, giving the internal name of the program (currently not supported by CICS).

Perform Goto:

1. Function (perform Goto)
2. Address of reason code
3. Address of system EIB
4. Address of 240-byte work-area for use by LE/370
5. Address of LE/370 partition token
6. Address of LE/370 thread token for the user transaction
7. Address of LE/370 run-unit token for the user transaction
8. Address of the Language Definition bits
9. Address of the label argument of the Handle command
10. Address of the user's RSA reflecting the registers at the last EXEC CICS command
11. Address of a fullword into which LE/370 may set the Cross-Call error flag
12. Address of a field holding the abend code from the TACB
13. Address of a field holding the value of Register 13 at the time of the abend.

COBOL2 parameter lists

The parameter list passed to COBOL2 varies with the function as follows.

Partition initialization:

1. Function (partition initialization)
2. Address of system EIB
3. Address of take-token entry point (DFHEIPTT)
4. Address of GETMAIN entry point (DFHEIPGM)
5. Address of FREEMAIN entry point (DFHEIPFM)
6. Address of a 2-byte area 'system_flags' containing:
 - Mode Switching flag (X'80' bit)
 - CSZOPSYS (Operating System) value.
7. Address of a fullword containing the CICS interface-level number (always set to 1)
8. Address of a double-word into which COBOL2 saves its partition token
9. Address of a fullword into which COBOL2 saves its interface-level number.

Partition termination: This function is not supported for COBOL2.

Thread initialization:

1. Function (thread initialization)
2. Address of COBOL2 partition token
3. Address of user EIB
4. Address of CICS thread token (i.e. the TCA)
5. Address of a double-word into which COBOL2 saves its thread token.

Thread termination:

1. Function (thread termination)
2. Address of COBOL2 partition token

3. Address of COBOL2 thread token.

Run-unit initialization:

1. Function (run-unit initialization)
2. Address of COBOL2 partition token
3. Address of COBOL2 thread token
4. Address of module entry point
5. Address of EIB and COMMAREA address vector.

Run-unit begin invocation: This function is not supported for COBOL2.

Run-unit end invocation: This function is not supported for COBOL2.

Run-unit termination:

1. Function (run-unit termination)
2. Address of COBOL2 partition token
3. Address of COBOL2 thread token
4. Address of COBOL2 run-unit token
5. Address of terminfo.

Determine program type:

1. Function (determine program type)
2. Address of COBOL2 partition token
3. Reserved
4. Address of token-holding program load point
5. Address of token-holding program entry point
6. Address of fullword containing program flags to be set by COBOL2
7. Program flags fullword.

Working storage locate:

1. Function (working storage locate)
2. Address of COBOL2 partition token
3. Address of COBOL2 thread token for the transaction
4. Address of COBOL2 run-unit token for the transaction
5. Address of a fullword into which COBOL2 saves the address of the user program's working storage
6. Address of a fullword into which COBOL2 saves the length of the user program's working storage.

Perform Goto: This function is not supported for COBOL2.

C/370 parameter lists

The parameter list passed to C/370 varies with the function as follows.

Partition initialization:

1. Function (partition initialization)
2. Address of reason code
3. Address of system EIB
4. Address of 240-byte work-area for use by LE/370
5. Address of a double-word into which C/370 saves its partition token
6. Reserved
7. Address of a fullword containing the length of the EIB
8. Address of a fullword into which C/370 saves the length of the thread work-area required for C programs
9. Address of a fullword into which C/370 saves its interface-level number.

Partition termination:

1. Function (partition termination)
2. Address of reason code
3. Address of user EIB
4. Address of 240-byte work-area for use by C/370
5. Address of C/370 partition token.

Thread initialization:

1. Function (thread initialization)
2. Address of reason code
3. Address of user EIB
4. Address of 240-byte work-area for use by C/370
5. Address of C/370 partition token
6. Address of a double-word into which C/370 saves its thread token
7. Address of C/370 thread Work-area.

Thread termination:

1. Function (thread termination)
2. Address of reason code
3. Address of user EIB
4. Address of 240-byte work-area for use by C/370
5. Address of C/370 partition token
6. Address of C/370 thread token.

Run-unit initialization:

1. Function (run-unit initialization)
2. Address of reason code
3. Address of user EIB
4. Address of 240-byte work-area for use by C/370
5. Address of C/370 partition token
6. Address of C/370 thread token
7. Address of C/370 run-unit token
8. Address of C/370 run-unit work area
9. Address of token-holding module entry point
10. Address of EIB and COMMAREA address vector
11. Address of ioinfo.

Run-unit begin invocation: This function is not supported for C/370.

Run-unit end invocation: This function is not supported for C/370.

Run-unit termination:

1. Function (run-unit termination)
2. Address of reason code
3. Address of user EIB
4. Address of 240-byte work-area for use by C/370
5. Address of C/370 partition token
6. Address of C/370 thread token
7. Address of C/370 run-unit token
8. Address of celinfo.

Determine program type:

1. Function (determine program type)
2. Address of reason code
3. Address of user EIB
4. Address of 240-byte work-area for use by C/370
5. Address of C/370 partition token
6. Address of C/370 thread token

7. Address of token-holding program load point
8. Address of token-holding program entry point
9. Address of fullword containing program flags to be set by C/370
10. Address of fullword to receive the length of the required run-unit work-area
11. Program flags fullword.

Working storage locate:

1. Function (working storage locate)
2. Address of reason code
3. Address of user EIB
4. Address of 240-byte work-area for use by C/370
5. Address of C/370 partition token
6. Address of C/370 thread token for the user transaction
7. Address of the user program's register save area
8. Address of a fullword into which C/370 saves the address of the user program's working storage
9. Address of a fullword into which C/370 saves the length of the user program's working storage.

Perform Goto: This function is not supported for C/370.

Java virtual machine

Table 58. Connection to quiesce processing trace points

Point ID	Module	Lvl	Type	Data	
AP 1970	DFHCJVM	AP 1	Entry	1	Program name
				2	Class name
				3	Debug option
AP 1971	DFHCJVM	AP 1	Exit	1	Program name
				2	Class name
				3	Debug option
AP 1972	DFHCJVM	AP 2	Before Initargs call		
AP 1973	DFHCJVM	AP 2	After Initargs call		
AP 1974	DFHCJVM	AP 2	Before CreateJVM call		
AP 1975	DFHCJVM	AP 2	After CreateJVM call	1	jvm token
				2	eyecatcher text
				3	JNI InvokeInterface structure
				4	JNI NativeInterface token
				5	eyecatcher text
				6	JNI NativeInterface structure
				7	JNI Initargs structure
AP 1976	DFHCJVM	AP 2	Before find wrapper class call	1	Wrapper classname
AP 1977	DFHCJVM	AP 2	After find wrapper class call	1	Wrapper classname
AP 1978	DFHCJVM	AP 2	Before find Wrapper main method call		
AP 1979	DFHCJVM	AP 2	After find Wrapper main method call		
AP 197A	DFHCJVM	AP 2	Before build arguments call		
AP 197B	DFHCJVM	AP 2	After build arguments call		
AP 197C	DFHCJVM	AP 2	Before invoke wrapper and user class call	1	classname
AP 197D	DFHCJVM	AP 2	After invoke wrapper and user class call	1	classname

Table 58. Connection to quiesce processing trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 197E	DFHCJVM	AP 2	Before DestroyJVM call	1 JVM token
AP 197F	DFHCJVM	AP 2	After DestroyJVM call	1 JVM token
AP 1980	DFHCJVM	Exc	Add CICS Recovery failed	1 Return code
AP 1981	DFHCJVM	Exc	Delete CICS Recovery failed	1 Return code
AP 1982	DFHCJVM	Exc	Create_JVM Failed	
AP 1983	DFHCJVM	Exc	Find Wrapper Class failed	1 Wrapper classname 2 Eyecatcher 3 Classpath value
AP 1984	DFHCJVM	Exc	Find Wrapper main method failed	
AP 1985	DFHCJVM	Exc	Build arguments call failed	
AP 1987	DFHCJVM	Exc	Exception from Wrapper	1 Exception
AP 1988	DFHCJVM	AP 2	Before fetch of DFHJVMAT	
AP 1989	DFHCJVM	AP 2	After fetch of DFHJVMAT	
AP 198A	DFHCJVM	Exc	Fetch of DFHJVMAT failed	
AP 198B	DFHCJVM	Exc	Before call of DFHJVMAT	
AP 198C	DFHCJVM	Exc	After call of DFHJVMAT	
AP 198D	DFHCJVM	AP 2	After call of DFHJVMAT	1 eyecatcher 2 classpath value 3 eyecatcher 4 libpath value 5 eyecatcher 6 JNI Initargs structure
AP 198E	DFHCJVM	Exc	Change dir call failed	1 Pathname 2 Error message

Java hot-pooling

Table 59. Java hot pooling trace points

# Point ID	# Module	# Lvl	# Type	# Data
# AP 19A0	# DFHAPLH	# AP 1	# Entry	# 1 DFHAPLI parameter list
# AP 19A1	# DFHAPLH	# AP 1	# Exit	# 1 DFHAPLI parameter list
# AP 19A2	# DFHAPLH	# Exc	# Recovery	# 1 Current parameter list
# AP 19A3	# DFHAPLH	# Exc	# Invalid Format	# 1 DFHAPLI parameter list
# AP 19A4	# DFHAPLH	# Exc	# Invalid Function	# 1 DFHAPLI parameter list
# AP 19A5	# DFHAPLH	# AP 1	# Entry	# 1 DFHDSAT parameter list
# AP 19A6	# DFHAPLH	# Exc	# Error response from DFHAPPIS	# 1 DFHAPPI_ARG
# AP 19A7	# DFHAPLH	# AP 2	# Event PIP1 call init_sub_dp	# 1 APLH_PIP1_PARMS # 2 CEEXPTBL (PIPI) Table # 3 LE Runtime Options string

Table 59. Java hot pooling trace points (continued)

#	Point ID	Module	Lvl	Type	Data
#	AP 19A7	DFHAPLH	AP 2	Event PIPi call call_sub	1 APLH_PIPi_PARMS
#					2 AP_H8TCB
#					3 Program Name
#					4 Main Class Name (ASCII)
#	AP 19A7	DFHAPLH	AP 2	Event PIPi call term	1 APLH_PIPi_PARMS
#	AP 19A8	DFHAPLH	AP 2	Event PIPi return	1 APLH_PIPi_PARMS
#					2 AP_H8TCB
#					3 Program Name
#					4 Main Class Name (ASCII)
#	AP 19A9	DFHAPLH	AP 2	Error response from CEEPIPI	1 APLH_PIPi_PARMS
#	AP 19AA	DFHAPLH	AP 2	Event Hotpooling call	1 "fetch DFHJHPAT" or "1 program tranid *env"
#	AP 19AA	DFHAPLH	AP 2	Event Hotpooling return	1 "DFJHPAT"
#	AP 19AC	DFHAPLH	Exc	Error return from LE or HPJDLL	1 Message or Program Name
#	AP 19AD	DFHAPLH	AP 2	Event JavaVMInitArgs passed to JNICreateJavaVM()	1 createJVMoptions structure
#	AP 19AE	DFHAPLH	AP 2	Event JavaVMInitArgs structure returned from CreateJavaVM()	1 createJVMoptions structure
#	AP 19B0	DFHAPLH	Exc	DFHAPLH failed to load DFHAPPIV	1 DFHLDLD_ARG
#	AP 19B1	DFHAPLH	Exc	DFHAPLH failed to getmain PISV	1 DFHSMGF_ARG
#	AP 19B2	DFHAPLH	Exc	DFHAPLH failed to getmain PISB	1 DFHSMGF_ARG
#	AP 19B3	DFHAPLH	Exc	DFHAPLH failed to getmain work area	1 DFHSMGF_ARG
#	AP 19B4	DFHAPLH	Exc	LE passed invalid module name length to DFHAPLH	1 erroneous length
#	AP 19B5	DFHAPLH	Exc	DFHAPLH failed to load a program	1 DFHPGLD_ARG
#	AP 19B6	DFHAPLH	Exc	LE requested DFHAPLH to delete a program it had not loaded	1 erroneous program name
#	AP 19B7	DFHAPLH	Exc	DFHAPLH failed to release a program	1 DFHPGLD_ARG
#	AP 19B8	DFHAPLH	Exc	DFHAPLH failed to getmain storage for LE	1 DFHSMGF_ARG
#	AP 19B9	DFHAPLH	Exc	LE requested DFHAPLH to free storage it had not allocated	1 erroneous address & length
#	AP 19BA	DFHAPLH	Exc	DFHAPLH failed to freemain storage for LE	1 DFHSMGF_ARG
#	AP 19BB	DFHAPLH	Exc	DFHAPLH failed to inquire transaction data	1 DFHXMIQ_ARG
#	AP 19BC	DFHAPLH	Exc	DFHAPLH failed to write TD queue	1 DFHTDTD_ARG
#	AP 19BD	DFHAPLH	Exc	DFHAPLH failed to getmain internal storage	1 DFHSMGF_ARG
#	AP 19BE	DFHAPLH	Exc	DFHAPLH failed to freemain internal storage	1 DFHSMGF_ARG

Table 59. Java hot pooling trace points (continued)

# Point ID	Module	Lvl	Type	Data
# AP 19BF	DFHAPLH	Exc	DFHAPLH termination failed to release a program	1 DFHPGLD_ARG
# AP 19C0	DFHAPLH	Exc	DFHAPLH termination failed to freemain storage	1 DFHSMGF_ARG
# AP 19C1	DFHAPLH	Exc	DFHAPLH termination failed to freemain work area	1 DFHSMGF_ARG
# AP 19C2	DFHAPLH	Exc	DFHAPLH termination failed to freemain PISB	1 DFHSMGF_ARG
# AP 19C3	DFHAPLH	Exc	DFHAPLH termination failed to freemain PISV	1 DFHSMGF_ARG
# AP 19C4	DFHAPLH	Exc	DFHAPLH termination failed to release DFHAPPV	1 DFHLDLD_ARG

Program control

Table 60. Program control trace points

Point ID	Module	Lvl	Type	Data
AP 2000	DFHPCPG	PC 1	Entry	1 TCAPCTR type 2 TCAPCSR secondary request byte
AP 2001	DFHPCPG	PC 1	Exit	1 TCAPCTR type 2 TCAPCSR secondary request byte
AP 2003	DFHPCPG	Exc	Invalid function	1 TCAPCTR type 2 TCAPCSR secondary request byte 3 Program name

Signon

Table 61. Signon trace points

Point ID	Module	Lvl	Type	Data
AP 2040	DFHSNUS	AP 1	Entry	1 DFHSNUS parameter list
AP 2041	DFHSNUS	AP 1	Exit	1 DFHSNUS parameter list
AP 2042	DFHSNUS	Exc	Invalid function	1 DFHSNUS parameter list
AP 2043	DFHSNUS	Exc	Invalid format	1 DFHSNUS parameter list
AP 2044	DFHSNUS	AP 1	Recovery entered	1 DFHSNUS parameter list 2 Kernel error data
AP 2045	DFHSNUS	Exc	Unknown exception	1 DFHSNUS parameter list
AP 2046	DFHSNUS	Exc	Corrupted user token	1 DFHSNUS parameter list
AP 2047	DFHSNUS	Exc	DFHZCUT failure	1 DFHSNUS parameter list
AP 2048	DFHSNUS	AP 1	DFHSNEX before signon or signoff	1 DFHSNEX control block

Table 61. Signon trace points (continued)

Point ID	Module	Lvl	Type	Data	
AP 2049	DFHSNUS	AP 1	DFHSNEX after signon or signoff	1	DFHSNEX control block
AP 2050	DFHSNAS	AP 1	Entry	1	DFHSNUS parameter list
AP 2051	DFHSNAS	AP 1	Exit	1	DFHSNUS parameter list
AP 2052	DFHSNAS	AP 1	Recovery entered	1 2	DFHSNUS parameter list Kernel error data
AP 2053	DFHSNAS	Exc	Corrupted user token	1	DFHSNUS parameter list
AP 2054	DFHSNAS	Exc	Unknown exception	1	DFHSNUS parameter list
AP 2055	DFHSNAS	Exc	Unexpected reason	1	DFHSNUS parameter list
AP 2056	DFHSNAS	Exc	User token mismatch	1	DFHSNUS parameter list
AP 2060	DFHSNSU	AP 1	Entry	1	DFHSNUS parameter list
AP 2061	DFHSNSU	AP 1	Exit	1	DFHSNUS parameter list
AP 2062	DFHSNSU	AP 1	Recovery entered	1 2	DFHSNUS parameter list Kernel error data
AP 2063	DFHSNSU	Exc	Unknown exception	1	DFHSNUS parameter list
AP 2064	DFHSNSU	Exc	Corrupted user token	1	DFHSNUS parameter list
AP 2065	DFHSNSU	Exc	Language not supported	1	DFHSNUS parameter list
AP 2066	DFHSNSU	Exc	Second delete failed	1	DFHSNUS parameter list
AP 2067	DFHSNSU	Exc	User token mismatch	1	DFHSNUS parameter list
AP 2068	DFHSNSU	AP 1	Signon not by session	1	DFHSNUS parameter list
AP 2069	DFHSNSU	AP 1	Signon by surrogate	1	DFHSNUS parameter list
AP 206A	DFHSNSU	Exc	Default session signon failure	1	DFHSNUS parameter list
AP 206B	DFHSNSU	AP 1	Signoff not by session	1	DFHSNUS parameter list
AP 206C	DFHSNSU	AP 1	Signoff by surrogate	1	DFHSNUS parameter list
AP 206D	DFHSNSU	AP 1	Session not signed on	1	DFHSNUS parameter list
AP 2070	DFHSNPU	AP 1	Entry	1	DFHSNUS parameter list
AP 2071	DFHSNPU	AP 1	Exit	1	DFHSNUS parameter list
AP 2072	DFHSNPU	AP 1	Recovery entered	1 2	DFHSNUS parameter list Kernel error data
AP 2073	DFHSNPU	Exc	Language not supported	1	DFHSNUS parameter list

Table 61. Signon trace points (continued)

Point ID	Module	Lvl	Type	Data	
AP 2074	DFHSNPU	Exc	Language suffix error	1	DFHSNUS parameter list
AP 2075	DFHSNPU	Exc	Unknown exception	1	DFHSNUS parameter list
AP 2076	DFHSNPU	Exc	Corrupted user token	1	DFHSNUS parameter list
AP 2077	DFHSNPU	Exc	Message domain failure	1	DFHSNUS parameter list
AP 2078	DFHSNPU	Exc	User inquiry default error in signon	1	DFHSNUS parameter list
AP 2079	DFHSNPU	Exc	User inquiry default error in signoff	1	DFHSNUS parameter list
AP 2080	DFHSNTU	Exc	Entry	1	DFHSNUS parameter list
AP 2081	DFHSNTU	Exc	Exit	1	DFHSNUS parameter list
AP 2082	DFHSNTU	Exc	Invalid function	1	DFHSNUS parameter list
AP 2083	DFHSNTU	Exc	Recovery entered	1 2	DFHSNUS parameter list Kernel error data
AP 2084	DFHSNTU	Exc	DFHXMIQ failure in signon	1	DFHSNUS parameter list
AP 2085	DFHSNTU	Exc	Validate language code error	1	DFHSNUS parameter list
AP 2086	DFHSNTU	Exc	Unknown exception	1	DFHSNUS parameter list
AP 2087	DFHSNTU	Exc	User domain failure	1	DFHSNUS parameter list
AP 2088	DFHSNTU	Exc	Corrupted user token	1	DFHSNUS parameter list
AP 2089	DFHSNTU	Exc	Message domain failure	1	DFHSNUS parameter list
AP 208A	DFHSNTU	Exc	User inquiry default error in signon	1	DFHSNUS parameter list
AP 208B	DFHSNTU	Exc	Add transaction user error in signon	1	DFHSNUS parameter list
AP 208C	DFHSNTU	Exc	Delete transaction user error in signon	1	DFHSNUS parameter list
AP 208D	DFHSNTU	Exc	Unsuccessful backout	1	DFHSNUS parameter list
AP 208E	DFHSNTU	Exc	DFHXMIQ failure in signoff	1	DFHSNUS parameter list
AP 208F	DFHSNTU	Exc	User inquiry default error in signoff	1	DFHSNUS parameter list
AP 2090	DFHSNTU	Exc	Add transaction user error in signoff	1	DFHSNUS parameter list
AP 2091	DFHSNTU	Exc	Delete transaction user error in signoff	1	DFHSNUS parameter list
AP 2092	DFHSNTU	Exc	Delete user error in signoff	1	DFHSNUS parameter list
AP 2093	DFHSNTU	Exc	TCAM pool signon error	1	DFHSNUS parameter list
AP 2094	DFHSNTU	Exc	TCAM pool signoff error	1	DFHSNUS parameter list

Table 61. Signon trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 2095	DFHSNTU	Exc	Language not supported	1 DFHSNUS parameter list
AP 2096	DFHSNTU	Exc	Failure in XRF tracking	1 DFHSNUS parameter list
AP 2097	DFHSNTU	Exc	Failure to externalize signon	1 DFHSNUS parameter list
AP 20A0	DFHSNXR	Exc	Entry	1 DFHSNUS parameter list
AP 20A1	DFHSNXR	Exc	Exit	1 DFHSNUS parameter list
AP 20A2	DFHSNXR	Exc	Recovery entered	1 DFHSNUS parameter list 2 Kernel error data
AP 20A3	DFHSNXR	Exc	Invalid format	1 DFHSNUS parameter list
AP 20A4	DFHSNXR	Exc	Invalid function	1 DFHSNUS parameter list
AP 20A5	DFHSNXR	Exc	Invalid externalized buffer	1 DFHSNUS parameter list
AP 20A6	DFHSNXR	Exc	Invalid externalized block	1 DFHSNUS parameter list
AP 20A7	DFHSNXR	Exc	Message domain failure	1 DFHSNUS parameter list
AP 20A8	DFHSNXR	Exc	User inquiry default user error	1 DFHSNUS parameter list
AP 20A9	DFHSNXR	Exc	Null TCTTE address	1 DFHSNUS parameter list
AP 20AA	DFHSNXR	Exc	Invalid terminal type	1 DFHSNUS parameter list
AP 20AB	DFHSNXR	Exc	Invalid user token	1 DFHSNUS parameter list
AP 20AC	DFHSNXR	Exc	User domain failure	1 DFHSNUS parameter list
AP 20C0	DFHSNSG	AP 2	Before signon	1 Pointer to surrogate TCTTE 2 Surrogate TCTTE's DFHSNEX control block 3 Pointer to session's TCTTE 4 Session TCTTE's DFHSNEX control block
AP 20C1	DFHSNSG	AP 2	After signon	1 Pointer to surrogate TCTTE 2 Surrogate TCTTE's DFHSNEX control block 3 Pointer to session's TCTTE 4 Session TCTTE's DFHSNEX control block
AP 20C2	DFHSNSG	AP 2	Before signoff	1 Pointer to surrogate TCTTE 2 Surrogate TCTTE's DFHSNEX control block 3 Pointer to session's TCTTE 4 Session TCTTE's DFHSNEX control block

Table 61. Signon trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 20C3	DFHSNSG	AP 2	After signoff	1 Pointer to surrogate TCTTE 2 Surrogate TCTTE's DFHSNEX control block 3 Pointer to session's TCTTE 4 Session TCTTE's DFHSNEX control block
AP 20C4	DFHSNSG	AP 1	Entry	1 DFHSNUS parameter list
AP 20C5	DFHSNSG	AP 1	Exit	1 DFHSNUS parameter list
AP 20C6	DFHSNSG	AP 1	Recovery entered	1 DFHSNUS parameter list 2 Kernel error data
AP 20FB	DFHXSEV	AP 1	Entry	1 Pointers to SAF parameter list and SAF work area 2 SAF parameter list 3 RACINIT parameter list
AP 20FC	DFHXSEV	AP 1	Exit	1 Four-word return code data area
AP 20FD	DFHXSEV	AP 2	Vendor code entry	1 Pointers to SAF parameter list and SAF work area 2 SAF parameter list 3 RACINIT parameter list
AP 20FE	DFHXSEV	AP 2	Vendor code exit	1 Four-word return code data area
AP 20FF	DFHXSEV	AP 1	Recovery entered	1 Kernel error data

Bridge facility management

Table 62. Bridge facility management trace points

Point ID	Module	Lvl	Type	Data
AP 2140	DFHBRFM	BR 1	Entry	1 BRFM parameter list
AP 2141	DFHBRFM	BR 1	Exit	1 BRFM parameter list
AP 2142	DFHBRFM	Exc	Invalid format	1 BRFM parameter list
AP 2143	DFHBRFM	Exc	Invalid function	1 BRFM parameter list
AP 2144	DFHBRFM	Exc	Invalid token	1 BRFM parameter list
AP 2145	DFHBRFM	Exc	Invalid template	1 BRFM parameter list
AP 2146	DFHBRFM	Exc	Token not current	1 BRFM parameter list
AP 2147	DFHBRFM	Exc	GETMAIN failed	1 BRFM parameter list
AP 2148	DFHBRFM	Exc	No free name	1 BRFM parameter list

Table 62. Bridge facility management trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 2149	DFHBRFM	Exc	Name create failed	1 BRFM parameter list
AP 214A	DFHBRFM	Exc	Recovery entered	1 BRFM parameter list 2 Kernel error data
AP 214B	DFHBRFM	BR 1	Kept BFB expired	1 BFB name 2 BFB index 3 BFB expiry time
AP 214C	DFHBRFM	BR 1	Kept BFB used	1 BFB name 2 BFB index 3 BFB expiry time
AP 214D	DFHBRFM	BR 1	BFB added to keep chain	1 BFB name 2 BFB index 3 BFB expiry time
AP 214E	DFHBRFM	Exc	SNUS signon failed	1 BRFM parameter list
AP 2160	DFHBRMS	BR 1	Entry	1 Exec parameter list
AP 2161	DFHBRMS	BR 1	Exit	1 Exec parameter list
AP 2162	DFHBRMS	Exc	Recovery	1 Exec parameter list 2 Kernel error data
AP 2163	DFHBRTC	BR 1	Entry	1 Exec parameter list
AP 2164	DFHBRTC	BR 1	Exit	1 Exec parameter list
AP 2165	DFHBRTC	Exc	Recovery	1 Exec parameter list 2 Kernel error data
AP 2166	DFHBRIC	BR 1	Entry	1 Exec parameter list
AP 2167	DFHBRIC	BR 1	Exit	1 Exec parameter list
AP 2168	DFHBRIC	Exc	Recovery	1 Exec parameter list 2 Kernel error data
AP 2169	DFHBRxx	Exc	Invalid function	1 Exec parameter list
AP 216A	DFHBRxx	Exc	Invalid group	1 Exec parameter list
AP 216B	DFHBRxx	Exc	Invalid EXEC function	1 Exec parameter list
AP 216C	DFHBRSP	BR 1	Entry	1 Exec parameter list
AP 216D	DFHBRSP	BR 1	Exit	1 Exec parameter list
AP 216E	DFHBRSP	Exc	Recovery	1 Exec parameter list 2 Kernel error data
AP 216F	DFHBRMS	BR 2	Call user exit	1 BRXA transaction area 2 BRXA command area

Table 62. Bridge facility management trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 2170	DFHBRMS	BR 2	Return from user exit	1 BRXA transaction area 2 BRXA command area
AP 2171	DFHBRTC	BR 2	Call user exit	1 BRXA transaction area 2 BRXA command area
AP 2172	DFHBRTC	BR 2	Return from user exit	1 BRXA transaction area 2 BRXA command area
AP 2173	DFHBRIC	BR 2	Call user exit	1 BRXA transaction area 2 BRXA command area
AP 2174	DFHBRIC	BR 2	Return from user exit	1 BRXA transaction area 2 BRXA command area
AP 2175	DFHBRSP	BR 2	Call user exit	1 BRXA transaction area 2 BRXA command area
AP 2176	DFHBRSP	BR 2	Return from user exit	1 BRXA transaction area 2 BRXA command area
AP 2177	DFHBRSP	Exc	Syncpoint change	1 BRSP parameter list 2 BRXA transaction area 3 BRXA command area
AP 2178	DFHBRMS	BR 2	Call formatter	1 BRXA transaction area 2 BRXA command area
AP 2179	DFHBRMS	BR 2	Formatter return	1 BRXA transaction area 2 BRXA command area
AP 217A	DFHBRTC	BR 2	Call formatter	1 BRXA transaction area 2 BRXA command area
AP 217B	DFHBRTC	BR 2	Formatter return	1 BRXA transaction area 2 BRXA command area
AP 217C	DFHBRIC	BR 2	Call formatter	1 BRXA transaction area 2; BRXA command area
AP 217D	DFHBRIC	BR 2	Call formatter	1 BRXA transaction area 2 BRXA command area

C++ and JAVA

Table 63. C++ and JAVA trace points

Point ID	Module	Lvl	Type	Data
AP 2180	ICCFCDLL, DFJCZDTC	See Table 67 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 67 on page 130
AP 2181	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130

Table 63. C++ and JAVA trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 2182	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2183	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2184	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2185	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2186	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2187	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2188	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2189	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 218A	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 218B	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 218C	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 218D	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 218E	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 218F	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130

Table 63. C++ and JAVA trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 2190	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2191	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2192	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2193	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2194	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2195	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2196	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2197	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2198	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 2199	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 219A	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 219B	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 219C	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 219D	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130

Table 63. C++ and JAVA trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 219E	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 219F	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21A0	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21A1	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21A2	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21A3	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21A4	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21A5	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21A6	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21A7	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21A8	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21A9	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21AA	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21AB	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130

Table 63. C++ and JAVA trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 21AC	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21AD	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21AE	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21AF	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21B0	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21B1	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21B2	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21B3	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21B4	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21B5	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21B6	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21B7	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21B8	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21B9	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130

Table 63. C++ and JAVA trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 21BA	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21BB	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21BC	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21BD	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21BE	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21BF	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21C0	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21C1	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21C2	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21C3	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21C4	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21C5	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21C6	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21C7	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130

Table 63. C++ and JAVA trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 21C8	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21C9	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21CA	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21CB	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21CC	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21CD	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21CE	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21CF	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21D0	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21D1	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21D2	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21D3	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21D4	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130
AP 21D5	ICCFCDLL	See Table 68 on page 130	See data-1	1 See Table 64 on page 129 2 Reserved 3-7 See Table 68 on page 130

Table 63. C++ and JAVA trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 21E0	DFJCZDTC	See Table 69 on page 186	See data-1	1 See Table 64 2 Reserved 3-7 See Table 69 on page 186
AP 21E1	DFJIOP	See Table 70 on page 193	See data-1	1 See Table 64 2 Reserved 3-7 See Table 70 on page 193
AP 21E3	DFJGFAC	See Table 71 on page 196	See data-1	1 See Table 64 2 Reserved 3-7 See Table 71 on page 196
AP 21E6	DFJCICS	See Table 72 on page 196	See data-1	1 See Table 64 2 Reserved 3-7 See Table 72 on page 196

Table 64. C++, JCICS and IIOp data-1 layout

Offset	Description
0	Number of data fields in addition to data-1 and data-2
4	Trace point ID
6	Trace point type. See Table 65.
8	Caller type. See Table 66.
A	Method identifier. See Table 70 on page 193.

Table 65. C++, JCICS and IIOp trace point types

Type value	Description
1001	Entry
1002 - 1005	Exit, Exit0 - Exit8
1006 - 100F	Exception
1010 - 101A	Error
101B - 101E	Warning
101F - 1022	Information

Table 66. C++, JCICS and IIOp caller types

Type value	Description
2001	Method
2002	Function
2003 - 2004	Constructor
2005 - 2006	Destructor
2007	Class static initialization

Table 67. Direct CICS classes

Method ID	Class_Method	Lvl	Type	Data
3002	DtcExec	2	Entry	1 &Options 2 &I->arg0.grpcode
3002	DtcExec	2	Info	1 &Options 2 ptr
3002	DtcExec	2	Exit	1 I->R.Resp);
3005	DtcInit	2	Info	1 &Verb 2 &I->arg0.grpcode
3006	DtcNew	2	Entry	1 Options);
3006	DtcNew	Exc	Error0	
3006	DtcNew	2	Info0	1 ptr);
3006	DtcNew	2	Exit	
3007	DtcSet	2	Info	1 &Keyword 2 &Value
3196	DtcGetMessageText	Exc	Entry	1 msgId);
3196	DtcGetMessageText	Exc	Info	1 messageBuffer
3196	DtcGetMessageText	Exc	Entry	1 insert3A 2 insert4A 3 insert5A 4 insert6A 5 insert7A
3196	DtcGetMessageText	Exc	Exit	1 messageBuffer

Table 68. C++ foundation classes

Method ID	Class_Method	Lvl	Type	Data
3008	IccGI::abend	1	Info	
3008	IccTask::abend	2	Entry	1 abendCode 2 &opt1 3 &opt2
3008	IccTask::abend	2	Exit	1 abendCode 2 &opt1 3 &opt2
3009	IccAbendData::abendCode	2	Entry	1 &opt
3009	IccAbendData::abendCode	2	Exit	1 ivpI->ivabcode

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
300A	IccTask::abendData	2	Entry	
300A	IccTask::abendData	2	Exit	1 &IccAbendDataI::cvpEObj
300B	IccClock::absTime	2	Entry	
300B	IccClock::absTime	2	Exit	1 ivpI->ivAbsTime.traceData()
300C	IccFile::access	2	Entry	1 &opt
300C	IccFile::access	2	Exit	1 &ret
300D	IccFile::accessMethod	2	Entry	1 &opt
300D	IccFile::accessMethod	2	Exit	1 &(ivpI->ivpSPData->accessMethod)
300E	IccResource::actionsOnConditionsText	2	Entry	
300E	IccResource::actionsOnConditionsText	1	Info	
300E	IccResource::actionsOnConditionsText	2	Exit	
300F	IccResource::actionOnCondition	2	Entry	
300F	IccResource::actionOnCondition	2	Exit	
3010	IccResource::actionOnConditionAsChar	2	Entry	
3010	IccResource::actionOnConditionAsChar	2	Exit	
3011	IccProgram::address	2	Entry	
3011	IccProgram::address	2	Exit	1 &ivpI->ivpAddress
3012	IccSession::allocate	2	Entry	1 &opt
3012	IccSession::allocate	2	Exit	1 &opt
3013	IccTerminalData::alternateHeight	2	Entry	1 &opt
3013	IccTerminalData::alternateHeight	2	Exit	1 &ivpI->ivaltscrnht
3014	IccTerminalData::alternateWidth	2	Entry	1 &opt
3014	IccTerminalData::alternateWidth	2	Exit	1 &ivpI->ivaltscrnwd
3015	IccBuf::append	2	Entry	1 &length 2 &pData
3015	IccBuf::append	2	Exit	1 this->traceData()
3016	IccSystem::applName	2	Entry	
3016	IccSystem::applName	2	Exit	1 ivpI->ivAppIName

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3017	IccBuf::assign	2	Entry	1 &length 2 &pData
3017	IccBuf::assign	2	Exit	1 this->traceData()
3017	IccKey::assign	2	Entry	1 &length 2 &dataArea
3017	IccKey::assign	2	Exit	1 &length 2 &dataArea
3017	IccResourceId::assign	2	Entry	1 &length 2 dataArea
3017	IccResourceId::assign	2	Exit	1 &length 2 dataArea
3018	IccAbendDataI::assignValues	2	Entry	
3018	IccAbendDataI::assignValues	2	Exit	
3019	IccSystem::beginBrowse	2	Entry	1 &resource 2 &resId
3019	IccSystem::beginBrowse	2	Exit	1 &resource 2 &resId
301A	IccFile::beginInsert	2	Entry	
301A	IccFile::beginInsert	2	Exit	
301C	IccFileIteratorI::browseRecord	2	Entry	
301C	IccFileIteratorI::browseRecord	2	Exit	
301D	IccBaseI::buildFmtString	2	Entry	1 fmt 2 &args
301D	IccBaseI::buildFmtString	2	Exit	1 ivpFmtIntBuf->traceData()
301E	IccSessionI::buildSendCmd	2	Entry	
301E	IccSessionI::buildSendCmd	2	Exit	
301F	IccControl::callingProgramId	2	Entry	
301F	IccControl::callingProgramId	2	Exit	1 ivpI->ivInvokingProgId.traceData()
3020	IccStartRequestQ::cancel	2	Entry	1 reqId.traceData() 2 &transId
3020	IccStartRequestQ::cancel	2	Exit	1 reqId.traceData() 2 &transId
3021	IccControl::cancelAbendHandler	2	Entry	
3021	IccControl::cancelAbendHandler	2	Exit	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3022	IccClock::cancelAlarm	2	Entry	1 &reqId
3022	IccClock::cancelAlarm	2	Exit	1 &reqId
3024	IccGI::catchException	1	Info	
3025	IccUser::changePassword	2	Entry	1 password 2 newPassword
3025	IccUser::changePassword	2	Exit	1 password 2 newPassword
3027	IccGI::checkFacilityType	2	Entry	
3027	IccGI::checkFacilityType	Exc	Error	
3027	IccGI::checkFacilityType	Exc	Error	
3027	IccGI::checkFacilityType	1	Info	
3027	IccGI::checkFacilityType	2	Exit	
3028	IccResourceI::checkForSYSID	2	Entry	
3028	IccResourceI::checkForSYSID	2	Exit	
302A	IccEvent::className	2	Entry	
302A	IccEvent::className	2	Exit	1 ret
302A	IccBase::className	2	Entry	1 &opt
302A	IccBase::className	2	Exit	1 pName
302A	IccException::className	2	Entry	
302A	IccException::className	2	Exit	1 ret
302A	IccMessage::className	2	Entry	
302A	IccMessage::className	2	Exit	1 ret
302B	IccEvent::classType	2	Entry	
302B	IccEvent::classType	2	Exit	1 &ret
302B	IccBase::classType	2	Entry	
302B	IccBase::classType	2	Exit	1 &ivpIB->ivType
302B	IccException::classType	2	Entry	
302B	IccException::classType	2	Exit	1 &ivpI->ivThrowType
302C	IccDataQueue::clear	2	Entry	
302C	IccDataQueue::clear	2	Exit	
302C	IccTempStore::clear	2	Entry	
302C	IccTempStore::clear	2	Exit	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
302C	IccTerminal::clear	2	Entry	
302C	IccTerminal::clear	2	Exit	
302E	IccTask::commitUOW	2	Entry	
302E	IccTask::commitUOW	2	Exit	
302F	IccControl::commArea	2	Entry	
302F	IccControl::commArea	2	Exit	1 *ivpI->ivpCommArea->traceData()
3030	IccKey::completeLength	2	Entry	
3030	IccKey::completeLength	2	Exit	1 &ivpI->ivCompleteLength
3031	IccEvent::condition	2	Entry	1 &c
3031	IccEvent::condition	2	Exit	1 &ret
3031	IccResource::condition	2	Entry	
3031	IccResource::condition	2	Exit	
3033	IccEvent::conditionText	2	Entry	
3033	IccEvent::conditionText	2	Exit	1 ret
3033	IccResource::conditionText	2	Entry	
3033	IccResource::conditionText	2	Exit	
3034	IccSession::connectProcess	2	Entry	1 &level 2 &PIP
3034	IccSession::connectProcess	2	Exit	1 &level 2 &PIP
3035	IccControl::console	2	Entry	
3035	IccControl::console	2	Exit	1 &IccConsoleI::cvpEObj
3036	IccSession::converse	2	Entry	1 send.traceData()
3036	IccSession::converse	2	Exit	1 ivpIB->ivpOvlIntBuf->traceData()
3037	IccGI::convertPackedToDouble	2	Entry	
3037	IccGI::convertPackedToDouble	2	Exit	
3038	IccGI::convertPackedToLong	2	Entry	
3038	IccGI::convertPackedToLong	2	Exit	
3039	IccTimeI::convertToHrsMinsSecs	2	Entry	1 timeHHMMSS
3039	IccTimeI::convertToHrsMinsSecs	2	Exit	1 timeHHMMSS
303A	IccSession::convId	2	Entry	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
303A	IccSession::convId	2	Exit	1 ivpI->ivConvId.traceData()
303B	IccControlIG::createConsoleObj	2	Entry	
303B	IccControlIG::createConsoleObj	2	Exit	
303C	IccTerminalI::createDataObj	2	Entry	
303C	IccTerminalI::createDataObj	2	Exit	
303E	IccControlIG::createSessionObj	2	Entry	
303E	IccControlIG::createSessionObj	2	Exit	
303F	IccControlIG::createStartRequestQObj	2	Entry	
303F	IccControlIG::createStartRequestQObj	2	Exit	
3040	IccControlIG::createSystemObj	2	Entry	
3040	IccControlIG::createSystemObj	2	Exit	
3041	IccControlIG::createTaskObj	2	Entry	
3041	IccControlIG::createTaskObj	2	Exit	
3042	IccControlIG::createTerminalObj	2	Entry	
3042	IccControlIG::createTerminalObj	2	Exit	
3043	IccTerminal::cursor	2	Entry	
3043	IccTerminal::cursor	1	Info	
3043	IccTerminal::cursor	2	Exit	
3044	IccBase::customClassNum	2	Entry	
3044	IccBase::customClassNum	2	Exit	1 &ivpIB->ivCustomClassNum
3045	IccBuf::cut	2	Entry	1 &length 2 &offset
3045	IccBuf::cut	2	Exit	1 this->traceData()
3045	IccBufI::cut	2	Entry	1 &length 2 &offset
3045	IccBufI::cut	2	Exit	1 &length 2 &offset
3046	IccStartRequestQ::data	2	Entry	
3046	IccStartRequestQ::data	2	Exit	1 ivpIB->ivpOvIIntBuf->traceData()
3046	IccTerminal::data	2	Entry	
3046	IccTerminal::data	2	Exit	
3047	IccBuf::dataArea	2	Entry	1 &offset
3047	IccBuf::dataArea	2	Exit	1 &offset
3048	IccBuf::dataAreaLength	2	Entry	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3048	IccBuf::dataAreaLength	2	Exit	1 &ivpI->ivDataAreaLength
3049	IccBuf::dataAreaOwner	2	Entry	
3049	IccBuf::dataAreaOwner	2	Exit	1 &ivpI->ivOwner
304A	IccBuf::dataAreaType	2	Entry	
304A	IccBuf::dataAreaType	2	Exit	1 &ivpI->ivType
304B	IccBuf::dataLength	2	Entry	
304B	IccBuf::dataLength	2	Exit	1 &ivpI->ivDataLength
304C	IccClock::date	2	Entry	1 &fmt 2 &dateSeparator
304C	IccClock::date	2	Exit	1 ret
304C	IccAbsTime::date	2	Entry	1 &fmt 2 &dateSeparator
304C	IccAbsTime::date	2	Exit	1 ivpI->ivDate
304D	IccSystem::dateFormat	2	Entry	
304D	IccSystem::dateFormat	2	Exit	1 ivpI->ivDateFormat
304E	IccClock::daysSince1900	2	Entry	
304E	IccClock::daysSince1900	2	Exit	1 &ret
304E	IccAbsTime::daysSince1900	2	Entry	
304E	IccAbsTime::daysSince1900	2	Exit	1 &ivpI->ivDayCount
304F	IccUser::daysUntilPasswordExpires	2	Entry	
304F	IccUser::daysUntilPasswordExpires	2	Exit	1 &ivpI->ivDaysLeft
3050	IccClock::dayOfMonth	2	Entry	
3050	IccClock::dayOfMonth	2	Exit	1 &ret
3050	IccAbsTime::dayOfMonth	2	Entry	
3050	IccAbsTime::dayOfMonth	2	Exit	1 &ivpI->ivDayOfMonth
3051	IccClock::dayOfWeek	2	Entry	
3051	IccClock::dayOfWeek	2	Exit	1 &ret
3051	IccAbsTime::dayOfWeek	2	Entry	
3051	IccAbsTime::dayOfWeek	2	Exit	1 &(ivpI->ivDayOfWeek)

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3053	IccTerminalData::defaultHeight	2	Entry	1 &opt
3053	IccTerminalData::defaultHeight	2	Exit	1 &ivpI->ivdefscrnht
3054	IccTerminalData::defaultWidth	2	Entry	1 &opt
3054	IccTerminalData::defaultWidth	2	Exit	1 &ivpI->ivdefscrnwd
3055	IccTask::delay	2	Entry	1 time.traceData() 2 &reqId
3055	IccTask::delay	2	Exit	1 time.traceData() 2 &reqId
3056	IccBase::delete	2	Entry	1 &obj
3056	IccBase::delete	2	Exit	1 &obj
3057	IccFile::deleteLockedRecord	2	Entry	1 &updateToken
3057	IccFile::deleteLockedRecord	2	Exit	1 &updateToken
3058	IccFile::deleteRecord	2	Entry	
3058	IccFile::deleteRecord	2	Exit	1 &deletedRecords
3059	IccBaseI::deregDependentObjPtr	2	Entry	1 &pObj
3059	IccBaseI::deregDependentObjPtr	Exc	Exception	
3059	IccBaseI::deregDependentObjPtr	2	Exit	1 &pObj
305A	IccControlIG::destroyTaskObj	2	Entry	
305A	IccControlIG::destroyTaskObj	2	Exit	
305B	IccControlIG::destroyTerminalObj	2	Entry	
305B	IccControlIG::destroyTerminalObj	2	Exit	
305C	IccTask::dump	2	Entry	1 dumpCode 2 &buf
305C	IccTask::dump	2	Exit	
305D	IccDataQueue::empty	2	Entry	
305D	IccDataQueue::empty	2	Exit	
305D	IccTempStore::empty	2	Entry	
305D	IccTempStore::empty	2	Exit	
305E	IccFile::enableStatus	2	Entry	1 &opt
305E	IccFile::enableStatus	2	Exit	1 &(ivpI->ivpSPData->enableStatus)

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
305F	IccTerminalI::encodeASCIIBufferAddress	2	Entry	
305F	IccTerminalI::encodeASCIIBufferAddress	2	Exit	
3060	Icc::endl	2	Entry	
3060	Icc::endl	2	Exit	
3061	IccSystem::endBrowse	2	Entry	1 &resource
3061	IccSystem::endBrowse	2	Exit	1 &resource
3062	IccFile::endInsert	2	Entry	
3062	IccFile::endInsert	2	Exit	
3063	IccTask::enterTrace	2	Entry	1 &traceNum 2 resource 3 &data 4 &opt
3063	IccTask::enterTrace	2	Exit	1 &traceNum 2 resource 3 &data 4 &opt
3064	IccProgram::entryPoint	2	Entry	
3064	IccProgram::entryPoint	2	Exit	1 &ivpI->ivpEntryPoint
3065	IccTerminal::erase	2	Entry	
3065	IccTerminal::erase	2	Exit	
3066	IccSession::errorCode	2	Entry	
3066	IccSession::errorCode	2	Exit	1 ivpI->ivEIBERRCD
3068	IccResourceI::execCICSCmd	2	Entry	
3068	IccResourceI::execCICSCmd	1	Info	
3068	IccResourceI::execCICSCmd	2	Exit	1 &ivResp
3069	IccSession::extractProcess	2	Entry	
3069	IccSession::extractProcess	2	Exit	
306A	IccTask::facilityType	2	Entry	
306A	IccTask::facilityType	2	Exit	1 &ivpI->ivFacilityType
306C	IccSession::flush	2	Entry	
306C	IccSession::flush	2	Exit	
306C	Icc::flush	2	Entry	
306C	Icc::flush	2	Exit	
306D	IccSession::free	2	Entry	
306D	IccSession::free	2	Exit	
306E	IccTerminal::freeKeyboard	2	Entry	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
306E	IccTerminal::freeKeyboard	2	Exit	
306F	IccSystem::freeStorage	2	Entry	1 &pStorage
306F	IccSystem::freeStorage	2	Exit	1 &pStorage
306F	IccTask::freeStorage	2	Entry	1 &pStorage
306F	IccTask::freeStorage	2	Exit	1 &pStorage
3071	IccDataQueue::get	2	Entry	
3071	IccDataQueue::get	2	Exit	1 buf.traceData()
3071	IccSession::get	2	Entry	
3071	IccSession::get	2	Exit	1 ret.traceData()
3071	IccTempStore::get	2	Entry	
3071	IccTempStore::get	2	Exit	1 buf.traceData()
3071	IccTerminal::get	2	Entry	
3071	IccTerminal::get	2	Exit	
3073	IccSystem::getFile	2	Entry	1 id.traceData()
3073	IccSystem::getFile	2	Exit	1 &pFile
3074	IccGI::getFCI	2	Entry	
3074	IccGI::getFCI	2	Exit	
3077	IccSystem::getNextFile	2	Entry	
3077	IccSystem::getNextFile	2	Exit	1 &pFile
3078	IccGI::getPrinSysId	2	Entry	
3078	IccGI::getPrinSysId	2	Exit	
3079	IccGI::getRelease	2	Entry	
3079	IccGI::getRelease	Exc	Exception	
3079	IccGI::getRelease	2	Exit	
307A	IccGI::getStartCode	2	Entry	
307A	IccGI::getStartCode	2	Exit	
307B	IccSystem::getStorage	2	Entry	1 &size 2 &initByte 3 &storageOpts
307B	IccSystem::getStorage	2	Exit	1 &pStorage

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
307B	IccTask::getStorage	2	Entry	1 &size 2 &initByte 3 &storageOpts
307B	IccTask::getStorage	2	Exit	1 &pStorage
307C	IccGI::getTermCode	2	Entry	
307C	IccGI::getTermCode	2	Exit	
307D	IccTerminalData::graphicCharCodeSet	2	Entry	1 &opt
307D	IccTerminalData::graphicCharCodeSet	2	Exit	1 &ivpI->ivgcodes
307E	IccTerminalData::graphicCharSetId	2	Entry	1 &opt
307E	IccTerminalData::graphicCharSetId	2	Exit	1 &ivpI->ivgchars
307F	IccUser::groupId	2	Entry	
307F	IccUser::groupId	2	Exit	1 ivpI->ivpGroupId->traceData()
3080	IccResource::handleCICSCmd	2	Entry	1 &obj
3080	IccResource::handleCICSCmd	2	Info	
3080	IccResource::handleCICSCmd	2	Info	
3080	IccResource::handleCICSCmd	2	Info	
3080	IccResource::handleCICSCmd	2	Info	
3080	IccResource::handleCICSCmd	Exc	Exception	
3080	IccResource::handleCICSCmd	2	Info	
3080	IccResource::handleCICSCmd	2	Info	
3080	IccResource::handleCICSCmd	2	Exit	1 &obj
3081	IccResource::handleEvent	Exc	Exception	
3082	IccTerminal::height	2	Entry	
3082	IccTerminal::height	2	Exit	
3082	IccTerminal::height	1	Info	
3083	IccTime::hours	2	Entry	
3083	IccTime::hours	2	Exit	1 &ivpIT->ivHours
3084	IccGI::initialize	Exc	Exception	
3084	IccGI::initialize	1	Info	
3084	IccGI::initialize	1	Info	
3084	IccGI::initialize	2	Exit	
3086	IccControl::initData	2	Entry	
3086	IccControl::initData	2	Exit	1 *ivpI->ivpInitparm->traceData()

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3087	IccFileI::initSPData	2	Entry	
3087	IccFileI::initSPData	2	Exit	1 &ivpSPData
3088	IccTerminal::inputCursor	2	Entry	
3088	IccTerminal::inputCursor	1	Info	
3088	IccTerminal::inputCursor	2	Exit	
3089	IccFileI::inquireAccess	2	Entry	
3089	IccFileI::inquireAccess	2	Exit	
308A	IccBuf::insert	2	Entry	1 &length 2 &pData 3 &offset
308A	IccBuf::insert	2	Exit	1 this->traceData()
308C	IccAbendData::instance	2	Entry	
308C	IccAbendData::instance	2	Exit	1 &IccAbendDataI::cvpEObj
308C	IccConsole::instance	2	Entry	
308C	IccConsole::instance	2	Exit	1 &IccConsoleI::cvpEObj
308C	IccControl::instance	2	Entry	
308C	IccControl::instance	2	Exit	1 &IccControlIG::cvpEObj IccControlIG::cvControlNum
308C	IccStartRequestQ::instance	2	Entry	
308C	IccStartRequestQ::instance	2	Exit	1 &IccStartRequestQI::cvpEObj
308C	IccSystem::instance	2	Entry	
308C	IccSystem::instance	2	Exit	1 &IccSystemI::cvpEObj
308C	IccTask::instance	2	Entry	
308C	IccTask::instance	2	Exit	1 &IccTaskI::cvpEObj
308D	IccUser::invalidPasswordAttempts	2	Entry	
308D	IccUser::invalidPasswordAttempts	2	Exit	1 &ivpI->ivInvalidCount
308E	IccSession::issueAbend	2	Entry	
308E	IccSession::issueAbend	2	Exit	
308F	IccSession::issueConfirmation	2	Entry	
308F	IccSession::issueConfirmation	2	Exit	
3090	IccSession::issueError	2	Entry	
3090	IccSession::issueError	2	Exit	
3091	IccSession::issuePrepare	2	Entry	
3091	IccSession::issuePrepare	2	Exit	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3092	IccSession::issueSignal	2	Entry	
3092	IccSession::issueSignal	2	Exit	
3093	IccFile::isAddable	2	Entry	1 &opt
3093	IccFile::isAddable	2	Exit	1 &test
3094	IccTerminalData::isAPLKeyboard	2	Entry	1 &opt
3094	IccTerminalData::isAPLKeyboard	2	Exit	1 &bool
3095	IccTerminalData::isAPLText	2	Entry	1 &opt
3095	IccTerminalData::isAPLText	2	Exit	1 &bool
3096	IccFile::isBrowsable	2	Entry	1 &opt
3096	IccFile::isBrowsable	2	Exit	1 &test
3097	IccTerminalData::isBTrans	2	Entry	1 &opt
3097	IccTerminalData::isBTrans	2	Exit	1 &bool
3099	IccTerminalData::isColor	2	Entry	1 &opt
3099	IccTerminalData::isColor	2	Exit	1 &bool
309A	IccTask::isCommandSecurityOn	2	Entry	
309A	IccTask::isCommandSecurityOn	2	Exit	1 &bool
309B	IccTask::isCommitSupported	2	Entry	
309B	IccTask::isCommitSupported	2	Exit	1 &ivpI->ivCommitSupported
309C	IccControl::isCreated	2	Entry	
309C	IccControl::isCreated	2	Exit	1 &test
309D	IccFile::isDeletable	2	Entry	1 &opt
309D	IccFile::isDeletable	2	Exit	1 &test
309E	IccAbendData::isDumpAvailable	2	Entry	1 &opt
309E	IccAbendData::isDumpAvailable	2	Exit	
309F	IccFile::isEmptyOnOpen	2	Entry	1 &opt
309F	IccFile::isEmptyOnOpen	2	Exit	1 &test

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
30A0	IccSession::isErrorSet	2	Entry	
30A0	IccSession::isErrorSet	2	Exit	1 &ivpI->ivEIBERR
30A1	IccAlarmRequestId::isExpired	2	Entry	
30A1	IccAlarmRequestId::isExpired	2	Exit	1 &test
30A2	IccTerminalData::isExtended3270	2	Entry	1 &opt
30A2	IccTerminalData::isExtended3270	2	Exit	1 &bool
30A3	IccResource::isEDFOn	2	Entry	
30A3	IccResource::isEDFOn	2	Exit	
30A4	IccTerminalData::isEWA	2	Entry	1 &opt
30A4	IccTerminalData::isEWA	2	Exit	1 &bool
30A6	IccTerminalData::isFieldOutline	2	Entry	1 &opt
30A6	IccTerminalData::isFieldOutline	2	Exit	1 &bool
30A7	IccBuf::isFMHContained	2	Entry	
30A7	IccBuf::isFMHContained	2	Exit	1 &ivpI->ivFMH
30A8	IccTerminalData::isGoodMorning	2	Entry	1 &opt
30A8	IccTerminalData::isGoodMorning	2	Exit	1 &bool
30A9	IccTerminalData::isHighlight	2	Entry	1 &opt
30A9	IccTerminalData::isHighlight	2	Exit	1 &bool
30AA	IccTerminalData::isKatakana	2	Entry	1 &opt
30AA	IccTerminalData::isKatakana	2	Exit	1 &bool
30AB	IccTerminalData::isMSRControl	2	Entry	1 &opt
30AB	IccTerminalData::isMSRControl	2	Exit	1 &bool
30AC	IccSession::isNoDataSet	2	Entry	
30AC	IccSession::isNoDataSet	2	Exit	1 &ivpI->ivEIBNODAT
30AD	IccTerminalData::isPS	2	Entry	1 &opt
30AD	IccTerminalData::isPS	2	Exit	1 &bool

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
30AE	IccFile::isReadable	2	Entry	1 &opt
30AE	IccFile::isReadable	2	Exit	1 &test
30AF	IccFile::isRecoverable	2	Entry	1 &opt
30AF	IccFile::isRecoverable	2	Exit	1 &test
30B0	IccTask::isResourceSecurityOn	2	Entry	
30B0	IccTask::isResourceSecurityOn	2	Exit	
30B1	IccTask::isRestarted	2	Entry	
30B1	IccTask::isRestarted	2	Exit	
30B2	IccResource::isRouteOptionOn	2	Entry	
30B2	IccResource::isRouteOptionOn	2	Exit	
30B3	IccSession::isSignalSet	2	Entry	
30B3	IccSession::isSignalSet	2	Exit	1 &ivpl->ivEIBSIG
30B4	IccTask::isStartDataAvailable	2	Entry	
30B4	IccTask::isStartDataAvailable	2	Exit	1 &ivpl->ivStartData
30B5	IccTerminalData::isSOSI	2	Entry	1 &opt
30B5	IccTerminalData::isSOSI	2	Exit	1 &bool
30B6	IccTerminalData::isTextKeyboard	2	Entry	1 &opt
30B6	IccTerminalData::isTextKeyboard	2	Exit	1 &bool
30B7	IccTerminalData::isTextPrint	2	Entry	1 &opt
30B7	IccTerminalData::isTextPrint	2	Exit	1 &bool
30B9	IccFile::isUpdatable	2	Entry	1 &opt
30B9	IccFile::isUpdatable	2	Exit	1 &test
30BA	IccTerminalData::isValidation	2	Entry	1 &opt
30BA	IccTerminalData::isValidation	2	Exit	1 &bool
30BC	IccJournal::journalTypeId	2	Entry	
30BC	IccJournal::journalTypeId	2	Exit	1 ivpl->ivJTypeId.traceData()
30BD	IccFile::keyLength	2	Entry	1 &opt

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
30BD	IccFile::keyLength	2	Exit	1 &ivpI->ivpSPData->keyLength
30BE	IccFile::keyPosition	2	Entry	1 &opt
30BE	IccFile::keyPosition	2	Exit	1 &ivpI->ivpSPData->keyPosition
30BF	IccKey::kind	2	Entry	
30BF	IccKey::kind	2	Exit	1 &ivpI->ivKind
30C0	IccUser::language	2	Entry	
30C0	IccUser::language	2	Exit	1 ivpI->ivLangInUse
30C1	IccUser::lastPasswordChange	2	Entry	
30C1	IccUser::lastPasswordChange	2	Exit	1 ivpI->ivAbsChangeTime.traceData()
30C2	IccUser::lastUseTime	2	Entry	
30C2	IccUser::lastUseTime	2	Exit	1 ivpI->ivAbsLastUseTime.traceData()
30C3	IccProgram::length	2	Entry	
30C3	IccProgram::length	2	Exit	1 &ivpI->ivProgramLength
30C3	IccRecordIndex::length	2	Entry	
30C3	IccRecordIndex::length	2	Exit	1 &ret
30C4	IccSemaphore::lifeTime	2	Entry	
30C4	IccSemaphore::lifeTime	2	Exit	1 &ivpI->ivLifeTime
30C5	IccTerminal::line	2	Entry	
30C5	IccTerminal::line	2	Exit	
30C6	IccProgram::link	2	Entry	1 &commArea 2 &transId 3 &opt
30C6	IccProgram::link	1	Info	
30C6	IccProgram::link	2	Exit	1 &commArea 2 &transId 3 &opt
30C8	IccProgram::load	2	Entry	1 &opt
30C8	IccProgram::load	2	Exit	1 &opt
30C9	IccSemaphore::lock	2	Entry	
30C9	IccSemaphore::lock	2	Exit	
30CA	IccBaseI::makeDefaultIntBufs	2	Entry	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
30CA	IccBaseI::makeDefaultIntBufs	2	Exit	
30CB	IccBaseI::makeFmtIntBuf	2	Entry	1 &opt 2 &size
30CB	IccBaseI::makeFmtIntBuf	2	Exit	1 &opt 2 &size
30CC	IccBaseI::makeOvlIntBuf	2	Entry	1 &opt
30CC	IccBaseI::makeOvlIntBuf	2	Exit	1 &opt
30CD	IccBaseI::makePriIntBuf	2	Entry	1 &opt 2 &size
30CD	IccBaseI::makePriIntBuf	2	Exit	1 &opt 2 &size
30CE	IccException::message	2	Entry	
30CE	IccException::message	2	Exit	1 &ivpI->ivpMessage
30CF	IccEvent::methodName	2	Entry	
30CF	IccEvent::methodName	2	Exit	1 ret
30CF	IccException::methodName	2	Entry	
30CF	IccException::methodName	2	Exit	1 ret
30CF	IccMessage::methodName	2	Entry	
30CF	IccMessage::methodName	2	Exit	1 ret
30D0	IccClock::milliSeconds	2	Entry	
30D0	IccClock::milliSeconds	2	Exit	1 &ret
30D0	IccAbsTime::milliSeconds	2	Entry	
30D0	IccAbsTime::milliSeconds	2	Exit	1 &ret
30D1	IccTime::minutes	2	Entry	
30D1	IccTime::minutes	2	Exit	1 &ivpIT->ivMinutes
30D2	IccClock::monthOfYear	2	Entry	
30D2	IccClock::monthOfYear	2	Exit	1 &ret
30D2	IccAbsTime::monthOfYear	2	Entry	
30D2	IccAbsTime::monthOfYear	2	Exit	1 &(ivpI->ivMonthOfYear)
30D3	IccResource::name	2	Entry	
30D3	IccResource::name	2	Exit	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
30D3	IccResourceId::name	2	Entry	
30D3	IccResourceId::name	2	Exit	1 ret
30D4	IccResourceId::nameLength	2	Entry	
30D4	IccResourceId::nameLength	2	Exit	1 &ivpIR->ivNameLength
30D5	IccTerminal::netName	2	Entry	
30D5	IccTerminal::netName	2	Exit	
30D6	IccBase::new	2	Entry	1 &size
30D6	IccBase::new	2	Exit	1 &pObjStorage
30D8	IccTempStore::numberOfItems	2	Entry	
30D8	IccTempStore::numberOfItems	2	Exit	1 &ivpI->ivNumItems
30D9	IccException::object	2	Entry	
30D9	IccException::object	2	Exit	1 &ivpI->ivpObject
30DA	IccFile::openStatus	2	Entry	1 &opt
30DA	IccFile::openStatus	2	Exit	1 &(ivpI->ivpSPData->openStatus)
30DB	IccSystem::operatingSystem	2	Entry	
30DB	IccSystem::operatingSystem	2	Exit	1 &ivpI->ivOpSys
30DC	IccSystem::operatingSystemLevel	2	Entry	
30DC	IccSystem::operatingSystemLevel	2	Exit	1 &ivpI->ivOpRel
30DD	IccAbendData::originalAbendCode	2	Entry	1 &opt
30DD	IccAbendData::originalAbendCode	2	Exit	1 ivpI->ivorgabcode
30DE	IccBuf::overlay	2	Entry	1 &length 2 &dataArea
30DE	IccBuf::overlay	2	Exit	1 this->traceData()
30DF	IccAbsTime::packedDecimal	2	Entry	
30DF	IccAbsTime::packedDecimal	2	Exit	1 ivpI->ivAbsTime
30E0	IccUser::passwordExpiration	2	Entry	
30E0	IccUser::passwordExpiration	2	Exit	1 ivpI->ivAbsExpiryTime.traceData()
30E1	IccTask::principalSysId	2	Entry	1 &opt

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
30E1	IccTask::principalSysId	2	Exit	1 ivpI->ivPrinSysId.traceData()
30E2	IccTask::priority	2	Entry	1 &opt
30E2	IccTask::priority	2	Exit	1 &ivpI->ivtaskpriority
30E3	IccSession::process	2	Entry	
30E3	IccSession::process	2	Exit	1 ivpI->ivpProcname->traceData()
30E4	IccControl::programId	2	Entry	
30E4	IccControl::programId	2	Exit	1 ivpI->ivProgramId.traceData()
30E5	IccAbendData::programName	2	Entry	1 &opt
30E5	IccAbendData::programName	2	Exit	1 ivpI->ivabprogram
30E6	IccConsole::put	2	Entry	1 send.traceData()
30E6	IccConsole::put	2	Entry	
30E6	IccDataQueue::put	2	Entry	1 buf.traceData()
30E6	IccDataQueue::put	2	Exit	1 buf.traceData()
30E6	IccJournal::put	2	Entry	1 buf.traceData()
30E6	IccJournal::put	2	Exit	1 buf.traceData()
30E6	IccSession::put	2	Entry	1 buf.traceData()
30E6	IccSession::put	2	Exit	1 buf.traceData()
30E6	IccTempStore::put	2	Entry	1 buf.traceData()
30E6	IccTempStore::put	2	Exit	1 buf.traceData()
30E6	IccTerminal::put	1	Entry	
30E6	IccTerminal::put	1	Exit	
30E7	IccStartRequestQ::queueName	2	Entry	
30E7	IccStartRequestQ::queueName	2	Exit	1 ivpI->ivRetrievedQueueName
30E9	IccDataQueue::readItem	2	Entry	
30E9	IccDataQueue::readItem	2	Exit	1 ivpIB->ivpOvIntBuf->traceData()
30E9	IccTempStore::readItem	2	Entry	1 &itemno

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
30E9	IccTempStore::readItem	2	Exit	1 &itemno
30EA	IccTempStore::readNextItem	2	Entry	
30EA	IccTempStore::readNextItem	2	Exit	1 ivpIB->ivpOvlIntBuf->traceData()
30EB	IccFileIterator::readNextRecord	2	Entry	1 &mode 2 &updateToken
30EB	IccFileIterator::readNextRecord	2	Exit	1 buf.traceData()
30EC	IccFileIterator::readPreviousRecord	2	Entry	1 &mode 2 &updateToken
30EC	IccFileIterator::readPreviousRecord	2	Exit	1 buf.traceData()
30ED	IccFile::readRecord	2	Entry	1 &mode 2 &updateToken
30ED	IccFile::readRecord	2	Exit	1 ivpIB->ivpOvlIntBuf->traceData()
30EE	IccSession::receive	2	Entry	
30EE	IccSession::receive	2	Exit	1 ivpIB->ivpOvlIntBuf->traceData()
30EE	IccTerminal::receive	1	Entry	
30EE	IccTerminal::receive	1	Exit	
30EF	IccTerminal::receive3270Data	1	Entry	
30EF	IccTerminal::receive3270Data	1	Exit	
30F0	IccFile::recordFormat	2	Entry	1 &opt
30F0	IccFile::recordFormat	2	Exit	1 &(ivpI->ivpSPData->recordFormat)
30F1	IccFile::recordIndex	2	Entry	
30F1	IccFile::recordIndex	2	Exit	1 &ivpI->ivpRecIdx
30F2	IccFile::recordLength	2	Entry	1 &opt
30F2	IccFile::recordLength	2	Exit	1 &ivpI->ivpSPData->recordSize
30F3	IccStartRequestQ::registerData	2	Entry	1 &data
30F3	IccStartRequestQ::registerData	2	Exit	1 &data
30F4	IccJournal::registerPrefix	2	Entry	1 &prefix
30F4	IccJournal::registerPrefix	2	Exit	1 &prefix

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
30F5	IccFile::registerRecordIndex	2	Entry	1 &index
30F5	IccFile::registerRecordIndex	2	Exit	1 &index
30F6	IccBaseI::regDependentObjPtr	2	Entry	1 &pObj
30F6	IccBaseI::regDependentObjPtr	2	Exit	1 &pObj
30F7	IccSystem::release	2	Entry	
30F7	IccSystem::release	2	Exit	1 &ivpI->ivReleaseNum
30F8	IccSystem::releaseText	2	Entry	
30F8	IccSystem::releaseText	2	Exit	1 ivpI->ivRelease
30F9	IccBuf::replace	2	Entry	1 &length 2 &pData 3 &offset
30F9	IccBuf::replace	2	Exit	1 this->traceData()
30F9	IccBufI::replace	2	Entry	1 &length 2 &pData 3 &offset
30F9	IccBufI::replace	2	Info	
30F9	IccBufI::replace	2	Exit	1 &length 2 &pData 3 &offset
30FA	IccConsole::replyTimeout	2	Entry	
30FA	IccConsole::replyTimeout	2	Exit	
30FB	IccFileIterator::reset	2	Entry	1 &index 2 &search
30FB	IccFileIterator::reset	2	Exit	1 &index 2 &search
30FB	IccStartRequestQ::reset	2	Entry	
30FB	IccStartRequestQ::reset	2	Exit	
30FC	IccControl::resetAbendHandler	2	Entry	
30FC	IccControl::resetAbendHandler	2	Exit	
30FD	IccConsole::resetRouteCodes	2	Entry	
30FD	IccConsole::resetRouteCodes	2	Exit	
30FE	IccStartRequestQ::retrieveData	2	Entry	1 &opt
30FE	IccStartRequestQ::retrieveData	2	Exit	1 &opt

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3100	IccControl::returnProgramId	2	Entry	
3100	IccControl::returnProgramId	2	Exit	
3101	IccStartRequestQ::returnTermId	2	Entry	
3101	IccStartRequestQ::returnTermId	2	Exit	
3102	IccGI::returnToCICS	1	Info	
3102	IccGI::returnToCICS	Exc	Exception	
3103	IccStartRequestQ::returnTransId	2	Entry	
3103	IccStartRequestQ::returnTransId	2	Exit	
3104	IccTempStore::rewriteItem	2	Entry	1 &itemNum 2 item.traceData() 3 &opt
3104	IccTempStore::rewriteItem	2	Exit	1 &itemNum 2 item.traceData() 3 &opt
3105	IccFile::rewriteRecord	2	Entry	1 record.traceData() 2 &updateToken
3105	IccFile::rewriteRecord	2	Exit	1 record.traceData() 2 &updateToken
3106	IccTask::rollBackUOW	2	Entry	
3106	IccTask::rollBackUOW	2	Exit	
3107	IccResource::routeOption	2	Entry	
3107	IccResource::routeOption	2	Exit	
3109	IccSessionI::saveConvId	2	Entry	
3109	IccSessionI::saveConvId	2	Exit	
310A	IccSessionI::saveEIBFields	2	Entry	
310A	IccSessionI::saveEIBFields	2	Exit	
310B	IccFile::searchCriterion	2	Entry	
310B	IccFile::searchCriterion	2	Exit	1 &ivpI->ivSearchCriterion
310C	IccTime::seconds	2	Entry	
310C	IccTime::seconds	2	Exit	1 &ivpIT->ivSeconds
310D	IccSession::send	2	Entry	1 send.traceData() 2 &opt
310D	IccSession::send	2	Exit	1 send.traceData() 2 &opt
310D	IccTerminal::send	1	Entry	
310D	IccTerminal::send	1	Exit	
310D	IccTerminal::send	1	Entry	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
310D	IccTerminal::send	1	Exit	
310D	IccTerminal::send	1	Entry	
310D	IccTerminal::send	1	Exit	
310D	IccTerminal::send	1	Entry	
310D	IccTerminal::send	1	Exit	
310E	IccSession::sendInvite	2	Entry	1 send.traceData() 2 &opt
310E	IccSession::sendInvite	2	Exit	1 send.traceData() 2 &opt
310F	IccSession::sendLast	2	Entry	1 send.traceData() 2 &opt
310F	IccSession::sendLast	2	Exit	1 send.traceData() 2 &opt
3110	IccTerminal::sendLine	1	Entry	
3110	IccTerminal::sendLine	1	Exit	
3110	IccTerminal::sendLine	1	Entry	
3110	IccTerminal::sendLine	1	Exit	
3110	IccTerminal::sendLine	1	Entry	
3110	IccTerminal::sendLine	1	Exit	
3110	IccTerminal::sendLine	1	Entry	
3110	IccTerminal::sendLine	1	Exit	
3111	IccTerminal::send3270Data	1	Entry	
3111	IccTerminal::send3270Data	1	Exit	
3113	IccControl::session	2	Entry	
3113	IccControl::session	2	Exit	1 &IccControlIG::cvpSession
3114	IccTimeOfDay::set	2	Entry	1 &hours 2 &minutes 3 &seconds
3114	IccTimeOfDay::set	2	Exit	1 &hours 2 &minutes 3 &seconds
3115	IccControl::setAbendHandler	2	Entry	1 programName
3115	IccControl::setAbendHandler	2	Exit	1 programName
3116	IccFile::setAccess	2	Entry	1 &access
3116	IccFile::setAccess	2	Exit	1 &access

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3117	IccResource::setActionsOnConditions	2	Entry	
3117	IccResource::setActionsOnConditions	2	Exit	
3118	IccResource::setActionOnAnyCondition	2	Entry	
3118	IccResource::setActionOnAnyCondition	2	Exit	
311A	IccFile::setActionOnLockedRecord	2	Entry	1 &action
311A	IccFile::setActionOnLockedRecord	2	Exit	1 &action
311B	IccClock::setAlarm	2	Entry	1 time.traceData() 2 &reqId
311B	IccClock::setAlarm	2	Exit	1 ivpI->ivAlarmRequestId.traceData()
311C	IccConsole::setAllRouteCodes	2	Entry	
311C	IccConsole::setAllRouteCodes	2	Exit	
311D	IccBase::setClassName	2	Entry	1 className
311D	IccBase::setClassName	2	Exit	1 className
311D	IccBaseI::setClassName	2	Entry	1 className
311D	IccBaseI::setClassName	2	Exit	1 className
311E	IccTerminal::setColor	2	Entry	
311E	IccTerminal::setColor	2	Exit	
311F	IccTerminal::setCursor	1	Entry	
311F	IccTerminal::setCursor	1	Exit	
311F	IccTerminal::setCursor	1	Entry	
311F	IccTerminal::setCursor	1	Exit	
3120	IccBase::setCustomClassNum	2	Entry	1 &num
3120	IccBase::setCustomClassNum	2	Exit	1 &num
3121	IccStartRequestQ::setData	2	Entry	1 data.traceData()
3121	IccStartRequestQ::setData	2	Exit	1 data.traceData()
3122	IccBuf::setDataLength	2	Entry	1 &length
3122	IccBuf::setDataLength	2	Exit	1 &ret
3122	IccBufI::setDataLength	2	Entry	1 &length
3122	IccBufI::setDataLength	2	Info	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3122	IccBufI::setDataLength	2	Exit	1 &ivDataLength
3123	IccBaseI::setDependentObjPtrsToNull	2	Entry	
3123	IccBaseI::setDependentObjPtrsToNull	2	Info	
3123	IccBaseI::setDependentObjPtrsToNull	2	Exit	
3124	IccTask::setDumpOpts	2	Entry	1 &opts
3124	IccTask::setDumpOpts	2	Exit	1 &opts
3125	IccFile::setEmptyOnOpen	2	Entry	1 &>trueFalse
3125	IccFile::setEmptyOnOpen	2	Exit	1 &>trueFalse
3126	Icc::setEDF	2	Entry	
3126	Icc::setEDF	2	Exit	
3126	IccResource::setEDF	2	Entry	
3126	IccResource::setEDF	2	Exit	
3127	IccBuf::setFMHContained	2	Entry	1 &yn
3127	IccBuf::setFMHContained	2	Exit	1 &yn
3129	IccBaseI::setIccClassName	2	Entry	1 className
3129	IccBaseI::setIccClassName	2	Exit	1 className
312A	IccProgram::setInputMessage	2	Entry	
312A	IccProgram::setInputMessage	2	Exit	
312B	IccJournal::setJournalTypeId	2	Entry	1 id.traceData()
312B	IccJournal::setJournalTypeId	2	Exit	1 id.traceData()
312C	IccKey::setKind	2	Entry	1 &kind
312C	IccKey::setKind	2	Exit	1 &kind
312D	IccUser::setLanguage	2	Entry	1 language
312D	IccUser::setLanguage	2	Exit	1 language
312E	IccTerminal::setLine	2	Entry	
312E	IccTerminal::setLine	2	Exit	
312F	IccTerminal::setNewLine	2	Entry	
312F	IccTerminal::setNewLine	2	Exit	
3130	IccTerminal::setNextCommArea	2	Entry	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3130	IccTerminal::setNextCommArea	2	Exit	
3131	IccTerminal::setNextInputMessage	2	Entry	
3131	IccTerminal::setNextInputMessage	2	Exit	
3132	IccTerminal::setNextTransId	2	Entry	
3132	IccTerminal::setNextTransId	2	Exit	
3133	IccJournal::setPrefix	2	Entry	1 prefix.traceData()
3133	IccJournal::setPrefix	2	Exit	1 prefix.traceData()
3134	IccTask::setPriority	2	Entry	1 &pri
3134	IccTask::setPriority	2	Exit	1 &pri
3135	IccStartRequestQ::setQueueName	2	Entry	1 queueName
3135	IccStartRequestQ::setQueueName	2	Exit	1 queueName
3136	IccConsole::setReplyTimeout	2	Entry	1 &seconds
3136	IccConsole::setReplyTimeout	2	Exit	1 &seconds
3137	IccStartRequestQ::setReturnTermId	2	Entry	1 termName
3137	IccStartRequestQ::setReturnTermId	2	Exit	1 termName
3138	IccStartRequestQ::setReturnTransId	2	Entry	1 transName
3138	IccStartRequestQ::setReturnTransId	2	Exit	1 transName
3139	IccConsole::setRouteCodes	2	Entry	1 &numRoutes
3139	IccConsole::setRouteCodes	1	Info	
3139	IccConsole::setRouteCodes	2	Exit	1 &numRoutes
313A	IccResource::setRouteOption	2	Entry	
313A	IccResource::setRouteOption	2	Exit	
313A	IccResource::setRouteOption	2	Entry	
313A	IccResource::setRouteOption	2	Exit	
313B	IccFile::setSearchCriterion	2	Entry	1 &search
313B	IccFile::setSearchCriterion	2	Exit	1 &search
313C	IccStartRequestQ::setStartOpts	2	Entry	1 &popt 2 &copt

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
313C	IccStartRequestQ::setStartOpts	2	Exit	1 &popt 2 &copt
313D	IccFile::setStatus	2	Entry	1 &status
313D	IccFile::setStatus	1	Info	
313D	IccFile::setStatus	2	Exit	1 &status
313F	IccIdI::setText	2	Entry	1 text 2 &policy
313F	IccIdI::setText	2	Exit	1 text 2 &policy
3140	IccAlarmRequestId::setTimerECA	2	Entry	1 &ptr
3140	IccAlarmRequestId::setTimerECA	2	Exit	1 &ptr
3143	IccTask::setWaitText	2	Entry	1 name
3143	IccTask::setWaitText	2	Exit	1 name
3144	IccTerminal::signoff	1	Entry	
3144	IccTerminal::signoff	1	Entry	
3145	IccTerminal::signon	1	Entry	
3145	IccTerminal::signon	1	Entry	
3145	IccTerminal::signon	1	Entry	
3145	IccTerminal::signon	1	Exit	
3146	IccStartRequestQ::start	2	Entry	1 transId.traceData() 2 &termId 3 &time 4 &reqId
3146	IccStartRequestQ::start	2	Exit	1 ivpI->ivRequestId.traceData()
3147	IccTerminalI::startBufferedInput	2	Entry	
3147	IccTerminalI::startBufferedInput	2	Exit	
3148	IccControl::startRequestQ	2	Entry	
3148	IccControl::startRequestQ	2	Exit	1 &IccStartRequestQI::cvpEObj
3149	IccTask::startType	2	Entry	
3149	IccTask::startType	2	Exit	1 &ivpI->ivStartType
314A	IccSession::state	2	Entry	1 &opt
314A	IccSession::state	2	Exit	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
314B	IccSession::stateText	2	Entry	1 &opt
314B	IccSession::stateText	2	Exit	
314C	IccEvent::summary	2	Entry	
314C	IccEvent::summary	2	Exit	
314C	IccException::summary	2	Entry	
314C	IccException::summary	2	Exit	1 ret
314C	IccMessage::summary	2	Entry	
314C	IccMessage::summary	2	Exit	1 ret
314D	IccTask::suspend	2	Entry	
314D	IccTask::suspend	2	Exit	
314E	IccSession::syncLevel	2	Entry	
314E	IccSession::syncLevel	2	Exit	1 &(ivpI->ivSyncLevel)
314F	IccControl::system	2	Entry	
314F	IccControl::system	2	Exit	1 &IccSystemI::cvpEObj
3150	IccSystem::sysId	2	Entry	
3150	IccSystem::sysId	2	Exit	1 ivpI->ivpSysId->traceData()
3151	IccControl::task	2	Entry	
3151	IccControl::task	2	Exit	1 &IccTaskI::cvpEObj
3152	IccControl::terminal	2	Entry	
3152	IccControl::terminal	2	Exit	1 &IccTerminalI::cvpEObj
3153	IccTerminalI::termId	2	Entry	
3153	IccTerminalI::termId	2	Exit	
3154	IccMessage::text	2	Entry	
3154	IccMessage::text	2	Exit	1 ret
3156	IccGI::throwExc	1	Info	
3156	IccGI::throwExc	2	Entry	
3156	IccGI::throwExc	2	Exit	
3157	IccClock::time	2	Entry	1 &timeSeparator
3157	IccClock::time	2	Exit	1 ret
3157	IccAbsTime::time	2	Entry	1 &timeSeparator
3157	IccAbsTime::time	2	Exit	1 ivpI->ivTime

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3158	IccAlarmRequestId::timerECA	2	Entry	
3158	IccAlarmRequestId::timerECA	2	Exit	1 &ivpIR->ivpAddress
3159	IccTime::timeInHours	2	Entry	
3159	IccTime::timeInHours	2	Exit	1 &ret
315A	IccTime::timeInMinutes	2	Entry	
315A	IccTime::timeInMinutes	2	Exit	1 &ret
315B	IccTime::timeInSeconds	2	Entry	
315B	IccTime::timeInSeconds	2	Exit	1 &ret
315D	IccTask::transId	2	Entry	
315D	IccTask::transId	2	Exit	1 ivpI->ivpTransId->traceData()
315E	IccGI::trapDtcInitError	Exc	Error	
315F	IccGI::trapDtcSetError	Exc	Error	
3160	IccGI::trapMemoryExhausted	Exc	Error	
3162	IccTask::triggerDataQueueId	2	Entry	
3162	IccTask::triggerDataQueueId	2	Exit	1 ivpI->ivTriggerDataQueueId.traceData()
3163	IccSemaphore::tryLock	2	Entry	
3163	IccSemaphore::tryLock	2	Exit	1 &ret
3164	IccException::type	2	Entry	
3164	IccException::type	2	Exit	1 &ivpI->ivType
3164	IccFile::type	2	Entry	1 &opt
3164	IccFile::type	2	Exit	1 &(ivpI->ivpSPData->type)
3164	IccRecordIndex::type	2	Entry	
3164	IccRecordIndex::type	2	Exit	1 &ivpI->ivType
3164	IccSemaphore::type	2	Entry	
3164	IccSemaphore::type	2	Exit	1 &ivpI->ivLockType
3164	IccTime::type	2	Entry	
3164	IccTime::type	2	Exit	1 &ivpIT->ivType
3165	IccException::typeText	2	Entry	
3165	IccException::typeText	2	Exit	1 ret

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3166	IccGI::unknownException	Exc	Error	
3167	IccProgram::unload	2	Entry	
3167	IccProgram::unload	2	Exit	
3168	IccSemaphore::unlock	2	Entry	
3168	IccSemaphore::unlock	2	Exit	
3169	IccFile::unlockRecord	2	Entry	1 &updateToken
3169	IccFile::unlockRecord	2	Exit	1 &updateToken
316A	IccClock::update	2	Entry	
316A	IccClock::update	2	Exit	
316B	IccTask::userId	2	Entry	1 &opt
316B	IccTask::userId	2	Exit	1 ivpI->ivUserId.traceData()
316C	IccKey::value	2	Entry	
316C	IccKey::value	2	Exit	1 ret
316C	IccRecordIndexI::value	2	Entry	
316C	IccRecordIndexI::value	2	Exit	1 &ret
316D	IccUser::verifyPassword	2	Entry	1 password
316D	IccUser::verifyPassword	2	Exit	1 password
316E	IccJournal::wait	2	Entry	1 &requestNum 2 &opt
316E	IccJournal::wait	2	Exit	1 &requestNum 2 &opt
316F	IccTask::waitExternal	2	Entry	1 &ECBList 2 &numEvents 3 &opt 4 &type
316F	IccTask::waitExternal	2	Exit	1 &ECBList 2 &numEvents 3 &opt 4 &type
3170	IccTerminal::waitForAID	1	Entry	
3170	IccTerminal::waitForAID	1	Exit	
3170	IccTerminal::waitForAID	1	Entry	
3170	IccTerminal::waitForAID	1	Exit	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3171	IccTask::waitOnAlarm	2	Entry	1 id.traceData()
3171	IccTask::waitOnAlarm	2	Exit	1 id.traceData()
3172	IccTerminal::width	1	Entry	
3172	IccTerminal::width	1	Exit	
3172	IccTerminal::width	1	Info	
3173	IccSystem::workArea	2	Entry	
3173	IccSystem::workArea	2	Exit	1 ivpI->ivpCWA->traceData()
3173	IccTerminal::workArea	1	Entry	
3173	IccTerminal::workArea	1	Exit	
3173	IccTask::workArea	2	Entry	
3173	IccTask::workArea	2	Exit	1 ivpI->ivpTWA->traceData()
3174	IccConsole::write	2	Entry	1 send.traceData() 2 &opt
3174	IccConsole::write	2	Exit	1 send.traceData() 2 &opt
3175	IccConsole::writeAndGetReply	2	Entry	1 send.traceData() 2 &opt
3175	IccConsole::writeAndGetReply	2	Exit	1 send.traceData() 2 &opt
3176	IccDataQueue::writeItem	2	Entry	1 item.traceData()
3176	IccDataQueue::writeItem	2	Exit	1 item.traceData()
3176	IccTempStore::writeItem	2	Entry	1 item.traceData() 2 &opt
3176	IccTempStore::writeItem	2	Exit	1 &itemNumber
3177	IccFile::writeRecord	2	Entry	1 record.traceData()
3177	IccFile::writeRecord	2	Exit	1 record.traceData()
3177	IccJournal::writeRecord	2	Entry	1 record.traceData() 2 &opts
3177	IccJournal::writeRecord	2	Exit	1 &reqid
3178	IccClock::year	2	Entry	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3178	IccClock::year	2	Exit	1 &ret
3178	IccAbsTime::year	2	Entry	
3178	IccAbsTime::year	2	Exit	1 &ivpI->ivYear
3179	IccTerminal::AID	2	Entry	
3179	IccTerminal::AID	2	Exit	
317A	IccAbendData::ASRAInterrupt	2	Entry	1 &opt
317A	IccAbendData::ASRAInterrupt	2	Exit	1 ivpI->ivasraintrpt
317B	IccAbendData::ASRAKeyType	2	Entry	1 &opt
317B	IccAbendData::ASRAKeyType	2	Exit	1 &(ivpI->ivasrakey)
317C	IccAbendData::ASRAPSW	2	Entry	1 &opt
317C	IccAbendData::ASRAPSW	2	Exit	1 ivpI->ivasrapsw
317D	IccAbendData::ASRARegisters	2	Entry	1 &opt
317D	IccAbendData::ASRARegisters	2	Exit	1 ivpI->ivasraregs
317E	IccAbendData::ASRASpaceType	2	Entry	1 &opt
317E	IccAbendData::ASRASpaceType	2	Exit	1 &(ivpI->ivasraspc)
317F	IccAbendData::ASRAStorageType	2	Entry	1 &opt
317F	IccAbendData::ASRAStorageType	2	Exit	1 &(ivpI->ivasrastg)
3184	IccUser::ESMReason	2	Entry	
3184	IccUser::ESMReason	2	Exit	1 &ivpI->ivESMReason
3185	IccUser::ESMResponse	2	Entry	
3185	IccUser::ESMResponse	2	Exit	1 &ivpI->ivESMResponse
3186	IccSession::PIPList	2	Entry	
3186	IccSession::PIPList	2	Exit	1 ivpI->ivpPIPList->traceData()
3188	IccBuf::operatorLL	2	Entry	1 &ch
3188	IccBuf::operatorLL	2	Exit	1 this->traceData()
3188	IccTerminal::operatorLL	2	Entry	
3188	IccTerminal::operatorLL	2	Exit	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
318A	IccBuf::operatorAs	2	Entry	1 buf.traceData()
318A	IccBuf::operatorAs	2	Exit	1 this->traceData()
318A	IccKey::operatorAs	2	Entry	1 key.traceData()
318A	IccKey::operatorAs	2	Exit	1 this->traceData()
318A	IccResourceId::operatorAs	2	Entry	1 id.traceData()
318A	IccResourceId::operatorAs	2	Exit	1 id.traceData()
318A	IccAbsTime::operatorAs	2	Entry	1 absTime.traceData()
318A	IccAbsTime::operatorAs	2	Exit	1 absTime.traceData()
318B	IccBuf::operatorPE	2	Entry	1 buf.traceData()
318B	IccBuf::operatorPE	2	Exit	1 this->traceData()
318C	IccBuf::operatorNE	2	Entry	1 buf.traceData()
318C	IccBuf::operatorNE	2	Exit	1 &bool
318C	IccKey::operatorNE	2	Entry	1 key.traceData()
318C	IccKey::operatorNE	2	Exit	1 &same
318D	IccBase::operatorNew	1	Info	
318D	IccBase::operatorNew	Exc	Error	
318D	IccBase::operatorNew	1	Info	
318E	IccBase::operatorDelete	Exc	Error	
318E	IccBase::operatorDelete	1	Info	
318E	IccBase::operatorDelete	Exc	Error	
3191	IccGI::terminateTrap	Exc	Error	
3192	IccResource::id	2	Entry	
3192	IccResource::id	2	Exit	
3195	IccTerminal::setAttrs	2	Entry	
3195	IccTerminal::setAttrs	2	Exit	
3212	IccGI::getCICSTSlevel	2	Entry	
3212	IccGI::getCICSTSlevel	Exc	Exception	
3212	IccGI::getCICSTSlevel	2	Exit	
3213	IccProgram::registerInputMessage	2	Entry	
3213	IccProgram::registerInputMessage	2	Exit	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3214	IccProgram::clearInputMessage	2	Entry	
3214	IccProgram::clearInputMessage	2	Exit	
3215	IccJournal::clearPrefix	2	Entry	
3215	IccJournal::clearPrefix	2	Exit	
3216	IccStartRequestQ::clearData	2	Entry	
3216	IccStartRequestQ::clearData	2	Exit	
321B	IccAbendData::IccAbendData_C	2	Entry	
321B	IccAbendData::IccAbendData_C	2	Exit	
321C	IccAbendData::IccAbendData_D	2	Entry	
321C	IccAbendData::IccAbendData_D	2	Exit	
321D	IccBuf::IccBuf_C	2	Entry	1 &length 2 &type
321D	IccBuf::IccBuf_C	2	Exit	1 &length 2 &type
321E	IccBuf::IccBuf_C1	2	Entry	1 &length 2 &pData
321E	IccBuf::IccBuf_C1	2	Exit	1 &length 2 &pData
321F	IccBuf::IccBuf_C2	2	Entry	1 text 2 &type
321F	IccBuf::IccBuf_C2	2	Exit	1 text 2 &type
3220	IccBuf::IccBuf_C3	2	Entry	1 buf.traceData()
3220	IccBuf::IccBuf_C3	2	Exit	1 buf.traceData()
3221	IccBuf::IccBuf_D	2	Entry	
3221	IccBuf::IccBuf_D	2	Exit	
3222	IccBuf::operatorAs1	2	Entry	1 pData
3222	IccBuf::operatorAs1	2	Exit	1 this->traceData()
3222	IccKey::operatorAs1	2	Entry	1 buffer.traceData()
3222	IccKey::operatorAs1	2	Exit	1 this->traceData()
3222	IccConvId::operatorAs1	2	Entry	1 convName
3222	IccConvId::operatorAs1	2	Exit	1 this->traceData()

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3222	IccTimeOfDay::operatorAs1	2	Entry	1 timeOfDay.traceData()
3222	IccTimeOfDay::operatorAs1	2	Exit	1 timeOfDay.traceData()
3223	IccBuf::operatorPE1	2	Entry	1 pData
3223	IccBuf::operatorPE1	2	Exit	1 this->traceData()
3224	IccBuf::operatorEq1	2	Entry	1 text
3224	IccBuf::operatorEq1	2	Exit	1 &bool
3224	IccKey::operatorEq1	2	Entry	1 buffer.traceData()
3224	IccKey::operatorEq1	2	Exit	1 &same
3225	IccBuf::operatorNE1	2	Entry	1 text
3225	IccBuf::operatorNE1	2	Exit	1 &bool
3225	IccKey::operatorNE1	2	Entry	1 buffer.traceData()
3225	IccKey::operatorNE1	2	Exit	1 &same
3226	IccBuf::operatorLL1	2	Entry	1 &ch
3226	IccBuf::operatorLL1	2	Exit	1 this->traceData()
3227	IccBuf::operatorLL2	2	Entry	1 &ch
3227	IccBuf::operatorLL2	2	Exit	1 this->traceData()
3228	IccBuf::operatorLL3	2	Entry	1 text
3228	IccBuf::operatorLL3	2	Exit	1 this->traceData()
3229	IccBuf::operatorLL4	2	Entry	1 text
3229	IccBuf::operatorLL4	2	Exit	1 this->traceData()
322A	IccBuf::operatorLL5	2	Entry	1 text
322A	IccBuf::operatorLL5	2	Exit	1 this->traceData()
322B	IccBuf::operatorLL6	2	Entry	1 &num

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
322B	IccBuf::operatorLL6	2	Exit	1 this->traceData()
322C	IccBuf::operatorLL7	2	Entry	1 &num
322C	IccBuf::operatorLL7	2	Exit	1 this->traceData()
322D	IccBuf::operatorLL8	2	Entry	1 &num
322D	IccBuf::operatorLL8	2	Exit	1 this->traceData()
322E	IccBuf::operatorLL9	2	Entry	1 &num
322E	IccBuf::operatorLL9	2	Exit	1 this->traceData()
322F	IccBuf::operatorLL10	2	Entry	1 &num
322F	IccBuf::operatorLL10	2	Exit	1 this->traceData()
3230	IccBuf::operatorLL11	2	Entry	1 &num
3230	IccBuf::operatorLL11	2	Exit	1 this->traceData()
3231	IccBuf::operatorLL12	2	Entry	1 &num
3231	IccBuf::operatorLL12	2	Exit	1 this->traceData()
3232	IccBuf::operatorLL13	2	Entry	1 &num
3232	IccBuf::operatorLL13	2	Exit	1 this->traceData()
3233	IccBuf::operatorLL14	2	Entry	1 buf.traceData()
3233	IccBuf::operatorLL14	2	Exit	1 this->traceData()
3234	IccBuf::append1	2	Entry	1 fmt
3234	IccBuf::append1	2	Exit	1 this->traceData()
3235	IccBuf::assign1	2	Entry	1 fmt
3235	IccBuf::assign1	2	Exit	1 this->traceData()
3236	IccClock::IccClock_C	2	Entry	1 &um
3236	IccClock::IccClock_C	2	Exit	1 &um
3237	IccClock::IccClock_D	2	Entry	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3237	IccClock::IccClock_D	2	Exit	
3238	IccConsole::IccConsole_C	2	Entry	
3238	IccConsole::IccConsole_C	2	Exit	
3239	IccConsole::IccConsole_D	2	Entry	
3239	IccConsole::IccConsole_D	2	Exit	
323A	IccConsole::setReplyTimeout1	2	Entry	1 interval.traceData()
323A	IccConsole::setReplyTimeout1	2	Exit	1 interval.traceData()
323B	IccControl::IccControl_C	2	Entry	
323B	IccControl::IccControl_C	2	Exit	
323C	IccControl::IccControl_D	2	Entry	
323C	IccControl::IccControl_D	2	Exit	
323D	IccControl::setAbendHandler1	2	Entry	1 programid.traceData()
323D	IccControl::setAbendHandler1	2	Exit	1 programid.traceData()
323E	IccDataQueue::IccDataQueue_C	2	Entry	1 id.traceData()
323E	IccDataQueue::IccDataQueue_C	2	Exit	1 id.traceData()
323F	IccDataQueue::IccDataQueue_C1	2	Entry	1 queueName
323F	IccDataQueue::IccDataQueue_C1	2	Exit	1 queueName
3240	IccDataQueue::IccDataQueue_D	2	Entry	
3240	IccDataQueue::IccDataQueue_D	2	Exit	
3241	IccDataQueue::writeItem1	2	Entry	1 text
3241	IccDataQueue::writeItem1	2	Exit	1 text
3241	IccTempStore::writeItem1	2	Entry	1 text 2 &opt
3241	IccTempStore::writeItem1	2	Exit	1 &ret
3242	IccEvent::IccEvent_C	2	Entry	1 &object 2 methodName
3242	IccEvent::IccEvent_C	2	Exit	1 &object 2 methodName
3243	IccEvent::IccEvent_C1	2	Entry	1 event.traceData()
3243	IccEvent::IccEvent_C1	2	Exit	1 event.traceData()

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3244	IccEvent::IccEvent_D	2	Entry	
3244	IccEvent::IccEvent_D	2	Exit	
3245	IccException::IccException_C	2	Entry	1 &exceptionType 2 &classType 3 className 4 methodName 5 &message
3245	IccException::IccException_C	2	Exit	1 &exceptionType 2 &classType 3 className 4 methodName 5 &message
3246	IccException::IccException_C1	2	Entry	1 exc.traceData()
3246	IccException::IccException_C1	2	Exit	1 exc.traceData()
3247	IccException::IccException_D	2	Entry	
3247	IccException::IccException_D	2	Exit	
3248	IccFile::IccFile_C	2	Entry	1 id.traceData() 2 &index
3248	IccFile::IccFile_C	2	Exit	1 id.traceData() 2 &index
3249	IccFile::IccFile_C1	2	Entry	1 fileName 2 &index
3249	IccFile::IccFile_C1	2	Exit	1 fileName 2 &index
324A	IccFile::IccFile_C2	2	Entry	
324A	IccFile::IccFile_C2	2	Exit	
324B	IccFile::IccFile_D	2	Entry	
324B	IccFile::IccFile_D	2	Exit	
324C	IccFileIterator::IccFileIterator_C	2	Entry	1 &file 2 &index 3 &search
324C	IccFileIterator::IccFileIterator_C	2	Exit	1 &file 2 &index 3 &search
324D	IccFileIterator::IccFileIterator_D	2	Entry	
324D	IccFileIterator::IccFileIterator_D	2	Exit	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
324E	IccJournal::IccJournal_C	2	Entry	1 id.traceData() 2 &opts
324E	IccJournal::IccJournal_C	2	Exit	1 id.traceData() 2 &opts
324F	IccJournal::IccJournal_C1	2	Entry	1 &journalNum 2 &opts
324F	IccJournal::IccJournal_C1	2	Exit	1 &journalNum 2 &opts
3250	IccJournal::IccJournal_D	2	Entry	
3250	IccJournal::IccJournal_D	2	Exit	
3251	IccJournal::setJournalTypeId1	2	Entry	1 jtypeid
3251	IccJournal::setJournalTypeId1	2	Exit	1 jtypeid
3252	IccJournal::setPrefix1	2	Entry	1 prefix
3252	IccJournal::setPrefix1	2	Exit	1 prefix
3253	IccJournal::writeRecord1	2	Entry	1 text 2 &opts
3253	IccJournal::writeRecord1	2	Exit	1 &ret
3254	IccMessage::IccMessage_C	2	Entry	1 &number 2 text 3 className 4 methodName
3254	IccMessage::IccMessage_C	2	Exit	1 &number 2 text 3 className 4 methodName
3255	IccMessage::IccMessage_C1	2	Entry	1 msg.traceData()
3255	IccMessage::IccMessage_C1	2	Exit	1 msg.traceData()
3256	IccMessage::IccMessage_D	2	Entry	
3256	IccMessage::IccMessage_D	2	Exit	
3257	IccProgram::IccProgram_C	2	Entry	1 id.traceData()
3257	IccProgram::IccProgram_C	2	Exit	1 id.traceData()

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3258	IccProgram::IccProgram_C1	2	Entry	1 progName
3258	IccProgram::IccProgram_C1	2	Exit	1 progName
3259	IccProgram::IccProgram_D	2	Entry	
3259	IccProgram::IccProgram_D	2	Exit	
325A	IccRecordIndex::IccRecordIndex_C	2	Entry	1 &type
325A	IccRecordIndex::IccRecordIndex_C	2	Exit	1 &type
325B	IccRecordIndex::IccRecordIndex_D	2	Entry	
325B	IccRecordIndex::IccRecordIndex_D	2	Exit	
325C	IccKey::IccKey_C	2	Entry	1 initValue 2 &kind
325C	IccKey::IccKey_C	2	Exit	1 initValue 2 &kind
325D	IccKey::IccKey_C1	2	Entry	1 &completeLength 2 &kind
325D	IccKey::IccKey_C1	2	Exit	1 &completeLength 2 &kind
325E	IccKey::IccKey_C2	2	Entry	1 key.traceData()
325E	IccKey::IccKey_C2	2	Exit	1 key.traceData()
325F	IccKey::IccKey_D	2	Entry	
325F	IccKey::IccKey_D	2	Exit	
3260	IccBuf::charStar	2	Entry	
3260	IccBuf::charStar	2	Exit	
3261	IccBase::IccBase_C	2	Entry	1 &type
3261	IccBase::IccBase_C	2	Exit	1 &type
3262	IccBase::IccBase_D	2	Entry	
3262	IccBase::IccBase_D	2	Exit	
3263	IccKey::operatorEq2	2	Entry	1 text
3263	IccKey::operatorEq2	2	Exit	1 &same
3264	IccUserI::IccUserI_C	2	Entry	
3264	IccUserI::IccUserI_C	2	Exit	
3265	IccKey::operatorNE2	2	Entry	1 text

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3265	IccKey::operatorNE2	2	Exit	1 &same
3266	IccRBA::IccRBA_C	2	Entry	1 &initRBA
3266	IccRBA::IccRBA_C	2	Exit	1 &initRBA
3267	IccRBA::IccRBA_C1	2	Entry	1 rba.traceData()
3267	IccRBA::IccRBA_C1	2	Exit	1 rba.traceData()
3268	IccRBA::IccRBA_D	2	Entry	
3268	IccRBA::IccRBA_D	2	Exit	
3269	IccRBA::operatorAs3	2	Entry	1 rba.traceData()
3269	IccRBA::operatorAs3	2	Exit	1 this->traceData()
3269	IccDataQueueId::operatorAs3	2	Entry	1 queueName
3269	IccDataQueueId::operatorAs3	2	Exit	1 queueName
326A	IccRBA::operatorAs4	2	Entry	1 &num
326A	IccRBA::operatorAs4	2	Exit	1 this->traceData()
326A	IccDataQueueId::operatorAs4	2	Entry	1 id.traceData()
326A	IccDataQueueId::operatorAs4	2	Exit	1 id.traceData()
326B	IccRBA::operatorEq3	2	Entry	1 rba.traceData()
326B	IccRBA::operatorEq3	2	Exit	1 &ret
326C	IccRBA::operatorEq4	2	Entry	1 &num
326C	IccRBA::operatorEq4	2	Exit	1 &ret
326D	IccRBA::operatorNE3	2	Entry	1 rba.traceData()
326D	IccRBA::operatorNE3	2	Exit	1 &ret
326E	IccRBA::operatorNE4	2	Entry	1 &num
326E	IccRBA::operatorNE4	2	Exit	1 &ret
326F	IccRRN::IccRRN_C	2	Entry	1 &initRRN

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
326F	IccRRN::IccRRN_C	2	Exit	1 &initRRN
3270	IccRRN::IccRRN_C1	2	Entry	1 rrn.traceData()
3270	IccRRN::IccRRN_C1	2	Exit	1 rrn.traceData()
3271	IccRRN::IccRRN_D	2	Entry	
3271	IccRRN::IccRRN_D	2	Exit	
3272	IccRRN::operatorAs5	2	Entry	1 rrn.traceData()
3272	IccRRN::operatorAs5	2	Exit	1 this->traceData()
3272	IccFileId::operatorAs5	2	Entry	1 fileName
3272	IccFileId::operatorAs5	2	Exit	1 this->traceData()
3273	IccRRN::operatorAs6	2	Entry	1 &num
3273	IccRRN::operatorAs6	2	Exit	1 this->traceData()
3273	IccFileId::operatorAs6	2	Entry	1 id.traceData()
3273	IccFileId::operatorAs6	2	Exit	1 this
3274	IccRRN::operatorEq5	2	Entry	1 rrn.traceData()
3274	IccRRN::operatorEq5	2	Exit	1 &ret
3275	IccRRN::operatorEq6	2	Entry	1 &num
3275	IccRRN::operatorEq6	2	Exit	1 &ret
3276	IccRRN::operatorNE5	2	Entry	1 rrn.traceData()
3276	IccRRN::operatorNE5	2	Exit	1 &ret
3277	IccRRN::operatorNE6	2	Entry	1 &num
3277	IccRRN::operatorNE6	2	Exit	1 &ret
3278	IccRRN::number1	2	Entry	
3278	IccRRN::number1	2	Exit	1 &ivpI->ivNumber
327C	IccResourceId::IccResourceId_C	2	Entry	1 &type 2 id.traceData()

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
327C	IccResourceId::IccResourceId_C	2	Exit	1 &type 2 id.traceData()
327D	IccResourceId::IccResourceId_D	2	Entry	
327D	IccResourceId::IccResourceId_D	2	Exit	
327E	IccConvId::IccConvId_C	2	Entry	1 convName
327E	IccConvId::IccConvId_C	2	Exit	1 convName
327F	IccConvId::IccConvId_C1	2	Entry	1 convId.traceData()
327F	IccConvId::IccConvId_C1	2	Exit	1 convId.traceData()
3280	IccTaskI::IccTaskI_C	2	Entry	1 &baseObjI
3280	IccTaskI::IccTaskI_C	2	Exit	1 &baseObjI
3281	IccTaskI::IccTaskI_D	2	Entry	
3281	IccTaskI::IccTaskI_D	2	Exit	
3282	IccDataQueueId::IccDataQueueId_C	2	Entry	1 queueName
3282	IccDataQueueId::IccDataQueueId_C	2	Exit	1 queueName
3283	IccDataQueueId::IccDataQueueId_C1	2	Entry	1 id.traceData()
3283	IccDataQueueId::IccDataQueueId_C1	2	Exit	1 id.traceData()
3284	IccTextI::IccTextI_C	2	Entry	1 textData 2 &textLength
3284	IccTextI::IccTextI_C	2	Exit	1 textData 2 &textLength
3285	IccTextI::IccTextI_C1	2	Entry	1 text.traceData()
3285	IccTextI::IccTextI_C1	2	Exit	1 text.traceData()
3286	IccFileId::IccFileId_C	2	Entry	1 fileName
3286	IccFileId::IccFileId_C	2	Exit	1 fileName
3287	IccFileId::IccFileId_C1	2	Entry	1 id.traceData()
3287	IccFileId::IccFileId_C1	2	Exit	1 id.traceData()
3288	IccTerminalDataI::IccTerminalDataI_C	2	Entry	
3288	IccTerminalDataI::IccTerminalDataI_C	2	Exit	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3289	IccTerminalDataI::IccTerminalDataI_D	2	Entry	
3289	IccTerminalDataI::IccTerminalDataI_D	2	Exit	
328A	IccGroupId::IccGroupId_C	2	Entry	1 groupName
328A	IccGroupId::IccGroupId_C	2	Exit	1 groupName
328B	IccGroupId::IccGroupId_C1	2	Entry	1 id.traceData()
328B	IccGroupId::IccGroupId_C1	2	Exit	1 id.traceData()
328C	IccGroupId::operatorAs7	2	Entry	1 groupName
328C	IccGroupId::operatorAs7	2	Exit	1 this->traceData()
328D	IccGroupId::operatorAs8	2	Entry	1 id.traceData()
328D	IccGroupId::operatorAs8	2	Exit	1 this
328E	IccJournalId::IccJournalId_C	2	Entry	1 &journalNum
328E	IccJournalId::IccJournalId_C	2	Exit	1 &journalNum
328F	IccJournalId::IccJournalId_C1	2	Entry	1 id.traceData()
328F	IccJournalId::IccJournalId_C1	2	Exit	1 id.traceData()
3290	IccJournalId::operatorAs9	2	Entry	1 &journalNum
3290	IccJournalId::operatorAs9	2	Exit	1 &journalNum
3291	IccJournalId::operatorAs10	2	Entry	1 id.traceData()
3291	IccJournalId::operatorAs10	2	Exit	1 id.traceData()
3292	IccJournalTypeId::IccJournalTypeId_C	2	Entry	1 journalTypeName
3292	IccJournalTypeId::IccJournalTypeId_C	2	Exit	1 journalTypeName
3293	IccJournalTypeId::IccJournalTypeId_C1	2	Entry	1 id.traceData()
3293	IccJournalTypeId::IccJournalTypeId_C1	2	Exit	1 id.traceData()
3294	IccJournalTypeId::operatorAs11	2	Entry	1 journalTypeName
3294	IccJournalTypeId::operatorAs11	2	Exit	1 journalTypeName

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3295	IccJournalTypeId::operatorAs12	2	Entry	1 id.traceData()
3295	IccJournalTypeId::operatorAs12	2	Exit	1 id.traceData()
3296	IccLockId::IccLockId_C	2	Entry	1 resName
3296	IccLockId::IccLockId_C	2	Exit	1 resName
3297	IccLockId::IccLockId_C1	2	Entry	1 id.traceData()
3297	IccLockId::IccLockId_C1	2	Exit	1 id.traceData()
3298	IccLockId::operatorAs13	2	Entry	1 resName
3298	IccLockId::operatorAs13	2	Exit	1 this->traceData()
3299	IccLockId::operatorAs14	2	Entry	1 id.traceData()
3299	IccLockId::operatorAs14	2	Exit	1 this
329A	IccPartnerId::IccPartnerId_C	2	Entry	1 partnerName
329A	IccPartnerId::IccPartnerId_C	2	Exit	1 partnerName
329B	IccPartnerId::IccPartnerId_C1	2	Entry	1 id.traceData()
329B	IccPartnerId::IccPartnerId_C1	2	Exit	1 id.traceData()
329C	IccPartnerId::operatorAs15	2	Entry	1 partnerName
329C	IccPartnerId::operatorAs15	2	Exit	1 partnerName
329D	IccPartnerId::operatorAs16	2	Entry	1 id.traceData()
329D	IccPartnerId::operatorAs16	2	Exit	1 id.traceData()
329E	IccProgramId::IccProgramId_C	2	Entry	1 progName
329E	IccProgramId::IccProgramId_C	2	Exit	1 progName
329F	IccProgramId::IccProgramId_C1	2	Entry	1 id.traceData()
329F	IccProgramId::IccProgramId_C1	2	Exit	1 id.traceData()
32A0	IccProgramId::operatorAs17	2	Entry	1 progName

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
32A0	IccProgramId::operatorAs17	2	Exit	1 progName
32A1	IccProgramId::operatorAs18	2	Entry	1 id.traceData()
32A1	IccProgramId::operatorAs18	2	Exit	1 id.traceData()
32A2	IccRequestId::IccRequestId_C	2	Entry	
32A2	IccRequestId::IccRequestId_C	2	Exit	
32A3	IccRequestId::IccRequestId_C1	2	Entry	1 reqName
32A3	IccRequestId::IccRequestId_C1	2	Exit	1 reqName
32A4	IccRequestId::IccRequestId_C2	2	Entry	1 reqId.traceData()
32A4	IccRequestId::IccRequestId_C2	2	Exit	1 reqId.traceData()
32A5	IccRequestId::operatorAs19	2	Entry	1 reqName
32A5	IccRequestId::operatorAs19	2	Exit	1 reqName
32A6	IccRequestId::operatorAs20	2	Entry	1 id.traceData()
32A6	IccRequestId::operatorAs20	2	Exit	1 id.traceData()
32A7	IccAlarmRequestId::IccAlarmRequestId_C2		Entry	
32A7	IccAlarmRequestId::IccAlarmRequestId_C2		Exit	
32A8	IccAlarmRequestId::IccAlarmRequestId_C2		Entry	1 reqName 2 &timerECA
32A8	IccAlarmRequestId::IccAlarmRequestId_C2		Exit	1 reqName 2 &timerECA
32A9	IccAlarmRequestId::IccAlarmRequestId_C2		Entry	1 id.traceData()
32A9	IccAlarmRequestId::IccAlarmRequestId_C2		Exit	1 id.traceData()
32AA	IccAlarmRequestId::operatorAs21	2	Entry	1 reqName
32AA	IccAlarmRequestId::operatorAs21	2	Exit	1 reqName
32AB	IccAlarmRequestId::operatorAs22	2	Entry	1 id.traceData()
32AB	IccAlarmRequestId::operatorAs22	2	Exit	1 id.traceData()
32AC	IccAlarmRequestId::operatorAs23	2	Entry	1 id.traceData()

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
32AC	IccAlarmRequestId::operatorAs23	2	Exit	1 id.traceData()
32AD	IccSysId::IccSysId_C	2	Entry	1 sysName
32AD	IccSysId::IccSysId_C	2	Exit	1 sysName
32AE	IccSysId::IccSysId_C1	2	Entry	1 sysId.traceData()
32AE	IccSysId::IccSysId_C1	2	Exit	1 sysId.traceData()
32AF	IccSysId::operatorAs24	2	Entry	1 sysName
32AF	IccSysId::operatorAs24	2	Exit	1 this->traceData()
32B0	IccSysId::operatorAs25	2	Entry	1 id.traceData()
32B0	IccSysId::operatorAs25	2	Exit	1 this
32B1	IccTempStoreId::IccTempStoreId_C	2	Entry	1 storeName
32B1	IccTempStoreId::IccTempStoreId_C	2	Exit	1 storeName
32B2	IccTempStoreId::IccTempStoreId_C1	2	Entry	1 id.traceData()
32B2	IccTempStoreId::IccTempStoreId_C1	2	Exit	1 id.traceData()
32B3	IccTempStoreId::operatorAs26	2	Entry	1 storeName
32B3	IccTempStoreId::operatorAs26	2	Exit	1 storeName
32B4	IccTempStoreId::operatorAs27	2	Entry	1 id.traceData()
32B4	IccTempStoreId::operatorAs27	2	Exit	1 id.traceData()
32B5	IccTermId::IccTermId_C	2	Entry	1 termName
32B5	IccTermId::IccTermId_C	2	Exit	1 termName
32B6	IccTermId::IccTermId_C1	2	Entry	1 id.traceData()
32B6	IccTermId::IccTermId_C1	2	Exit	1 id.traceData()
32B7	IccTermId::operatorAs28	2	Entry	1 termName
32B7	IccTermId::operatorAs28	2	Exit	1 this->traceData()

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
32B8	IccTermId::operatorAs29	2	Entry	1 id.traceData()
32B8	IccTermId::operatorAs29	2	Exit	1 this
32B9	IccTPNameId::IccTPNameId_C	2	Entry	1 TPName
32B9	IccTPNameId::IccTPNameId_C	2	Exit	1 TPName
32BA	IccTPNameId::IccTPNameId_C1	2	Entry	1 id.traceData()
32BA	IccTPNameId::IccTPNameId_C1	2	Exit	1 id.traceData()
32BB	IccTPNameId::operatorAs30	2	Entry	1 TPName
32BB	IccTPNameId::operatorAs30	2	Exit	1 this->traceData()
32BC	IccTPNameId::operatorAs31	2	Entry	1 id.traceData()
32BC	IccTPNameId::operatorAs31	2	Exit	1 id.traceData()
32BD	IccTransId::IccTransId_C	2	Entry	1 transName
32BD	IccTransId::IccTransId_C	2	Exit	1 transName
32BE	IccTransId::IccTransId_C1	2	Entry	1 id.traceData()
32BE	IccTransId::IccTransId_C1	2	Exit	1 id.traceData()
32BF	IccTransId::operatorAs32	2	Entry	1 transName
32BF	IccTransId::operatorAs32	2	Exit	1 this->traceData()
32C0	IccTransId::operatorAs33	2	Entry	1 id.traceData()
32C0	IccTransId::operatorAs33	2	Exit	1 this
32C1	IccUserId::IccUserId_C	2	Entry	1 userName
32C1	IccUserId::IccUserId_C	2	Exit	1 userName
32C2	IccUserId::IccUserId_C1	2	Entry	1 id.traceData()
32C2	IccUserId::IccUserId_C1	2	Exit	1 id.traceData()
32C3	IccUserId::operatorAs34	2	Entry	1 userName

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
32C3	IccUserId::operatorAs34	2	Exit	1 this->traceData()
32C4	IccUserId::operatorAs35	2	Entry	1 id.traceData()
32C4	IccUserId::operatorAs35	2	Exit	1 this
32C5	IccSemaphore::IccSemaphore_C	2	Entry	1 id.traceData() 2 &life
32C5	IccSemaphore::IccSemaphore_C	2	Exit	1 id.traceData() 2 &life
32C6	IccSemaphore::IccSemaphore_C1	2	Entry	1 resource 2 &type 3 &life
32C6	IccSemaphore::IccSemaphore_C1	2	Exit	1 resource 2 &type 3 &life
32C7	IccSemaphore::IccSemaphore_D	2	Entry	
32C7	IccSemaphore::IccSemaphore_D	2	Exit	
32C8	IccSession::IccSession_C	2	Entry	
32C8	IccSession::IccSession_C	2	Exit	
32C9	IccSession::IccSession_C1	2	Entry	1 id.traceData()
32C9	IccSession::IccSession_C1	2	Exit	1 id.traceData()
32CA	IccSession::IccSession_C2	2	Entry	1 sysName 2 profile
32CA	IccSession::IccSession_C2	2	Exit	1 sysName 2 profile
32CB	IccSession::IccSession_C3	2	Entry	1 sysId.traceData() 2 profile
32CB	IccSession::IccSession_C3	2	Exit	1 sysId.traceData() 2 profile
32CC	IccSession::IccSession_D	2	Entry	
32CC	IccSession::IccSession_D	2	Exit	
32CD	IccSession::connectProcess1	2	Entry	1 &level 2 transid.traceData() 3 &PIP

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
32CD	IccSession::connectProcess1	2	Exit	1 &level 2 transid.traceData() 3 &PIP
32CE	IccSession::connectProcess2	2	Entry	1 &level 2 TPName.traceData() 3 &PIP
32CE	IccSession::connectProcess2	2	Exit	1 &level 2 TPName.traceData() 3 &PIP
32CF	IccSession::send1	2	Entry	1 &opt
32CF	IccSession::send1	2	Exit	1 &opt
32D0	IccSession::sendInvite1	2	Entry	1 &opt
32D0	IccSession::sendInvite1	2	Exit	1 &opt
32D1	IccSession::sendLast1	2	Entry	1 &opt
32D1	IccSession::sendLast1	2	Exit	1 &opt
32D2	IccStartRequestQ::IccStartRequestQ_C	2	Entry	
32D2	IccStartRequestQ::IccStartRequestQ_C	2	Exit	
32D3	IccStartRequestQ::IccStartRequestQ_D	2	Entry	
32D3	IccStartRequestQ::IccStartRequestQ_D	2	Exit	
32D4	IccStartRequestQ::setReturnTermId1	2	Entry	1 termId.traceData()
32D4	IccStartRequestQ::setReturnTermId1	2	Exit	1 termId.traceData()
32D5	IccStartRequestQ::setReturnTransId1	2	Entry	1 transId.traceData()
32D5	IccStartRequestQ::setReturnTransId1	2	Exit	1 transId.traceData()
32D6	IccStartRequestQ::start1	2	Entry	1 transId.traceData() 2 &userId 3 &time 4 &reqId
32D6	IccStartRequestQ::start1	2	Exit	1 ivpI->ivRequestId.traceData()
32D7	IccStartRequestQ::start2	2	Entry	1 transId.traceData() 2 &time 3 &reqId

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
32D7	IccStartRequestQ::start2	2	Exit	1 ivpI->ivRequestId.traceData()
32D8	IccSystem::IccSystem_C	2	Entry	
32D8	IccSystem::IccSystem_C	2	Exit	
32D9	IccSystem::IccSystem_D	2	Entry	
32D9	IccSystem::IccSystem_D	2	Exit	
32DA	IccSystem::beginBrowse1	2	Entry	1 &resource 2 resName
32DA	IccSystem::beginBrowse1	2	Exit	1 &resource 2 resName
32DB	IccSystem::getFile1	2	Entry	1 fileName
32DB	IccSystem::getFile1	2	Exit	1 &pFile
32DC	IccTime::IccTime_C	2	Entry	1 &hours 2 &minutes 3 &seconds
32DC	IccTime::IccTime_C	2	Exit	1 &hours 2 &minutes 3 &seconds
32DD	IccTime::IccTime_C1	2	Entry	1 time.traceData()
32DD	IccTime::IccTime_C1	2	Exit	1 time.traceData()
32DE	IccTime::IccTime_D	2	Entry	
32DE	IccTime::IccTime_D	2	Exit	
32DF	IccAbsTime::IccAbsTime_C	2	Entry	1 packedDecimal
32DF	IccAbsTime::IccAbsTime_C	2	Exit	1 packedDecimal
32E0	IccAbsTime::IccAbsTime_C1	2	Entry	1 absTime.traceData()
32E0	IccAbsTime::IccAbsTime_C1	2	Exit	1 absTime.traceData()
32E1	IccAbsTime::hours1	2	Entry	
32E1	IccAbsTime::hours1	2	Exit	1 &ivpIT->ivHours
32E2	IccAbsTime::minutes1	2	Entry	
32E2	IccAbsTime::minutes1	2	Exit	1 &ivpIT->ivMinutes
32E3	IccAbsTime::seconds1	2	Entry	
32E3	IccAbsTime::seconds1	2	Exit	1 &ivpIT->ivSeconds

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
32E4	IccAbsTime::timeInHours1	2	Entry	
32E4	IccAbsTime::timeInHours1	2	Exit	1 &ret
32E5	IccAbsTime::timeInMinutes1	2	Entry	
32E5	IccAbsTime::timeInMinutes1	2	Exit	1 &ret
32E6	IccAbsTime::timeInSeconds1	2	Entry	
32E6	IccAbsTime::timeInSeconds1	2	Exit	1 &ret
32E7	IccTimeOfDay::IccTimeOfDay_C	2	Entry	1 &hours 2 &minutes 3 &seconds
32E7	IccTimeOfDay::IccTimeOfDay_C	2	Exit	1 &hours 2 &minutes 3 &seconds
32E8	IccTimeOfDay::IccTimeOfDay_C1	2	Entry	1 timeOfDay.traceData()
32E8	IccTimeOfDay::IccTimeOfDay_C1	2	Exit	1 timeOfDay.traceData()
32EA	IccTimeInterval::IccTimeInterval_C	2	Entry	1 &hours 2 &minutes 3 &seconds
32EA	IccTimeInterval::IccTimeInterval_C	2	Exit	1 &hours 2 &minutes 3 &seconds
32EB	IccTimeInterval::IccTimeInterval_C1	2	Entry	1 timeInt.traceData()
32EB	IccTimeInterval::IccTimeInterval_C1	2	Exit	1 timeInt.traceData()
32EC	IccKey::operatorAs2	2	Entry	1 text
32EC	IccKey::operatorAs2	2	Exit	1 this->traceData()
32EC	IccConvId::operatorAs2	2	Entry	1 id.traceData()
32EC	IccConvId::operatorAs2	2	Exit	1 this
32EC	IccTimeInterval::operatorAs2	2	Entry	1 timeInterval.traceData()
32EC	IccTimeInterval::operatorAs2	2	Exit	1 timeInterval.traceData()

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
32ED	IccTimeInterval::set1	2	Entry	1 &hours 2 &minutes 3 &seconds
32ED	IccTimeInterval::set1	2	Exit	1 &hours 2 &minutes 3 &seconds
32EE	IccTerminalData::IccTerminalData_C	2	Entry	
32EE	IccTerminalData::IccTerminalData_C	2	Exit	
32EF	IccTerminalData::IccTerminalData_D	2	Entry	
32EF	IccTerminalData::IccTerminalData_D	2	Exit	
32F0	IccTempStore::IccTempStore_C	2	Entry	1 id.traceData() 2 &loc
32F0	IccTempStore::IccTempStore_C	2	Exit	1 id.traceData() 2 &loc
32F1	IccTempStore::IccTempStore_C1	2	Entry	1 storeName 2 &loc
32F1	IccTempStore::IccTempStore_C1	2	Exit	1 storeName 2 &loc
32F2	IccTempStore::IccTempStore_D	2	Entry	
32F2	IccTempStore::IccTempStore_D	2	Exit	
32F3	IccAbsTimeI::IccAbsTimeI_C	2	Entry	
32F3	IccAbsTimeI::IccAbsTimeI_C	2	Exit	
32F4	IccTask::IccTask_C	2	Entry	
32F4	IccTask::IccTask_C	2	Exit	
32F5	IccTask::IccTask_D	2	Entry	
32F5	IccTask::IccTask_D	2	Exit	
32F6	IccUser::IccUser_C	2	Entry	1 id.traceData() 2 &gid
32F6	IccUser::IccUser_C	2	Exit	1 id.traceData() 2 &gid
32F7	IccUser::IccUser_C1	2	Entry	1 userName 2 groupName
32F7	IccUser::IccUser_C1	2	Exit	1 userName 2 groupName
32F8	IccUser::IccUser_D	2	Entry	
32F8	IccUser::IccUser_D	2	Exit	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
32F9	IccAbendDataI::IccAbendDataI_C	2	Entry	1 &p2
32F9	IccAbendDataI::IccAbendDataI_C	2	Exit	1 &p2
32FA	IccAbendDataI::IccAbendDataI_D	2	Entry	
32FA	IccAbendDataI::IccAbendDataI_D	2	Exit	
32FB	IccIdI::IccIdI_C	2	Entry	1 resName 2 &fieldLength
32FB	IccIdI::IccIdI_C	2	Exit	1 resName 2 &fieldLength
32FC	IccIdI::IccIdI_C1	2	Entry	1 &resNum 2 &fieldLength
32FC	IccIdI::IccIdI_C1	2	Exit	1 &resNum 2 &fieldLength
32FD	IccIdI::IccIdI_C2	2	Entry	1 &resNum 2 &fieldLength
32FD	IccIdI::IccIdI_C2	2	Exit	1 &resNum 2 &fieldLength
32FE	IccIdI::IccIdI_C3	2	Entry	1 id.traceData()
32FE	IccIdI::IccIdI_C3	2	Exit	1 id.traceData()
32FF	IccBaseI::IccBaseI_C	2	Entry	1 &type 2 &pEObj
32FF	IccBaseI::IccBaseI_C	2	Exit	1 &type 2 &pEObj
3300	IccBaseI::IccBaseI_D	2	Entry	
3300	IccBaseI::IccBaseI_D	2	Exit	
3301	IccBufI::IccBufI_C	2	Entry	1 &length 2 pData 3 &type 4 &owner 5 &p
3301	IccBufI::IccBufI_C	2	Exit	1 &length 2 pData 3 &type 4 &owner 5 &p
3302	IccBufI::IccBufI_D	2	Entry	

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3302	IccBufI::IccBufI_D	2	Exit	
3304	IccControll::IccControll_C	2	Entry	
3304	IccControll::IccControll_C	2	Exit	
3305	IccControll::IccControll_D	2	Entry	
3305	IccControll::IccControll_D	2	Exit	
3306	IccControllIG::IccControllIG_C	2	Entry	
3306	IccControllIG::IccControllIG_C	2	Exit	
3307	IccEventI::IccEventI_C	2	Entry	
3307	IccEventI::IccEventI_C	2	Exit	
3308	IccEventI::IccEventI_D	2	Entry	
3308	IccEventI::IccEventI_D	2	Exit	
330A	IccFileI::IccFileI_C	2	Entry	1 &p 2 &p2
330A	IccFileI::IccFileI_C	2	Exit	1 &ivpSPData
330B	IccFileI::IccFileI_D	2	Entry	
330B	IccFileI::IccFileI_D	2	Exit	
330C	IccMessageI::IccMessageI_D	2	Entry	
330C	IccMessageI::IccMessageI_D	2	Exit	
330D	IccRecordIndexI::IccRecordIndexI_C	2	Entry	
330D	IccRecordIndexI::IccRecordIndexI_C	2	Exit	
330E	IccRecordIndexI::IccRecordIndexI_D	2	Entry	
330E	IccRecordIndexI::IccRecordIndexI_D	2	Exit	
330F	IccResourceI::IccResourceI_C	2	Entry	1 &p 2 &p2
330F	IccResourceI::IccResourceI_C	2	Exit	1 &p 2 &p2
3310	IccResourceI::IccResourceI_D	2	Entry	
3310	IccResourceI::IccResourceI_D	2	Exit	
3311	IccResourceIdI::IccResourceIdI_C	2	Entry	1 &type
3311	IccResourceIdI::IccResourceIdI_C	2	Exit	1 &type
3312	IccResourceIdI::IccResourceIdI_D	2	Entry	
3312	IccResourceIdI::IccResourceIdI_D	2	Exit	
3316	IccSystemI::IccSystemI_C	2	Entry	
3316	IccSystemI::IccSystemI_C	2	Exit	
3317	IccException::number	2	Entry	
3317	IccException::number	2	Exit	1 &ivpI->ivNumber

Table 68. C++ foundation classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3317	IccMessage::number	2	Entry	
3317	IccMessage::number	2	Exit	1 &ret
3317	IccRBA::number	2	Entry	
3317	IccRBA::number	2	Exit	1 &ivpI->ivNumber
3317	IccJournalId::number	2	Entry	
3317	IccJournalId::number	2	Exit	1 &ivpIR->ivNumber
3317	IccSystemI::IccSystemI_D	2	Entry	
3317	IccSystemI::IccSystemI_D	2	Exit	
3317	IccTask::number	2	Entry	
3317	IccTask::number	2	Exit	1 &ivpI->ivTaskNumber

Table 69. Java native method entries

Method ID	Class_Method	Lvl	Type	Data
3029	DTCSupport_UpdateState	1	Entry	
3029	DTCSupport_UpdateState	1	Exit	
30E8	DTCSupport_UpdatePFState	1	Entry	
30E8	DTCSupport_UpdatePFState	1	Exit	
3197	Wrapper_GetCommArea	1	Entry	1 envp
3197	Wrapper_GetCommArea	2	Info	
3197	Wrapper_GetCommArea	Exc	Error	
3197	Wrapper_GetCommArea	Exc	Error0	
3197	Wrapper_GetCommArea	1	Exit	
3198	Wrapper_SetCommArea	1	Entry	1 envp
3198	Wrapper_SetCommArea	1	Exit	
3199	Wrapper_SetAbend	1	Entry	1 envp
3199	Wrapper_SetAbend	1	Info	1 AbcodeString
319A	Wrapper_SetAbendForCondition	1	Entry	1 envp
319A	Wrapper_SetAbendForCondition	1	Exit	
319B	AttachInitiator_ALLOCATE	1	Entry	1 envp
319B	AttachInitiator_ALLOCATE	1	Exit	1 envp
319C	AttachInitiator_CONNECT_1PROCESS	1	Entry	1 envp

Table 69. Java native method entries (continued)

Method ID	Class_Method	Lvl	Type	Data
319C	AttachInitiator_CONNECT_1PROCESS	1	Error0	1 Rc
319C	AttachInitiator_CONNECT_1PROCESS	1	Exit	1 envp
319D	Conversation_SEND	1	Entry	1 envp
319D	Conversation_SEND	1	Exit	1 envp
319E	Conversation_RECEIVE	1	Entry	1 envp
319E	Conversation_RECEIVE	1	Info	1 State
319E	Conversation_RECEIVE	1	Exit	1 &envp 2 &newState
319F	Conversation_CONVERSE	1	Entry	1 envp
319F	Conversation_CONVERSE	1	Exit	1 envp
31A0	Conversation_FREE	1	Entry	1 envp
31A0	Conversation_FREE	1	Exit	1 envp
31A1	Conversation_ISSUE_1CONTROL	1	Entry	1 envp
31A1	Conversation_ISSUE_1CONTROL	1	Exit	1 envp
31A2	DTCABEND_ABCODE	1	Entry	1 envp
31A2	DTCABEND_ABCODE	1	Exit	1 envp
31A3	DTCCCondition_getResponseCode	1	Entry	1 envp
31A3	DTCCCondition_getResponseCode	1	Exit	1 envp
31A4	DTCFile_DELETE_1KSDS	1	Entry	1 envp
31A4	DTCFile_DELETE_1KSDS	1	Exit	1 envp
31A5	DTCFile_DELETE_1RRDS	1	Entry	1 envp
31A5	DTCFile_DELETE_1RRDS	1	Exit	1 envp
31A6	DTCFile_DELETE_1ESDS	1	Entry	1 envp
31A6	DTCFile_DELETE_1ESDS	1	Exit	1 envp

Table 69. Java native method entries (continued)

Method ID	Class_Method	Lvl	Type	Data
31A7	DTCFile_READ_1Keyed	1	Entry	1 envp
31A7	DTCFile_READ_1Keyed	1	Exit	1 envp
31A8	DTCFile_READ_1RRDS	1	Entry	1 envp
31A8	DTCFile_READ_1RRDS	1	Exit	1 envp
31A9	DTCFile_REWRITE	1	Entry	1 envp
31A9	DTCFile_REWRITE	1	Exit	1 envp
31AA	DTCFile_UNLOCK	1	Entry	1 envp
31AA	DTCFile_UNLOCK	1	Exit	1 envp
31AB	DTCFile_WRITE_1ESDS	1	Entry	1 envp
31AB	DTCFile_WRITE_1ESDS	1	Exit	1 envp
31AC	DTCFile_WRITE_1KSDS	1	Entry	1 envp
31AC	DTCFile_WRITE_1KSDS	1	Exit	1 envp
31AD	DTCFile_WRITE_1RRDS	1	Entry	1 envp
31AD	DTCFile_WRITE_1RRDS	1	Exit	1 envp
31AE	STARTBR_RESETBR_ESDS	1	Entry	1 envp
31AE	STARTBR_RESETBR_ESDS	1	Exit	1 envp
31AF	DTCFile_STARTBR_1ESDS	1	Entry	1 envp
31AF	DTCFile_STARTBR_1ESDS	1	Exit	1 envp
31B0	STARTBR_RESETBR_Keyed	1	Entry	1 envp
31B0	STARTBR_RESETBR_Keyed	1	Exit	1 envp
31B1	DTCFile_STARTBR_1Keyed	1	Entry	1 envp
31B1	DTCFile_STARTBR_1Keyed	1	Exit	1 envp
31B2	STARTBR_RESETBR_RRDS	1	Entry	1 envp

Table 69. Java native method entries (continued)

Method ID	Class_Method	Lvl	Type	Data
31B2	STARTBR_RESETBR_RRDS	1	Exit	1 envp
31B3	DTCFile_STARTBR_1RRDS	1	Entry	1 envp
31B3	DTCFile_STARTBR_1RRDS	1	Exit	1 envp
31B4	READNORP_ESDS	1	Entry	1 envp
31B4	READNORP_ESDS	1	Exit	1 envp
31B5	DTCFile_READNEXT_1ESDS	1	Entry	1 envp
31B5	DTCFile_READNEXT_1ESDS	1	Exit	1 envp
31B6	READNORP_1Keyed	1	Entry	1 envp
31B6	READNORP_1Keyed	1	Exit	1 envp
31B7	DTCFile_READNEXT_1Keyed	1	Entry	1 envp
31B7	DTCFile_READNEXT_1Keyed	1	Exit	1 envp
31B8	READNORP_RRDS	1	Entry	1 envp
31B8	READNORP_RRDS	1	Exit	1 envp
31B9	DTCFile_READNEXT_1RRDS	1	Entry	1 envp
31B9	DTCFile_READNEXT_1RRDS	1	Exit	1 envp
31BA	DTCFile_READPREV_1ESDS	1	Entry	1 envp
31BB	DTCFile_READPREV_1Keyed	1	Entry	1 envp
31BB	DTCFile_READPREV_1Keyed	1	Exit	1 envp
31BC	DTCFile_READPREV_1RRDS	1	Exit	1 envp
31BC	DTCFile_READPREV_1RRDS	1	Entry	1 envp
31BC	DTCFile_READPREV_1RRDS	1	Exit	1 envp
31BD	DTCFile_RESETBR_1ESDS	1	Entry	1 envp
31BD	DTCFile_RESETBR_1ESDS	1	Exit	1 envp

Table 69. Java native method entries (continued)

Method ID	Class_Method	Lvl	Type	Data
31BE	DTCFile_RESETBR_1Keyed	1	Entry	1 envp
31BE	DTCFile_RESETBR_1Keyed	1	Exit	1 envp
31BF	DTCFile_RESETBR_1RRDS	1	Entry	1 envp
31BF	DTCFile_RESETBR_1RRDS	1	Exit	1 envp
31C0	DTCFile_ENDBR	1	Entry	1 envp
31C0	DTCFile_ENDBR	1	Exit	1 envp
31C1	DTC_Init	1	Entry	1 envp
31C1	DTC_Init	1	Exit	1 DTCP
31C2	DTCProgram_LINK	1	Entry	1 envp
31C2	DTCProgram_LINK	1	Exit	1 envp
31C3	DTCProgram_XCTL	1	Entry	1 envp
31C3	DTCProgram_XCTL	1	Exit	1 envp
31C4	DTCProgram_RETURN	1	Entry	1 envp
31C4	DTCProgram_RETURN	1	Exit	1 envp
31C5	DTCRegion_getRegionData	1	Entry	1 envp
31C5	DTCRegion_getRegionData	1	Exit	1 envp
31C6	ADDRESS_CWA	1	Entry	1 CWAlength
31C6	ADDRESS_CWA	1	Exit	1 CWAlength
31C7	DTCRegion_ADDRESS_1CWA	1	Entry	1 CWAP
31C7	DTCRegion_ADDRESS_1CWA	1	Exit	1 CWAP
31C8	DTCRegion_UPDATE_1CWA	1	Entry	1 envp
31C8	DTCRegion_UPDATE_1CWA	1	Exit	
31C9	DTCSupport_ThrowCicsCondition	1	Entry	1 2 ClassName Message
31C9	DTCSupport_ThrowCicsCondition	1	Exit	

Table 69. Java native method entries (continued)

Method ID	Class_Method	Lvl	Type	Data
31CA	DTCSupport_SetConversationPF	1	Entry	
31CA	DTCSupport_SetConversationPF	1	Exit	
31CB	DTCSupport_ExtractAttributes	1	Entry	
31CB	DTCSupport_ExtractAttributes	1	Exit	
31CC	DTCSupport_ExtractProcess	1	Entry	
31CC	DTCSupport_ExtractProcess	1	Exit	
31CD	DTCSupport_UpdateConversation	1	Entry	
31CD	DTCSupport_UpdateConversation	1	Exit	
31CE	DTCSupport_MapAbendToException	1	Entry	1 envp
31CE	DTCSupport_MapAbendToException	1	Exit	1 envp
31CF	DTCSupport_MapConditionToException	1	Entry	1 Resp
31CF	DTCSupport_MapConditionToException	1	Exit	
31D0	DTCSupport_ByteArrayAlloc	1	Entry	
31D0	DTCSupport_ByteArrayAlloc	1	Exit	
31D1	DTCSupport_MakeJavaString	1	Entry	1 C_String
31D1	DTCSupport_MakeJavaString	1	Exit	
31D2	DTCSupport_ThrowUnknownCicsError	1	Entry	1 Message
31D2	DTCSupport_ThrowUnknownCicsError	1	Exit	
31D3	DTCSupport_SetHolderValue	1	Entry	
31D3	DTCSupport_SetHolderValue	1	Exit	
31D4	DTCSupport_MakeConversation	1	Entry	1 convId 2 &state
31D4	DTCSupport_MakeConversation	1	Exit	
31D5	DTCSupport_MakeConversationPF	1	Entry	
31D5	DTCSupport_MakeConversationPF	1	Exit	
31D6	DTCSupport_MakeRetrievedData	1	Entry	
31D6	DTCSupport_MakeRetrievedData	1	Exit	
31D7	DTCTask_ProcessEIB	1	Entry	1 &envp 2 &TCA_EIB
31D7	DTCTask_ProcessEIB	1	Exit	
31D8	DTCTask_ProcessPrincipalFacility	1	Entry	
31D8	DTCTask_ProcessPrincipalFacility	1	Exit	
31D9	DTCTask_getCommonData	1	Entry	
31D9	DTCTask_getCommonData	1	Exit	
31DA	DTCTask_commitTask	1	Entry	
31DA	DTCTask_commitTask	1	Exit	

Table 69. Java native method entries (continued)

Method ID	Class_Method	Lvl	Type	Data
31DB	DTCTask_rollbackTask	1	Entry	
31DB	DTCTask_rollbackTask	1	Exit	
31DC	DTCTask_Abend	1	Entry	
31DC	DTCTask_Abend	1	Exit	
31DD	DTCTask_RETRIEVE	1	Entry	
31DD	DTCTask_RETRIEVE	1	Exit	
31DE	DTCTDQ_DELETE	1	Entry	
31DE	DTCTDQ_DELETE	1	Exit	
31DE	DTCTDQ_DELETE	1	Entry	
31DE	DTCTDQ_DELETE	1	Exit	
31E0	DTCTDQ_WRITE	1	Entry	
31E0	DTCTDQ_WRITE	1	Exit	
31E1	DTCTerminal_RECEIVE	1	Entry	
31E1	DTCTerminal_RECEIVE	1	Exit	
31E2	DTCTerminal_SEND	1	Entry	
31E2	DTCTerminal_SEND	1	Exit	
31E3	DTCTerminal_SEND_1CONTROL	1	Entry	
31E3	DTCTerminal_SEND_1CONTROL	1	Exit	
31E4	DTCTerminal_SEND_1TEXT	1	Entry	
31E4	DTCTerminal_SEND_1TEXT	1	Exit	
31E5	DTCTerminal_getCommonData	1	Entry	
31E5	DTCTerminal_getCommonData	1	Exit	
31E6	DTCTerminal_ADDRESS_1TCTUA	1	Entry	
31E6	DTCTerminal_ADDRESS_1TCTUA	1	Exit	
31E7	DTCTerminal_UPDATE_1TCTUA	1	Entry	
31E7	DTCTerminal_UPDATE_1TCTUA	1	Exit	
31E8	DTCTSQ_DELETE	1	Entry	
31E8	DTCTSQ_DELETE	1	Exit	
31E9	DTCTSQ_READITEM	1	Entry	
31E9	DTCTSQ_READITEM	1	Exit	
31E9	DTCTSQ_READITEM	1	Exit	
31EA	DTCTSQ_READNEXT	1	Entry	
31EB	DTCTSQ_WRITE	1	Entry	
31EB	DTCTSQ_WRITE	1	Exit	
31EC	DTCTSQ_REWRITE	1	Entry	
31EC	DTCTSQ_REWRITE	1	Exit	
31ED	StartRequest_CANCEL	1	Entry	
31ED	StartRequest_CANCEL	1	Exit	
31EE	StartRequest_START	1	Entry	
31EE	StartRequest_START	1	Exit	

Table 69. Java native method entries (continued)

Method ID	Class_Method	Lvl	Type	Data
31EF	SynchronizationResource_ENQUEUE	1	Entry	
31EF	SynchronizationResource_ENQUEUE	1	Exit	
31F0	SynchronizationResource_DEQUEUE	1	Entry	
31F0	SynchronizationResource_DEQUEUE	1	Entry	
31F1	DTCondition_RESP2	1	Info	1 Rc
3211	DTCTerminal_getUserId	1	Entry	
3211	DTCTerminal_getUserId	1	Exit	1 C_USERID
3320	Wrapper_GetTCBMode	1	Entry	1 envp
3320	Wrapper_GetTCBMode	1	Info	1 TCBmode
3320	Wrapper_GetTCBMode	1	Exit	1 envp
3321	DTCTask_JDBC_extCommit	1	Exit	
3321	DTCTask_JDBC_extCommit	1	Exit	
3322	DTCTask_JDBC_extRollback	1	Entry	
3322	DTCTask_JDBC_extRollback	1	Exit	

Table 70. Direct CICS classes

Method ID	Class_Method	Lvl	Type	Data
31F2	CDRInputStream_read_Object	Exc	Exception	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace()
31F5	CICSCommareaMapping_checkBytes	Exc	Error	3 commarea 4 commarea length, length of prefix
31F5	CICSCommareaMapping_checkBytes	Exc	Error0	3 commarea 4 commarea length, length in prefix
31F6	CICSCommareaMapping_setBytes	Exc	Exception	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace() 6 codepage
31F6	CICSCommareaMapping_setBytes	Exc	Error	3 commarea prefix 4 current version, version offset
31F6	CICSCommareaMapping_setBytes	Exc	Error0	3 commarea prefix 4 hostname length offset

Table 70. Direct CICS classes (continued)

Method ID	Class_Method	Lvl	Type	Data
31F8	CICSCommareaMapping_setIOPDataFromTSQ	1	Entry	3 tsqName 4 num items expected 5 data length expected
31F8	CICSCommareaMapping_setIOPDataFromTSQ	1	Exit	
31F8	CICSCommareaMapping_setIOPDataFromTSQ	Exc	Exception	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace()
31F8	CICSCommareaMapping_setIOPDataFromTSQ	Exc	Exception0	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace() 6 bytes read 7 bytes expected
31F8	CICSCommareaMapping_setIOPDataFromTSQ	Exc	Error	3 num items read 4 num items expected
31F8	CICSCommareaMapping_setIOPDataFromTSQ	Exc	Error0	3 bytes read 4 bytes expected
31F9	CICSCommareaMapping_writeIOPDataToTSQ	1	Entry	3 tsqName 4 data length
31F9	CICSCommareaMapping_writeIOPDataToTSQ	1	Exit	3 tsqName 4 num items written 5 data length written
31F9	CICSCommareaMapping_writeIOPDataToTSQ	Exc	Error	3 num items written 4 itemnum returned from writeq
31F9	CICSCommareaMapping_writeIOPDataToTSQ	Exc	Exception	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace()
31FA	CICSmain_main	1	Entry	
31FA	CICSmain_main	1	Exit	3 return commarea
31FA	CICSmain_main	2	Info	3 commarea prefix 4 IOP message
31FA	CICSmain_main	Exc	Exception	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace()
31FB	CICSmain_ProcessMessage	2	Entry	3 message type
31FB	CICSmain_ProcessMessage	2	Exit	3 message type 4 return code

Table 70. Direct CICS classes (continued)

Method ID	Class_Method	Lvl	Type	Data
31FB	CICSmain_ProcessMessage	Exc	Error	3 message type 4 return code
31FD	GenericServerSC_constructKey	Exc	Exception	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace() 6 codepage
31FF	GenericServerSC_dispatch	1	Entry	
31FF	GenericServerSC_dispatch	1	Exit	3 method
31FF	GenericServerSC_dispatch	1	Exit0	3 method 4 input type id string 5 result 1=true,0=false
31FF	GenericServerSC_dispatch	2	Info	3 method
31FF	GenericServerSC_dispatch	2	Info0	3-7 object's type_id strings
31FF	GenericServerSC_dispatch	2	Info1	3 method 4 no of params n, param offset in IIOP message 5 array of n (param type, direction)
31FF	GenericServerSC_dispatch	Exc	Error	
31FF	GenericServerSC_dispatch	Exc	Error0	3 method
31FF	GenericServerSC_dispatch	Exc	Error1	
31FF	GenericServerSC_dispatch	Exc	Exception Exception0	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace() 6 method
31FF	GenericServerSC_dispatch	Exc	Exception 1-7	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace()
3201	GenericServerSC_getServant	Exc	Exception	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace() 6 codepage
3201	GenericServerSC_getServant	Exc	Exception0	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace()
3200	GenericServerSC_locate	1	Info	3 classname 4 ex.toString()

Table 70. Direct CICS classes (continued)

Method ID	Class_Method	Lvl	Type	Data
3217	IOR_stringify	Exc	Exception	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace() 6 codepage
3202	NEOServerInvocation constructor	1	Entry	
3202	NEOServerInvocation constructor	1	Exit	3 classname
3202	NEOServerInvocation constructor	2	Info	3 classname
3202	NEOServerInvocation constructor	2	Info0	
3202	NEOServerInvocation constructor	Exc	Exception	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace() 6 classname
3203	NEOServerInvocation_init	Exc	Error	3 object key 4 object key type
3203	NEOServerInvocation_init	Exc	Exception	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace() 6 codepage
3209	ORB_iorToObjRef	Exc	Error	3 ior hostname 4 object key

Table 71. GenericFactory entries by method identifier

Method ID	Class_Method	Lvl	Type	Data
3210	_GenericFactoryImpl_create_object	1	Entry	3 classname
3210	_GenericFactoryImpl_create_object	1	Exit	3 java classname
3210	_GenericFactoryImpl_create_object	Exc	Exception Exception0	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace() 6 java classname

Table 72. JCICS java entries by method identifier

Method ID	Class_Method	Lvl	Type	Data
3218	Wrapper static initializer	1	Info	
3219	Wrapper_callUserClass	1	Entry	3 args[0]
3219	Wrapper_callUserClass	1	Exit	3 java classname

Table 72. JCICS java entries by method identifier (continued)

Method ID	Class_Method	Lvl	Type	Data
3219	Wrapper_callUserClass	2	Info	3 java classname
3219	Wrapper_callUserClass	2	Info0	3-7 args[0]-args[4]
3219	Wrapper_callUserClass	Exc	Exception	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace() 6 java classname
321A	Wrapper_checkRealException	Exc	Exception Exception0	3 ex.toString() 4 ex.getMessage() 5 ex.printStackTrace()
# 331C	Wrapper_JDBC_pre_reset	2	Entry	
# 331D	Wrapper_JDBC_post_reset	2	Exit	
# 331E	Wrapper_JDBC_pre_terminate	2	Entry	
# 331F	Wrapper_JDBC_post_terminate	2	Exit	

File control

Table 73. File control trace points

Point ID	Module	Lvl	Type	Data
AP 2300	DFHFCQS	FC 1	Entry	1 FCQS parameter list
AP 2301	DFHFCQS	FC 1	Exit	1 FCQS parameter list
AP 2302	DFHFCQS	Exc	Recovery	1 FCQS parameter list 2 Kernel error data
AP 2303	DFHFCQS	Exc	Invalid format	1 FCQS parameter list
AP 2304	DFHFCQS	Exc	Invalid function	1 FCQS parameter list
AP 2305	DFHFCQS	Exc	DFHFCQI call failure	1 FCQI parameter list
AP 2306	DFHFCQS	FC 2	Before wait	1 Timeout seconds
AP 2307	DFHFCQS	FC 2	After wakeup	
AP 2308	DFHFCQS	FC 2	Before quiesce issued	1 FCQSE
AP 2309	DFHFCQS	FC 2	Successful quiesce	1 FCQSE
AP 230A	DFHFCQS	Exc	Quiesce not possible	1 FCQSE
AP 230B	DFHFCQS	Exc	Quiesce cancelled	1 FCQSE
AP 230C	DFHFCQS	Exc	Quiesce timed out	1 FCQSE
AP 230D	DFHFCQS	Exc	Quiesce SMSVSAM server failure	1 FCQSE
AP 230E	DFHFCQS	Exc	Quiesce VSAM RLS i/o error	1 FCQSE

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data	
AP 230F	DFHFCQS	Exc	Quiesce dataset unknown	1	FCQSE
AP 2310	DFHFCQS	FC 2	Quiesce dataset migrated	1	FCQSE
AP 2315	DFHFCQS	FC 2	Before backup cancel issued	1	FCQSE
AP 2316	DFHFCQS	FC 2	Successful backup cancel	1	FCQSE
AP 2317	DFHFCQS	Exc	Backup cancel underway	1	FCQSE
AP 2318	DFHFCQS	Exc	Backup cancel SMSVSAM server failure	1	FCQSE
AP 2319	DFHFCQS	Exc	Backup cancel VSAM RLS i/o error	1	FCQSE
AP 2320	DFHFCQU	FC 1	Entry	1	FCQU parameter list
AP 2321	DFHFCQU	FC 1	Exit	1	FCQU parameter list
AP 2322	DFHFCQU	Exc	Recovery	1 2	FCQU parameter list Kernel error data
AP 2323	DFHFCQU	Exc	Invalid format	1	FCQU parameter list
AP 2324	DFHFCQU	Exc	Invalid function	1	FCQU parameter list
AP 2325	DFHFCQU	Exc	Invalid quiesce type	1	FCQU parameter list
AP 2326	DFHFCQU	Exc	DFHFCFS call failure	1 2	FCQU parameter list FCFS parameter list
AP 2327	DFHFCQU	Exc	DFHFCRR call failure	1 2	FCQU parameter list FCRR parameter list
AP 2328	DFHFCQU	Exc	DFHFCQI call failure	1 2	FCQU parameter list FCQI parameter list
AP 2329	DFHFCQU	Exc	DFHTM call failure	1 2	FCQU parameter list DFHTMP return code
AP 232A	DFHFCQU	FC 1	Quiesce suppressed by XFCVSDS	1	FCQU parameter list
AP 232B	DFHFCQU	FC 1	Backup suppressed by XFCVSDS	1	FCQU parameter list
AP 2330	DFHFCQR	FC 1	Entry	1	FCQR parameter list
AP 2331	DFHFCQR	FC 1	Exit	1	FCQR parameter list
AP 2332	DFHFCQR	Exc	Recovery	1 2	FCQR parameter list Kernel error data
AP 2333	DFHFCQR	Exc	Invalid format	1	FCQR parameter list
AP 2334	DFHFCQR	Exc	Invalid function	1	FCQR parameter list
AP 2335	DFHFCQR	Exc	DFHFCQU call failure	1	FCQU parameter list

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 2336	DFHFCQR	FC 2	Before wait	
AP 2337	DFHFCQR	FC 2	After wakeup	
AP 2338	DFHFCQR	Exc	Quiesce exit failure	1 Error FCQRE
AP 2339	DFHFCQR	FC 2	FCQRE received from quiesce exit	1 FCQRE
AP 233D	DFHFCQX	GTF	Entry	1 VSAM IFGQUIES
AP 233E	DFHFCQX	GTF	Exit	1 VSAM IFGQUIES 2 Quiesce exit retcode
AP 233F	DFHFCQX	GTF	STORAGE OBTAIN failure	1 VSAM IFGQUIES 2 STORAGE register 15
AP 2340	DFHFCQI	FC 1	Entry	1 FCQI parameter list
AP 2341	DFHFCQI	FC 1	Exit	1 FCQI parameter list
AP 2342	DFHFCQI	Exc	Recovery	1 FCQI parameter list 2 Kernel error data
AP 2343	DFHFCQI	Exc	Invalid format	1 FCQI parameter list
AP 2344	DFHFCQI	Exc	Invalid function	1 FCQI parameter list
AP 2345	DFHFCQI	Exc	Invalid quiesce	1 FCQI parameter list
AP 2346	DFHFCQI	Exc	DFHFCAT call failure	1 FCQI parameter list 2 FCAT parameter list
AP 2347	DFHFCQI	FC 2	Before suspend	1 FCQSE
AP 2348	DFHFCQI	FC 2	After suspend	1 FCQSE
AP 2349	DFHFCQI	FC 2	New FCQSE built	1 FCQSE
AP 234A	DFHFCQI	Exc	Quiesce complete VSAM RLS. i/o error	1 FCQI parameter list 2 FCCA parameter list
AP 234B	DFHFCQI	Exc	Quiesce complete SMSVSAM server failure	1 FCQI parameter list 2 FCCA parameter list
AP 234E	DFHFCQT	FC 1	Entry	1 Transid
AP 234F	DFHFCQT	FC 1	Exit	1 Transid
AP 2350	DFHFCLF	FC 1	Entry	1 LGGL parameter list
AP 2351	DFHFCLF	FC 1	Exit	1 LGGL parameter list
AP 2352	DFHFCLF	Exc	Invalid format	1 Supplied parameter list
AP 2353	DFHFCLF	Exc	Invalid function	1 LGGL parameter list

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 2354	DFHFCLF	Exc	Recovery routine	1 LGGL parameter list 2 Kernel error data
AP 2357	DFHFCLF	Exc	Invalid component supplied	1 LGGL parameter list
AP 2358	DFHFCLF	Exc	Invalid general log error type supplied	1 LGGL parameter list
AP 2359	DFHFCLF	Exc	Invalid user token supplied	1 LGGL parameter list
AP 235A	DFHFCLF	Exc	Set dataset unavailable error	1 LGGL parameter list 2 FCDN parameter list
AP 235B	DFHFCLF	Exc	Initiate RLS quiesce error	1 LGGL parameter list 2 FCQI parameter list
AP 235C	DFHFCLF	Exc	Close down non-RLS dataset error	1 LGGL parameter list 2 FCQU parameter list
AP 235D	DFHFCLF	Exc	Close file error	1 LGGL parameter list 2 FCFS parameter list
AP 235E	DFHFCLF	Exc	Invalid DSNB	1 LGGL parameter list
AP 2360	DFHFCDRD	FC 1	Entry	None
AP 2361	DFHFCDRD	FC 1	Exit	None
AP 2362	DFHFCDRD	Exc	DFHFCCA call failed	1 DFHFCCA parameter list
AP 2370	DFHFCCAT	Exc	I/O error from IGWARLS call	1 FCAT parameter list 2 Return code 3 Reason code 4 Prob determination
AP 2371	DFHFCCAT	Exc	Not VSAM base (BDAM or VSAM path)	1 FCAT parameter list
AP 2373	DFHFCCAT	Exc	Set availability I/O error	1 FCAT parameter list 2 Return code 3 Reason code 3 Prob determination
AP 2374	DFHFCCAT	FC 2	Before IGWARLS call	1 IGWARLS parameter list
AP 2375	DFHFCCAT	FC 2	After IGWARLS call	IGWARLS parameter list
AP 2376	DFHFCCAT	FC 2	Before IDARRST call	1 IFGRETNS parameter list
AP 2377	DFHFCCAT	FC 2	After IDARRST call	1 IFGRETNS parameter list
AP 2378	DFHFCCAT	FC 2	Before IDARREND call	1 IFGRETNS parameter list
AP 2379	DFHFCCAT	FC 2	After IDARREND call	1 IFGRETNS parameter list
AP 237A	DFHFCCAT	Exc	Showcat error	1 FCAT parameter list 2 Return code
AP 237B	DFHFCCAT	Exc	assoc_not_found	1 FCAT parameter list

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data	
AP 237C	DFHFCAT	Exc	showcat_aix_error	1	Return code
				2	FCAT parameter list
AP 237D	DFHFCAT	Exc	unknown_path_type	1	Path type
				2	FCAT parameter list
AP 237E	DFHFCAT	Exc	Locate error	1	FCAT parameter list
				2	Return code
AP 2380	DFHFCFL	FC 1	Entry	1	FCFL parameter list
AP 2381	DFHFCFL	FC 1	Exit	1	FCFL parameter list
AP 2382	DFHFCFL	Exc	Recovery	1	FCFL parameter list
AP 2383	DFHFCFL	Exc	Invalid format	1	FCFL parameter list
AP 2384	DFHFCFL	Exc	Invalid function	1	FCFL parameter list
AP 2385	DFHFCFL	Exc	Remove failure	1	FCFL parameter list
				2	RMRE parameter list
AP 2386	DFHFCFL	Exc	Resource not found	1	FCFL parameter list
				2	FCRR parameter list
AP 2387	DFHFCFL	Exc	Invalid browse token	1	FCFL parameter list
AP 2390	DFHFCDN	Exc	VSAM catalog_error	1	FCDN parameter list
				2	FCAT parameter list
AP 2396	DFHFCAT	FC 2	Showcat before	1	FCAT parameter list
AP 2397	DFHFCAT	FC 2	Showcat after	1	FCAT parm list
				2	SHOWCAT
AP 2398	DFHFCAT	FC 2	Showcat aix before	1	FCAT parameter list
AP 2399	DFHFCAT	FC 2	Showcat aix after	1	FCAT parm list
				2	SHOWCAT
AP 239A	DFHFCAT	FC 2	Locate before	1	FCAT parameter list
AP 239B	DFHFCAT	FC 2	Locate after	1	FCAT parameter list
AP 239C	DFHFCAT	FC 2	Before locate to see if dataset migrated	1	FCAT parameter list
AP 239D	DFHFCAT	FC 2	After locate to see if dataset migrated	1	FCAT parameter list
AP 23A0	DFHFCRR	FC 1	Entry	1	FCRR parameter list
AP 23A1	DFHFCRR	FC 1	Exit	1	FCRR parameter list
AP 23A2	DFHFCRR	Exc	Invalid function	1	FCRR parameter list
AP 23A3	DFHFCRR	Exc	Invalid format	1	Supplied parameter list

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data	
AP 23A4	DFHFCRR	Exc	Recovery routine	1	FCRR parameter list
				2	Kernel error data
AP 23A5	DFHFCRR	Exc	Purged	1	FCRR parameter list
AP 23A6	DFHFCRR	Exc	Disaster detected	1	FCRR parameter list
				2	FCRR parameter list
AP 23A8	DFHFCRR	Exc	Table manager locate DSNB error	1	Table manager return code
				2	FCRR parameter list
AP 23A9	DFHFCRR	Exc	Table manager unlock DSNB error	1	Table manager return code
				2	FCRR parameter list
AP 23AA	DFHFCRR	Exc	Invalid resource type	1	FCRR parameter list
AP 23AB	DFHFCRR	Exc	Invalid restart type	1	FCRR parameter list
AP 23AC	DFHFCRR	Exc	Drain RLS error	1	FCRR parameter list
				2	FCCA parameter list
AP 23AD	DFHFCRR	Exc	Register RLS control ACB error	1	FCRR parameter list
				2	FCCA parameter list
AP 23AE	DFHFCRR	Exc	Cold start RLS error	1	FCRR parameter list
				2	FCCA parameter list
AP 23AF	DFHFCRR	Exc	Inquire on recovery error	1	FCRR parameter list
				2	FCCA parameter list
AP 23B0	DFHFCRR	Exc	Lost locks complete error	1	FCRR parameter list
				2	FCCA parameter list
AP 23B1	DFHFCRR	Exc	Orphan locks release error	1	FCRR parameter list
				2	FCCA parameter list
AP 23B2	DFHFCRR	Exc	Transaction purge error	1	FCRR parameter list
				2	FCCA parameter list
AP 23B3	DFHFCRR	Exc	Transaction attach error	1	FCRR parameter list
				2	XMAT parameter list
AP 23B4	DFHFCRR	Exc	Open failure on offsite recovery	1	FCRR parameter list
				2	FCFS parameter list
AP 23C0	DFHFCRS	Exc	First trace entry after deadlock	1	VSAM IFGVPDI header
AP 23C1	DFHFCRS	Exc	Second trace entry after deadlock	1	IFGVPDII #1
				2	IFGVPDII #2 (if present)
				3	IFGVPDII #3 (if present)
				4	IFGVPDII #4 (if present)
				5	IFGVPDII #5 (if present)
				6	IFGVPDII #6 (if present)
				7	IFGVPDII #7 (if present)

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 23C2	DFHFCRS	Exc	First trace entry after timeout	1 VSAM IFGVDPDI header 2 Kernel error data
AP 23C3	DFHFCRS	Exc	Second trace entry after timeout	1 IFGVDPDI #1 2 IFGVDPDI #2 (if present) 3 IFGVDPDI #3 (if present) 4 IFGVDPDI #4 (if present) 5 IFGVDPDI #5 (if present) 6 IFGVDPDI #6 (if present) 7 IFGVDPDI #7 (if present)
AP 23C4	DFHFCRS	Exc	Locked record	1 VSAM IFGVDPDI header 2 VSAM IFGVDPDI
AP 23C5	DFHFCRS	Exc	No VPDI from VSAM	1 None
AP 23E0	DFHFCOR	FC 1	Entry	None
AP 23E1	DFHFCOR	FC 1	Exit	None
AP 23E2	DFHFCOR	Exc	Error issuing message	1 MEME parameter list
AP 2400	DFHFCRO	FC 2	Before GENCB issued on file open	1 Macro (GENCB) 2 ACB address 3 ACB
AP 2401	DFHFCRO	FC 2	After GENCB issued on file open	1 Macro (GENCB) 2 ACB address 3 ACB
AP 2402	DFHFCRO	Exc	Error from GENCB on file open	1 Macro (GENCB) 2 R15 return code 3 ACB address 4 ACB
AP 2403	DFHFCRO	FC 2	Before IGWARLS call on file open	1 IGWARLS area
AP 2404	DFHFCRO	FC 2	After IGWARLS call on file open	1 IGWARLS area
AP 2405	DFHFCRO	Exc	Error from IGWARLS call on file open	1 IGWARLS area (contains return code)
AP 2406	DFHFCRO	FC 2	Before OPEN call to VSAM on file open	1 Macro (OPEN) 2 ACB address 3 ACB
AP 2407	DFHFCRO	FC 2	After OPEN call to VSAM on file open	1 Macro (OPEN) 2 ACB address 3 ACB
AP 2408	DFHFCRO	Exc	Error from OPEN call to VSAM	1 Macro (OPEN) 2 ACB address 3 ACB (contains return code)
AP 2409	DFHFCRO	FC 2	Before OPEN SHOWCB	1 Macro (SHOWCB) 2 ACB address 3 ACB

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 240A	DFHFCRO	FC 2	After OPEN SHOWCB	1 Macro (SHOWCB) 2 OPEN return code 3 ACB address 4 ACB
AP 240B	DFHFCRO	Exc	Error from OPEN SHOWCB	1 Macro (SHOWCB) 2 R0 return code 3 ACB address 4 ACB
AP 240C	DFHFCRO	Exc	Disaster from OPEN SHOWCB	1 None
AP 240D	DFHFCRO	FC 2	Before OPEN SHOWCB for data EXCPs	1 Macro (SHOWCB) 2 ACB address 3 ACB
AP 240E	DFHFCRO	FC 2	After OPEN SHOWCB for data EXCPs	1 Macro (SHOWCB) 2 Data EXCP count 3 ACB address 4 ACB
AP 2410	DFHFCRO	FC 2	Before OPEN SHOWCB for index EXCPs	1 Macro (SHOWCB) 2 ACB address 3 ACB
AP 2411	DFHFCRO	FC 2	After OPEN SHOWCB for index EXCPs	1 Macro (SHOWCB) 2 Index EXCP count 3 ACB address 4 ACB
AP 2413	DFHFCRO	FC 2	Before OPEN SHOWCB for key details	1 Macro (SHOWCB) 2 ACB address 3 ACB
AP 2414	DFHFCRO	FC 2	After OPEN SHOWCB for index EXCPs	1 Macro (SHOWCB) 2 Key details 3 ACB address 4 ACB
AP 2416	DFHFCRO	FC 2	Before CLOSE call to VSAM	1 Macro (CLOSE) 2 ACB address 3 ACB
AP 2417	DFHFCRO	FC 2	After CLOSE call to VSAM	1 Macro (CLOSE) 2 ACB address 3 ACB
AP 2418	DFHFCRO	Exc	Error from CLOSE call to VSAM	1 Macro (CLOSE) 2 ACB address 3 ACB (contains return code)
AP 2419	DFHFCRO	FC 2	Before CLOSE SHOWCB	1 Macro (SHOWCB) 2 ACB address 3 ACB

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 241A	DFHFCRO	FC 2	After CLOSE SHOWCB	1 Macro (SHOWCB) 2 CLOSE return code 3 ACB address 4 ACB
AP 241B	DFHFCRO	Exc	Error from OPEN SHOWCB	1 Macro (SHOWCB) 2 R0 return code 3 ACB address 4 ACB
AP 241C	DFHFCRO	Exc	Disaster from CLOSE SHOWCB	1 None
AP 241D	DFHFCRO	FC 2	Before CLOSE SHOWCB for data EXCPs	1 Macro (SHOWCB) 2 ACB address 3 ACB
AP 241E	DFHFCRO	FC 2	After CLOSE SHOWCB for data EXCPs	1 Macro (SHOWCB) 2 Data EXCP count 3 ACB address 4 ACB
AP 2420	DFHFCRO	FC 2	Before CLOSE SHOWCB for index EXCPs	1 Macro (SHOWCB) 2 ACB address 3 ACB
AP 2421	DFHFCRO	FC 2	After CLOSE SHOWCB for index EXCPs	1 Macro (SHOWCB) 2 Index EXCP count 3 ACB address 4 ACB
AP 2423	DFHFCRO	Exc	SVC 26 base cluster error	1 Macro (SVC 26) 2 Catalog parameter list 3 Address of field parameter list for data set name 4 ACB address 5 ACB
AP 2424	DFHFCRO	Exc	SVC 26 data entry error	1 Macro (SVC 26) 2 Catalog parameter list 3 Address of field parameter list for key details 4 Address of field parameter list for high RBA 5 Address of field parameter list for share options 6 ACB address 7 ACB
AP 2425	DFHFCRO	Exc	Error from SHOWCAT on file open for object data set name	1 Macro (SHOWCAT) 2 SHOWCAT parameter list 3 R15 return code 4 ACB address 5 ACB

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 2426	DFHFCRO	Exc	Error from SHOWCAT on file open for base cluster entry	1 Macro (SHOWCAT) 2 SHOWCAT parameter list 3 R15 return code 4 ACB address 5 ACB
AP 2427	DFHFCRO	Exc	Error from SHOWCAT on file open for AIX [®] details	1 Macro (SHOWCAT) 2 SHOWCAT parameter list 3 R15 return code 4 ACB address 5 ACB
AP 2428	DFHFCRO	Exc	Unrecognized catalog record	1 Macro (SHOWCAT) 2 ACB address 3 ACB
AP 2429	DFHFCRO	Exc	Unrecognized catalog record	1 Macro (SHOWCAT) 2 ACB address 3 ACB
AP 242A	DFHFCRO	Exc	Unrecognized catalog record	1 Macro (SHOWCAT) 2 ACB address 3 ACB
AP 2430	DFHFCN	FC 2	Before IGWARLS call on file open	1 IGWARLS area
AP 2431	DFHFCN	FC 2	After IGWARLS call on file open	1 IGWARLS area
AP 2432	DFHFCN	Exc	Error from IGWARLS call on file open	1 IGWARLS area (contains return code)
AP 2433	DFHFCDO	Exc	Failure on XMAT attach	1 FCFS parameter list 2 XMAT parameter list
AP 243D	DFHFCDO	FC 2	Before re-open	1 FCCT parameter list 2 CFDT pool name 3 DFHFCDO's wait exit EP address
AP 243E	DFHFCDO	FC 2	After re-open	1 FCCT parameter list 2 CFDT pool name 3 R15 return code
AP 243F	DFHFCDO	Exc	Error on re-open	1 FCFS or FCDS parameter list 2 FCCT parameter list
AP 2440	DFHFCDO	FC 2	Entry	1 FCFS or FCDS parameter list
AP 2441	DFHFCDO	FC 2	Exit	1 FCFS or FCDS parameter list
AP 2442	DFHFCDO	Exc	Invalid Format	1 Input parameter list
AP 2443	DFHFCDO	Exc	Recovery routine entered	1 FCFS or FCDS parameter list
AP 2444	DFHFCDO	Exc	Disaster	1 FCFS or FCDS parameter list

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data	
AP 2445	DFHFCDO	Exc	Purged	1	FCFS or FCDS parameter list
AP 2446	DFHFCDO	FC 2	Before connect to CFDT server	1	Pool name
				2	MaxReqs limit
				3	Wait exit stub EP address
AP 2447	DFHFCDO	FC 2	After connect to CFDT server	1	CFDT pool name
				2	Connection token
				3	Server token
				4	R15 return code
				5	R0 reason code (if connect failed)
AP 2448	DFHFCDO	FC 2	Before disconnect from CFDT server	1	Connection token
				2	CFDT pool name
AP 2449	DFHFCDO	FC 2	After disconnect from CFDT server	1	CFDT pool name
				2	R15 return code
AP 244A	DFHFCDO	FC 2	Before Query Server Instance	1	CFDT pool name
AP 244B	DFHFCDO	FC 2	After Query Server Instance	1	CFDT pool name
				2	Server instance token
				3	R15 return code
				4	R0 reason code
				5	R1 server token
AP 244C	DFHFCDO	FC 2	Before CFDT server call	1	FCCT parameter list
				2	CFDT pool name
				3	DFHFCDO's wait exit EP addr
AP 244D	DFHFCDO	FC 2	After CFDT server call	1	FCCT parameter list
				2	CFDT pool name
				3	R15 return code
AP 244E	DFHFCDO	Exc	Error on connect to CFDT server	1	CFDT pool name
				2	R15 return code
				3	R0 reason code
AP 244F	DFHFCDO	Exc	Error on disconnect from CFDT server	1	CFDT pool name
				2	Connection token
				3	R15 return code
AP 2450	DFHFCDO	Exc	CFDT OPEN error	1	FCCT parameter list
				2	R15 return code
				3	R0 reason code
AP 2451	DFHFCDO	Exc	CFDT CLOSE error	1	FCCT parameter list
				2	R15 return code
				3	R0 reason code
AP 2452	DFHFCDO	Exc	CFDT statistics error	1	FCCT parameter list
				2	R15 return code
				3	R0 reason code

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 2453	DFHFCDO	Exc	CFDT server error	1 FCCT parameter list 2 R15 return code 3 R0 reason code
AP 2454	DFHFCDO	Exc	CFDT SET error	1 FCCT parameter list 2 R15 return code 3 R0 reason code
AP 2455	DFHFCDO	FC 2	Entry to FCDO's wait exit	1 FCCT parameter list
AP 2456	DFHFCDO	FC 2	Exit from FCDO's wait exit	1 FCCT parameter list
AP 2457	DFHFCDO	FC 2	Before attach of load transaction	1 FCFS parameter list
AP 2458	DFHFCDO	FC 2	After attach of load transaction	None
AP 2459	DFHFCDO	Exc	CFDT INQUIRE error	1 FCCT parameter list 2 R15 return code 3 R0 reason code
AP 245A	DFHFCDO	FC 2	Before MaxReqs wait	1 CFDT pool name 2 FCPW (pool wait element)
AP 245B	DFHFCDO	FC 2	After MaxReqs wait	1 CFDT pool name 2 FCPW (pool wait element)
AP 245C	DFHFCDO	Exc	Error on MaxReqs wait	1 FCFS or FCDS parameter list 2 DSSR parameter list
AP 245D	DFHFCDO	Exc	Pool resynchronization error	1 FCFS or FCDS parameter list 2 FCDY parameter list
AP 245E	DFHFCDO	Exc	LMLM call failed	1 FCFS or FCDS parameter list 2 LMLM parameter list
AP 245F	DFHFCDO	Exc	Pool resynchronization retry failed	1 FCFS parameter list 2 FCDY parameter list
AP 248A	DFHFCDL	FC 2	Entry	1 FCFS parameter list
AP 248B	DFHFCDL	FC 2	Exit	None
AP 2460	DFHFCDR	FC 2	Entry	1 FCFR parameter list 2 Filename (if appropriate)
AP 2461	DFHFCDR	FC 2	Exit	1 FCFR parameter list 2 Filename (if appropriate)
AP 2462	DFHFCDR	Exc	Recovery routine entered	1 FCFR parameter list 2 Kernel error data
AP 2463	DFHFCDR	Exc	Purged	1 FCFR parameter list
AP 2464	DFHFCDR	FC 2	Before CFDT server call	1 FCCR parameter list 2 CFDT pool name 3 # of free locking request slots 4 FCDR's wait exit EP addr

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 2465	DFHFCDR	FC 2	After CFDT server call	1 FCCR parameter list 2 CFDT pool name 3 Server R15 return code
AP 2466	DFHFCDR	FC 2	Entry to FCDR's wait exit	1 FCCR or FCCT parameter list 2 Wait ECB address
AP 2467	DFHFCDR	FC 2	Exit from FCDR's wait exit	1 FCCR or FCCT parameter list 2 R15 return code from wait exit
AP 2468	DFHFCDR	Exc	CFDT server call failed	1 FCFR parameter list 2 FCCR parameter list
AP 2469	DFHFCDR	Exc	DSSR call failed	1 FCFR parameter list
AP 246A	DFHFCDR	Exc	XDTRD returned invalid record length	1 Record length returned by user exit
AP 246B	DFHFCDR	FC 2	Before Query Server Instance	1 CFDT pool name
AP 246C	DFHFCDR	FC 2	After Query Server Instance	1 CFDT pool name 2 Server instance token 3 R15 return code 4 R0 reason code 5 R1 server token
AP 246D	DFHFCDR	FC 2	Before connect to CFDT server	1 Pool name 2 MaxReqs limit 3 Wait exit stub EP addr
AP 246E	DFHFCDR	FC 2	After connect to CFDT server	1 CFDT pool name 2 Connection token 3 Server token 4 R15 return code 5 R0 reason code (if connect failed)
AP 246F	DFHFCDR	Exc	Error on connect to CFDT server	1 CFDT pool name 2 R15 return code 3 R0 reason code
AP 2470	DFHFCDR	FC 2	Before disconnect from CFDT server	1 Connection token 2 CFDT pool name
AP 2471	DFHFCDR	FC 2	After disconnect from CFDT server	1 CFDT pool name 2 R15 return code
AP 2472	DFHFCDR	Exc	Error on disconnect from CFDT server	1 CFDT pool name 2 Connection token 3 R15 return code
AP 2473	DFHFCDR	FC 2	Before re-open	1 FCCT parameter list 2 CFDT pool name 3 FCDR's wait exit EP addr

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 2474	DFHFCDR	FC 2	After re-open	1 FCCT parameter list 2 CFDT pool name 3 Server R15 return code
AP 2475	DFHFCDR	Exc	Error on re-open	1 FCFR parameter list 2 FCCT parameter list
AP 2476	DFHFCDR	FC 2	Before MaxReqs wait	1 CFDT pool name 2 FCPW (pool wait element)
AP 2477	DFHFCDR	FC 2	After MaxReqs wait	1 CFDT pool name 2 FCPW (pool wait element)
AP 2478	DFHFCDR	Exc	Error on MaxReqs wait	1 FCFR parameter list 2 DSSR parameter list
AP 2479	DFHFCDR	Exc	Pool resynchronization error	1 FCFR parameter list 2 FCDY parameter list
AP 247A	DFHFCDR	FC 2	LMLM call failed	1 FCFR parameter list 2 LMLM parameter list
AP 247B	DFHFCDR	Exc	Pool resynchronization retry failed	1 FCFR parameter list 2 FCDY parameter list
AP 247C	DFHFCDR	Exc	Retained lock encountered	1 FCFR parameter list 2 FCCR parameter list
AP 247D	DFHFCDR	Exc	Lock wait has timed out	1 FCFR parameter list 2 FCCR parameter list
AP 247E	DFHFCDR	FC 2	Before locking request slot wait	1 CFDT pool name 2 FCPW (pool wait element)
AP 247F	DFHFCDR	FC 2	After locking request slot wait	1 CFDT pool name 2 FCPW (pool wait element)
AP 2480	DFHFCDR	Exc	Error on locking request slot wait	1 FCFR parameter list 2 DSSR parameter list
AP 24A0	DFHFCDW	FC 2	Entry	1 RMLK parameter list
AP 24A1	DFHFCDW	FC 2	Exit	1 RMLK parameter list
AP 24A2	DFHFCDW	Exc	Recovery routine entered	1 RMLK parameter list 2 Kernel error data
AP 24A3	DFHFCDW	Exc	Purged	1 RMLK parameter list
AP 24A4	DFHFCDW	Exc	Invalid function	1 RMLK parameter list
AP 24A5	DFHFCDW	Exc	FCDU call failed	1 RMLK parameter list 2 FCDU parameter list
AP 24B0	DFHFCDU	FC 2	Entry	1 FCDU parameter list

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 24B1	DFHFCDU	FC 2	Exit	1 FCDU parameter list
AP 24B2	DFHFCDU	Exc	Recovery routine entered	1 FCDU parameter list 2 Kernel error data
AP 24B3	DFHFCDU	Exc	Purged	1 FCDU parameter list
AP 24B4	DFHFCDU	Exc	Invalid function	1 FCDU parameter list
AP 24B5	DFHFCDU	FC 2	Before CFDT server call	1 FCCU parameter list 2 CFDT pool name 3 FCDU's wait exit EP addr
AP 24B6	DFHFCDU	FC 2	After CFDT server call	1 FCCU parameter list 2 CFDT pool name 3 Server R15 return code
AP 24B7	DFHFCDU	FC 2	Entry to FCDU's wait exit	1 FCCU parameter list 2 Wait ECB address
AP 24B8	DFHFCDU	FC 2	Exit from FCDU's wait exit	1 FCCU parameter list 2 R15 return code from wait exit
AP 24B9	DFHFCDU	Exc	CFDT server call failed	1 FCDU parameter list 2 FCCU parameter list
AP 24BA	DFHFCDU	FC 2	Before Query Server Instance	1 CFDT pool name
AP 24BB	DFHFCDU	FC 2	After Query Server Instance	1 CFDT pool name 2 Server instance token 3 R15 return code 4 R0 reason code 5 R1 server token
AP 24BC	DFHFCDU	FC 2	Before connect to CFDT server	1 Pool name 2 MaxReqs limit 3 Wait exit stub EP addr
AP 24BD	DFHFCDU	FC 2	After connect to CFDT server	1 CFDT pool name 2 Connection token 3 Server token 4 R15 return code 5 R0 reason code (if connect failed)
AP 24BE	DFHFCDU	Exc	Error on connect to CFDT server	1 CFDT pool name 2 R15 return code 3 R0 reason code
AP 24BF	DFHFCDU	FC 2	Before disconnect from CFDT server	1 Connection token 2 CFDT pool name
AP 24C0	DFHFCDU	FC 2	After disconnect from CFDT server	1 CFDT pool name 2 R15 return code

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 24C1	DFHFCDU	Exc	Error on disconnect from CFDT server	1 CFDT pool name 2 Connection token 3 R15 return code
AP 24C2	DFHFCDU	FC 2	Before MaxReqs wait	1 CFDT pool name 2 FCPW (pool wait element)
AP 24C3	DFHFCDU	FC 2	After MaxReqs wait	1 CFDT pool name 2 FCPW (pool wait element)
AP 24C4	DFHFCDU	Exc	Error on MaxReqs wait	1 FCDU parameter list 2 DSSR parameter list
AP 24C5	DFHFCDU	Exc	Pool resynchronization error	1 FCDU parameter list 2 FCDY parameter list
AP 24C6	DFHFCDU	Exc	LMLM call failed	1 FCDU parameter list 2 LMLM parameter list
AP 24C7	DFHFCDU	Exc	Pool resynchronization retry failed	1 FCDU parameter list 2 FCDY parameter list
AP 24D0	DFHFCDY	FC 2	Entry	1 FCDY parameter list
AP 24D1	DFHFCDY	FC 2	Exit	1 FCDY parameter list
AP 24D2	DFHFCDY	Exc	Recovery routine entered	1 FCDY parameter list 2 Kernel error data
AP 24D3	DFHFCDY	Exc	Purged	1 FCDY parameter list
AP 24D4	DFHFCDY	Exc	Invalid format	1 Input parameter list
AP 24D5	DFHFCDY	Exc	Invalid function	1 FCDY parameter list
AP 24D6	DFHFCDY	Exc	Unknown CFDT pool	1 FCDY parameter list
AP 24D7	DFHFCDY	Exc	FCDU call failed	1 FCDY parameter list 2 FCDU parameter list
AP 24D8	DFHFCDY	Exc	RMLN call failed	1 FCDY parameter list 2 RMLN parameter list
AP 24D9	DFHFCDY	Exc	RMDM call failed	1 FCDY parameter list 2 RMDM parameter list
AP 24DA	DFHFCDY	Exc	Lost CFDT RMC link	1 FCDY parameter list 2 UOW ID of link
AP 24DB	DFHFCDY	Exc	Error on purging transaction	1 FCDY parameter list 2 XMIQ parameter list
AP 24E0	DFHEIQCF	FC 2	Before Query Server Instance	1 CFDT pool name

Table 73. File control trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 24E1	DFHEIQCF	FC 2	After Query Server Instance	1 CFDT pool name 2 Server instance token 3 R15 return code 4 R0 reason code 5 R1 server token

Note: For more file control trace entries, see “File control” on page 38 and “File control” on page 58.

RMI trace entries

Table 74. RMI trace entries

Point ID	Module	Lvl	Type	Data
AP 2500	DFHERMSP	RI 1	Entry	1 RMxx parameter list
AP 2501	DFHERMSP	RI 1	Exit	1 RMxx parameter list
AP 2502	DFHERMSP	Exc	Invalid format	1 RMxx parameter list
AP 2503	DFHERMSP	Exc	Invalid RMRO function	1 RMRO parameter list
AP 2504	DFHERMSP	Exc	Invalid RMLK function	1 RMLK parameter list
AP 2505	DFHERMSP	Exc	Recovery	1 RMxx parameter list 2 Kernel error data
AP 2506	DFHERMSP	Exc	RMWTI set failed	1 RMWT parameter list
AP 2507	DFHERMSP	Exc	RMUWM INQ unit of work failed	1 RMUW parameter list
AP 2508	DFHERMSP	Exc	XMATM attach failed	1 XMAT parameter list
AP 2509	DFHERMSP	RI 2	ERMSP event - call RMI	1 TRUE's entryname 2 RMI SP arg1 3 RMI SP arg10
AP 2510	DFHERMSP	RI 2	ERMSP event - return from RMI	1 TRUE's entryname 2 RMI SP arg1 3 RMI SP arg10 4 TRUE's SP return code
# AP 2520	DFHERM	RI 1	Entry	1 Request byte 2 TRUE's entryname 3 Local unit of work ID 4 PLB block (if application call)
#				
#				
#				
#				
# AP 2521	DFHERM	RI 1	Exit	1 Request byte 2 TRUE's entryname 3 Local unit of work ID 4 PLB block (if application call)
#				
#				
AP 2522	DFHERM	RI 2	ERM event - about to call TRUE	1 Request byte 2 TRUE's entryname 3 Local unit of work ID 4 UEPAR parameter list 5 EIS_Program_Mode

Table 74. RMI trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP 2523	DFHERM	RI 2	ERM event -rReturn from TRUE	1 Request byte 2 TRUE's entryname 3 Local unit of work ID 4 UEPAR parameter list 5 EIS_Program_Mode
AP 2524	DFHERM	Exc	TRUE unavailable	1 Request byte 2 TRUE's entryname 3 Local unit of work ID
AP 2525	DFHERM	Exc	RMLN add LINK failed	1 RMLN parameter list
AP 2526	DFHERM	Exc	RMLN set LINK failed	1 RMLN parameter list
AP 2527	DFHERM	Exc	RMWT set work token failed	1 RMWT response
AP 2528	DFHERM	Exc	RMUW inq uow failed	1 RMUW response
AP 2529	DFHERM	Exc	RMUW set uow failed	1 RMUW parameter list
AP 2530	DFHERM	Exc	PGEX prepare Exit failed	1 PGEX response
AP 2531	DFHERM	Exc	PGEX clear exit failed	1 PGEX response
AP 2532	DFHERM	Exc	PGEX clear exit in recovery routine failed	1 PGEX response
AP 2533	DFHERM	Exc	Recovery	1 UEPAR parameter list 2 Kernel error data 3 TRUE's name or DFHERM
AP 2534	DFHERM	Exc	XPCHAIR modified handle	1 Branch address 2 XPCHAIR program name
AP 2540	DFHRMSY	RI 1	Entry	1 TRUE's entryname 2 TRUE's qualifier 3 unit of work ID to resync
AP 2541	DFHRMSY	RI 1	Exit	1 TRUE's entryname 2 TRUE's qualifier 3 unit of work ID to resync 4 Resync type
AP 2542	DFHRMSY	Exc	XMIQ inq transaction failed	1 XMIQ parameter list
AP 2543	DFHRMSY	Exc	RMUW inq unit of work failed	1 RMUW parameter list
AP 2544	DFHRMSY	Exc	RMDM inq startup failed	1 RMDM parameter list
AP 2545	DFHRMSY	Exc	RMLN unexpected reason	1 RMLN parameter list
AP 2546	DFHRMSY	Exc	RMLN init recovery failed	1 RMLN parameter list
AP 2547	DFHRMSY	Exc	RMLN term recovery failed	1 RMLN parameter list
AP 2548	DFHRMSY	RI 2	RMSY event - about to call TRUE	1 TRUE's entryname 2 RMI SP ARG1

Table 74. RMI trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP 2549	DFHRMSY	RI 2	RMSY event - return from TRUE	1 TRUE's entryname 2 RMI SP ARG1 3 TRUE's response
AP 2560	DFHERMRS	RI 1	Entry	1 EIEI parameter list
AP 2561	DFHERMRS	RI 1	Exit	1 EIEI parameter list
AP 2562	DFHERMRS	Exc	Invalid EIP function	1 EID
AP 2563	DFHERMRS	Exc	Invalid EIEI function	1 EIEI parameter list
AP 2564	DFHERMRS	Exc	RMLN start link failed	1 RMLN parameter list
AP 2565	DFHERMRS	Exc	RMLN getnext link failed	1 RMLN parameter list
AP 2566	DFHERMRS	Exc	RMLN end link browse failed	1 RMLN parameter list
AP 2567	DFHERMRS	Exc	Recovery	1 EIEI parameter list 2 Kernel error data
AP 2568	DFHERMRS	Exc	RMUW Inq unit of work failed	1 RMUW parameter list
AP 2569	DFHERMRS	Exc	RMLN Unexpected reason	1 RMLN parameter list
AP 2570	DFHERMRS	Exc	RMLN Init recovery failed	1 RMLN parameter list
AP 2571	DFHERMRS	Exc	RMLN term recovery failed	1 RMLN parameter list
AP 2572	DFHERMRS	Exc	RMLN set mark failed	1 RMLN parameter list
AP 2573	DFHERMRS	Exc	XMAT attach failed	1 XMAT parameter list

DFHCRRSY trace entries

Table 75. DFHCRRSY trace entries

Point ID	Module	Lvl	Type	Data
AP 2600	DFHCRRSY	RM 1	Entry	1 DFHCRRSY parameter list
AP 2601	DFHCRRSY	RM 1	Entry inbound	1 Inbound data 2 Conversation data type
AP 2602	DFHCRRSY	Exc	Invalid device	1 TCTTE, first 8 bytes 2 TCSEFLGS
AP 2603	DFHCRRSY	Exc	Invalid start code	1 Start code
AP 2604	DFHCRRSY	Exc	Not basic conv	1 Conversation data type
AP 2605	DFHCRRSY	Exc	XLN req parse failure	1 Parsed data 2 Received data

Table 75. DFHCRRSY trace entries (continued)

Point ID	Module	Lvl	Type	Data	
AP 2606	DFHCRRSY	Exc	XLN reply parse failure	1	Parsed data
				2	Received data
AP 2607	DFHCRRSY	RM 1	XLN neg	1	Results so far of XLN negotiation
				2	Log exchange type data derived from local system's data
				3	Log exchange type data derived from received data
AP 2608	DFHCRRSY	RM 1	XLN result	1	Log exchange data type resulting from negotiation
AP 2609	DFHCRRSY	Exc	CS req parse failure	1	Log exchange data type
				2	Received data
AP 260A	DFHCRRSY	Exc	CS reply parse failure	1	Parsed data
				2	Received data
AP 260B	DFHCRRSY	RM 1	Action for link	1	Local link data type
				2	Action code
AP 260C	DFHCRRSY	Exc	LUC call error	1	LUC call plist of failing LUC command
				2	Session ID
AP 260D	DFHCRRSY	Exc	MRO call error	1	Conversation data type
AP 260E	DFHCRRSY	Exc	Conv error	1	Conversation data type
AP 260F	DFHCRRSY	Exc	Handle abend	1	DFHCRRSY plist, or null
				2	Conversation data type, or null
				3	Local link data type, or null
				4	Recovery type data type
				5	Number of program restarts
AP 2610	DFHCRRSY	Exc	Connection not found	1	Netname of partner system
				2	Conversation data type
AP 2611	DFHCRRSY	RM 1	Loc link data	1	Local link data type
AP 2612	DFHCRRSY	RM 1	XLN data	1	Log exchange type data type
AP 2613	DFHCRRSY	RM 1	Conv data	1	Conversation data type
AP 2614	DFHCRRSY	RM 2	XLN data debug	1	Log exchange type data type
AP 2615	DFHCRRSY	RM 2	Loc link data debug	1	Local link data type
AP 2616	DFHCRRSY	RM 2	Link in data debug	1	Link in data type
				2	Received data
AP 2617	DFHCRRSY	RM 2	Conv data debug	1	Conversation data type
				2	Received data

Table 75. DFHCRRSY trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP 2618	DFHCRRSY	RM 2	Conv data debug MRO	1 Conversation data type 2 Received data 3 MRO control byte 4 Trace point origin description
AP 2619	DFHCRRSY	RM 1	Compare states action	1 Local link data type 2 Link in data type 3 Resync case flags type data type
AP 261A	DFHCRRSY	RM 1	Old MRO partner	1 Log exchange data type data
AP 261B	DFHCRRSY	RM 1	Wait for decision	1 Local link data type
AP 261C	DFHCRRSY	Exc	Partner logname not found	1 Log exchange type data type
AP 261D	DFHCRRSY	RM 1	Unshunt entry	1 Local link data type
AP 261E	DFHCRRSY	RM 1	Resync entry	1 Local link data type
AP 261F	DFHCRRSY	RM 1	Partner restart entry	1 Connection type data type
AP 2620	DFHCRRSY	RM 2	Conn data debug	1 Conversation data type 2 Received data 3 Trace point origin description
AP 2621	DFHCRRSY	Exc	Sess fail	1 Conversation data type
AP 2622	DFHCRRSY	Exc	Conn fail	1 Conversation data type
AP 2623	DFHCRRSY	RM 1	Unbind session	1 Conversation data type
AP 2624	DFHCRRSY	RM 1	Scan for links	1 Local link data type 2 Action request type
AP 2625	DFHCRRSY	Exc	Handle error	1 Existence bits describing existence of following 3 fields: 2 Local link data type 3 Conversation data type 4 Batch list type data type 5 Recovery type data type
AP 2626	DFHCRRSY	RM 1	List overflow	1 Connection type data type
AP 2627	DFHCRRSY	Exc	XLN neg reject	1 Exchange lognames negotiation result 2 Log exchange type locally derived data 3 Log exchange type received data
AP 2628	DFHCRRSY	Exc	XLN result	1 Log exchange type resulting from negotiation
AP 262A	DFHCRRSY	RM 1	Shunt reply received	1 Local link data type

Table 75. DFHCRRSY trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP 262B	DFHCRRSY	RM 1	Partner SPM not active	1 Conversation data type
AP 262C	DFHCRRSY	RM 2	STG list	1 Recovery type data type
AP 262D	DFHCRRSY	RM 1	CRERP enter	1 None
AP 262E	DFHCRRSY	RM 1	CRERP exit	1 None
AP 262F	DFHCRRSY	RM 1	Event inbound	1 Inbound data 2 Conversation data type

LU6.1 Resynchronization

Table 76. LU6.1 Resynchronization

Point ID	Module	Lvl	Type	Data
AP 2700	DFHZRSY1	1	Entry	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE
AP 2701	DFHZRSY1	1	Exit	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE
AP 2702	DFHZRSY1	Exc	Invalid first STSN	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE 3 Local sequence numbers and unit of work disposition 4 Partner's sequence numbers
AP 2703	DFHZRSY1	Exc	Invalid second STSN	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE 3 Local sequence numbers and unit of work disposition 4 Partner's sequence numbers
AP 2704	DFHZRSY2	1	Entry	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE
AP 2705	DFHZRSY2	1	Exit	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE
AP 2706	DFHZRSY3	1	Entry	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE
AP 2707	DFHZRSY3	1	Exit	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE

Table 76. LU6.1 Resynchronization (continued)

Point ID	Module	Lvl	Type	Data
AP 2708	DFHZRSY4	1	Entry	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE
AP 2709	DFHZRSY4	1	Exit	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE
AP 270A	DFHZRSY5	1	Entry	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE
AP 270B	DFHZRSY5	1	Exit	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE
AP 270C	DFHZRSY5	Exc	Both partners cold	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE 3 Local sequence numbers and unit of work disposition 4 Partner's sequence numbers
AP 270D	DFHZRSY5	Exc	PLU's numbers rejected	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE 3 Local sequence numbers and unit of work disposition
AP 270E	DFHZRSY5	Exc	Invalid response to STSN	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE 3 Local sequence numbers and unit of work disposition 4 Partner's sequence numbers 5 STSN response
AP 270F	DFHZRSY5	Exc	Invalid response to cold	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE 3 Local sequence numbers and unit of work disposition 4 Partner's sequence numbers
AP 2710	DFHZRSY6	1	Entry	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE
AP 2711	DFHZRSY6	1	Exit	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE

Table 76. LU6.1 Resynchronization (continued)

Point ID	Module	Lvl	Type	Data
AP 2712	DFHZRSY6	Exc	Invalid response to STSN	1 TCTTE address 2 TCTE_TRACE_1 fields in TCTTE 3 Local sequence numbers and unit of work disposition 4 Partner's sequence numbers 5 STSN response

Bridge facility management 2

Table 77. Bridge facility management trace points

Point ID	Module	Lvl	Type	Data
AP 2800	DFHBRAT	BR 1	Entry	1 BRAT parameter list
AP 2801	DFHBRAT	BR 1	Exit	1 BRAT parameter list
AP 2802	DFHBRAT	Exc	Invalid format	1 BRAT parameter list
AP 2803	DFHBRAT	Exc	Invalid function	1 BRAT parameter list
AP 2804	DFHBRAT	Exc	Recovery	1 BRAT parameter list 2 Kernel error data
AP 2805	DFHBRAT	Exc	Xmat sno	1 BRAT parameter list
AP 2806	DFHBRAT	Exc	Xmxd sno	1 BRAT parameter list
AP 2807	DFHBRAT	Exc	Xsrc sno	1 BRAT parameter list
AP 2808	DFHBRAT	Exc	Usad sno	1 BRAT parameter list
AP 2809	DFHBRAT	Exc	Brfm allocate failed	1 BRAT parameter list
AP 280A	DFHBRAT	Exc	Tm locate failed	1 BRAT parameter list
AP 2820	DFHBRIQ	BR 1	Entry	1 BRIQ parameter list
AP 2821	DFHBRIQ	BR 1	Exit	1 BRIQ parameter list
AP 2822	DFHBRIQ	Exc	Invalid format	1 BRIQ parameter list
AP 2823	DFHBRIQ	Exc	Invalid function	1 BRIQ parameter list
AP 2824	DFHBRIQ	Exc	Recovery	1 BRIQ parameter list 2 Kernel error data
AP 2840	DFHBRRM	BR 1	Entry	1 RMRO parameter list
AP 2841	DFHBRRM	BR 1	Exit	1 RMRO parameter list
AP 2842	DFHBRRM	Exc	Recovery	1 RMRO parameter list 2 Kernel error data

Table 77. Bridge facility management trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 2847	DFHBRRM	BR 2	Call user exit	1 BRXA transaction area 2 BRXA command area
AP 2848	DFHBRRM	BR 2	Return from user exit	1 BRXA transaction area 2 BRXA command area
AP 2860	DFHBRXM	BR 1	Entry	1 XMAC parameter list
AP 2861	DFHBRXM	BR 1	Exit	1 XMAC parameter list
AP 2862	DFHBRXM	Exc	Invalid format	1 XMAC parameter list
AP 2863	DFHBRXM	Exc	Invalid function	1 XMAC parameter list
AP 2864	DFHBRXM	Exc	Recovery	1 XMAC parameter list 2 Kernel error data
AP 2865	DFHBRXM	Exc	Smgf sno	1 XMAC parameter list
AP 2866	DFHBRXM	Exc	Xmxd sno	1 XMAC parameter list
AP 2867	DFHBRXM	BR 2	Call user exit	1 BRXA transaction area 2 BRXA command area
AP 2868	DFHBRXM	BR 2	Return from user exit	1 BRXA transaction area 2 BRXA command area

Connection to quiesce processing

Table 78. Connection to quiesce processing trace points

Point ID	Module	Lvl	Type	Data
AP 2900	DFHCLS5	1	Entry	
AP 2901	DFHCLS5	1	Exit	
AP 2902	DFHCLS5	Exc	Recovery entered	
AP 2903	DFHCLS5	Exc	Invalid start code	1 Start code
AP 2904	DFHCLS5	Exc	Invalid terminal type	1 Terminal TCTTE address 2 Terminal ID 3 Terminal type
AP 2905	DFHCLS5	Exc	Invalid TPN	1 TPN
AP 2906	DFHCLS5	Exc	Invalid GDS variable	1 GDS variable
AP 2907	DFHCLS5	Exc	Error from DFHLUC interface	1 DFHLUC parameter list
AP 2908	DFHCLS5	Exc	Unexpected response from recovery manager	1 Recovery manager parameter list
AP 2909	DFHCLS5	Exc	Unexpected response from recovery manager	1 Recovery manager parameter list
AP 290A	DFHCLS5	Exc	Invalid CQP response	1 CQP GDS variable

Table 78. Connection to quiesce processing trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 290B	DFHCLS5	Exc	Invalid facility	1 Facility indicator 2 Facility address
AP 290C	DFHCLS5	1	Event - CQP inbound	
AP 290D	DFHCLS5	1	Event - CQP outbound	

Server support for CICS Clients

Table 79 shows the trace entries for CICS Clients support.

Note: Turning on level 2 tracing when you are using DBCS code pages with client virtual terminals causes the amount of trace information to increase substantially.

Table 79. CICS Client support trace points

Point ID	Module	Lvl	Type	Data
AP 3000	DFHZCN1	TC 1	Entry	1 None
AP 3001	DFHZCN1	TC 1	Exit	1 Connection netname 2 CCIN output
AP 3002	DFHZCN1	Exc	Invalid function	1 Connection netname 2 Data received
AP 3003	DFHZCN1	Exc	Invalid synclevel	1 Connection netname
AP 3004	DFHZCN1	Exc	Length error	1 Connection netname 2 Length received
AP 3005	DFHZCN1	Exc	DFHZCN2 install error	1 Connection netname
AP 3006	DFHZCN1	Exc	DFHZCN2 uninstall error	1 Connection netname
AP 3007	DFHZCN1	Exc	Disaster	1 Connection netname
AP 3008	DFHZCN1	Exc	Invalid start type	1 Start type
AP 3009	DFHZCN1	Exc	Logic error	1 Connection netname
AP 300A	DFHZCN1	Exc	Install canceled	1 Connection netname
AP 300B	DFHZCN1	Exc	Invalid version	1 Connection netname 2 Data received
AP 300C	DFHZCN1	Exc	Invalid principal facility	1 TCZFCAAA
AP 300D	DFHZCN1	Exc	Invalid group	1 Connection netname 2 Data received
AP 300E	DFHZCN1	Exc	Invalid data	1 Connection netname 2 Data received
AP 300F	DFHZCN1	Exc	No code page given	1 Connection netname 2 CCIN input

Table 79. CICS Client support trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 3010	DFHZCN2	TC 1	Entry	1 DFHZCN2 input parameters
AP 3011	DFHZCN2	TC 1	Exit	1 DFHZCN2 output parameters
AP 3014	DFHZCN2	Exc	Invalid function	1 Connection netname 2 Data received
AP 3015	DFHZCN2	Exc	Cond. enqueue failed	1 None
AP 3016	DFHZCN2	Exc	Recovery entered	1 DFHZCN2 parameter list 2 Kernel error data
AP 3018	DFHZCN2	Exc	CDTS attach failed	1 CCIN input 2 Termid 3 Connection netname
AP 3019	DFHZCN2	Exc	CDTS timeout	1 CCIN input 2 Termid 3 Connection netname
AP 301A	DFHZCN2	Exc	Invalid capabilities	1 Connection netname 2 CCIN input
AP 301C	DFHZCN2	Exc	Surrogate busy	1 CCIN input 2 Termid 3 Connection netname
AP 3020	DFHZCT1	TC 1	Entry	1 None
AP 3021	DFHZCT1	TC 1	Exit	1 CTIN input 2 Termid 3 Netname 4 CTIN output
AP 3022	DFHZCT1	Exc	Receive failed	1 Netname 2 Data length
AP 3023	DFHZCT1	TC 1	Input data	1 Netname 2 CTIN input
AP 3024	DFHZCT1	Exc	CTIN group is not for event	1 Netname 2 CTIN input
AP 3025	DFHZCT1	Exc	CITS attach failed	1 CTIN input 2 Termid 3 Netname 4 CTIN output 5 RWE
AP 3026	DFHZCT1	Exc	Duplicate found	1 CTIN input 2 Termid 3 Netname 4 CTIN output 5 RWE

Table 79. CICS Client support trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 3027	DFHZCT1	Exc	CITS timeout	1 CTIN input 2 Termid 3 Netname 4 CTIN output 5 RWE
AP 3028	DFHZCT1	Exc	CDTS attach failed	1 CTIN input 2 Termid 3 Netname 4 CTIN output 5 RWE
AP 3029	DFHZCT1	Exc	CDTS timeout	1 CTIN input 2 Termid 3 Netname 4 CTIN output 5 RWE
AP 302A	DFHZCT1	Exc	Invalid start type	1 Start type
AP 302B	DFHZCT1	Exc	Invalid synclevel	1 Netname
AP 302D	DFHZCT1	Exc	Data length error	1 Netname 2 Data length
AP 302E	DFHZCT1	Exc	Install surrogate in use	1 CTIN input 2 Termid 3 Netname 4 CTIN output
AP 302F	DFHZCT1	Exc	Delete surrogate in use	1 CTIN input 2 Termid 3 Netname 4 CTIN output
AP 3030	DFHZCT1	Exc	CITS abend	1 CTIN input 2 Termid 3 Netname 4 CTIN output 5 RWE
AP 3031	DFHZCT1	Exc	Get BPS failed	1 CTIN input 2 Termid 3 Netname 4 CTIN output
AP 3032	DFHZCT1	Exc	Invalid principal facility	1 TCZFCAAA
AP 3033	DFHZCT1	Exc	Invalid data	1 Netname 2 CTIN input
AP 3034	DFHZCT1	Exc	Invalid function	1 Netname 2 CTIN input

Table 79. CICS Client support trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 3035	DFHZCT1	Exc	Invalid code page	1 CTIN input 2 Termid 3 Netname 4 CTIN output 5 CGCSGID
AP 3036	DFHZCT1	Exc	Wrong version	1 Netname 2 CTIN input
AP 3037	DFHZCT1	Exc	Netname missing for delete	1 Netname 2 CTIN input
AP 3038	DFHZCT1	Exc	Unexpected response from DFHCCNV	1 CTIN input 2 Termid 3 Netname 4 CTIN output 5 DFHC32 commarea
AP 3039	DFHZCT1	Exc	CTIN remote	1 Netname
AP 3040	DFHZCN1	Exc	No capabilities given	1 Connection netname 2 CCIN input
AP 3041	DFHZCN1	Exc	CCIN remote	1 Connection netname
AP 3050	DFHCCNV3	TC 1	Check client code page entry	1 Client code page
AP 3051	DFHCCNV3	TC 1	Check client code page exit	1 Response, reason
AP 3052	DFHCCNV3	TC 1	Check convertible entry	1 Client code page 2 Server character set 3 Server code page
AP 3053	DFHCCNV3	TC 1	Check convertible exit	1 Conversion token 2 Response, reason
AP 3054	DFHCCNV3	TC 1	Entry	1 None
AP 3055	DFHCCNV3	TC 1	Exit	1 Response, reason
AP 3056	DFHCCNV3	Exc	Invalid function	1 Function
AP 3057	DFHCCNV3	TC 1	Convert 3270 data stream for entry	1 Target 2 Conversion token 3 Data length 4 Length of data converted 4 Erase (Yes No)
AP 3058	DFHCCNV3	TC 2	Convert 3270 data stream for entry	1 Data
AP 3059	DFHCCNV3	TC 2	Convert 3270 data stream for exit	1 Data converted
AP 305A	DFHCCNV3	TC 1	Convert 3270 data stream for exit	1 Response, reason 2 Data converted 2 Length of data converted

Table 79. CICS Client support trace points (continued)

Point ID	Module	Lvl	Type	Data	
AP 305B	DFHCCNV3	Exc	3270 data length zero	1	Data length
AP 305C	DFHCCNV3	Exc	Target invalid	1	Target
AP 305D	DFHCCNV3	Exc	Conversion token has bad checker field	1	Conversion token
AP 305E	DFHCCNV3	Exc	Conversion token has bad client index	1	Conversion token
AP 305F	DFHCCNV3	Exc	Conversion token has bad server index	1	Conversion token
AP 3060	DFHCCNV3	Exc	Conversion token not for SBCS	1	Conversion token
AP 3061	DFHCCNV3	Exc	3270 SBA incomplete	1 2 3	Offset in data Data after offset Data before offset
AP 3062	DFHCCNV3	Exc	3270 SF incomplete	1 2 3	Offset in data Data after offset Data before offset
AP 3063	DFHCCNV3	Exc	3270 SFE/MF incomplete	1 2 3	Offset in data Data after offset Data before offset
AP 3064	DFHCCNV3	Exc	3270 SA incomplete	1 2 3	Offset in data Data after offset Data before offset
AP 3065	DFHCCNV3	Exc	3270 RA incomplete	1 2 3	Offset in data Data after offset Data before offset
AP 3066	DFHCCNV3	Exc	3270 GE used	1 2 3	Offset in data Data after offset Data before offset
AP 3067	DFHCCNV3	Exc	3270 EUA incomplete	1 2 3	Offset in data Data after offset Data before offset
AP 3068	DFHCCNV3	TC 1	Convert 3270 AID entry	1 2	3270 AID Target
AP 3069	DFHCCNV3	TC 1	Convert 3270 AID exit	1 2	Response, reason Converted AID
AP 306A	DFHCCNV3	Exc	Invalid target	1	Target
AP 306B	DFHCCNV3	TC 1	Free conversion token entry	1	Conversion token
AP 306C	DFHCCNV3	TC 1	Free conversion token exit	1	Response, reason
AP 306D	DFHCCNV3	Exc	Getmain failure	1	None
AP 306E	DFHCCNV3	Exc	Freemain failure	1	None

Table 79. CICS Client support trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 306F	DFHCCNV3	Exc	SBA too high for screen size	1 Offset in data 2 Data after offset 3 Data before offset
AP 3070	DFHCCNV3	TC 2	Before DBCS screen map update	1 DBCS screen map
AP 3071	DFHCCNV3	TC 2	After DBCS screen map update	1 DBCS screen map
AP 3072	DFHCCNV3	TC 1	Get conversion token entry	1 Terminal token 2 Client code page 3 Server character set 4 Server code page 5 Screen columns 6 Screen rows
AP 3073	DFHCCNV3	TC 1	Get conversion token exit	1 Response, reason 2 Conversion token
AP 3074	DFHCCNV3	Exc	Conversion token has invalid token storage address	1 Conversion token
AP 3075	DFHCCNV3	Exc	Length of 3270 data converted is zero	1 Length of data converted

RDO for RCT

Table 80. RDO for RCT

Point ID	Module	Lvl	Type	Data
AP 3100	DFHD2IN1	FC 1	Entry	1 ROIN parameter list
AP 3101	DFHD2IN1	FC 1	Exit	1 ROIN parameter list
AP 3102	DFHD2IN1	Exc	Invalid function	1 ROIN parameter list
AP 3103	DFHD2IN1	Exc	Bad attach of DFHD2IN2	1 TCAKCRC
AP 3104	DFHD2IN1	Exc	Recovery	1 ROIN parameter list 2 Kernel error data
AP 3110	DFHD2RP	FC 1	Entry	1 D2S_D2ST_RESP
AP 3111	DFHD2RP	FC 1	Exit	1 D2S_D2ST_RESP
AP 3112	DFHD2RP	Exc	Add gate failed	1 KEDD parameter list
AP 3113	DFHD2RP	Exc	Define program failed	1 LDLD parameter list
AP 3114	DFHD2RP	Exc	Acquire program failed	1 LDLD parameter list
AP 3115	DFHD2RP	Exc	Add lock failed	1 LMLM parameter list
AP 3116	DFHD2RP	Exc	Unlock failed	1 LMLM parameter list
AP 3117	DFHD2RP	Exc	Add subpool failed	1 SMAD parameter list

Table 80. RDO for RCT (continued)

Point ID	Module	Lvl	Type	Data	
AP 3118	DFHD2RP	Exc	Catalog startbr failed	1	CCCC parameter list
AP 3119	DFHD2RP	Exc	Catalog getnext failed	1	CCCC parameter list
AP 311A	DFHD2RP	Exc	Catalog endbr failed	1	CCCC parameter list
AP 311B	DFHD2RP	Exc	Purge failed	1	CCCC parameter list
AP 311C	DFHD2RP	Exc	Create directory failed	1	DDDI parameter list
AP 311D	DFHD2RP	Exc	Inquire startup failed	1	RMDM parameter list
AP 311E	DFHD2RP	Exc	Add DB2 [®] conn failed	1	D2TM parameter list
AP 311F	DFHD2RP	Exc	Add DB2entry failed	1	D2TM parameter list
AP 3120	DFHD2RP	Exc	Add DB2tran failed	1	D2TM parameter list
AP 3130	DFHD2TM	FC 1	Entry	1	D2TM parameter list
AP 3131	DFHD2TM	FC 1	Exit	1	D2TM parameter list
AP 3132	DFHD2TM	Exc	Invalid function	1	D2TM parameter list
AP 3133	DFHD2TM	Exc	Recovery	1 2	D2TM parameter list Kernel error data
AP 3134	DFHD2TM	Exc	GETMAIN failed	1	SMGF parameter list
AP 3135	DFHD2TM	Exc	Acquire lock failed	1	LMLM parameter list
AP 3136	DFHD2TM	Exc	Release lock failed	1	LMLM parameter list
AP 3137	DFHD2TM	Exc	Catalog delete failed	1	CCCC parameter list
AP 3138	DFHD2TM	Exc	Catalog purge failed	1	CCCC parameter list
AP 3139	DFHD2TM	Exc	Catalog writenext failed	1	CCCC parameter list
AP 313A	DFHD2TM	Exc	Catalog write failed	1	CCCC parameter list
AP 313B	DFHD2TM	Exc	Directory add failed	1	DDDI parameter list
AP 313C	DFHD2TM	Exc	Directory delete failed	1	DDDI parameter list
AP 313D	DFHD2TM	Exc	Directory startbr failed	1	DDBR parameter list
AP 313E	DFHD2TM	Exc	Directory getnext failed	1	DDBR parameter list
AP 313F	DFHD2TM	Exc	Directory endbr failed	1	DDBR parameter list
AP 3140	DFHD2TM	Exc	Directory locate failed	1	DDLO parameter list
AP 3141	DFHD2TM	Exc	FREEMAIN failed	1	SMGF parameter list

Table 80. RDO for RCT (continued)

Point ID	Module	Lvl	Type	Data
AP 3142	DFHD2TM	Exc	Inquire security failed	1 XSIS parameter list
AP 3143	DFHD2TM	Exc	Non-CICS resource failed	1 XSRC parameter list
AP 3144	DFHD2TM	Exc	Surrogate check failed	1 XSRC parameter list
AP 3145	DFHD2TM	Exc	Start DB2 attach failed	1 D2CC parameter list
AP 3146	DFHD2TM	Exc	Stop DB2 attach failed	1 D2CC parameter list
AP 3147	DFHD2TM	Exc	Wait oldc failed	1 DSSR parameter list
AP 3148	DFHD2TM	FC 2	Post-CICS task awaiting command thread	1 TCATXNO
AP 3149	DFHD2TM	FC 2	Post-CICS task awaiting db2entry thread	1 TCATXNO
AP 314A	DFHD2TM	FC 2	Post-CICS task awaiting pool thread	1 TCATXNO
AP 314B	DFHD2TM	FC 2	Post-CICS task awaiting thread TCB	1 TCATXNO
AP 3180	DFHD2EX1	RI 1	Entry	1 UERTFID 2 DFHD2LOT
# AP 3181	DFHD2EX1	RI 1	Exit	1 UERTFID + SQL Plist (if SQL application call) 2 DFHD2LOT block 3 LOT_RMI_RETURN CODE 4 DFHD2RCT block (if RI lvl 2) 5 DFHD2CSB ¹ block (if RI lvl 2)
#				
#				
#				
#				
#				
#				
AP 3182	DFHD2EX1	RI 2	Post subtask	1 LOT_REQUEST INDICATORS 2 Plan name 3 DFHD2LOT block 4 DFHD2RCT block 5 DFHD2CSB ¹ block
AP 3183	DFHD2EX1	RI 2	Return from subtask	1 LOT_REQUEST INDICATORS LOT_RETURN_CODES 2 Plan name 3 DFHD2LOT block 4 DFHD2RCT block 5 DFHD2CSB ¹ block
AP 3184	DFHD2EX1	RI 2	Post D2MSB for attach	1 LOT_REQUEST INDICATORS 2 Plan name 3 DFHD2LOT block 4 DFHD2RCT block 5 DFHD2CSB ¹ block
AP 3185	DFHD2EX1	RI 2	Post D2MSB for detach	1 LOT_REQUEST INDICATORS 2 Plan name 3 DFHD2LOT block 4 DFHD2RCT block 5 DFHD2CSB ¹ block

Table 80. RDO for RCT (continued)

Point ID	Module	Lvl	Type	Data
AP 3186	DFHD2EX1	Exc	Invalid UERTFGP	1 UERTFGP 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 3187	DFHD2EX1	Exc	Invalid RMI	1 EIBRSRCE 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 3188	DFHD2EX1	Exc	Invalid UERTFID	1 UERTFID 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 3189	DFHD2EX1	Exc	Invalid thread state	1 DFHD2LOT 2 DFHD2RCT block 3 DFHD2CSB ¹ block
AP 318A	DFHD2EX1	Exc	Bad DDLO reason	1 DDLO parameter list 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 318B	DFHD2EX1	Exc	Bad DDLO response	1 DDLO parameter list 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 318C	DFHD2EX1	Exc	Acquire lock failed	1 LMLM parameter list 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 318D	DFHD2EX1	Exc	Release lock failed	1 LMLM parameter list 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 318E	DFHD2EX1	Exc	Recovery	1 Kernel error data 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 318F	DFHD2EX1	RI 2	Call dynamic plan exit	1 Program name 2 Plan name 3 Primary auth 4 User anchor
AP 3190	DFHD2EX1	RI 2	Return from plan exit	1 Program name 2 Plan name 3 Primary auth 4 User anchor

Table 80. RDO for RCT (continued)

Point ID	Module	Lvl	Type	Data
AP 3191	DFHD2EX1	Exc	Thread lost	1 DFHD2LOT 2 DFHD2RCT block 3 DFHD2CSB ¹ block
AP 3192	DFHD2EX1	Exc	Wait MVS failed	1 DSSR parameter list 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 3193	DFHD2EX1	Exc	GETMAIN failed	1 SMGF parameter list 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 3194	DFHD2EX1	Exc	FREEMAIN failed	1 SMGF parameter list 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 3196	DFHD2EX1	Exc	Directory add failed	1 DDDI parameter list 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 3197	DFHD2EX1	Exc	Directory delete failed	1 DDDI parameter list 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 3198	DFHD2EX1	Exc	Set DB2conn failed	1 D2TM parameter list 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 3199	DFHD2EX1	Exc	Set DB2entry failed	1 D2TM parameter list 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 319A	DFHD2EX1	Exc	Invalid syncpoint call	1 Syncpoint request 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 319B	DFHD2EX1	Exc	Deadlock - rolling back	1 LOT_REQUEST INDICATORS LOT_RETURN_CODES 2 Plan name 3 DFHD2LOT block 4 DFHD2RCT block 5 DFHD2CSB ¹ block
AP 319C	DFHD2EX1	RI 2	Post D2MSB for resync	1 LOT_REQUEST INDICATORS 2 Plan name 3 DFHD2LOT block

Table 80. RDO for RCT (continued)

Point ID	Module	Lvl	Type	Data
AP 319D	DFHD2EX1	Exc	Subtask abended	1 LOT_SUBTASK ABEND REASON 2 DFHD2LOT block 3 DFHD2RCT block 4 DFHD2CSB ¹ block
AP 319E	DFHD2EX1	RI 2	Post-CICS task awaiting thread TCB	1 LOT_REQUEST INDICATORS 2 Plan name 3 DFHD2LOT block 4 DFHD2RCT block 5 DFHD2CSB ¹ block
AP 319F	DFHD2EX1	RI 2	Overflowing to pool	1 DFHD2RCT block
AP 31A0	DFHD2EX1	Exc	XMAT Attach failed	1 XMAT parameter list 2 DFHD2LOT block
AP 31B0	DFHD2STP	FC 1	Entry	1 D2CC parameter list
AP 31B1	DFHD2STP	FC 1	Exit	1 D2CC parameter list
AP 31B2	DFHD2STP	Exc	Invalid function	1 D2CC parameter list
AP 31B3	DFHD2STP	Exc	Delete PRH failed	1 Return code
AP 31B4	DFHD2STP	Exc	Disable exit failed	1 EIB
AP 31B5	DFHD2STP	Exc	Discard DB2conn failed	1 D2TM parameter list
AP 31B6	DFHD2STP	Exc	Detach DFHD2MSB failed	1 Return code
AP 31B7	DFHD2STP	Exc	Recovery	1 D2CC parameter list 2 Kernel error data
AP 31B8	DFHD2STP	Exc	FREEMAIN failed	1 SMGF parameter list
AP 31C0	DFHD2STR	FC 1	Entry	1 D2CC parameter list
AP 31C1	DFHD2STR	Exc	Invalid function	1 D2CC parameter list
AP 31C2	DFHD2STR	FC 2	Exit	1 D2CC parameter list
AP 31C3	DFHD2STR	Exc	Load PRH failed	1 Return code 2 Abend code
AP 31C4	DFHD2STR	Exc	Enable exit failed	1 EIB
AP 31C5	DFHD2STR	Exc	Extract exit failed	1 EIB
AP 31C6	DFHD2STR	Exc	Start service task failed	1 XMAT parameter list
AP 31C7	DFHD2STR	Exc	Change priority failed	1 DSAT parameter list
AP 31C8	DFHD2STR	Exc	Attach DFHD2MSB failed	1 Return code

Table 80. RDO for RCT (continued)

Point ID	Module	Lvl	Type	Data	
AP 31C9	DFHD2STR	Exc	Resync GETMAIN failed	1	SMGF parameter list
AP 31CA	DFHD2STR	Exc	FREEMAIN failed	1	SMGF parameter list
AP 31CB	DFHD2STR	Exc	Invalid tsqueue length	1	TSQR parameter list
AP 31CC	DFHD2STR	Exc	Read tsqueue failed	1	TSQR parameter list
AP 31CD	DFHD2STR	Exc	Write tsqueue failed	1	TSQR parameter list
AP 31CE	DFHD2STR	Exc	Acquire lock failed	1	LMLM parameter list
AP 31CF	DFHD2STR	Exc	Release lock failed	1	LMLM parameter list
AP 31D0	DFHD2STR	Exc	Recovery	1 2	D2CC parameter list Kernel error data
AP 31D1	DFHD2STR	Exc	DB2 not active	1 2	GLB_MSB_PARM3 FRB
AP 31D2	DFHD2STR	Exc	Authorization failed	1 2	GLB_MSB_PARM3 FRB
AP 31D3	DFHD2STR	Exc	Connection error	1 2	GLB_MSB_PARM3 FRB
AP 31D4	DFHD2STR	Exc	Invalid initparm	1 2 3	Initparm string Suffix Subsystem id
AP 31D5	DFHD2STR	FC 2	Initparm data	1 2 3	Initparm string Suffix Subsystem id
AP 31D6	DFHD2STR	Exc	Stats GETMAIN failed	1	SMGF parameter list
AP 31E0	DFHD2CC	FC 1	Entry	1	D2CC parameter list
AP 31E1	DFHD2CC	FC 1	Exit	1	D2CC parameter list
AP 31E2	DFHD2CC	Exc	Recovery	1 2	D2CC parameter list Kernel error data
AP 31E3	DFHD2CC	Exc	Invalid function	1	D2CC parameter list
AP 31E4	DFHD2CC	Exc	Directory startbr failed	1	DDBR parameter list
AP 31E5	DFHD2CC	Exc	Directory getnext failed	1	DDBR parameter list
AP 31E6	DFHD2CC	Exc	Directory endbr failed	1	DDBR parameter list
AP 31E7	DFHD2CC	Exc	Acquire lock failed	1	LMLM parameter list
AP 31E8	DFHD2CC	Exc	Release lock failed	1	LMLM parameter list

Table 80. RDO for RCT (continued)

Point ID	Module	Lvl	Type	Data	
AP 31E9	DFHD2CC	Exc	Record statistics failed	1	STST parameter list
AP 31F0	DFHD2EX2	FC 2	Entry	None	
AP 31F2	DFHD2EX2	FC 2	Exit	None	
AP 31F3	DFHD2EX2	Exc	Handle abend occurred	1	Abend code
AP 31F4	DFHD2EX2	FC 2	EX2 invoked to shutdown attach	None	
AP 31F5	DFHD2EX2	FC 2	EX2 invoked for protected thread purge	None	
AP 31F6	DFHD2EX2	FC 2	EX2 will wait for DB2	None	
AP 31F7	DFHD2EX2	FC 2	EX2 terminating subtasks	None	
AP 31F8	DFHD2EX2	Exc	Acquire lock failed	1	LMLM parameter list
AP 31F9	DFHD2EX2	Exc	Release lock failed	1	LMLM parameter list
AP 3200	DFHD2CM1	Exc	Inquire DB2conn failed	1	EIB
AP 3201	DFHD2CM1	Exc	Set DB2conn failed	1	EIB
AP 3202	DFHD2CM1	Exc	Set DB2entry failed	1	EIB
AP 3203	DFHD2CM1	Exc	Writeq failed	1	EIB
AP 3204	DFHD2CM1	Exc	Readq failed	1	EIB
AP 3205	DFHD2CM1	Exc	Deleteq failed	1	EIB
AP 3206	DFHD2CM1	Exc	GETMAIN failed	1	EIB
AP 3210	DFHD2ST	FC 2	Entry	1	ASSU parameter list
AP 3211	DFHD2ST	FC 2	Exit	1	ASSU parameter list
AP 3212	DFHD2ST	Exc	Recovery	1 2	ASSU parameter list Kernel error data
AP 3213	DFHD2ST	Exc	Invalid function	1	ASSU parameter list
AP 3214	DFHD2ST	Exc	Directory locate failed	1	DDLO parameter list
AP 3215	DFHD2ST	Exc	Directory startbr failed	1	DDBR parameter list
AP 3216	DFHD2ST	Exc	Directory getnext failed	1	DDBR parameter list
AP 3217	DFHD2ST	Exc	Directory endbr failed	1	DDBR parameter list
AP 3218	DFHD2ST	Exc	Record statistics failed	1	STST parameter list
AP 3219	DFHD2ST	Exc	Acquire lock failed	1	LMLM parameter list
AP 321A	DFHD2ST	Exc	Release lock failed	1	LMLM parameter list
AP 3220	DFHD2EX3	RI 2	Subtask posting CICS task	1 2	TCATXNO ECB address

Notes:

1. The CSUB trace block is 160 bytes long, allowing ten 16-byte entries to be stored. It wraps when full. The format of each entry is as follows:

Bytes	Content	Information
0 - 3	Trace request number	Number of trace entry. Use it to find the last-written entry.
4 - 7	Trace request	Four-character representation of the DB2 request. Possible values: ABRT Abort request API SQL or IFI request COMM Commit request CTHD Create thread request ERRH Error handler request IDEN Identify request PREP Prepare request PSGN Partial signon request SIGN Full signon request SYNC Single phase request TERM Terminate thread request *REC Subtask ESTAI recovery routine entered
8 - 9	Reserved	
10 - 11	FRB return code	Two-byte FRB return code
12 - 15	FRB reason code	Four-byte FRB return code

Web trace points

Table 81. Web trace points

Point ID	Module	Lvl	Type	Data
AP 4000	DFHWPBIP	WB 1	Entry	1 WBIP parameters
AP 4001	DFHWPBIP	WB 1	Exit	1 WBIP parameters
AP 4002	DFHWPBIP	Exc	Recovery	1 WBIP parameters 2 Kernel error data
AP 4100	DFHWBLT	WB 1	Entry	None
AP 4101	DFHWBLT	WB 1	Exit	None
AP 4102	DFHWBLT	Exc	Recovery	1 WBLT parameters
AP 4103	DFHWBLT	Exc	Invalid brxa function	1 DFHBRARC
AP 4104	DFHWBLT	Exc	Invalid function code	1 DFHBRARC
AP 4105	DFHWBLT	Exc	Invalid BMS command	1 DFHBRARC
AP 4106	DFHWBLT	Exc	Make Partnership failed	1 WBST parameters

Table 81. Web trace points (continued)

Point ID	Module	Lvl	Type	Data	
AP 4107	DFHWBLT	Exc	Terminate Partnership failed	1	WBST parameters
AP 4108	DFHWBLT	Exc	Wait for Partner failed	1	WBST parameters
AP 4109	DFHWBLT	Exc	Trigger Partner failed	1	WBST parameters
AP 410A	DFHWBLT	Exc	GETMAIN buffer failed	1	DFHEIB
AP 410B	DFHWBLT	Exc	Init handle failed	1	WBTC parameters
AP 410C	DFHWBLT	Exc	No state token	1	State token
AP 410D	DFHWBLT	Exc	GETMAIN brxa failed	1	DFHEIB
AP 410E	DFHWBLT	Exc	PUT form failed	1	WBTC parameters
AP 410F	DFHWBLT	Exc	READ 3270 failed	1	WBTC parameters
AP 4110	DFHWBLT	Exc	WRITE 3270 failed	1	WBTC parameters
AP 4111	DFHWBLT	Exc	Get HTML failed	1	WBTC parameters
AP 4112	DFHWBLT	Exc	Store state data failed	1	WBST parameters
AP 4113	DFHWBLT	Exc	Retrieve state data failed	1	WBST parameters
AP 4114	DFHWBLT	Exc	Query partner failed	1	WBST parameters
AP 4115	DFHWBLT	Exc	Destroy handle failed	1	WBTC parameters
AP 4116	DFHWBLT	Exc	Break Partnership failed	1	WBST parameters
AP 4117	DFHWBLT	Exc	ASSIGN failed	1	DFHEIB
AP 4118	DFHWBLT	Exc	RECEIVE map failed	1	WBTC parameters
AP 4119	DFHWBLT	Exc	SEND map failed	1	WBTC parameters
AP 411A	DFHWBLT	Exc	Initialize environment error	1	WBTC parameters
AP 4200	DFHWBTTA	WB 1	Entry	None	
AP 4201	DFHWBTTA	WB 1	Exit	None	
AP 4203	DFHWBTTA	Exc	Make Partnership failed	1	WBST parameters
AP 4204	DFHWBTTA	Exc	Initialize Partnership failed	1	WBST parameters
AP 4205	DFHWBTTA	Exc	Query Partner failed	1	WBST parameters
AP 4206	DFHWBTTA	Exc	Create state block failed	1	WBST parameters
AP 4207	DFHWBTTA	Exc	Destroy state block failed	1	WBST parameters
AP 4208	DFHWBTTA	Exc	Retrieve state data failed	1	WBST parameters
AP 4209	DFHWBTTA	Exc	Break Partnership failed	1	WBST parameters

Table 81. Web trace points (continued)

Point ID	Module	Lvl	Type	Data	
AP 420A	DFHWBTTA	Exc	Trigger Partner failed	1	WBST parameters
AP 420B	DFHWBTTA	Exc	Wait for Partner failed	1	WBST parameters
AP 420C	DFHWBTTA	Exc	Terminate Partnership failed	1	WBST parameters
AP 420D	DFHWBTTA	Exc	Bridge start failed	1	Bridge_definitions
AP 420E	DFHWBTTA	Exc	No aid found	1	HTML form
AP 420F	DFHWBTTA	Exc	No next transaction id	1	HTML form
AP 4210	DFHWBTTA	Exc	LOCATE and LOCK failed	1	Bridge_definitions
AP 4211	DFHWBTTA	Exc	Inquire trandef failed	1	Bridge_definitions
AP 4212	DFHWBTTA	Exc	UNLOCK trandef failed	1	Bridge_definitions
AP 4213	DFHWBTTA	Exc	Store state data failed	1	WBST parameters
AP 4300	DFHWBC01	WB 1	Entry	None	
AP 4301	DFHWBC01	WB 1	Exit	None	
AP 4303	DFHWBC01	Exc	Invalid GWA length	1 2	DFHWBCMC HTTP GWA
AP 4304	DFHWBC01	Exc	EXTRACT error	1	DFHWBCMC
AP 4305	DFHWBC01	Exc	CWBM running	1	DFHWBCMC
AP 4306	DFHWBC01	Exc	TRUE enabled without CWBM	1	DFHWBCMC
AP 4307	DFHWBC01	Exc	ASSIGN failed	1	DFHWBCMC
AP 4308	DFHWBC01	Exc	Invalid terminal	1	DFHWBCMC
AP 4309	DFHWBC01	Exc	REGISTER error	1	DFHWBCMC
AP 430A	DFHWBC01	Exc	GETMAIN buffer error	1	DFHWBCMC
AP 430B	DFHWBC01	Exc	RECEIVE error	1	DFHWBCMC
AP 430C	DFHWBC01	Exc	RETRIEVE error	1	DFHWBCMC
AP 430D	DFHWBC01	Exc	Invalid STARTCODE	1	DFHWBCMC
AP 4330	DFHWBC03	WB 1	Entry	1	DFHWBCMC
AP 4331	DFHWBC03	WB 1	Exit	1	DFHWBCMC
AP 4333	DFHWBC03	Exc	ENQ error	1 2	DFHWBCMC EIBRESP
AP 4334	DFHWBC03	Exc	DEQ error	1 2	DFHWBCMC EIBRESP

Table 81. Web trace points (continued)

Point ID	Module	Lvl	Type	Data	
AP 4340	DFHWBC04	WB 1	Entry	1	DFHWBCMC
AP 4341	DFHWBC04	WB 1	Exit	1	DFHWBCMC
AP 4343	DFHWBC04	WB 1	Entry	1	DFHWBCMC
AP 4344	DFHWBC04	WB 1	Exit	1	DFHWBCMC
AP 4345	DFHWBC04	Exc	Update DEQ error	1 2 3	DFHWBCMC DFHWBGWC EIBRESP
AP 4346	DFHWBC04	Exc	Update ENQ error	1 2 3	DFHWBCMC DFHWBGWC EIBRESP
AP 4347	DFHWBC04	Exc	ASSIGN error	1	DFHWBCMC
AP 4360	DFHWBC09	WB 1	Entry	1	DFHWBCMC
AP 4361	DFHWBC09	WB 1	Exit	1	DFHWBCMC
AP 4363	DFHWBC09	Exc	READ error	1 2	DFHWBCMC DFHEIB
AP 4364	DFHWBC09	Exc	WRITE error	1 2	DFHWBCMC DFHWBCMC (dataset definition)
AP 4365	DFHWBC09	Exc	READ update error	1 2	DFHWBCM DFHWBCMC (dataset definition)
AP 4366	DFHWBC09	Exc	WRITE update error	1 2	DFHWBCM DFHWBCMC (dataset definition)
AP 4370	DFHWBC0B	WB 1	Entry	1	DFHWBCMC
AP 4371	DFHWBC0B	WB 1	Exit	1	DFHWBCMC
AP 4373	DFHWBC0B	Exc	WRITE queue error	1 2	DFHEIB DFHWBCMC
AP 4374	DFHWBC0B	Exc	SEND message error	1 2	DFHEIB DFHWBCMC
AP 4376	DFHWBC0B	WB 1	Display errors entry	1	DFHWBCMC
AP 4377	DFHWBC0B	WB 1	Display errors exit	1	DFHWBCMC
AP 4378	DFHWBC0B	WB 1	Help panels entry	1	DFHWBCMC
AP 4379	DFHWBC0B	WB 1	Help panels exit	1	DFHWBCMC

Table 81. Web trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 437A	DFHWBC0B	Exc	EXTRACT EXIT error	1 DFHWBCMC 2 DFHEIB
AP 437B	DFHWBC0B	Exc	Invalid GWA length	1 DFHWBCMC 2 DFHEIB
AP 437C	DFHWBC0B	Exc	Invalid GWA detected	1 DFHWBCMC 2 DFHEIB
AP 437D	DFHWBC0B	Exc	GETMAIN buffer error	1 DFHWBCMC 2 DFHEIB
AP 43A0	DFHWBC42	WB 1	Entry	1 DFHWBCMC
AP 43A1	DFHWBC42	WB 1	Exit	1 DFHWBCMC
AP 43A3	DFHWBC42	Exc	INQUIRE SECURITYMGR error	1 DFHWBCMC
AP 43A4	DFHWBC42	Exc	Update ENQ error	1 DFHWBCMC 2 DFHWBGWC 3 EIBRESP
AP 43A5	DFHWBC42	Exc	Update DEQ error	1 DFHWBCMC 2 DFHWBGWC 3 EIBRESP
AP 43A6	DFHWBC42	Exc	ENABLE EXIT error	1 DFHEIB 2 DFHWBCMC
AP 43A7	DFHWBC42	Exc	EXTRACT EXIT error	1 DFHEIB 2 DFHWBCMC 3 DFHWBGWC
AP 43A8	DFHWBC42	Exc	Invalid GWA status	1 DFHWBGWC
AP 43A9	DFHWBC42	Exc	START CWBM failed	1 DFHEIB 2 DFHWBCMC 3 DFHWBGWC
AP 43AA	DFHWBC42	Exc	DISABLE TRUE error	1 DFHEIB 2 DFHWBCMC
AP 43AB	DFHWBC42	Exc	Dump update error	1 DFHEIB 2 DFHWBCMC
AP 4400	DFHWBWB	WB 1	Entry	1 WBWB parameters
AP 4401	DFHWBWB	WB 1	Exit	1 WBWB parameters
AP 4402	DFHWBWB	Exc	WBWB recovery	1 WBWB parameters 2 Kernel error data
AP 4403	DFHWBWB	Exc	Invalid format	1 WBWB parameters
AP 4404	DFHWBWB	Exc	Invalid function	1 WBWB parameters

Table 81. Web trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 4406	DFHWBWB	Event	Call	1 HTTP parameters 2 PIFI token 3 DFHWBCGC
AP 4407	DFHWBWB	Event	Return	1 HTTP parameters 2 PIFI token 3 DFHWBCGC 4 PIFI return code
AP 4408	DFHWBWB	Exc	Invalid GWA	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 4409	DFHWBWB	Exc	Init error	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 440A	DFHWBWB	Exc	No storage	1 WBWB parameters
AP 440B	DFHWBWB	Exc	Socket error	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 440C	DFHWBWB	Exc	GETHOSTID error	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 440D	DFHWBWB	Exc	Port in use	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 440E	DFHWBWB	Exc	Port not available	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 440F	DFHWBWB	Exc	BIND error	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 4410	DFHWBWB	Exc	IOCTL failed	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 4411	DFHWBWB	Exc	Logic error	1 Unknown trace point id 2 WBWB parameters 3 DFHWBCGC
AP 4412	DFHWBWB	Exc	LISTEN error	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 4413	DFHWBWB	Exc	DELETE_LOCK error	1 WBWB parameters
AP 4414	DFHWBWB	Exc	Duplicate lock error	1 WBWB parameters
AP 4415	DFHWBWB	Exc	LOCK error	1 WBWB parameters

Table 81. Web trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 4416	DFHWBWB	Exc	Bad plist	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 4419	DFHWBWB	Exc	Handle not found	1 WBWB parameters
AP 441A	DFHWBWB	Exc	SEND error	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 441C	DFHWBWB	Exc	CLOSE error	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 441D	DFHWBWB	Exc	SELECT error	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 441E	DFHWBWB	Exc	ACCEPT error	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 4420	DFHWBWB	Exc	Invalid Socket	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 4421	DFHWBWB	Exc	Connection lost	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 4422	DFHWBWB	Exc	RECEIVE storage error	1 WBWB parameters
AP 4424	DFHWBWB	Exc	SEND socket error	1 WBWB parameters
AP 4425	DFHWBWB	Exc	SEND storage error	1 WBWB parameters
AP 4426	DFHWBWB	Exc	SETSOCKOPT error	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 4427	DFHWBWB	Exc	GETHOSTBYADDR error	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 4428	DFHWBWB	Exc	RECEIVE error	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 4429	DFHWBWB	Exc	No data received	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 442A	DFHWBWB	Exc	Not HTTP request	1 WBWB parameters

Table 81. Web trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 442B	DFHWBWB	Exc	Overlength data	1 WBWB parameters 2 HTTP parameters 3 DFHWBCGC
AP 442C	DFHWBWB	Exc	Receive select error	1 WBWB parameters 2 HTTP parameters
AP 442D	DFHWBWB	Exc	GETHOSTNAME error	1 WBWB parameters 2 HTTP parameters
AP 442E	DFHWBWB	Event	PIPI Init Entry	1 WBWB parameters
AP 442F	DFHWBWB	Event	PIPI Init Exit	1 WBWB parameters
AP 4430	DFHWBWB	Event	RECEIVE Data	1 WBWB parameters
AP 4500	DFHWBM	WB 1	Entry	None
AP 4501	DFHWBM	WB 1	Exit	None
AP 4503	DFHWBM	WB 2	Client codepage input	1 Input data in ASCII
AP 4504	DFHWBM	WB 1	Input HTTP data	1 First 256 bytes
AP 4504	DFHWBM	WB 2	Input HTTP data	1 Remaining data
AP 4505	DFHWBM	WB 1	Input user data	1 First 256 bytes
AP 4505	DFHWBM	WB 2	Input user data	1 Remaining data
AP 4506	DFHWBM	Event	Analyzer request	1 Analyzer parameters
AP 4507	DFHWBM	Event	Analyzer response	1 Analyzer parameters
AP 4508	DFHWBM	Exc	DISABLE TRUE	1 DFHEIB
AP 4509	DFHWBM	Exc	Handle analyzer abend	1 Analyzer parameters 2 HTTP GWA 3 Web request block
AP 450A	DFHWBM	Exc	CICS abend (client)	1 HTTP GWA 2 Web request block
AP 450B	DFHWBM	Exc	CICS abend (noclient)	1 HTTP GWA
AP 450C	DFHWBM	Exc	EXTRACT EXIT error	1 DFHEIB
AP 450D	DFHWBM	Exc	GWA corrupt	1 HTTP GWA
AP 450E	DFHWBM	Exc	SELECT error	1 WBWB parameters 2 HTTP GWA
AP 450F	DFHWBM	Exc	Anaylzer link error	1 DFHEIB 2 HTTP GWA 3 Analyzer parameters 4 Web request block

Table 81. Web trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 4510	DFHWBM	Exc	Analyzer return error	1 Analyzer parameters 2 HTTP GWA 3 Web request block
AP 4511	DFHWBM	Exc	GETMAIN failure	1 DFHEIB 2 HTTP GWA
AP 4513	DFHWBM	Exc	WAIT MVS error	1 DSSR parameters 2 HTTP GWA
AP 4514	DFHWBM	Exc	START failure	1 DFHEIB 2 HTTP GWA 3 Web request block
AP 4515	DFHWBM	Exc	CHANGE MODE error	1 DSAT parameters 2 HTTP GWA
AP 4516	DFHWBM	Exc	Free WBWB error	1 DFHEIB
AP 4517	DFHWBM	Exc	Activate TCB error	1 DSIT parameters
AP 4518	DFHWBM	Exc	Add subpool error	1 SMAD parameters
AP 4519	DFHWBM	Exc	Load WBWB error	1 DFHEIB
AP 451A	DFHWBM	Exc	Init HTTP error	1 WBWB parameters 2 HTTP GWA
AP 451B	DFHWBM	Exc	CICS CCNV abend	1 HTTP GWA 2 Web request block
AP 4540	DFHWBA	WB 1	Entry	None
AP 4541	DFHWBA	WB 1	Exit	None
AP 4543	DFHWBA	Exc	LINK error	1 DFHEIB 2 Web request block
AP 4544	DFHWBA	Exc	STARTCODE error	1 DFHEIB
AP 4545	DFHWBA	Exc	RETRIEVE data error	1 DFHEIB
AP 4548	DFHWBA	Exc	FREEMAIN output error	1 DFHEIB
AP 454A	DFHWBA	Event	GWA check	1 Enable time 2 GWA address 3 Web request block
AP 454C	DFHWBA	WB 1	Server output data	1 First 256 bytes
AP 454D	DFHWBA	WB 2	Server output data cont	1 Remaining data
AP 454E	DFHWBA	Exc	CHANGE MODE	1 Web request block
AP 454F	DFHWBA	Exc	Return error	1 Web request block
AP 4550	DFHWBA	Exc	Main abend	1 Web request block

Table 81. Web trace points (continued)

Point ID	Module	Lvl	Type	Data	
AP 4551	DFHWBA1	Event	DECODE Request	1	DECODE parameters
AP 4552	DFHWBA1	Event	DECODE Response	1	DECODE parameters
AP 4553	DFHWBA1	Event	ENCODE Request	1	ENCODE parameters
AP 4554	DFHWBA1	Event	ENCODE Response	1	ENCODE parameters
AP 4555	DFHWBA1	Exc	LINK Terminal error	1 2	Alias parameters DFHEIB
AP 4556	DFHWBA1	Exc	LINK error	1 2	Alias parameters DFHEIB
AP 4557	DFHWBA1	Exc	Main abend	1	Alias parameters
AP 4558	DFHWBA1	Exc	Return error	1	Alias parameters
AP 4559	DFHWBA1	Exc	Corrupt client data	1	Alias parameters
AP 455A	DFHWBA1	Exc	Security error	1	Alias parameters
AP 455B	DFHWBA1	Exc	EXCEPTION error	1	Alias parameters
AP 455C	DFHWBA1	Exc	INVALID response	1	Alias parameters
AP 455D	DFHWBA1	Exc	DISASTER response	1	Alias parameters
AP 455E	DFHWBA1	Exc	Bad response	1	Alias parameters
AP 4560	DFHWBA1	Exc	Parameter error	1	WBA1 eyecatcher
AP 4561	DFHWBA1	WB 1	Entry	1	COMMAREA
AP 4562	DFHWBA1	WB 1	Exit	None	
AP 4600	DFHWBTL	WB 1	Entry	1 2	WBTL parameters WBTL symbol list
AP 4601	DFHWBTL	WB 1	Exit	1 2	WBTL parameters Original buffer
AP 4620	DFHWBENV	WB 1	Entry	None	
AP 4621	DFHWBENV	WB 1	Exit	None	
AP 4623	DFHWBENV	Exc	Invalid task number	None	
AP 4640	DFHWBST	WB 1	Entry	1	WBST parameters
AP 4641	DFHWBST	WB 1	Exit	1	WBST parameters
AP 4642	DFHWBST	Exc	Recovery	1 2	WBST parameters Kernel error data
AP 4643	DFHWBST	Exc	Invalid format	1	WBST parameters
AP 4644	DFHWBST	Exc	Invalid function	1	WBST parameters

Table 81. Web trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 4645	DFHWPBST	Exc	Wait MVS error	1 WBST parameters 2 DFHWPBSC 3 DSSR parameters
AP 4646	DFHWPBST	Exc	No storage	1 WBST parameters 2 GETMAIN return code
AP 4647	DFHWPBST	Exc	Directory update error	1 WBST parameters 2 DDDI parameters
AP 4648	DFHWPBST	Exc	State token not found	1 WBST parameters
AP 4649	DFHWPBST	Exc	Destroy state block error	1 WBST parameters 2 DFHWPBSC
AP 464A	DFHWPBST	Exc	Initialize Partnership error	1 WBST parameters 2 DFHWPBSC
AP 464B	DFHWPBST	Exc	Make Partnership error	1 WBST parameters 2 DFHWPBSC
AP 464C	DFHWPBST	Exc	Break Partnership error	1 WBST parameters 2 DFHWPBSC
AP 464D	DFHWPBST	Exc	Trigger Partner error	1 WBST parameters 2 DFHWPBSC
AP 464E	DFHWPBST	Exc	Wait for partner error	1 WBST parameters 2 DFHWPBSC
AP 464F	DFHWPBST	Exc	Wait on ECB error	1 WBST parameters 2 DFHWPBSC
AP 4650	DFHWPBST	Exc	Query partner error	1 WBST parameters 2 DFHWPBSC
AP 4651	DFHWPBST	Exc	Terminate Partnership error	1 WBST parameters 2 DFHWPBSC
AP 4652	DFHWPBST	Exc	LOCK error	1 WBST parameters 2 LMLM parameters
AP 4653	DFHWPBST	Exc	UNLOCK error	1 WBST parameters 2 LMLM parameters
AP 4654	DFHWPBST	Exc	Directory browse error	1 WBST parameters 2 DDBR parameters
AP 4655	DFHWPBST	Event	Pre-garbage collect	1 WBST parameters 2 State token 3 DFHWPBSC
AP 4656	DFHWPBST	Event	Pre-garbage terminate	1 WBST parameters 2 DFHWPBSC

Table 81. Web trace points (continued)

Point ID	Module	Lvl	Type	Data
AP 4657	DFHWBST	Event	Post-garbage terminate	1 WBST parameters 2 DFHWBSTC
AP 4670	DFHWBGB	WB 1	Entry	None
AP 4671	DFHWBGB	WB 1	Exit	None
AP 4680	DFHWBTC	WB 1	Entry	1 WBTC parameters
AP 4681	DFHWBTC	WB 1	Exit	1 WBTC parameters
AP 4682	DFHWBTC	Exc	Recovery	1 WBTC parameters 2 Kernel error data
AP 4683	DFHWBTC	Exc	Invalid format	1 WBTC parameters
AP 4684	DFHWBTC	Exc	Invalid function	1 WBTC parameters
AP 4685	DFHWBTC	Exc	CEEPIPI error	1 WBTC parameters 2 Terminal emulator interface
AP 4686	DFHWBTC	Exc	Emulator error	1 WBTC parameters 2 Terminal emulator interface
AP 4687	DFHWBTC	Exc	BMS map not found	1 WBTC parameters
AP 4688	DFHWBTC	Exc	BMS adsd not found	1 WBTC parameters
AP 4689	DFHWBTC	Exc	Template manager error	1 WBTC parameters

User exit routines

Table 82. User exit routines

Point ID	Module	Lvl	Type	Data
AP D500	DFHUEH	UE 1	Before exit call	1 Exit ID 2 Exit program name
AP D501	DFHUEH	UE 1	After exit call	1 Return code 2 Address of EPB 3 Exit program name
AP D502	DFHSUEX	UE 1	Before exit call	1 Exit ID 2 Exit program name
AP D503	DFHSUEX	UE 1	After exit call	1 Return code 2 Address of EPB 3 Exit program name
AP D504	DFHSUEX	Exc	Invalid function	1 DFHSUEX parameter list
AP D505	DFHSUEX	Exc	Invalid format	1 DFHSUEX parameter list

Table 82. User exit routines (continued)

Point ID	Module	Lvl	Type	Data
AP D506	DFHSUEX	Exc	Clear error during recovery	1 PGEX_RESPONSE 2 PGEX_REASON 3 Program token 4 PLCB
AP D507	DFHSUEX	Exc	Prepare exit error	1 PGEX_RESPONSE 2 PGEX_REASON 3 Program token 4 PLCB
AP D508	DFHSUEX	Exc	Clear exit error	1 PGEX_RESPONSE 2 PGEX_REASON 3 Program token 4 PLCB
AP D509	DFHUEH	Exc	Prepare exit error	1 PGEX_RESPONSE 2 PGEX_REASON 3 Program token 4 PLCB
AP D50A	DFHUEH	Exc	Clear exit error	1 PGEX_RESPONSE 2 PGEX_REASON 3 Program token 4 PLCB
AP D50B	DFHUEH	Exc	Clear error during recovery	1 PGEX_RESPONSE 2 PGEX_REASON 3 Program token 4 PLCB
AP D50C	DFHSUEX	Exc	Switch subspace call failed	1 DFHSUEX parameter list
AP D50D	DFHUEH	UE 1	Handle abend exit modified address	1 Branch address 2 Program name
AP D50E	DFHUEH	Exc	Recovery	1 DFHUEPAR parameter list 2 Kernel error data
AP D50F	DFHSUEX	Exc	Recovery	1 DFHSUEX parameter list 2 Kernel error data 3 Name of program in error
AP D510	DFHAPEX	AP 1	Entry	1 DFHAPEX parameter list
AP D511	DFHAPEX	AP 2	Entry part 1	Up to 200 bytes of each exit parameter: 1 Exit parameter 1 2 Exit parameter 2 3 Exit parameter 3 4 Exit parameter 4 5 Exit parameter 5 6 Exit parameter 6 7 Exit parameter 7

Table 82. User exit routines (continued)

Point ID	Module	Lvl	Type	Data
AP D512	DFHAPEX	AP 2	Entry part 2	Up to 200 bytes of each exit parameter: 1 Exit parameter 8 2 Exit parameter 9 3 Exit parameter 10 4 Exit parameter 11 5 Exit parameter 12 6 Exit parameter 13 7 Exit parameter 14
AP D513	DFHAPEX	Exc	Invalid function	1 DFHAPEX parameter list
AP D514	DFHAPEX	Exc	Invalid format	1 DFHAPEX parameter list
AP D515	DFHAPEX	AP 1	Exit	1 DFHAPEX parameter list
AP D516	DFHAPEX	AP 2	Exit part 1	Up to 200 bytes of each exit parameter: 1 Exit parameter 1 2 Exit parameter 2 3 Exit parameter 3 4 Exit parameter 4 5 Exit parameter 5 6 Exit parameter 6 7 Exit parameter 7
AP D517	DFHAPEX	AP 2	Exit part 2	Up to 200 bytes of each exit parameter: 1 Exit parameter 8 2 Exit parameter 9 3 Exit parameter 10 4 Exit parameter 11 5 Exit parameter 12 6 Exit parameter 13 7 Exit parameter 14
AP D518	DFHAPEX	Exc	Change mode request failed	1 DFHAPEX parameter list
AP D519	DFHAPEX	Exc	Invalid exit	1 DFHAPEX parameter list
AP D51A	DFHAPEX	Exc	User exit program failed, part 1	Up to 200 bytes of each exit parameter: 1 Exit parameter 1 2 Exit parameter 2 3 Exit parameter 3 4 Exit parameter 4 5 Exit parameter 5 6 Exit parameter 6 7 Exit parameter 7
AP D51B	DFHAPEX	Exc	User exit program failed, part 2	Up to 200 bytes of each exit parameter: 1 Exit parameter 8 2 Exit parameter 9 3 Exit parameter 10 4 Exit parameter 11 5 Exit parameter 12 6 Exit parameter 13 7 Exit parameter 14
AP D51C	DFHAPEX	Exc	Call to invoke user exit program failed	1 DFHAPEX parameter list

Table 82. User exit routines (continued)

Point ID	Module	Lvl	Type	Data
AP D51D	DFHAPEX	Exc	Restore mode request failed	1 DFHAPEX parameter list
AP D51F	DFHAPEX	Exc	Recovery	1 DFHAPEX parameter list 2 Kernel error data
AP D522	DFHUEM	Exc	Recovery	1 EIB 2 Kernel error data
AP D523	DFHERM	Exc	Clear error during recovery	1 PGEX_RESPONSE 2 PGEX_REASON 3 Program token 4 PLCB
AP D524	DFHERM	Exc	Recovery	1 DFHUEPAR parameter list 2 Kernel error data
AP D525	DFHERM	EI 1	Handle abend exit modified address	1 Branch address 2 Program name
AP D530	DFHUEIQ	UE 1	Before inquire exit program	1 DFHUEIQ parameter list
AP D531	DFHUEIQ	UE 1	After inquire exit program	1 DFHUEIQ parameter list
AP D532	DFHUEIQ	Exc	Recovery	1 DFHUEIQ parameter list 2 Kernel error data

Cancel start requests

The trace entries in the following table support the function that allows you to cancel AID control blocks on the AID chain.

Table 83. Cancel AID trace entries

Point ID	Module	Lvl	Type	Data
AP D600	DFHALP	AP 1	Entry	1 DFHALP parameter list
AP D601	DFHALP	AP 1	Exit	1 DFHALP parameter list
AP D602	DFHALP	AP 1	Cancel AID entry	1 Address of cancelled AID 2 AID
AP D603	DFHALP	AP 1	DFHALP recovery invoked	1 DFHALP parameter list
AP D610	DFHALRC	AP 1	Entry	1 Parameter list (RMRO, RMKP, RMDE, ROIN)
AP D611	DFHALRC	AP 1	Exit	1 Parameter list (RMRO, RMKP, RMDE, ROIN)
AP D612	DFHALRC	Exc	Recovery	1 Parameter list 2 Kernel error data
AP D613	DFHALRC	Exc	Invalid format	1 Parameter list

Table 83. Cancel AID trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP D614	DFHALRC	Exc	Invalid function	1 Parameter list

Syncpoint program

Table 84. Syncpoint program

Point ID	Module	Lvl	Type	Data
AP D802	DFHSPP	AP 1	Entry	1 Syncpoint request byte 1 2 Backout required program state
AP D803	DFHSPP	SP 1	Exit	1 Return code

Function shipping data transformation

Table 85. Function shipping data transformation

Point ID	Module	Lvl	Type	Data
AP D900	DFHXFP	IS 1	Entry	1 Address of PLIST (4 bytes) Transformer number (1 byte) X'00' transform 1 X'02' transform 2 X'04' transform 3 X'06' transform 4 Error code (2 bytes) X'0000' on entry EXEC group/function code (EIBFN) (2 bytes)
AP D901	DFHXFP	IS 1	Exit	1 Address of PLIST (4 bytes) Transformer number (1 byte) Code type (error code — 2 bytes) X'0800' transform 1 error X'0004' transform 2 error EXEC group/function code (EIBFN) (2 bytes)
AP D902	DFHXFX	IS 1	Entry	1 Address of PLIST (4 bytes) Transformer number (1 byte) values as AP D900 Error code (2 bytes) X'0000' on entry EXEC group/function code (EIBFN) (2 bytes)
AP D903	DFHXFX	IS 1	Exit	1 Address of PLIST (4 bytes) Transformer number (1 byte) Code type (error code — 2 bytes) X'0800' transform 1 error EXEC group/function code (EIBFN) (2 bytes)

AP domain statistics gathering

Table 86. AP domain statistics gathering

Point ID	Module	Lvl	Type	Data
AP DA00	DFHAPST	AP 1	Entry	1 STST Parameter list
AP DA01	DFHAPST	AP 1	Exit	1 STST Parameter list
AP DA02	DFHSTDT	AP 1	Entry	1 APST-STxx parameter list
AP DA03	DFHSTDT	AP 1	Exit	1 APST-STxx parameter list
AP DA04	DFHSTFC	AP 1	Entry	1 APST-STxx parameter list
AP DA05	DFHSTFC	AP 1	Exit	1 APST-STxx parameter list
AP DA06	DFHSTIB	AP 1	Entry	1 APST-STxx parameter list
AP DA07	DFHSTIB	AP 1	Exit	1 APST-STxx parameter list
AP DA08	DFHSTJC	AP 1	Entry	1 APST-STxx parameter list
AP DA09	DFHSTJC	AP 1	Exit	1 APST-STxx parameter list
AP DA0A	DFHSTKC	AP 1	Entry	1 APST-STxx parameter list
AP DA0B	DFHSTKC	AP 1	Exit	1 APST-STxx parameter list
AP DA0C	DFHSTLK	AP 1	Entry	1 APST-STxx parameter list
AP DA0D	DFHSTLK	AP 1	Exit	1 APST-STxx parameter list
AP DA0E	DFHSTLS	AP 1	Entry	1 APST-STxx parameter list
AP DA0F	DFHSTLS	AP 1	Exit	1 APST-STxx parameter list
AP DA10	DFHSTTD	AP 1	Entry	1 APST-STxx parameter list
AP DA11	DFHSTTD	AP 1	Exit	1 APST-STxx parameter list
AP DA12	DFHSTTM	AP 1	Entry	1 APST-STxx parameter list
AP DA13	DFHSTTM	AP 1	Exit	1 APST-STxx parameter list
AP DA14	DFHSTTN	AP 1	Entry	1 APST-STxx parameter list
AP DA15	DFHSTTN	AP 1	Exit	1 APST-STxx parameter list
AP DA16	DFHSTTR	AP 1	Entry	1 APST-STxx parameter list
AP DA17	DFHSTTR	AP 1	Exit	1 APST-STxx parameter list
AP DA18	DFHSTTS	AP 1	Entry	1 APST-STxx parameter list
AP DA19	DFHSTTS	AP 1	Exit	1 APST-STxx parameter list

Table 86. AP domain statistics gathering (continued)

Point ID	Module	Lvl	Type	Data
AP DA1C	DFHAPST	Exc	Recovery (purged)	1 STST parameter list 2 Kernel error data
AP DA1D	DFHAPST	Exc	Recovery (looping)	1 STST parameter list 2 Kernel error data
AP DA1E	DFHAPST	Exc	Recovery (abend)	1 STST parameter list 2 Kernel error data
AP DA24	DFHAPST	Exc	Invalid format	1 STST parameter list
AP DA25	DFHAPST	Exc	Invalid function	1 STST parameter list
AP DA32	DFHSTDT	Exc	Recovery (looping)	1 APST-STxx parameter list 2 Kernel error data
AP DA33	DFHSTDT	Exc	Recovery (abend)	1 APST-STxx parameter list 2 Kernel error data
AP DA34	DFHSTDT	Exc	Recovery (macro failure)	1 APST-STxx parameter list 2 Kernel error data 3 Macro_call
AP DA36	DFHSTDT	Exc	Invalid function	1 APST-STxx parameter list
AP DA37	DFHSTDT	Exc	Invalid format	1 APST-STxx parameter list
AP DA38	DFHSTFC	Exc	Recovery (looping)	1 APST-STxx parameter list 2 Kernel error data
AP DA39	DFHSTFC	Exc	Recovery (abend)	1 APST-STxx parameter list 2 Kernel error data
AP DA3A	DFHSTFC	Exc	Recovery (macro failure)	1 APST-STxx parameter list 2 Kernel error data 3 Macro_call
AP DA3B	DFHSTFC	Exc	Invalid format	1 APST-STxx parameter list
AP DA3C	DFHSTFC	Exc	Invalid function	1 APST-STxx parameter list
AP DA3E	DFHSTIB	Exc	Recovery (macro failure)	1 APST-STxx parameter list 2 Kernel error data 3 Macro_call
AP DA3F	DFHSTIB	Exc	Recovery (looping)	1 APST-STxx parameter list 2 Kernel error data
AP DA40	DFHSTIB	Exc	Recovery (abend)	1 APST-STxx parameter list 2 Kernel error data
AP DA41	DFHSTIB	Exc	Invalid format	1 APST-STxx parameter list
AP DA42	DFHSTIB	Exc	Invalid function	1 APST-STxx parameter list

Table 86. AP domain statistics gathering (continued)

Point ID	Module	Lvl	Type	Data
AP DA44	DFHSTJC	Exc	Recovery (looping)	1 APST-STxx parameter list 2 Kernel error data
AP DA45	DFHSTJC	Exc	Recovery (abend)	1 APST-STxx parameter list 2 Kernel error data
AP DA46	DFHSTJC	Exc	Recovery (macro failure)	1 APST-STxx parameter list 2 Kernel error data 3 Macro_call
AP DA47	DFHSTJC	Exc	Invalid function	1 APST-STxx parameter list
AP DA48	DFHSTJC	Exc	Invalid format	1 APST-STxx parameter list
AP DA4A	DFHSTKC	Exc	Recovery (looping)	1 APST-STxx parameter list 2 Kernel error data
AP DA4B	DFHSTKC	Exc	Recovery (abend)	1 APST-STxx parameter list 2 Kernel error data
AP DA4C	DFHSTKC	Exc	Recovery (macro failure)	1 APST-STxx parameter list 2 Kernel error data 3 Macro_call
AP DA4D	DFHSTKC	Exc	Invalid function	1 APST-STxx parameter list
AP DA4E	DFHSTKC	Exc	Invalid format	1 APST-STxx parameter list
AP DA50	DFHSTLK	Exc	Recovery (macro failure)	1 APST-STxx parameter list 2 Kernel error data 3 Macro_call
AP DA51	DFHSTLK	Exc	Recovery (looping)	1 APST-STxx parameter list 2 Kernel error data
AP DA52	DFHSTLK	Exc	Recovery (abend)	1 APST-STxx parameter list 2 Kernel error data
AP DA53	DFHSTLK	Exc	Invalid format	1 APST-STxx parameter list
AP DA54	DFHSTLK	Exc	Invalid function	1 APST-STxx parameter list
AP DA56	DFHSTLS	Exc	Recovery (looping)	1 APST-STxx parameter list 2 Kernel error data
AP DA57	DFHSTLS	Exc	Recovery (abend)	1 APST-STxx parameter list 2 Kernel error data
AP DA58	DFHSTLS	Exc	Recovery (macro failure)	1 APST-STxx parameter list 2 Kernel error data 3 Macro_call
AP DA59	DFHSTLS	Exc	Invalid format	1 APST-STxx parameter list
AP DA5A	DFHSTLS	Exc	Invalid function	1 APST-STxx parameter list

Table 86. AP domain statistics gathering (continued)

Point ID	Module	Lvl	Type	Data
AP DA5C	DFHSTTD	Exc	Recovery (looping)	1 APST-STxx parameter list 2 Kernel error data
AP DA5D	DFHSTTD	Exc	Recovery (abend)	1 APST-STxx parameter list 2 Kernel error data
AP DA5E	DFHSTTD	Exc	Recovery (macro failure)	1 APST-STxx parameter list 2 Kernel error data 3 Macro_call
AP DA5F	DFHSTTD	Exc	Invalid function	1 APST-STxx parameter list
AP DA60	DFHSTTD	Exc	Invalid format	1 APST-STxx parameter list
AP DA61	DFHSTTD	Exc	Buffer too small	1 APST-STxx parameter List
AP DA63	DFHSTTM	Exc	Recovery (looping)	1 APST-STxx parameter list 2 Kernel error data
AP DA64	DFHSTTM	Exc	Recovery (abend)	1 APST-STxx parameter list 2 Kernel error data
AP DA65	DFHSTTM	Exc	Invalid format	1 APST-STxx parameter list
AP DA66	DFHSTTM	Exc	Invalid function	1 APST-STxx parameter list
AP DA68	DFHSTTN	Exc	Recovery (looping)	1 APST-STxx parameter list 2 Kernel error data
AP DA69	DFHSTTN	Exc	Recovery (abend)	1 APST-STxx parameter list 2 Kernel error data
AP DA6A	DFHSTTN	Exc	Recovery (macro failure)	1 APST-STxx parameter list 2 Kernel error data 3 Macro_call
AP DA6B	DFHSTTN	Exc	Invalid format	1 APST-STxx parameter list
AP DA6C	DFHSTTN	Exc	Invalid function	1 APST-STxx parameter list
AP DA6E	DFHSTTR	Exc	Recovery (macro failure)	1 APST-STxx parameter list 2 Kernel error data 3 Macro_call
AP DA6F	DFHSTTR	Exc	Recovery (looping)	1 APST-STxx parameter list 2 Kernel error data
AP DA70	DFHSTTR	Exc	Recovery (abend)	1 APST-STxx parameter list 2 Kernel error data
AP DA71	DFHSTTR	Exc	Invalid format	1 APST-STxx parameter list
AP DA72	DFHSTTR	Exc	Invalid function	1 APST-STxx parameter list
AP DA73	DFHSTTR	Exc	Invalid resource type	1 APST-STxx parameter list

Table 86. AP domain statistics gathering (continued)

Point ID	Module	Lvl	Type	Data
AP DA74	DFHSTTS	Exc	Recovery (macro failure)	1 APST-STxx parameter list 2 Kernel error data 3 Macro_call
AP DA75	DFHSTTS	Exc	Recovery (looping)	1 APST-STxx parameter list 2 Kernel error data
AP DA76	DFHSTTS	Exc	Recovery (abend)	1 APST-STxx parameter list 2 Kernel error data
AP DA77	DFHSTTS	Exc	Invalid format	1 APST-STxx parameter list
AP DA78	DFHSTTS	Exc	Invalid format	1 APST-STxx parameter list
AP DA80	DFHSII1	Exc	Add gate APST error	1 KEDD parameter list

Transaction routing data transformation

Table 87. Transaction routing data transformation

Point ID	Module	Lvl	Type	Data
AP DB00	DFHXTP	IS 1	Entry	1 Address of DFHXTSTG (4 bytes) Address of TCTTE (4 bytes) Transformer number (1 byte) X'00' transform 1 X'02' transform 2 X'04' transform 3 X'06' transform 4 Status code (1 byte) X'10' flush X'20' detach X'40' attach X'80' appl request
AP DB01	DFHXTP	IS 1	Exit	1 Address of DFHXTSTG (4 bytes) Address of TCTTE (4 bytes) Transformer number (1 byte) Status code (1 byte) X'00' normal response X'08' error response

IRC commands

Table 88. IRC commands

Point ID	Module	Lvl	Type	Data
AP DD00	DFHCRSP	IS 1	After DFHIR TYPE=LOGON	1 Logon flags, IRVCLGFL 2 Applid, IRVCLGIM 3 Userid, IRVCUSID 4 Address of SLCB, IRVCLGSL 5 Return code (see page "IRC command return codes" on page 260) 6 Reason code 6 Reason code
AP DD01	DFHCRSP	IS 2	After DFHIR TYPE=LOGON	1 Maxusers arg, IRVCLGMU (logon connections list - see LCL)
AP DD02	DFHCRSP	IS 1	After DFHIR TYPE=QUIESCE	1 Userid, IRVCUSID 2 Return code (see page "IRC command return codes" on page 260) 3 Reason code
AP DD03	DFHCRSP	IS 1	After DFHIR TYPE=LOGOFF	1 Userid, IRVCUSID 2 Return code (see page "IRC command return codes" on page 260) 3 Reason code
AP DD04	DFHCRSP	IS 1	After DFHIRP level check	1 Return code (1) 2 Caller's level ID 3 DFHIRP's level ID
AP DD11	DFHCRNP	IS 1	After DFHIR TYPE=PULL	1 Address of SCCB, CRSCCBEN 2 Applid of connectee, SCCBCNAM 3 Userid, IRVCUSID 4 Threadid, IRVCTHID 5 Return code (see page "IRC command return codes" on page 260) 6 Reason code
AP DD12	DFHCRNP	IS 2	Allocation of session TCTTE	1 Address of SCCB, CRSCCBEN 2 Applid of connectee, SCCBCNAM 3 Address of session TCTTE 4 Name of session TCTTE, TCTTETI
AP DD14	DFHCRNP	IS 1	LUWID from batch CONNECT	1 LUWID, TCTESLWD
AP DD15	DFHCRNP	IS 1	Inbound RH	1 Inbound RH, TCTESRHI 2 Inbound physical sequence number, TCTESQIP

Table 88. IRC commands (continued)

Point ID	Module	Lvl	Type	Data
AP DD16	DFHCRNP	IS 2	Inbound RU	1 RU length 2 First 2000 bytes of RU (if RU > 4000 bytes), else all RU 3 Final 2000 bytes of RU of RU (if RU > 4000 bytes), else none or 2, 3 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'
AP DD17	DFHCRNP	IS 1	After DFHIR TYPE=CONNECT	1 Address of session TCTTE 2 Userid, IRVCUSID 3 Threadid, IRVCTHID 4 Applid of connect-system, IRVCCNTO 5 Address of SCCB, IRVCCNSC 6 Return code (see page "IRC command return codes" on page 260) 7 Reason code
AP DD18	DFHCRNP	IS 1	MRO control task CSNC dequeues a work element from immediate or delay work queue	1 Element type concatenated with element subtype 2 Time stamp in STCK format (8 bytes) 3 Address of SCCB, or 0 if none (4 bytes) 4 applid of associated system, or blanks if none, or '***BATCH' if batch (8 bytes) 5 Address of session TCTTE, or 0 if none (4 bytes) 6 Name of session TCTTE, or 0 if none (4 bytes) 7 Address of TIOA if work element type=X'7' or 0 otherwise (4 bytes)
AP DD19	DFHCRNP	IS 1	CSNC dequeues a redundant work element for work related to a previous use of an MRO session. The work element is that last traced by CSNC	
AP DD20	DFHZIS2	IS 1	After DFHIR TYPE=PULL	1 Address of SCCB, TCTESCCB 2 Applid of connectee, SCCBCNAM 3 Userid, IRVCUSID 4 Threadid, IRVCTHID 5 Return code (see page "IRC command return codes" on page 260) 6 Reason code

Table 88. IRC commands (continued)

Point ID	Module	Lvl	Type	Data
AP DD21	DFHZIS2	IS 1	After DFHIR TYPE=SWITCH	<p>1 Address of SCCB, TCTESCCB</p> <p>2 Applid of connectee, SCCBCNAM</p> <p>3 Type of switch, first or subsequent, IRVCSTYP</p> <p>4 Userid, IRVCUSID</p> <p>5 Threadid, IRVCTHID</p> <p>6 Return code (see page "IRC command return codes" on page 260)</p> <p>7 Reason code</p>
AP DD22	DFHZIS2	IS 1	Outbound RH	<p>1 Outbound RH, TCTESRHO</p> <p>2 Outbound physical sequence number, TCTESQOP</p> <p>3 Outbound LU6.2 style attach FMH (if present), TCTEIRTA (see DFHFMHDS)</p>
AP DD23	DFHZIS2	IS 2	Outbound RU	<p>1 RU length</p> <p>2, 3 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'</p>
AP DD24	DFHZIS2	IS 1	Inbound RH	<p>1 Inbound RH, TCTESRHI</p> <p>2 Inbound physical sequence number, TCTESQIP</p>
AP DD25	DFHZIS2	IS 2	Inbound RU	<p>1 RU length</p> <p>2, 3 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'</p>
AP DD26	DFHZIS2	IS 1	After DFHIR TYPE=DISC	<p>1 Address of SCCB, ISCRQTCT</p> <p>2 Applid of disconnectee, SCCBCNAM</p> <p>3 Userid, IRVCUSID</p> <p>4 Threadid, IRVCTHID</p> <p>5 Return code (see page "IRC command return codes" on page 260)</p> <p>6 Reason code</p>
AP DD27	DFHZIS2	IS 1	After DFHIR TYPE=QUIESCE	<p>1 Userid, IRVCUSID</p> <p>2 Function modifier, immediate or normal quiesce, IRVCSTYP</p> <p>3 Applid of system to be quiesced, IRVCCNTO</p> <p>4 Return code (see page "IRC command return codes" on page 260)</p> <p>5 Reason code</p>
AP DD28	DFHZIS2	IS 1	After DFHIR TYPE=LOGOFF	<p>1 Userid, IRVCUSID</p> <p>2 Return code (see page "IRC command return codes" on page 260)</p> <p>3 Reason code</p>

Table 88. IRC commands (continued)

Point ID	Module	Lvl	Type	Data
AP DD29	DFHZIS2	IS 1	After DFHIR TYPE=INSERT	<p>1 Userid, IRVCUSID</p> <p>2 Applid of system to be brought into service, IRVCCNTO</p> <p>3 Return code (see page "IRC command return codes" on page 260)</p> <p>4 Reason code</p>
AP DD2A	DFHZIS2	IS 1	After DFHIR TYPE=ADD	<p>1 ADD type (PREPARE, COMMIT, or ROLLBACK)</p> <p>2 Userid, IRVCUSID</p> <p>3 Applid</p> <p>4 ADD token</p> <p>5 Dynamic ADD LCL if PREPARE, otherwise return code (see below)</p> <p>6 Return code if PREPARE (see below) otherwise reason code</p> <p>7 Reason code</p>
AP DD32	DFHCRR	AP 2	Process session recovery flow	<p>1 Address of session TCTTE</p> <p>2 Session identifier</p> <p>3 ISC flags (TCTEISC1)</p> <p>4 CR_SEQ_NOS (backout input, backout output, commit input, and commit output numbers respectively)</p> <p>5 Number of leg in bind conversation commit output numbers respectively)</p> <p>6 Current value of partners' logname commit output numbers respectively)</p>
AP DD33	DFHCRR	Exc	Failure to locate profile DFHCICSA, or to ALLOCATE the session	1 TCTTE Address of session
AP DD34	DFHCRR	Exc	DFHRMNM INQUIRE_LOGNAME failure, or logname too long	1 DFHRMNM parameter list
AP DD35	DFHCRR	Exc	DFHRMNM INQUIRE_LOGNAME failure	1 DFHRMNM parameter list
AP DD36	DFHCRR	Exc	XLN data missing from input datastream	1 Input TIOA
AP DD37	DFHCRR	Exc	Invalid XLN data in input datastream	1 Input TIOA
AP DD38	DFHCRR	Exc	DFHRMLNM INITIATE_RECOVERY failure	1 DFHRMLNM parameter list
AP DD39	DFHCRR	Exc	DFHRMLNM SET_RECOVERY failure	1 DFHRMLNM parameter list
AP DD3A	DFHCRR	Exc	DFHRMLNM TERMINATE_RECOVERY failure	1 DFHRMLNM parameter list
AP DD3B	DFHCRR	Exc	Input datastream responding to second XLN flow is invalid	1 Input TIOA
AP DD3C	DFHCRR	Exc	DFHTC WRITE or READ request failure on attempt to perform session I/O	1 Address of session TCTTE

Table 88. IRC commands (continued)

Point ID	Module	Lvl	Type	Data	
AP DD3D	DFHCRR	Exc	DFHRMNM CLEAR_PENDING failure	1	DFHRMNM parameter list
AP DD3E	DFHCRR	Exc	DFHRMNM SET_LOGNAME failure	1	DFHRMNM parameter list
AP DD3F	DFHCRR	Exc	Recovery	1	Original abend code

IRC command return codes

IRC command return codes are as follows:

- X'04' Invalid function requested
- X'08' User not authorized to use SVC
- X'0C' Environment incorrect or secondary to primary converter
- X'10' Invalid user number
- X'14' Invalid user identification
- X'18' Invalid LCB address (internal error)
- X'1C' Invalid thread number
- X'20' Invalid thread ID
- X'24' Set footprint failed
- X'34' No SCTE in the SVA
- X'38' No free LACBE for logon
- X'3C' Duplicate logon
- X'40' Maximum logons already reached
- X'48' GETMAIN failed LACB storage
- X'4C' GETMAIN failed SUDB storage
- X'50' GETMAIN failed LCB/CCB storage
- X'54' GETMAIN failed SLCB/SCCB storage
- X'58' LCB not on SUDB chain
- X'5C' System not logged on
- X'60' System not connectable
- X'64' GETMAIN failed CSB storage
- X'68' Secondary system not in primary LCB
- X'6C' No secondary CCB; found for primary system
- X'70' Secondary is in-quiesce
- X'74' Primary system not in secondary LCB
- X'78' No primary CCB found for secondary system
- X'7C' Primary is in-quiesce
- X'80' No primary CCB; retry request
- X'84' Link is already disconnected
- X'88' Other side cannot receive data
- X'8C' This side cannot send data
- X'90' Other side cannot be pulled from
- X'94' This side cannot pull data
- X'98' There is no pull pending
- X'9C' No data to be pulled (internal error)
- X'A0' LCB is in-quiesce
- X'A4' Target system not found in LCB
- X'A8' CSB cannot be found
- X'AC' Link is not connected
- X'B0' Security check failed
- X'B4' Attempt to schedule an SRB/subtask failed
- X'B8' GETMAIN failed for SRB storage
- X'BC' "Special" abend (for example, bad ECB)
- X'C0' Invalid argument or parameter addr
- X'C4' Invalid address in parameter list

X'C8' Invalid address in data list
X'CC' Load of DFHACEE failed
X'D0' GETMAIN failed for transfer buffer
X'D4' GETMAIN failed for SSVT, SCTE, workarea
X'D8' Subsystem notification error
X'DC' Invalid target for data movement
X'E0' Internal logic error
X'E4' GETMAIN failed for use count array
X'E8' Nonzero AX value currently set
X'EC' GETMAIN failed for logon connections list
X'F0' Connect SRB ATSET failed
X'F4' No free entries in AX array or
 No free entries in LX array or
 Cross memory environment error
X'F8' Total data length invalid for switch or pull
X'FC' M/C check paging I/O or data error
X'100' Bad name supplied for interregion work exit
X'104' Load failed for interregion work exit
X'108' Interregion work exit has bad format

EXEC interface

Table 89. Exec Interface

Point ID	Module	Lvl	Type	Data	
AP E110	DFHEISR	AP 2	Entry	1	EISR parameter list
AP E111	DFHEISR	AP 2	Exit	1	EISR parameter list
AP E112	DFHEISR	Exc	Recovery	1 2	EISR parameter list Kernel error data
AP E113	DFHEISR	Exc	Storage not within DSA	1	EISR parameter list
AP E114	DFHEISR	Exc	INQUIRE_ACCESS request failed	1 2	EISR parameter list SMSR parameter list
AP E115	DFHEISR	Exc	Invalid function	1	EISR parameter list
AP E116	DFHEISR	Exc	GETMAIN request failed	1 2	EISR parameter list SMMC parameter list
AP E117	DFHEISR	Exc	Invalid data length	1	EISR parameter list
AP E118	DFHETC	Exc	LENGERR	1 2 3 4	TIOADBA Data at TIOADBA (up to 128 bytes) Length of data Length of input area
AP E119	DFHEIQVT	Exc	Invalid response from ZOPA	1 2	ZOPA return code ZOPA reason code
AP E11A	DFHEKCC	Exc	WAIT EVENT bad ECB address	1	ECB address
AP E11B	DFHEIQSK	Exc	WAIT CICS bad ECB address	1 2	ECB address ECBlist address

Table 89. Exec Interface (continued)

Point ID	Module	Lvl	Type	Data	
AP E11C	DFHEIQSK	Exc	WAIT EXTERNAL bad ECB address	1	ECB address
				2	ECBlist address
AP E130	DFHEISP	AP 2	Entry	1	EIEI parameter list
AP E131	DFHEISP	AP 2	Exit	1	EIEI parameter list
AP E133	DFHEISP	Exc	Invalid EIEI function	1	EIEI parameter list
AP E134	DFHEISP	Exc	Recovery	1	EIEI parameter list
				2	Kernel error data
AP E135	DFHINDSP	EI 1	Entry	1	RMLK parameter list
AP E136	DFHINDSP	EI 1	Exit	1	RMLK parameter list
AP E137	DFHINDSP	Exc	Recovery	1	RMLK parameter list
				2	Kernel error data
AP E138	DFHINDSP	Exc	Invalid format	1	RMLK parameter list
AP E13A	DFHINTRU	Exc	RMLN add link failed	1	RMLN parameter list
AP E13B	DFHINDT	Exc	RMLN start link browse failed	1	RMLN parameter list
AP E13C	DFHINDT	Exc	RMLN getnext link failed	1	RMLN parameter list
AP E13D	DFHINDT	Exc	RMLN end link browse failed	1	RMLN parameter list
AP E13E	DFHINDT	Exc	RMUW inq unit of work failed	1	RMUW parameter list
AP E13F	DFHINDT	Exc	RMLN Unexpected reason	1	RMLN parameter list
AP E140	DFHINDT	Exc	RMLN init recovery failed	1	RMLN parameter list
AP E141	DFHINDT	Exc	RMLN set recovery status failed	1	RMLN parameter list
AP E142	DFHINDT	Exc	RMLN term recovery failed	1	RMLN parameter list
AP E150	DFHEIP	AP 2	Entry GETMAIN/FREEMAIN subroutines	1	Request
AP E151	DFHEIP	AP 2	Exit GETMAIN/FREEMAIN subroutines	1	Request
AP E160	DFHEISR	AP 2	Entry	1	Command parameters (see Note below)
				2	Application parameter list
				3	Application reg 1
				4	EIB
AP E161	DFHEISR	AP 2	Exit	1	Command parameters (see Note below)
				2	Application parameter list
				3	Application reg 1
				4	EIB

Table 89. Exec Interface (continued)

Point ID	Module	Lvl	Type	Data
----------	--------	-----	------	------

Note: The entries AP E160 and AP E161 trace the interface between an application and CICS. The entries represent the command and its parameters as passed to CICS and as returned to the application.

The interpreted data from the data 1 field is shown in the interpretation string. The uninterpreted form of this data (in the data 1 field) is laid out as follows:

- Bytes 1 and 2 - length of data in data 1 field.
- The commands and their parameters in the following format:
 - Byte 1 - flag byte
 - Bytes 2 and 3 - 2 bytes of existence bits
 - Byte 4 - length of address/data
 - Bytes 5 to 8 - 4 byte address of data
 - Byte 9 onward - data, up to a maximum of 100 bytes

The first command and parameter data after the length bytes (bytes 1 and 2 of data 1) represent the values in arg0. Thereafter, they represent the application program commands.

The interpretation string, in addition to containing the formatted data 1 information, tells you:

- Whether NOHANDLE has been specified on the command
- Which language has been used (ASM, C/370, COBOL, COBOLII, PL/I, or PLX)
- Statement number of the command as calculated by the translator when DEBUG option is selected (not applicable to assembler language, however)
- RESP and RESP2 values (decimal) on exit trace.

It is advised that traces containing entries AP 150, AP 151, AP 160, and AP 161 be formatted with the FULL trace control statement. Using the ABBREV trace control statement results in interpretation strings which do not give the same level of information.

Security

Table 90. Security

Point ID	Module	Lvl	Type	Data
AP E500	DFHXSWM	AP 1	Entry	1 Requested function
AP E501	DFHXSWM	AP 1	Exit	1 Requested function
AP E502	DFHXSWM	Exc	Invalid function	1 Requested function 2 Response code 3 Reason code 4 WMS parameter list
AP E503	DFHXSWM	Exc	Unexpected PUT failure	1 WMS parameter list
AP E504	DFHXSWM	Exc	GET received invalid data	1 WMS parameter list
AP E505	DFHXSWM	Exc	Unexpected GET failure	1 WMS parameter list
AP E506	DFHXSMN	Exc	Nonzero return code	1 R15 and R0 ¹ 2 DFHSEC parameter list 3 SNTTE

¹ After ESM failure, the R0 value contains SAF and ESM return codes and reason codes. If R15 contains X'18', then R0 contains the reason code as follows:

X'04' Preset security on TCTTE
X'08' No SNTTE or TCTTE

X'0C'	Request code error
X'20'	Security not active
X'24'	Request code out of range
X'28'	No ACEE address in SNTTE
X'2C'	Resource name length error
X'34'	GETMAIN failed for FRACHECK work area
X'40'	Storage failure
X'44'	ACEE address invalid
X'48'	Invalid function request
X'4C'	Class name not found
X'50'	Name length error
X'58'	Zero resource name length
X'5C'	No resource name on CHECK request
X'60'	No AFCB
X'64'	No AFCB
X'68'	Class name list is too short

Table Management Program

Table 91. Table Management Program

Point ID	Module	Lvl	Type	Data
AP EA00	DFHTMP	AP 1	Entry	1 TMP parameter list 2 Primary key (if applicable) 3 Alias key (if applicable)
AP EA01	DFHTMP	AP 1	Exit	1 TMP parameter list 2 Primary key (if applicable) 3 Alias key (if applicable)

Transaction manager

Table 92. Transaction manager

Point ID	Module	Lvl	Type	Data
AP F000	DFHXCP	KC 1	Entry	1 28 bytes of data starting at TCAKCPBA 2 32 bytes of data starting at TCACCCA (ATTACH only) 3 Terminal ID, if any, of the task being attached (ENQ/DEQ only) 3 Resource name (RESUME only) 3 New transaction number 4 Terminal ID, if any, to be used by transaction
AP F001	DFHXCP	KC 1	Exit	1 28 bytes of data starting at TCAKCPBA 2 32 bytes of data starting at TCACCCA 3 Request code from TCATCTR
AP F007	DFHXCP	Exc	Invalid DFHKC call	1 Reserved

Table 92. Transaction manager (continued)

Point ID	Module	Lvl	Type	Data
AP F008	DFHKCSC	KC 1	KC1 entry	1 KCSC parameter list
AP F009	DFHKCSC	KC 1	KC1 exit	1 KCSC parameter list

Storage control SM interface

Table 93. Storage control SM interface

Point ID	Module	Lvl	Type	Data
AP F101	DFHSMSCP	SC 1	Entry	1 TCASCSA
AP F102	DFHSMSCP	SC 1	Exit	1 TCASCSA 2 Address of storage
AP F104	DFHSMSCP	Exc	Invalid request	1 TCASCSA
AP F105	DFHSMSCP	Exc	GETMAIN failed	1 TCASCSA
AP F106	DFHSMSCP	Exc	FREEMAIN failed	1 TCASCSA
AP F110	DFHAPSM	SC 1	Entry	1 SMNT parameter list
AP F111	DFHAPSM	SC 1	Exit	1 SMNT parameter list
AP F112	DFHAPSM	Exc	Recovery	1 SMNT parameter list 2 Kernel error data
AP F113	DFHAPSM	Exc	Invalid format	1 SMNT parameter list
AP F114	DFHAPSM	SC 1	Invalid function	1 SMNT parameter list

Program control

Table 94. Program control

Point ID	Module	Lvl	Type	Data
AP F230	DFHPCPC2	Exc	Pre-load error for OS/VSE COBOL module	1 Failing function 2 COBOL module name 3 R15 on return from MVS macro (if present)
AP F240	DFHPCLI	PC 1	XPCTA address modified	1 Modified address 2 Program name 3 Modified key
AP F241	DFHPCLI	PC 1	XPCHAIR address modified	1 Modified address 2 Program name 3 Reserved
AP F242	DFHPCLI	PC 1	XPCFTCH address modified	1 Modified address 2 Program name 3 Reserved

Interval control

Table 95. Interval control

Point ID	Module	Lvl	Type	Data
AP F300	DFHAPTI	IC 1	Entry	1 TISR parameter list
AP F301	DFHAPTI	IC 1	Exit	1 TISR parameter list
AP F302	DFHAPTI	Exc	Invalid TIME format	1 TISR parameter list
AP F303	DFHAPTI	Exc	Invalid function	1 TISR parameter list
AP F304	DFHAPTI	Exc	Invalid domain token type	1 TISR parameter list
AP F305	DFHAPTI	Exc	Bad response to RESUME	1 TISR parameter list
AP F306	DFHAPTI	Exc	Invalid domain token	1 TISR parameter list
AP F310	DFHAPTIM	IC 1	Entry	1 ICP static storage
AP F311	DFHAPTIM	IC 1	Exit	1 ICP static storage
AP F312	DFHAPTIM	IC 1	Suspend resumed	1 ICP static storage
AP F313	DFHAPTIM	Exc	Bad response to RESUME	1 ICP static storage
AP F314	DFHAPTIM	Exc	Invalid REQUEST_NOTIFY	1 TISR parameter list
AP F320	DFHAPTIX	IC 1	Entry	1 ICP static storage
AP F321	DFHAPTIX	IC 1	Exit	1 ICP static storage
AP F322	DFHAPTIX	IC 1	Suspend resumed	1 ICP static storage
AP F323	DFHAPTIX	Exc	Bad response to RESUME	1 ICP static storage
AP F330	DFHICRC	AP 1	Entry	1 Parameter list (RMRO, RMKP, RMDE, RMRE, ROIN, TSIC)
AP F331	DFHICRC	AP 1	Exit	1 Parameter list (RMRO, RMKP, RMDE, RMRE, ROIN, TSIC)
AP F332	DFHICRC	Exc	Recovery	1 Parameter list 2 Kernel error data
AP F333	DFHICRC	Exc	Invalid format	1 Parameter list
AP F334	DFHICRC	Exc	Invalid function	1 Parameter list

Dump control

Table 96. Dump control

Point ID	Module	Lvl	Type	Data
AP F400	DFHDCP	DC 1	Entry	

Table 96. Dump control (continued)

Point ID	Module	Lvl	Type	Data
AP F401	DFHDCP	DC 1	Exit	1 Return code: 0 OK 4 Partial dump 8 Dump data set not open 12 Dump data set open error 32 Dump suppressed
AP F402	DFHFDP	DC 1	Entry	
AP F403	DFHFDP	DC 1	Exit	1 Return code: 0 OK 4 Partial dump 12 Suppressed 24 SDUMP error

Transient data

Table 97. Transient data

Point ID	Module	Lvl	Type	Data
AP F600	DFHTDA	TD 1	Entry	1 DFHTDTD or DFHROIN parameter list 2 First record to be written to the queue
AP F601	DFHTDA	TD 1	Exit	1 DFHTDTD or DFHROIN parameter list 2 First record to be written to the queue
AP F602	DFHTDA	Exc	Recovery entered	1 DFHTDTD parameter list 2 Kernel error data
AP F610	DFHTDA	Exc	Invalid format	1 DFHTDTD parameter list
AP F612	DFHTDA	Exc	Invalid function	1 DFHTDTD parameter list
AP F614	DFHTDA	Exc	Invalid pointer to record	1 DFHTDTD parameter list
AP F615	DFHTDA	Exc	Invalid pointer to record list	1 DFHTDTD parameter list
AP F616	DFHTDA	Exc	Invalid record length	1 DFHTDTD parameter list
AP F617	DFHTDA	Exc	Invalid number of records	1 DFHTDTD parameter list
AP F61E	DFHTDA	Exc	DSAT Change mode call failed	1 DFHTDTD parameter list
AP F640	DFHTDOC	TD 1	Entry	1 DFHTDOC parameter list
AP F641	DFHTDOC	TD 1	Exit	1 DFHTDOC parameter list
AP F642	DFHTDOC	Exc	Recovery entered	1 DFHTDOC parameter list 2 Kernel error data
AP F650	DFHTDOC	Exc	Invalid format	1 DFHTDOC parameter list

Table 97. Transient data (continued)

Point ID	Module	Lvl	Type	Data
AP F652	DFHTDOC	Exc	Invalid function	1 DFHTDOC parameter list
AP F660	DFHTDRM	TD 1	Entry	1 DFHRMRO, DFHRMDE, or DFHRMKP parameter list
AP F661	DFHTDRM	TD 1	Exit	1 DFHRMRO, DFHRMDE, or DFHRMKP parameter list
AP F662	DFHTDRM	Exc	Recovery entered	1 DFHRMRO, DFHRMDE, or DFHRMKP parameter list
AP F663	DFHTDRM	Exc	Delete queue failed	1 TDTM parameter list
AP F664	DFHTDA	Exc	SMAD add subpool failed	1 DFHTDTD parameter list
AP F665	DFHTDA	Exc	Failed to register with RM	1 DFHTDTD parameter list
AP F666	DFHTDA	Exc	KEDD Add gate failed	1 DFHTDTD parameter list
AP F669	DFHTDRM	Exc	Invalid RMRO function	1 DFHRMRO parameter list
AP F66A	DFHTDRM	Exc	Invalid RMKP function	1 DFHRMKP parameter list
AP F66B	DFHTDRM	Exc	Invalid RMDE function	1 DFHRMSE parameter list
AP F66C	DFHTDRM	Exc	Invalid format	1 DFHRMRO, DFHRMDE, or DFHRMKP parameter list
AP F66D	DFHTDRM	Exc	Failed to lock queue	1 DFHRMRO parameter list
AP F66E	DFHTDRM	Exc	Failed to lock queue	1 DFHRMRO parameter list
AP F66F	DFHTDRM	Exc	Failed to lock queue	1 DFHRMRO parameter list
AP F670	DFHTDRM	Exc	Failed to lock queue	1 DFHRMRO parameter list
AP F675	DFHTDA	Exc	LDLD acquire program failed	1 DFHTDTD parameter list
AP F676	DFHTDA	Exc	LDLD define program failed	1 DFHTDTD parameter list
AP F680	DFHTDTM	TD 1	Entry	1 TDTM parameter list
AP F681	DFHTDTM	TD 1	Exit	1 TDTM parameter list
AP F682	DFHTDTM	Exc	Recovery	1 TDTM parameter list 2 Kernel error data
AP F683	DFHTDTM	Exc	Invalid function	1 TDTM parameter list
AP F684	DFHTDTM	Exc	Invalid format	1 TDTM parameter list
AP F685	DFHTDB	Exc	Recovery entered	1 DFHTDTD parameter list 2 Kernel error data
AP F686	DFHTDTM	Exc	Failure to resume current task	1 TDTM parameter list

Table 97. Transient data (continued)

Point ID	Module	Lvl	Type	Data	
AP F687	DFHTDRM	Exc	Failed to log data	1	DFHRMRO parameter list
AP F688	DFHTDRM	Exc	Unknown start	1	DFHRMDE parameter list
AP F689	DFHTDRM	Exc	Unrecognised log record	1	DFHRMDE parameter list
AP F68A	DFHTDRM	Exc	Unrecognised log record	1	DFHRMDE parameter list
AP F68B	DFHTDRM	Exc	Unrecognised log record	1	DFHRMDE parameter list
AP F68C	DFHTDRM	Exc	Corrupt log record	1	DFHRMDE parameter list
AP F68D	DFHTDRM	Exc	Corrupt log record	1	DFHRMDE parameter list
AP F68F	DFHTDRM	Exc	Corrupt keypoint record	1	DFHRMDE parameter list
AP F692	DFHTDRM	Exc	Corrupt indoubt log record	1	DFHRMDE parameter list
AP F693	DFHTDRM	Exc	No DCTE definition for an indoubt queue	1	DFHRMDE parameter list
AP F694	DFHTDRM	Exc	Failed to get the next DCTE	1	DFHRMDE parameter list
AP F695	DFHTDRM	Exc	Failed to get the next DCTE	1	DFHRMDE parameter list
AP F696	DFHTDRM	Exc	Failed to get the next DCTE	1	DFHRMDE parameter list
AP F697	DFHTDRM	Exc	Failed to get the next DCTE	1	DFHRMDE parameter list
AP F698	DFHTDRM	Exc	Failed to schedule an AID	1	DFHRMDE or DFHRMRO parameter list
AP F699	DFHTDRM	Exc	DSSR resume failed	1	DFHRMDE or DFHRMRO parameter list
AP F69A	DFHTDRM	Exc	Bad CI found during start up	1	DFHRMDE parameter list
AP F69B	DFHTDRM	Exc	Attempted to commit resources after the warm keypoint	1	DFHRMRO parameter list
AP F69C	DFHTDRM	Exc	DDBR end browse failed	1	DFHRMDE or DFHRMRO parameter list
AP F69D	DFHTDRM	Exc	RMKD keypoint failed	1	DFHRMDE parameter list
AP F69E	DFHTDRM	Exc	Failed to lock queue	1	DFHRMDE parameter list
AP F99F	DFHTDRM	Exc	NQSQ reacquire enqueue failed	1	DFHRMDE parameter list
AP F6A0	DFHTDRM	Exc	DDBR start browse failed	1	DFHRMDE or DFHRMRO parameter list
AP F6A1	DFHTDRM	Exc	SMGF getmain failed	1	DFHSMGF parameter list
AP F6A2	DFHTDRM	Exc	SMGF getmain failed	1	DFHSMGF parameter list
AP F6A3	DFHTDRM	Exc	SMGF getmain failed	1	DFHSMGF parameter list

Table 97. Transient data (continued)

Point ID	Module	Lvl	Type	Data
AP F6A4	DFHTDRM	Exc	TDXM release facility failed	1 DFHRMDE parameter list
AP F6A6	DFHTDTM	Exc	Failure to get lock	1 TDTM parameter list
AP F6A7	DFHTDTM	Exc	Failure during queue deletion	1 TDTM parameter list
AP F6A7	DFHTDRM	Exc	Invalid CI encountered	1 DFHRMDE parameter list
AP F6A8	DFHTDRM	Exc	Failed to recover whole queue	1 DFHRMDE parameter list
AP F6A9	DFHTDRM	Exc	Invalid RBA encountered	1 DFHRMDE parameter list
AP F6AA	DFHTDA	Exc	XMXE get transaction environment failed	1 DFHTDTD parameter list
AP F6AB	DFHTDA	Exc	XMXE free transaction environment failed	1 DFHTDTD parameter list
AP F6B0	DFHTDTM	Exc	Failure during DCT browse	1 TDTM parameter list
AP F6B1	DFHTDTM	Exc	Failure during SM request	1 TDTM parameter list
AP F6B2	DFHTDTM	Exc	Failure during DM call	1 TDTM parameter list
AP F6B3	DFHTDTM	Exc	Failure during dispatcher call	1 TDTM parameter list
AP F6B4	DFHTDTM	Exc	Failure during open/close of queue	1 TDTM parameter list
AP F6B5	DFHTDTM	Exc	Failure during catalog manager call	1 TDTM parameter list

Temporary storage

Table 98. Temporary storage

Point ID	Module	Lvl	Type	Data
AP F701	DFHTSP	AP 1	Entry	1 TCATSTR 2 TCASTR2 3 TCASTR3 4 Queue name 5 Item number 6 Data address
AP F702	DFHTSP	AP 1	Exit	1 TCATSTR 2 TCATSR2 3 Item number 4 Data address 5 Total items
AP F703	DFHTSP	Exc	Invalid request	1 TCATSTR 2 TCATSTR2 3 TCATSTR3 4 Queue name 5 Item number 6 Data address
AP F704	DFHEITS	AP 2	Entry	1 EIEI parameter list

Table 98. Temporary storage (continued)

Point ID	Module	Lvl	Type	Data
AP F705	DFHEITS	AP 2	Exit	1 EIEI parameter list
AP F706	DFHEITS	Exc	Recovery entered	1 EIEI parameter list 2 Kernel error data
AP F707	DFHEITS	Exc	Invalid format	1 EIEI parameter list
AP F708	DFHEITS	Exc	Invalid function	1 EIEI parameter list
AP F709	DFHEITS	Exc	Invalid TS function	1 EIEI parameter list
AP F711	DFHTSDQ	AP 1	Entry	
AP F712	DFHTSDQ	AP 1	Exit	1 Attach parameters
AP F713	DFHTSDQ	Exc	Unexpected error	

Event manager trace points

Table 99. Event manager trace points

Point ID	Module	Lvl	Type	Data
AP F890	DFHEIEM	AP 2	Entry	1 EIEI parameter list
AP F891	DFHEIEM	AP 2	Exit	1 EIEI parameter list
AP F893	DFHEIEM	Exc	Invalid format	1 EIEI parameter list
AP F894	DFHEIEM	Exc	Invalid function	1 EIEI parameter list
AP F895	DFHEIEM	Exc	Invalid Event Manager function	1 EIEI parameter list
AP F801	DFHEIBAM	AP 2	Entry	1 EIEI parameter list
AP F802	DFHEIBAM	AP 2	Exit	1 EIEI parameter list
AP F804	DFHEIBAM	Exc	Invalid format	1 EIEI parameter list
AP F805	DFHEIBAM	Exc	Invalid function	1 EIEI parameter list
AP F806	DFHEIBAM	Exc	Invalid CICS BTS function	1 EIEI parameter list

TCPIP SPI

Table 100. TCPIP SPI trace points

Point ID	Module	Lvl	Type	Data
AP F930	DFHEIQSO	AP 2	Entry	None
AP F931	DFHEIQSO	AP 2	Exit	None
AP F932	DFHEIQSO	Exc	Invalid SPI function	None

Journaling

Table 101. Journaling

Point ID	Module	Lvl	Type	Data
AP F900	DFHAPJC	JC 1	Entry	1 JCJC parameter list
AP F901	DFHAPJC	JC 1	Exit	1 JCJC parameter list
AP F902	DFHAPJC	Exc	Invalid format	1 JCJC parameter list
AP F903	DFHAPJC	Exc	Invalid function	1 JCJC parameter list
AP F904	DFHAPJC	Exc	JC write error	1 JCJC parameter list
AP F905	DFHAPJC	Exc	Recovery	1 JCJC parameter list 2 Kernel error data
AP F910	DFHEIWB	Entry		1 EIEI parameter list
AP F911	DFHEIWB	Exit		1 EIEI parameter list
AP F912	DFHEIWB	Exc	Invalid format	1 EIEI parameter list
AP F913	DFHEIWB	Exc	Invalid function	1 EIEI parameter list
AP F914	DFHEIWB	Exc	Invalid API function	1 EIEI parameter list

Document handler AP trace points

Table 102. document handler

Point ID	Module	Lvl	Type	Data
AP F920	DFHEIDH	AP 2	Entry	1 EIEI parameter list
AP F921	DFHEIDH	AP 2	Exit	1 EIEI parameter list
AP F922	DFHEIDH	Exc	Invalid format	1 EIEI parameter list
AP F923	DFHEIDH	Exc	Invalid function	1 EIEI parameter list
AP F924	DFHEIDH	Exc	Invalid API function	1 EIEI parameter list

Autoinstall for APPC sessions

The trace entries listed in the following table support autoinstall for APPC sessions.

Table 103. Autoinstall for APPC sessions, trace entries

Point ID	Module	Lvl	Type	Data
AP FA00	DFHZGAI	TC 1	Entry	1 DFHZGAI parameter list
AP FA01	DFHZGAI	TC 1	Exit	1 DFHZGAI parameter list
AP FA02	DFHZGAI	Exc	Invalid format	1 DFHZGAI parameter list

Table 103. Autoinstall for APPC sessions, trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP FA03	DFHZGAI	Exc	Invalid function	1 DFHZGAI parameter list
AP FA04	DFHZGAI	Exc	Recovery entered	1 DFHZGAI parameter list 2 Kernel error data
AP FA05	DFHZGAI	TC 1	User exit entry	1 COMMAREA input
AP FA06	DFHZGAI	TC 1	User exit exit	1 COMMAREA
AP FA07	DFHZGAI	Exc	User vetoed	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code
AP FA08	DFHZGAI	Exc	No template supplied	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code
AP FA09	DFHZGAI	Exc	Invalid sysid	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code
AP FA0A	DFHZGAI	Exc	Sysid already exists	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code
AP FA0B	DFHZGAI	Exc	Template netname not found	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code
AP FA0C	DFHZGAI	Exc	Template sysid not found	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code

Table 103. Autoinstall for APPC sessions, trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP FA0D	DFHZGAI	Exc	Not APPC template	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code
AP FA0E	DFHZGAI	Exc	Template not parallel sess	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code
AP FA0F	DFHZGAI	Exc	Template not single sess	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code
AP FA10	DFHZGAI	Exc	Modename does not match	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code
AP FA11	DFHZGAI	Exc	Sysid inquire failed	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code
AP FA12	DFHZGAI	Exc	Session inquire failed	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code
AP FA13	DFHZGAI	Exc	Template has no modegroup	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code
AP FA14	DFHZGAI	Exc	Out of service	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code

Table 103. Autoinstall for APPC sessions, trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP FA15	DFHZGAI	Exc	PLUNAME missing	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code
AP FA16	DFHZGAI	Exc	MODENAME missing	1 Function 2 CINIT or BIND 3 Return code 4 Template netname/template sysid, sysid, and synclevel 5 Sense code
AP FA18	DFHZGAI	Exc	Sessid missing	1 PLU name 2 Sysid 3 Sense code 4 Bind 5 TCTTE 6 TCTTE LUC extension
AP FA19	DFHZGAI	Exc	PLU name missing	1 PLU name 2 Sysid 3 Sense code 4 Bind 5 TCTTE 6 TCTTE LUC extension
AP FA1A	DFHZGAI	Exc	PLU eq SLU	1 PLU name 2 Sysid 3 Sense code 4 Bind 5 TCTTE 6 TCTTE LUC extension
AP FA1B	DFHZGAI	Exc	Seed expected	1 PLU name 2 Sysid 3 Sense code 4 Bind 5 TCTTE 6 TCTTE LUC extension
AP FA1C	DFHZGAI	Exc	Seed long	1 PLU name 2 Sysid 3 Sense code 4 Bind 5 TCTTE 6 TCTTE LUC extension
AP FA1D	DFHZGAI	Exc	Seed unexpected	1 PLU name 2 Sysid 3 Sense code 4 Bind 5 TCTTE 6 TCTTE LUC extension

Table 103. Autoinstall for APPC sessions, trace entries (continued)

Point ID	Module	Lvl	Type	Data	
AP FA1E	DFHZGAI	Exc	Not negotiable	1	PLU name
				2	Sysid
				3	Sense code
				4	Bind
				5	TCTTE
				6	TCTTE LUC extension
AP FA1F	DFHZGAI	Exc	Primary RU 0	1	PLU name
				2	Sysid
				3	Sense code
				4	Bind
				5	TCTTE
				6	TCTTE LUC extension
AP FA20	DFHZGAI	Exc	Secondary RU 0	1	PLU name
				2	Sysid
				3	Sense code
				4	Bind
				5	TCTTE
				6	TCTTE LUC extension
AP FA21	DFHZGAI	Exc	Acc sec invalid	1	PLU name
				2	Sysid
				3	Sense code
				4	Bind
				5	TCTTE
				6	TCTTE LUC extension

VTAM

CICS VTAM trace points fall into the following ranges:

- Removal of affinities owned by CICS, AP FA50-FA58
- APPC/MRO bitmap manipulation, AP FB00-FB08
- Persistent sessions, AP FB10-FB7F AP FBD0-FBE9
- Generic resource registration, AP FB80-FB8F
- CNOS AP FB90-FBC9

Note: In a CICS emergency restart, message DFHZC0124 indicates that some VTAM sessions have persisted from the previous CICS run with a nonzero PSDI value. Each of these sessions has been restored or terminated. CICS issues messages DFHZC0146 and DFHZC0156 for restored non-APPC and APPC sessions respectively.

VTAM trace entries

Table 104. VTAM trace entries

Point ID	Module	Lvl	Type	Data	
Note: * indicates that the RPLRTNCD/FDB2 fields are of interest and are interpreted.					
AP FA50	DFHZGCH	ZG 1	Entry	1 DFHZGCH parameter list	
AP FA51	DFHZGCH	ZG 1	Exit	1 DFHZGCH parameter list	
AP FA52	DFHZGCH	ZG 2	Before CHANGE macro	1	Input NETNAME
				2	Input NETID

Table 104. VTAM trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP FA53	DFHZGCH	ZG 2	After CHANGE macro	1 Input NETNAME 2 Input NETID 3 VTAM return code 4 VTAM FDB2
AP FA54	DFHZGCH	Exc	CHANGE macro failed	1 Input NETNAME 2 Input NETID 3 Register 15
AP FA55	DFHZGCH	Exc	Recovery entered	1 DFHZGCH parameter list
AP FA56	DFHZGCH	Exc	ENDAFFIN rejected	1 Input NETNAME 2 Input NETID 3 VTAM return code 4 VTAM FDB2
AP FA57	DFHZGCH	Exc	Invalid function	1 DFHZGCH parameter list
AP FA58	DFHZGCH	Exc	Invalid format	1 DFHZGCH parameter list
AP FA59	DFHZGCH	Exc	ZGTA delete from TCSM index failed	1 ZGTA response 2 ZGTA reason 3 Address of membername 4 Address of sysid
# AP FA60	DFHZGTI	Entry		1 DFHZGTI parameter list
#				
# AP FA61	DFHZGTI	Exit		1 DFHZGTI parameter list
#				
# AP FA62	DFHZGTI	Exc	Invalid format	1 DFHZGTI parameter list
#				
# AP FA63	DFHZGTI	Exc	Invalid function	1 DFHZGTI parameter list
#				
# AP FA64	DFHZGTI	Exc	Recovery entered	1 DFHZGTI parameter list 2 Kernel error data
#				
# AP FA65	DFHZGTI	Exc	Invalid TERMID	1 DFHZGTI parameter list
#				
# AP FA66	DFHZGTI	Exc	Invalid SYSID	1 DFHZGTI parameter list
#				
# AP FA67	DFHZGTI	Exc	Invalid NETNAME	1 DFHZGTI parameter list
#				
# AP FA68	DFHZGTI	Exc	Invalid token	1 DFHZGTI parameter list
#				
# AP FA69	DFHZGTI	Exc	TMP error	1 DFHZGTI parameter list 2 TMP response code 3 TMP parameter list
#				
#				
# AP FA6A	DFHZGTI	Exc	Invalid domain	1 DFHZGTI parameter list
#				
# AP FA6C	DFHZGTI	Exc	Invalid tor_netname_termid	1 DFHZGTI parameter list
#				
# AP FA6D	DFHZGTI	Exc	GETMAIN failed	1 DFHZGTI parameter list 2 smgf response code 3 smgf reason code
#				
#				
#				

Table 104. VTAM trace entries (continued)

	Point ID	Module	Lvl	Type	Data	
#	AP FA6E	DFHZGTI	Exc	FREEMAIN failed	1	DFHZGTI parameter list
#					2	smgf response code
#					3	smgf reason code
#					4	Address and length of browse_token_ptr
#	AP FA6F	DFHZGTI	Exc	Task purged detected	1	DFHZGTI parameter list
#	AP FA70	DFHZGTI	Exc	Invalid ISYSID	1	DFHZGTI parameter list
#	AP FA71	DFHZGTI	Exc	Invalid RSYSID	1	DFHZGTI parameter list
#	AP FA72	DFHZGTI	Exc	Invalid MBRNAME	1	DFHZGTI parameter list
#	AP FA80	DFHZGTA	Entry		1	DFHZGTA parameter list
#	AP FA81	DFHZGTA	Exit		1	DFHZGTA parameter list
#	AP FA82	DFHZGTA	Exc	Invalid format	1	DFHZGTA parameter list
#	AP FA83	DFHZGTA	Exc	Invalid function	1	DFHZGTA parameter list
#	AP FA84	DFHZGTA	Exc	Recovery entered	1	DFHZGTA parameter list
#					2	Kernel error data
#	AP FA85	DFHZGTA	Exc	Invalid TERMID	1	DFHZGTA parameter list
#	AP FA86	DFHZGTA	Exc	Invalid SYSID	1	DFHZGTA parameter list
#	AP FA87	DFHZGTA	Exc	Invalid NETNAME	1	DFHZGTA parameter list
#	AP FA88	DFHZGTA	Exc	Invalid ISYSID	1	DFHZGTA parameter list
#	AP FA89	DFHZGTA	Exc	Invalid tor_netname_termid	1	DFHZGTA parameter list
#	AP FA8A	DFHZGTA	Exc	Invalid RSYSID	1	DFHZGTA parameter list
#	AP FA8B	DFHZGTA	Exc	TMP error	1	DFHZGTA parameter list
#					2	TMP response code
#					3	TMP plist
#	AP FA8C	DFHZGTA	Exc	Invalid domain	1	DFHZGTA parameter list
#	AP FA8D	DFHZGTA	Exc	Task purged detected	1	DFHZGTA parameter list
#	AP FA8E	DFHZGTA	Exc	Error	1	DFHZGTA parameter list
#	AP FA8F	DFHZGTA	Exc	Disaster	1	DFHZGTA parameter list
#	AP FA90	DFHZGTA	Exc	Invalid rrab	1	DFHZGTA parameter list
#					2	Address of rrab_ptr
#	AP FA91	DFHZGTA	Exc	Inquiry failed	1	DFHZGTA parameter list

Table 104. VTAM trace entries (continued)

Point ID	Module	Lvl	Type	Data
# AP FA92	DFHZGTA	Exc	rdub_get failed	1 DFHZGTA parameter list 2 smgf response code 3 smgf reason code
#				
#				
#				
# AP FA93	DFHZGTA	Exc	rdub_free failed	1 DFHZGTA parameter list 2 smgf response code 3 smgf reason code
#				
#				
#				
# AP FA94	DFHZGTA	Exc	Invalid rdab	1 DFHZGTA parameter list 2 rdab pointer
#				
#				
# AP FA95	DFHZGTA	Exc	Invalid rdub	1 DFHZGTA parameter list 2 rdub pointer
#				
#				
# AP FA96	DFHZGTA	Exc	Unknown rrab response failed	1 DFHZGTA parameter list 2 rrab response code
#				
#				
# AP FA97	DFHZGTA	Exc	No rrab	1 DFHZGTA parameter list
#				
# AP FA98	DFHZGTA	Exc	Error failed	1 DFHZGTA parameter list 2 zgti response code 3 zgti reason code
#				
#				
# AP FA99	DFHZGTA	Exc	Invalid mbrname	1 DFHZGTA parameter list
#				
# AP FA9A	DFHZGTA	Exc	mbrname error	1 DFHZGTA parameter list 2 zgti node 3 zgti_found_netname
#				
#				
AP FAB0	DFHZGIN	1	Entry	1 DFHZGIN parameter list
AP FAB1	DFHZGIN	1	Exit	1 DFHZGIN parameter list
AP FAB2	DFHZGIN	2	Before inquire macro	1 RPL 2 NIB
AP FAB3	DFHZGIN	2	After inquire macro	1 RPL 2 NIB
AP FAB4	DFHZGIN	Exc	Inquire nqn failed	1 RPL 2 NIB 3 VTAM response
AP FAB5	DFHZGIN	Exc	Inquire sessname failed	1 RPL 2 NIB 3 VTAM response
AP FAB6	DFHZGIN	Exc	Recovery entered	1 DFHZGIN parameter list 2 Kernel error data
AP FAB7	DFHZGIN	Exc	Inquire nqn rejected	1 RPL 2 NIB
AP FAB8	DFHZGIN	Exc	Inquire sessname rejected	1 RPL 2 NIB

Table 104. VTAM trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP FAB9	DFHZGIN	Exc	Invalid format	1 DFHZGIN parameter list
AP FABA	DFHZGIN	Exc	Invalid function	1 DFHZGIN parameter list
AP FB00	DFHZGBM	TC 1	Entry	1 ZGBM parameter list
AP FB01	DFHZGBM	TC 1	Exit	1 ZGBM parameter list
AP FB03	DFHZGBM	Exc	Invalid function	1 ZGBM parameter list
AP FB04	DFHZGBM	Exc	Recovery routine entered	1 ZGBM parameter list 2 Kernel error data
AP FB05	DFHZGBM	Exc	BITMAP corrupt	1 BITMAP prefix 2 BITMAP suffix
AP FB06	DFHZGBM	Exc	Sessid invalid	1 ZGBM parameter list
AP FB07	DFHTCRP	Exc	No APPC bitmap storage	1 ZGBM parameter list
AP FB08	DFHTCRP	Exc	No MRO bitmap storage	1 ZGBM parameter list
AP FB10	DFHZGRP	TC 1	Entry	1 ZGRP parameter list
AP FB11	DFHZGRP	TC 1	Exit	1 ZGRP parameter list
AP FB12	DFHZGRP	Exc	Switch to QR TCB failed	1 ZGRP parameter list
AP FB13	DFHZGRP	Exc	No storage for niblist	1 ZGRP parameter list
AP FB14	DFHZGRP	Exc	Recovery routine entered	1 ZGRP parameter list 2 Kernel error data
AP FB15	DFHZGRP	Exc	No storage for OPNDST	1 ZGRP parameter list
AP FB16	DFHZGRP	Exc	No storage for RPL pool	1 ZGRP parameter list
AP FB17	DFHZGRP	Exc	Invalid format	1 ZGRP parameter list
AP FB18	DFHZGRP	Exc	Invalid function	1 ZGRP parameter list
AP FB19	DFHZGRP	Exc	Invalid START_UP type	1 ZGRP parameter list
AP FB1A	DFHZGRP	Exc	VTAM short on storage	1 RPL *
AP FB1B	DFHZGRP	Exc	VTAM INQUIRE failed	1 RPL *
AP FB1C	DFHZGRP	Exc	ACB closed for INQUIRE	1 RPL *
AP FB1D	DFHZGRP	Exc	ACB closed for OPNDST	1 RPL *
AP FB1F	DFHZGRP	Exc	ZBAN says BIND invalid	1 RPL *
AP FB20	DFHZGRP	Exc	VTAM OPNDST failed	1 RPL *

Table 104. VTAM trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP FB21	DFHZGRP	Exc	No TIOA storage for LU62	1 NIB 2 TCTTE address 3 TCTTE ID
AP FB22	DFHZGRP	Exc	No TIOA storage for term	1 NIB 2 TCTTE address 3 TCTTE ID
AP FB23	DFHZGRP	Exc	VTAM Receive Any	1 RPL *
AP FB24	DFHZGRP	TC 1	Trace each NIB for emergency restart	1 NIB 2 TERMID (present only if session is to be restored)
AP FB25	DFHZGRP	Exc	NIB does not match TCTTE	1 NIB 2 TCTTE address 3 TCTTE ID
AP FB26	DFHZGRP	Exc	RAIA GETMAIN failed	None
AP FB27	DFHZGRP	TC 2	Before INQUIRE COUNTS	1 RPL
AP FB28	DFHZGRP	TC 2	After INQUIRE COUNTS	1 RPL * 2 Count of persisting sessions
AP FB29	DFHZGRP	TC 2	Before INQUIRE PERSESS	1 RPL
AP FB2A	DFHZGRP	TC 2	After INQUIRE PERSESS	1 RPL *
AP FB2B	DFHZGRP	TC 2	Before OPNDST RESTORE	1 RPL
AP FB2C	DFHZGRP	TC 2	After OPNDST RESTORE	1 RPL *
AP FB2D	DFHZGRP	TC 2	Before RECEIVE ANY	1 RPL
AP FB2E	DFHZGRP	TC 2	After RECEIVE ANY	1 RPL *
AP FB2F	DFHZGRP	TC 2	Before EXECRPL INQUIRE	1 RPL
AP FB30	DFHZGRP	TC 2	After EXECRPL INQUIRE	1 RPL *
AP FB31	DFHZGRP	TC 2	Before EXECRPL OPNDST	1 RPL
AP FB32	DFHZGRP	TC 2	After EXECRPL OPNDST	1 RPL *
AP FB33	DFHZGRP	TC 2	Before EXECRPL R.A.	1 RPL
AP FB34	DFHZGRP	TC 2	After EXECRPL R.A.	1 RPL *
AP FB38	DFHZCGRP	TC 1	Entry	None
AP FB39	DFHZCGRP	TC 1	Exit	None
AP FB40	DFHZGUB	TC 1	Entry	1 ZGUB parameter list
AP FB41	DFHZGUB	TC 1	Exit	1 ZGUB parameter list
AP FB42	DFHZGUB	Exc	Invalid format	1 ZGUB parameter list

Table 104. VTAM trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP FB43	DFHZGUB	Exc	Recovery routine entered	1 ZGUB parameter list 2 Kernel error data
AP FB44	DFHZGUB	Exc	Invalid function	1 ZGUB parameter list
AP FB45	DFHZGUB	Exc	ACB closed 1 RPL *	
AP FB46	DFHZGUB	Exc	Unbind macro failed 1 RPL *	
AP FB47	DFHZGUB	Exc	VTAM short on storage 1 RPL *	
AP FB48	DFHZGUB	Exc	Unbind failed 1 RPL	
AP FB49	DFHZGUB	TC 2	Before CLSDST	1 RPL * 2 NETNAME
AP FB4A	DFHZGUB	TC 2	After CLSDST	1 RPL * 2 NETNAME
AP FB4B	DFHZGUB	TC 2	Before TERMSESS	1 RPL * 2 NETNAME
AP FB4C	DFHZGUB	TC 2	After TERMSESS	1 RPL * 2 NETNAME
AP FB4D	DFHZGUB	TC 2	Before EXECRPL	1 RPL * 2 NETNAME
AP FB4E	DFHZGUB	TC 2	After EXECRPL	1 RPL * 2 NETNAME
AP FB50	DFHZGSL	TC 1	Entry	1 ZGSL parameter list
AP FB51	DFHZGSL	TC 1	Exit	1 ZGSL parameter list
AP FB52	DFHZGSL	TC 2	Before setlogon persist	1 RPL
AP FB53	DFHZGSL	TC 2	After setlogon persist	1 RPL *
AP FB54	DFHZGSL	TC 2	Before setlogon npersist	1 RPL
AP FB55	DFHZGSL	TC 2	After setlogon npersist	1 RPL *
AP FB57	DFHZGSL	Exc	Recovery routine entered	1 ZGSL parameter list 2 Kernel error data
AP FB58	DFHZGSL	Exc	Invalid function	1 ZGSL parameter list
AP FB59	DFHZGSL	Exc	Invalid format	1 ZGSL parameter list
AP FB5A	DFHZGSL	Exc	Invalid PSDI value	1 ZGSL parameter list

Table 104. VTAM trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP FB5B	DFHZGSL	Exc	VTAM setlogon failed	1 RPL *
AP FB60	DFHZGCC	TC 1	Entry	1 ZGCC parameter list
AP FB61	DFHZGCC	TC 1	Exit	1 ZGCC parameter list
AP FB62	DFHZGCC	Exc	Invalid format	1 ZGCC parameter list
AP FB63	DFHZGCC	Exc	Invalid function	1 ZGCC parameter list
AP FB64	DFHZGCC	Exc	Recovery routine entered	1 ZGCC parameter list 2 Kernel error data
AP FB65	DFHZGPC	TC 1	Entry	1 ZGPC parameter list
AP FB66	DFHZGPC	TC 1	Exit	1 ZGPC parameter list
AP FB67	DFHZGPC	Exc	Invalid format	1 ZGPC parameter list
AP FB68	DFHZGPC	Exc	Invalid function	1 ZGPC parameter list
AP FB69	DFHZGPC	Exc	Recovery routine entered	1 ZGPC parameter list 2 Kernel error data
AP FB6A	DFHZGPC	Exc	BIND and TCTTE mismatch	1 ZGPC parameter list 2 TCSE 3 NIB
AP FB6B	DFHZGPC	Exc	No session available to match a NIB	1 ZGPC parameter list 2 NIB
AP FB70	DFHZXRC	TC 2	Vector_29 data	1 CV29_data
AP FB71	DFHZGDA	TC 2	Entry	1 ZGDA input parameter list
AP FB72	DFHZGDA	TC 2	Exit	1 ZGDA input parameter list
AP FB73	DFHZGDA	Exc	Invalid function	1 ZGDA input parameter list
AP FB74	DFHZGDA	Exc	Invalid format	1 ZGDA input parameter list
AP FB76	DFHZGDA	Exc	Sense X'088B'	1 ZGDA input parameter list 2 tcte_prss status byte
AP FB78	DFHZGDA	Exc	Receive failed	1 ZGDA input parameter list 2 TCTTE address 3 tcte_prss status byte
AP FB79	DFHZGDA	Exc	Unexpected response	1 ZGDA input parameter list 2 sense received 3 tcte_prss status byte
AP FB7A	DFHZGDA	Exc	Bracket FSM error	1 ZGDA input parameter list 2 tctebkts bracket FSM 3 tcte_prss status byte

Table 104. VTAM trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP FB7B	DFHZGDA	Exc	Bracket FSM error	1 ZGDA input parameter list 2 tctebkts bracket FSM 3 tcte_prss status byte
AP FB7D	DFHZGDA	Exc	No FMH7 storage	1 ZGDA input parameter list
AP FB7E	DFHZGDA	Exc	Bracket FSM error	1 ZGDA input parameter list 2 tctebkts bracket FSM
AP FB7F	DFHZGDA	Exc	Recovery routine entered	1 ZGDA input parameter list 2 Kernel error data
AP FB80	DFHZGDA	Exc	Chain FSM error	1 ZGDA input parameter list 2 tctechss chain FSM 3 tcte_prss status byte
AP FB87	DFHZGSL	Event	Before NIB initialization	1 RPL
AP FB88	DFHZGSL	Event	After NIB initialization	1 RPL
AP FB89	DFHZGSL	Event	Before generic resource registration	1 RPL
AP FB8A	DFHZGSL	Event	After generic resource registration	1 RPL
AP FB8B	DFHZGSL	Event	Before generic resource deregistration	1 RPL
AP FB8C	DFHZGSL	Event	After generic resource deregistration	1 RPL
AP FB8D	DFHZGSL	Exc	NIB initialization failed	1 RPL
AP FB8E	DFHZGSL	Event	Generic resource registration failed	1 RPL
AP FB8F	DFHZGSL	Event	Generic resource deregistration failed	1 RPL
AP FB90	DFHZLS1	TC 1	Entry	None
AP FB91	DFHZLS1	TC 1	Exit	None
AP FB92	DFHZLS1	Exc	Invalid start type	1 XMIQ start code
AP FB93	DFHZLS1	Exc	IC GET failed	None
AP FB94	DFHZLS1	Exc	Invalid format	1 IC start data
AP FB95	DFHZLS1	Exc	Invalid function	1 IC start data
AP FB96	DFHZLS1	Exc	No receive data	None
AP FB97	DFHZLS1	Exc	Invalid receive data	1 Received data
AP FBA0	DFHZGCN	TC 1	Entry	1 ZGCN format parameter list 2 CNOS GDS (target system only)
AP FBA1	DFHZGCN	TC 1	Exit	1 ZGCN format parameter list
AP FBA2	DFHZGCN	Exc	Add lock failed	1 ZGCN format parameter list 2 TCTSE 2 TCTME

Table 104. VTAM trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP FBA3	DFHZGCN	Exc	Allocate failed	1 ZGCN format parameter list 2 TCTSE 2 DFHLUC parameter list
AP FBA4	DFHZGCN	Exc	Already shut	1 ZGCN format parameter list 2 TCTSE 2 TCTME
AP FBA5	DFHZGCN	Exc	CNOS impossible	1 ZGCN format parameter list 2 TCTSE 2 TCTME
AP FBA6	DFHZGCN	Exc	Get lock failed	1 ZGCN format parameter list 2 TCTSE 2 TCTME
AP FBA7	DFHZGCN	Exc	In shutdown	1 ZGCN format parameter list 2 TCTSE
AP FBA8	DFHZGCN	Exc	Invalid format	1 Unknown format parameter list
AP FBA9	DFHZGCN	Exc	Invalid function	1 ZGCN format parameter list
AP FBAA	DFHZGCN	Exc	Invalid modename	1 ZGCN format parameter list
AP FBAB	DFHZGCN	Exc	Invalid sysid	1 ZGCN format parameter list
AP FBAC	DFHZGCN	Exc	No TCTME found	1 ZGCN format parameter list 2 TCTSE
AP FBAD	DFHZGCN	Exc	No TCTTE found	1 ZGCN format parameter list 2 TCTSE 2 TCTME
AP FBAE	DFHZGCN	Exc	Race in shutdown	1 ZGCN format parameter list 2 TCTSE
AP FBAF	DFHZGCN	Exc	Receive failed	1 ZGCN format parameter list 2 TCTSE 2 TCTME
AP FBB0	DFHZGCN	Exc	Recovery routine entered	1 ZGCN format parameter list 2 Kernel error data
AP FBB1	DFHZGCN	Exc	Send failed	1 ZGCN format parameter list 2 TCTSE 2 TCTME 4 DFHLUC parameter list
AP FBB2	DFHZGCN	Exc	Single session error	1 ZGCN format parameter list 2 TCTSE 2 TCTME
AP FBB3	DFHZGCN	Exc	Sysid not found	1 ZGCN format parameter list

Table 104. VTAM trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP FBB4	DFHZGCM	Exc	TCTSE error	1 ZGCM format parameter list 2 TCTSE
AP FBB5	DFHZGCM	TC 1	CNOS command out	1 CNOS GDS 2 Sysid of target
AP FBB6	DFHZGCM	TC 1	CNOS command in	1 CNOS GDS 2 Sysid of source
AP FBB7	DFHZGCM	TC 1	CNOS reply out	1 CNOS GDS 2 Sysid of source
AP FBB8	DFHZGCM	TC 1	CNOS reply in	1 CNOS GDS 2 Sysid of target
AP FBC0	DFHZGCA	TC 1	Entry	1 ZGCA format parameter list
AP FBC1	DFHZGCA	TC 1	Exit	1 ZGCA format parameter list
AP FBC2	DFHZGCA	TC 2	Entry level 2	1 TCTME
AP FBC3	DFHZGCA	TC 2	Exit level 2	1 TCTME
AP FBC4	DFHZGCA	TC 2	Current counts	1 Current session state counts 2 Required session state counts
AP FBC5	DFHZGCA	TC 2	TC matrix	1 State transformation counts
AP FBC6	DFHZGCA	Exc	Recovery routine entered	1 ZGCA format parameter list 2 Kernel error data
AP FBC7	DFHZGCA	Exc	Invalid format	1 Unknown format parameter list
AP FBC8	DFHZGCA	Exc	Invalid function	1 ZGCA format parameter list
AP FBC9	DFHZGCA	Exc	Change uncompleted	1 ZGCA format parameter list 2 TCTME 3 Current session state counts 4 State transformation counts 5 Required session state counts
AP FBD0	DFHZXPS	TC 1	Entry	1 tcte_trace_1 2 TCTTE address
AP FBD1	DFHZXPS	TC 1	Exit	1 tcte_trace_1 2 TCTTE address
AP FBD2	DFHZXPS	Exc	Invalid TCTEPRSS data	1 tcte_trace_1 2 TCTTE address
AP FBD3	DFHZXPS	Exc	CV29 data missing	1 tcte_trace_1
AP FBD4	DFHZXPS	Exc	Invalid BIS data	1 tcte_trace_1 2 BIS data

Table 104. VTAM trace entries (continued)

Point ID	Module	Lvl	Type	Data
AP FBD5	DFHZXPS	Exc	Invalid BID data	1 tcte_trace_1 2 BID data
AP FBD6	DFHZXPS	Exc	No BID recovery	1 tcte_trace_1 2 BID data
AP FBD7	DFHZXPS	Exc	Missing BID flow	1 tcte_trace_1 2 BID data
AP FBD8	DFHZXPS	Exc	Invalid category for APPC session	1 tcte_trace_1 2 CV29 data
AP FBD9	DFHZXPS	Exc	Inconsistent data flow	1 tcte_trace_1 2 CV29 data
AP FBDA	DFHZXPS	Exc	Unidentified response	1 tcte_trace_1 2 CV29 data
AP FBDB	DFHZXPS	Exc	Unknown command	1 tcte_trace_1 2 CV29 data
AP FBDC	DFHZXPS	Exc	Unexpected BIS response	1 tcte_trace_1 2 CV29 data 3 BIS data
AP FBDD	DFHZXPS	Exc	Unknown command response	1 tcte_trace_1 2 CV29 data
AP FBDE	DFHZXPS	Exc	Invalid BID status	1 tcte_trace_1 2 tcte bid status
AP FBDF	DFHZXPS	Exc	Session not in CS mode	1 tcte_trace_1
AP FBE0	DFHZXPS	Exc	Invalid parameter list	1 tcte_trace_1 2 ZGDA parameter list
AP FBE1	DFHZXPS	Exc	Unknown state after SIG	1 tcte_trace_1 2 CV29 data
AP FBE2	DFHZXPS	Exc	CLS2 running	1 tcte_trace_1
AP FBE3	DFHZXPS	Exc	Bind security flow active	1 tcte_trace_1
AP FBE4	DFHZXPS	Exc	Recovery abandoned	1 tcte_trace_1
AP FBE5	DFHZXPS	Exc	RESETSR failed	1 tcte_trace_1 2 RESETSR return code
AP FBE6	DFHZXPS	Exc	Tracking data missing	1 tcte_trace_1
AP FBE7	DFHZXPS	Exc	Domain call failed	1 ZGDA parameter list
AP FBE8	DFHZXPS	Exc	Bind not complete	1 tcte_trace_1 2 CV29 data
AP FBE9	DFHZXPS	Event	Cleanup routine entered	1 tcte_trace_1

Terminal control

Table 105. Terminal control

Point ID	Module	Lvl	Type	Data
AP FC01	DFHZARQ DFHZIS1	TC 1	Event MRO/LU6.1 state setting	1 State set 2 Module setting it 3 Conversation TCTTE 4 Work area
AP FC17	DFHZRVX	TC 1	Receive specific VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC19	DFHZSDX	TC 1	Data completion VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC21	DFHZASX	TC 1	Data-flow asynchronous VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC23	DFHZCLX	TC 1	CLSDST VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC25	DFHZLEX	TC 1	LERAD VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC26	DFHZLGX	TC 1	LOGON VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC28	DFHZLTX	TC 1	LOSTERM VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC2A	DFHZOPX	TC 1	OPNDST VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC2E	DFHZRRX	TC 1	Release request VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC2F	DFHZNSP	TC 1	Network services procedure error VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC31	DFHZSAX	TC 1	Send DFASY VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC32	DFHZSCX	TC 1	SCIP VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC36	DFHZSEX	TC 1	SESSIONC VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC38	DFHZSIX	TC 1	SIMLOGON VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC3A	DFHZSSX	TC 1	SEND DFSYN VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC3B	DFHZSYX	TC 1	SYNAD VTAM exit	1 NETNAME, if known Other See Table 106 on page 296

Table 105. Terminal control (continued)

Point ID	Module	Lvl	Type	Data
AP FC3C	DFHZTAX	TC 1	Turnaround completion VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC3D	DFHZTPX	TC 1	TPEND VTAM exit	1 NETNAME, if known Other See Table 106 on page 296
AP FC4D	DFHZRLX	TC 1	Receive specific VTAM exit for LU6.2	1 NETNAME, if known Other See Table 106 on page 296
AP FC4F	DFHZSLX	TC 1	Data completion VTAM exit for LU6.2	1 NETNAME, if known Other See Table 106 on page 296
AP FC50	DFHSUZX	TC 1	Entry	1 SUZX parameter list
AP FC51	DFHSUZX	TC 1	Exit	1 SUZX parameter list
AP FC52	DFHSUZX	TC 1	Error exit (event)	1 SUZX parameter list
AP FC53	DFHZCUT	TC 1	Entry	1 ZCUT parameter list
AP FC54	DFHZCUT	TC 1	Exit	1 ZCUT parameter list
AP FC57	DFHZCUT	Exc	Invalid function	1 ZCUT parameter list
AP FC5A	DFHZCUT	Exc	Store clock failure	1 None
AP FC5B	DFHZCUT	Exc	Invalid userid length	1 ZCUT parameter list
AP FC70	DFHZNAC	TC 2	XRF tracking	1 XRF session details 2 TIOA
AP FC71	DFHZNAC	TC 1	ZNEP entry	1 COMMAREA
AP FC72	DFHZNAC	TC 1	ZNEP exit	1 COMMAREA
AP FC73	DFHZNAC	Exc	ZNAC system dump	1 TCTTE
AP FC74	DFHZNAC	Exc	After call to DFHRMLN	1 RMLN parameter list
AP FC80	DFHZATR	TC 1	Entry	1 None
AP FC81	DFHZATR	TC 1	Exit	1 Count of deletes scheduled
AP FC82	DFHZATA	TC 1	Entry	1 Network name
AP FC83	User exit (DFHZAT)	TC 1	Call	1 Network name
AP FC84	User exit (DFHZAT)	TC 1	Return	1 TERM_ID status
AP FC85	DFHZATA	TC 1	Exit	1 TERM_ID 2 TCTTE address 3 MODEL_NAME
AP FC86	DFHZATD	TC 1	Entry	1 TERM_ID 2 TCTTE address

Table 105. Terminal control (continued)

Point ID	Module	Lvl	Type	Data
AP FC87	User exit (DFHZAT)	TC 1	Call	1 TERM_ID
AP FC88	User exit (DFHZAT)	TC 1	Return	1 TERM_ID
AP FC89	DFHZATD	TC 1	Exit	1 TERM_ID
AP FC8A	DFHZATA	TC 1	Event	1 AWE (DFHTCTWE)
AP FC8B	DFHZATS	TC 1	Entry	1 Remote system ID 2 TERM_ID
AP FC8C	DFHZATS	TC 1	Exit	1 Remote system ID 2 TERM_ID 3 TCTTE address
# AP FC90	DFHZTRA	TC 1-2	VTAM I/O	1 TCTE_NIBD_TRACE 2 VTAM RPL and ZC extension 3 First buffer list entry, or 0 4 Last buffer list entry, or 0 5 Data 6 Data as required 7 Data as required or 5, 6, 7 4 bytes of data or 8 bytes of FMH followed by 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'
# AP FC91	DFHZTRA	TC 1-2	VTAM I/O additional data	1 Data as required 2 Data as required 3 Data as required 4 Data as required 5 Data as required 6 Data as required 7 Data as required or 1 - 7 'SUPPRESSED DUE TO CONFDATA=HIDETC IN SIT'
AP FC92	DFHZATMF	TC 1	Entry	None
AP FC93	DFHZATMF	TC 1	Exit	None
AP FC94	DFHZATMD	TC 1	Entry	None
AP FC95	DFHZATMD	TC 1	Exit	None
AP FC96	DFHZATS	TC 1	Call	1 Address of local TERM_ID
AP FC97	DFHZATS	TC 1	Return	1 Address of selected shipped TERM_ID 2 Address of selected shipped return code
AP FC98	DFHZATMD	TC 1	Call	1 Address of delete shipped local TERM_ID
AP FC99	DFHZATMD	TC 1	Return	1 Address of delete shipped local TERM_ID
AP FC9A	DFHZATS	TC 1	Return	1 Address of local TERM_ID

Table 105. Terminal control (continued)

Point ID	Module	Lvl	Type	Data
AP FC9B	DFHZATT	TC 1	Event delayed_data TCTTE	1 Address of TCTTE 2 Data from TIOA
AP FCA0	DFHZRAS	TC 1	Event	1 TCTE_TRACE_1 fields in TCTTE 2 TCTE_TRACE_5 fields in TCTTE 3 Exit footprints, address of TCTTE 4 TCTE_LUCX_TRACE fields in LUC extension
AP FCA1	DFHZRAS	TC 1	Event	1 RRLRTNCD 2 RPLFDB2
AP FCA2	DFHZRAS	Exc	Receive specific NQ failed	1 TCTTE 2 TCTTE LU6.2 extension 3 RA RPL
AP FCA3	DFHZATA2	TC 1	ENTRY	1 Console Name 2 TCTCWE_FLG (see <i>CICS Data Areas</i> for details.)
AP FCA4	DFHZATA2	TC 1	Event: call AI URM	1 Console Name
AP FCA5	DFHZATA2	TC 1	Event: exit AI URM	1 Term ID 2 Return Code
AP FCA6	DFHZATA2	TC 1	Exit	1 Term ID 2 TCTTE Address 3 Model name for install
AP FCA7	DFHZATA2	TC 1	Event	1 AWE/CWE
AP FCB0	DFHZCQIS	TC 1	Entry, install	1 BPS address (4 bytes) Node name (4 bytes)
AP FCB1	DFHZCQIS	TC 1	Exit, install	1 Response (4 bytes) Node address (4 bytes)
AP FCB2	DFHZCQRS	TC 1	Entry, recover	1 RR record address (4 bytes) Recovery record key (16 bytes)
AP FCB3	DFHZCQRS	TC 1	Exit, recover	1 Response (4 bytes) Node address (4 bytes) Node name (4 bytes) RID for ZCQRS (1 byte)
AP FCB4	DFHZCQDL	TC 1	Entry, delete	1 Node address (4 bytes) Node name (4 bytes)
AP FCB5	DFHZCQRS	TC 1	Exit, delete	1 Response (4 bytes)
AP FCB6	DFHZCQCH	TC 1	Entry, catalog	1 Node address (4 bytes) Node name (4 bytes)

Table 105. Terminal control (continued)

Point ID	Module	Lvl	Type	Data
AP FCB7	DFHZCQCH	TC 1	Exit, catalog	1 Response (4 bytes)
AP FCB8	DFHZCQIQ	TC 1	Entry, inquire	1 Node address (4 bytes) Node name (4 bytes) BPS address (4 bytes)
AP FCB9	DFHZCQIQ	TC 1	Exit, inquire	1 Response (4 bytes)
AP FCBA	DFHZCQ00	TC 1	Entry, router	None
AP FCBB	DFHZCQ00	TC 1	Exit, router	1 Response (4 bytes) Message set address (4 bytes)
AP FCBC	DFHZCQIN	TC 1	Entry, initialize	None
AP FCBD	DFHZCQIN	TC 1	Exit, initialize	None
AP FCBE	DFHZBAN	TC 2	Entry, validate BIND	1 Node address (4 bytes) Node name (4 bytes) BIND address (4 bytes)
AP FCBF	DFHZBAN	TC 1	Exit, validate BIND	1 Response (4 bytes) Reason (4 bytes)
AP FCC0	DFHTBSB	TC 1	Entry, build	1 Pattern name (8 bytes) Type of commit (1 byte) X'00' SYNCPOINT X'40' DELAY X'80' NOW
AP FCC1	DFHTBSB	TC 1	Exit, build	1 Response (4 bytes) Message set address (4 bytes) DWE address (4 bytes) Node address (4 bytes) Node name (4 bytes)
AP FCC2	DFHTBSR	TC 1	Entry, restore	1 Pattern name (8 bytes) Type of commit (1 byte) X'00' SYNCPOINT X'40' DELAY X'80' NOW
AP FCC3	DFHTBSB	TC 1	Exit, restore	1 Response (4 bytes) Message set address (4 bytes) DWE address (4 bytes) Node address (4 bytes) Node name (4 bytes)
AP FCC4	DFHTBSD	TC 1	Entry, destroy	1 Pattern name (8 bytes) Type of commit (1 byte) X'00' SYNCPOINT X'40' DELAY X'80' NOW
AP FCC5	DFHTBSD	TC 1	Exit, destroy	1 Response (4 bytes) Message set address (4 bytes) DWE address (4 bytes)
AP FCC6	DFHTBSL	TC 1	Entry, catalog	1 Pattern name (8 bytes)

Table 105. Terminal control (continued)

Point ID	Module	Lvl	Type	Data
AP FCC7	DFHTBSL	TC 1	Exit, catalog	1 Response (4 bytes) Message set address (4 bytes) DWE address (4 bytes)
AP FCC8	DFHTBSQ	TC 1	Entry, inquire	1 Pattern name (8 bytes)
AP FCC9	DFHTBSL	TC 1	Exit, inquire	1 Response (4 bytes) Message set address (4 bytes)
AP FCCA	DFHTBSSP	TC 1	Entry, syncpoint	1 DWE address (4 bytes) R=rollback, C=commit (1 byte) Phase 1 or 2 (1 byte)
AP FCCB	DFHTBSSP	TC 1	Exit, syncpoint	None
AP FCCC	DFHTBSSP	TC 1	Call, destroy ready	1 Builder name (3 bytes) Ready Destroy (7 bytes)
AP FCCD	DFHTBSSP	TC 1	Return, destroy ready	1 Builder name (3 bytes) Ready Destroy (7 bytes)
AP FCD0	DFHTBSBP	TC 1	Entry, build	1 Builder name (3 bytes)
AP FCD1	DFHTBSBP	TC 1	Exit, build	1 Response (4 bytes) Message set address (4 bytes) Node address (4 bytes) Builder name (3 bytes)
AP FCD2	DFHTBSRP	TC 1	Entry, restore	1 Builder name (3 bytes)
AP FCD3	DFHTBSRP	TC 1	Exit, restore	1 Response (4 bytes) Message set address (4 bytes) Node address (4 bytes) Builder name (3 bytes)
AP FCD4	DFHTBSDP	TC 1	Entry, destroy	1 Builder name (3 bytes)
AP FCD5	DFHTBSDP	TC 1	Exit, destroy	1 Response (4 bytes) Message set address (4 bytes) Node address (4 bytes) Builder name (3 bytes)
AP FCD6	DFHTBSLP	TC 1	Entry, catalog	1 Builder name (3 bytes)
AP FCD7	DFHTBSLP	TC 1	Exit, catalog	1 Response (4 bytes) Message set address (4 bytes) Node address (4 bytes) Builder name (3 bytes)
AP FCD8	DFHTBSQP	TC 1	Entry, inquire	1 Builder name (3 bytes)
AP FCD9	DFHTBSQP	TC 1	Exit, inquire	1 Response (4 bytes) Message set address (4 bytes) Node address (4 bytes) Builder name (3 bytes)

Table 105. Terminal control (continued)

Point ID	Module	Lvl	Type	Data
AP FCDA	DFHBSHDR	TC 2	Call function	1 Builder name (3 bytes) Function index (1 byte) 1 BUILD 2 DESTROY 3 READY 4 UNREADY 5 CONNECT 6 FLATTEN 7 UNFLATTEN 8 FIND_FIRST 9 FIND_NEXT 10 MAKEKEY 11 INQUIRE 12 RESET 13 CHECKSET other values unknown Node address (4 bytes)
AP FCDB	DFHBSHDR	TC 2	Return function	1 Builder name (3 bytes) Function index (1 byte) 1 BUILD 2 DESTROY 3 READY 4 UNREADY 5 CONNECT 6 FLATTEN 7 UNFLATTEN 8 FIND_FIRST 9 FIND_NEXT 10 MAKEKEY 11 INQUIRE 12 RESET 13 CHECKSET other values unknown Node address (4 bytes)
AP FCDC	DFHTBSSP	TC 2	DFHTBSSP EVENT	1 Action element address (4 bytes) Pattern address (4 bytes) Recovery record address (4 bytes) Node address (4 bytes) Node ID (4 bytes) ADD DEL (1 byte) bit 0, 0 = DELETE 1 = ADD
AP FCDD	DFHTBSM	Exc	DFHBSMSG SET_ADD	1 MSG_REASON_ELEM (50 bytes)
AP FCDE	DFHBSTZA	Exc	Delete vetoed, ZCP activity pending	1 TCTEACR action flags (4 bytes) TCTEHACP (4 bytes) TCTECNTE (4 bytes) TCTEVTPS (1 byte) TCTEISSQ (1 byte)

Table 105. Terminal control (continued)

Point ID	Module	Lvl	Type	Data
AP FCE0	DFHZGET	TC 1	Entry	1 TCTTEAR 2 Option byte
AP FCE1	DFHZGET	TC 1	Exit	1 6 fullwords: address of TIOA address of RPL and HPO extension address of NIB/BIND address of LUC SEND/RECV_BFR and BUFFERLIST address of buffer list return code from DFHZGET GETMAIN
AP FCE2	DFHZFRE	TC 1	Entry	1 TCTTEAR 2 Option byte
AP FCE3	DFHZFRE	TC 1	Exit	1 7 fullwords: address of TIOA address of RPL and HPO extension address of NIB/BIND address of LUC SEND/RECV_BFR and BUFFERLIST address of buffer list address of extracted logon data return code from DFHZFRE FREEMAIN
AP FCF0	DFHZCNA	TC 1	Event	1 Command input buffer (CIB) 2 CIB extension 3 Console name 4 CIB data 5 CIB CONID
AP FCF1	DFHZNAC	Exc	Error	1 TCTTE
AP FCF2	DFHZNAC	Exc	Missing LOSTERM	1 Number of missing entries
AP FCF3	DFHZNAC	Exc	Error code	1 Dummy TCTTE
AP FCF4	DFHZCLS	Exc	Open destination limit	1 Prefix count
AP FCF5	DFHZOPN	Exc	Open destination limit	1 Prefix count
AP FCF6	DFHZRAC	Exc	About to reach maxtasks - no further receives issued	
AP FCF7	DFHTCRP	Exc	Insufficient storage	1 SMAD call parameter list 2 Subpool name 3 Initial free storage
AP FCF8	DFHSUZX	Exc	Invalid function	1 SUZX parameter list

Table 105. Terminal control (continued)

Point ID	Module	Lvl	Type	Data
AP FCF9	DFHSUZX	Exc	Invalid locate type	1 SUZX parameter list
AP FCFB	DFHZRAC	Exc	Race hang	1 RACE 2 RPL 3 TCTTE 4 RACE address

CICS VTAM exit trace destination

CICS VTAM exit traces are sent to the GTF trace data set *only*, and not to any other currently active CICS trace destinations.

Table 106. Exit trace data fields for entries AP FC17 through AP FC4F

ID	Description	Field	Length
BA	BIND area	(R14)	variable
BR	BIND response	RPLAAREA	RPLAARLN
CI	VTAM CID	TCTECID	4
LE	LUC extension	TCTTELUC	TCTTELUL
NI	NIB descriptor	TCTENIBA	TCTENIBE-TCTENIB
RA	RPL data area	RPLAREA	RPLRLEN
RF	contents of register 15	R15	4
R1	first RPL	(RPLBAR)	ATCLEN+ZRPLAD
RV	first RPL	(RPLBAR)	ATCLEN
R2	second RPL	(RPLBAR)	ATCLEN+ZRPLAD
SY	symbolic name	D4(R1)	8
T3	section of TCTTE	TCTE_TRACE_3	TCTE_TRACE_3_LEN
T5	section of TCTTE	TCTE_TRACE_5	TCTE_TRACE_5_LEN
UR	UNBIND RU	RPLAREA	RPLRLEN
VP	VTAM parameter list	(R1)	24
WE	autoinstall work element	DFHTCTWE	TCTWELEN

Notes:

1. The exit trace data fields for each trace entry are the NETNAME, if any, followed by one or more other data fields in any order, depending on the path through CICS system code. The first two bytes of a data field hold the ID.
2. BIND is described in the *SNA Reference Summary*, GA27-3136.
3. The LUC extension (DFHTCTTE), the NIB descriptor (DFHTCTTE), and the autoinstall work element (DFHTCTWE) are described in *CICS Data Areas*.
4. The RPL and the VTAM parameter list are described in the *VTAM Programming manual*, SC23-0115.

Terminal control (intersystem communication)

For the data formats referred to in Table 107, see page "Formats for AP FDxx traces" on page 298.

Table 107. Intersystem communication

Point ID	Module	Lvl	Type	Data
AP FD01	DFHZARQ	TC 1	APPL_REQ entry	Format 02
AP FD02	DFHZLOC	TC 1	LOCATE entry	Format 02
AP FD03	DFHZDET	TC 1	DETACH entry	Format 01
AP FD05	DFHZSUP	TC 1	TASK_STARTUP entry	Format 02
AP FD06	DFHZCRQ	TC 1	CMD_REQ entry	Format 01

Table 107. Intersystem communication (continued)

Point ID	Module	Lvl	Type	Data
AP FD08	DFHZSTU	TC 1	STATUS entry	Format 02
AP FD09	DFHZTSP	TC 1	TRANS_ROUTING entry	Format 14
AP FD0B	DFHZISP	TC 1	FACILITY_REQ entry	Format 02
AP FD0C	DFHZIS1	TC 1	ISC_SYNC_REQ entry	Format 02
AP FD0D	DFHZIS2	TC 1	IRC entry	Format 13
AP FD0E	DFHZABD	TC 1	ABEND entry	Format 02
AP FD10	DFHZATI	TC 1	ATI entry	Format 01
AP FD11	DFHZATT	TC 1	ATTACH entry	Format 01
AP FD14	DFHZRAC	TC 1	RECV_ANY event	Format 01
AP FD15	DFHZRST	TC 1	RESETSR entry	Format 01
AP FD16	DFHZRVS	TC 1	RECV_SPEC entry	Format 01
AP FD18	DFHZSDS	TC 1	SEND_DFSYN entry	Format 01
AP FD1C	DFHZACT	TC 1	ACTIVATE_SCAN event	Format 01
AP FD1D	DFHZSDR	TC 1	SEND_DFSYN_RESP entry	Format 01
AP FD1E	DFHZHPSR	TC 1	HPO_SEND_RECV entry	Format 01
AP FD22	DFHZCLS	TC 1	CLSDST entry	Format 01
AP FD27	DFHZLRP	TC 1	LOGREC entry	Format 01
AP FD29	DFHZOPN	TC 1	OPNDST entry	Format 01
AP FD2B	DFHZRAQ	TC 1	RA_QUEUEING entry	Format 01
AP FD2C	DFHZRAR	TC 1	RA_RETRIEVAL entry	Format 01
AP FD33	DFHZSDA	TC 1	SEND_DFASY entry	Format 01
AP FD34	DFHZSKR	TC 1	SEND_SESSIONC_RESPONSE entry	Format 01
AP FD35	DFHZSES	TC 1	SESSIONC entry	Format 01
AP FD37	DFHZSIM	TC 1	SIMLOGON entry	Format 01
AP FD39	DFHZSLS	TC 1	INIT_RECV_ANY entry	Format 05
AP FD3E	DFHZOPA	TC 1	OPEN_VTAM_ACB entry	Format 03
AP FD3F	DFHZSHU	TC 1	SHUTDOWN event	Format 04
AP FD41	DFHZEMW	TC 1	APPL_ERP entry	Format 01
AP FD42	DFHZSYN	TC 1	SYNCPOINT entry	Format 02
AP FD44	DFHZAND	TC 1	TACB_CREATE entry	Format 01
AP FD45	DFHZCNA	TC 1	CONSOLE_CTRL event	Format 06
AP FD46	DFHZCNR	TC 1	CONSOLE_REQ entry	Format 06
AP FD4A	DFHZARL	TC 1	ISC_APPL_REQ entry	Format 07
AP FD4B	DFHZARM	TC 1	ISC_MIGR_REQ entry	Format 08
AP FD4C	DFHZRVL	TC 1	ISC_RECV_REQ entry	Format 10
AP FD4E	DFHZSDL	TC 1	ISC_SEND_DFSYN entry	Format 10
AP FD50	DFHZERH	TC 1	ISC_APPL_ERP entry	Format 07
AP FD51	DFHZLUS	TC 1	ISC_LU_SERV entry	Format 09
AP FD52	DFHZBKT	TC 1	ISC_BRACKET_FSM entry	Format 11
AP FD53	DFHZCNT	TC 1	ISC_CONT_FSM entry	Format 11
AP FD54	DFHZCHS	TC 1	ISC_CHAIN_FSM entry	Format 11
AP FD56	DFHZUSR	TC 1	ISC_CONV_FSM entry	Format 11
AP FD58	DFHZEV1	TC 1	ISC_1ARY_BIND_SEC entry	Format 01
AP FD59	DFHZEV2	TC 1	ISC_2ARY_BIND_SEC entry	Format 01
AP FD5E	DFHZXRC	TC 1	XRF_SW_ANALYSIS entry	Format 01
AP FD63	DFHZSTAP	TC 1	APPL_STATE entry	Format 15
AP FD64	DFHZRLP	TC 1	ISC_RECV_SPEC_PV entry	Format 10
AP FD65	DFHZCRT	TC 1	ISC_RECV_SPEC_PV entry	Format 99
AP FD66	DFHZRAS	TC 1	RECV_ANY_SLOWDOWN entry	Format 98
AP FD7D	DFHZRLG	TC 1	RESP_LOGGER event	Format 01
AP FD7E	DFHZNAC	TC 1	NACP_START event	Format 01
AP FD81	DFHZARQ	TC 1	APPL_REQ exit	Format 02
AP FD82	DFHZLOC	TC 1	LOCATE exit	Format 02
AP FD88	DFHZSTU	TC 1	STATUS exit	Format 02

Table 107. Intersystem communication (continued)

Point ID	Module	Lvl	Type	Data
AP FD89	DFHZTSP	TC 1	TRANS_ROUTING exit	Format 14
AP FD8B	DFHZISP	TC 1	FACILITY_REQ exit	Format 02
AP FD8C	DFHZIS1	TC 1	ISC_SYNC_REQ exit	Format 02
AP FD8D	DFHZIS2	TC 1	IRC exit	Format 13
AP FD91	DFHZATT	TC 1	ATTACH exit	Format 05
AP FDBE	DFHZOPA	TC 1	OPEN_VTAM_ACB exit	Format 05
AP FDBF	DFHZSHU	TC 1	SHUTDOWN exit	Format 03
AP FDC1	DFHZEMW	TC 1	APPL_ERP exit	Format 02
AP FDC4	DFHZAND	TC 1	TACB_CREATE exit	Format 05
AP FDC6	DFHZCNR	TC 1	CONSOLE_REQ exit	Format 02
AP FDCA	DFHZARL	TC 1	ISC_APPL_REQ exit	Format 07
AP FDCB	DFHZARM	TC 1	ISC_MIGR_REQ exit	Format 08
AP FDCC	DFHZRVL	TC 1	ISC_RECV_REQ exit	Format 10
AP FDD0	DFHZERH	TC 1	ISC_APPL_ERP exit	Format 05
AP FDD1	DFHZLUS	TC 1	ISC_LU_SERV exit	Format 02
AP FDE3	DFHZSTAP	TC 1	APPL_STATE exit	Format 15
AP FDE4	DFHZRLP	TC 1	ISC_RECV_SPEC_PV exit	Format 10
AP FDE5	DFHZCRT	TC 1	ISC_RECV_SPEC_PV exit	Format 99
AP FDE6	DFHZRAS	TC 1	RECV_ANY_SLOWDOWN exit	Format 98

Formats for AP FDxx traces

AP FDxx trace entries take one of the following forms:

Format 01

- # 1 TCTE_TRACE_1 fields in TCTTE
- # 2 TCTE_TRACE_5 fields in TCTTE (VTAM only)
- # 3 Exit footprints¹, address of TCTTE (VTAM only)

Format 02

- 1 TCATP_TRACE fields in TCA
- 2 TCA from DFHUSTCA to TCAFCAAA

Format 03

- 1 TCTV_TRACE fields in TCT prefix

Format 04

- 1 TCTE_TRACE_1 fields in TCTTE
- 2 TCTE_TRACE_5 fields in TCTTE
- 3 Exit footprints¹, address of TCTTE
- 4 TCTV_TRACE fields in TCT prefix

Format 05

No data

Format 06

- 1 TCTE_TRACE_1 fields in TCTTE
- 2 TCTEOS console overlay of TCTTE
- 3 Console control element

Format 07

- 1 LUC parameter list

Format 08

- 1 LUM parameter list

Format 09

- 1 LUS parameter list

Format 10

- 1 TCTE_TRACE_1 fields in TCTTE
- 2 TCTE_TRACE_5 fields in TCTTE
- 3 Exit footprints¹, address of TCTTE
- 4 TCTE_LUCX_TRACE fields in LUC extension

Format 11	
1	TCTE_TRACE_1 fields in TCTTE
2	TCTE_TRACE_5 fields in TCTTE
3	Exit footprints ¹ , address of TCTTE
4	FSM parameter list (request word, address of TCTTE)
Format 12	
Not used.	
Format 13	
1	ISCRQ
Format 14	
1	ISCRQ
2	TCA from DFHUSTCA to TCAFCAAA
3	Field XTSAATTEU address of TCTTE
Format 15	
1	ZSTA parameter list
Format 98	
1	(on entry) TCTVNPRC
2	(on exit) RSNQCNT
Format 99	
1	TCTE_TRACE_1 fields in TCTTE
2	TCTERPBS
3	Exit footprints ¹ , address of TCTTE
4	FSM parameter list (request word, address of TCTTE)

¹ An exit footprint is a CICS DFHZC* module name.

Terminal control (LU6.2 application requests)

Table 108. Terminal control (LU6.2 application requests)

Point ID	Module	Lvl	Type	Data
AP FE00	DFHZARR	TC 2	Entry	1 DFHLUC parameter list
AP FE01	DFHZARR	TC 2	Exit	1 DFHLUC parameter list
AP FE02	DFHZARRA	TC 2	Entry	1 Call function code 2 Data address 3 Data length 4 DFHLUC parameter list 5 TCTTE address 6 Application buffer address 7 Application buffer length
AP FE03	DFHZARRA	TC 2	Exit	1 Call function code 2 Data address 3 Data length 4 DFHLUC parameter list 5 TCTTE address 6 Application buffer address 7 Application buffer length
AP FE04	DFHZARR0	TC 2	Entry	1 Call function code 2 Item to process 3 Record length 4 TCTTE address 5 LU6.2 logical buffer address 6 LU6.2 logical buffer length

Table 108. Terminal control (LU6.2 application requests) (continued)

Point ID	Module	Lvl	Type	Data
AP FE05	DFHZARR0	TC 2	Exit	1 Call function code 2 Item to process 3 Record length 4 TCTTE address 5 LU6.2 logical buffer address 6 LU6.2 logical buffer length 7 Response code
AP FE06	DFHZARRC	TC 2	Entry	1 LU6.2 logical buffer address 2 LU6.2 logical buffer length 3 TCTTE address
AP FE07	DFHZARRC	TC 2	Exit	1 LU6.2 logical buffer address 2 LU6.2 logical buffer length 3 TCTTE address 4 Item to process 5 Current record length 6 Complete record length 7 Response code
AP FE08	DFHZARRF	TC 2	Entry	1 Call function code 2 Request_type 3 DFHLUC parameter list 4 TCTTE address 5 LU6.2 logical buffer address 6 LU6.2 logical buffer length
AP FE09	DFHZARRF	TC 2	Exit	1 Call function code 2 Request_type 3 DFHLUC parameter list 4 TCTTE address 5 LU6.2 logical buffer address 6 LU6.2 logical buffer length 7 Response code
AP FE0A	DFHZARR1	TC 2	Entry	1 Receive request code 2 Minimum buffer length 3 TCTTE address 4 LU6.2 logical buffer address 5 LU6.2 logical buffer length
AP FE0B	DFHZARR1	TC 2	Exit	1 Receive request code 2 Minimum buffer length 3 TCTTE address 4 LU6.2 logical buffer address 5 LU6.2 logical buffer length 6 Response code
AP FE0C	DFHZARER	TC 2	Entry	1 Error Code 2 DFHLUC parameter list 3 TCTTE address
AP FE0D	DFHZARER	TC 2	Exit	1 Error Code 2 DFHLUC parameter list 3 TCTTE address

Table 108. Terminal control (LU6.2 application requests) (continued)

Point ID	Module	Lvl	Type	Data
AP FE20	DFHZARER	Exc	Invalid call to DFHZARER	1 Error type 2 DFHLUC parameter list 3 TCTTE address
AP FE22	DFHZARRF	Exc	Error not returned from ZERH	1 Call function code 2 Receive_type 3 DFHLUC parameter list 4 TCTTE address 5 LU6.2 logical buffer address 6 LU6.2 logical buffer length
AP FE23	DFHZARR	Exc	Internal logic error	1 Error code 2 DFHLUC parameter list 3 Receive_type 4 Request_type
AP FE24	DFHZARRF	Exc	Invalid call to DFHZARRF	1 Call function code 2 Receive_type 3 DFHLUC parameter list 4 TCTTE address 5 LU6.2 logical buffer address 6 LU6.2 logical buffer length
AP FE25	DFHZARRF	Exc	Bad LUCSDBLK from DFHZERH	1 Call function code 2 Receive_type 3 DFHLUC parameter list 4 TCTTE address 5 LU6.2 logical buffer address 6 LU6.2 logical buffer length
AP FE26	DFHZARR0	Exc	Record length > buffer length	1 Call function code 2 Item to process 3 Record length 4 TCTTE address 5 LU6.2 logical buffer address 6 LU6.2 logical buffer length
AP FE27	DFHZARR1	Exc	Invalid call to DFHZARR1	1 Request_type 2 Minimum buffer length required 3 TCTTE address 4 LU6.2 logical buffer address 5 LU6.2 logical buffer length
AP FE28	DFHZARR	Exc	Unexpected receive type	1 DFHLUC parameter list 2 Receive_type
AP FE29	DFHZARR	Exc	Unexpected DFHZUSR state error	1 State transition required 2 DFHLUC parameter list 3 TCTTE address 4 Response from DFHZUSR (R15)

Table 108. Terminal control (LU6.2 application requests) (continued)

Point ID	Module	Lvl	Type	Data
AP FE2A	DFHZARRF	Exc	Unexpected DFHZUSR state error	1 State transition required 2 DFHLUC parameter list 3 TCTTE address 4 Response from DFHZUSR (R15) 2 TCTTE address 3 TCTTE field TCTERBA 4 TCTTE field TCTERBLA 5 TCTTE LUC extension
AP FE2C	DFHZARR0	Exc	Corrupted LU6.2 buffer	1 Call function code 2 TCTTE address 3 TCTTE field TCTERBA 4 TCTTE field TCTERBLA 5 TCTTE LUC extension
AP FE2D	DFHZARR0	Exc	Invalid LU6.2 buffer pointers	1 Call function code 2 TCTTE address 3 TCTTE field TCTERBA 4 TCTTE field TCTERBLA 5 TCTTE field TCTERBDL 6 TCTTE field TCTERBLL 7 TCTTE LUC extension
AP FE2E	DFHZARR0	Exc	Invalid call to DFHZARR0	1 Call function code 2 Item to process 3 Record length 4 TCTTE address 5 LU6.2 logical buffer address 6 LU6.2 logical buffer length
AP FE2F	DFHZARRC	Exc	Invalid FMH address	1 TCTTE field TCTEFMHA 2 LU6.2 logical buffer address 3 LU6.2 logical buffer length 4 TCTTE address
AP FE30	DFHZARRA	Exc	Negative TCTELLC detected	1 Call function code 2 TCTTE field TCTELLC 3 TCTTE address 2 Response code
AP FE32	DFHZARR	Exc	Unexpected resp from DFHZARRC	1 Error code 2 DFHLUC parameter list 3 LU6.2 logical buffer address 4 LU6.2 logical buffer length 5 Item to process 6 Current record length 7 Complete record length
AP FE33	DFHZARR	Exc	Unexpected resp from internal subroutine	1 DFHLUC parameter list 2 Response code
AP FE34	DFHZARR1	Exc	Unexpected resp from DFHZARR0	1 Response code 2 TCTTE address 3 Call function code

Table 108. Terminal control (LU6.2 application requests) (continued)

Point ID	Module	Lvl	Type	Data
AP FE35	DFHZARRF	Exc	Unexpected resp from DFHZARR0	1 Response code 2 TCTTE address 3 Call function code
AP FE36	DFHZARRA	Exc	Corrupted eyecatcher	1 Call function code 2 TCTTE field TCTERCSA 3 TCTTE address
AP FE37	DFHZARRA	Exc	Invalid application buffer	1 Call function code 2 Data address 3 Data length 4 DFHLUC parameter list 5 TCTTE address 6 Application buffer address 7 Application buffer length
AP FE38	DFHZARRA	Exc	Unable to GETMAIN buffer	1 Call function code 2 Data address 3 Data length 4 DFHLUC parameter list 5 TCTTE address 6 Application buffer address 7 Application buffer length
AP FE39	DFHZARRA	Exc	Invalid call to DFHZARRA	1 Call function code 2 Data address 3 Data length 4 DFHLUC parameter list 5 TCTTE address 6 Application buffer address 7 Application buffer length
AP FE3A	DFHZARER	Exc	DFHZNAC logic error	1 Error type 2 DFHLUC parameter list 3 TCTTE address
AP FE3B	DFHZARR1	Exc	Returning bad resp to caller	1 Response code 2 TCTTE address
AP FE3C	DFHZARRF	Exc	Returning bad resp to caller	1 Response code 2 TCTTE address
AP FE3D	DFHZARRC	Exc	Returning bad resp to caller	1 Response code 2 TCTTE address 3 LU6.2 logical buffer address 4 LU6.2 logical buffer length
AP FE3E	DFHZARR0	Exc	Returning bad resp to caller	1 Response code 2 Call function code 3 Item to process 4 Record length 5 TCTTE address 6 TCTTE LUC extension
AP FE3F	DFHZARRA	Exc	GETMAIN failed	
AP FE40	DFHZARRA	Exc	Task purged detected	

Table 108. Terminal control (LU6.2 application requests) (continued)

Point ID	Module	Lvl	Type	Data
AP FE41	DFHZARER	Exc	Task purge detected	1 DFHLUC plist 2 Call function
AP FE42	DFHZARER	Exc	Errors during error processing	1 TCTTE address 2 Call function 3 DFHLUC plist
AP FE43	DFHZARER	Exc	CLSDST requested	1 Call function 2 DFHLUC plist 3 TCTTE address 4 TCTEER15 5 Termid
AP FE44	DFHZARER	Exc	Unexpected DFHZUSR state error	1 DFHLUC parameter list 2 TCTTE address 3 Response from DFHZUSR (R15)
AP FE45	DFHZARR1	Exc	Unexpected response from dispatcher	1 DSSR parameter list 2 TCTTE address
AP FE46	DFHZARER	Exc	Session failure detected	1 LUC parameter list 2 TCTTE address
AP FE47	DFHZARER	Exc	Unexpected response from dispatcher	1 LUC parameter list 2 TCTTE address 3 DSSR parameter list

For further possible trace points, see "Trace points in common subroutines" on page 35.

Business application manager trace points

Table 109. Business application manager trace points

Point ID	Module	Lvl	Type	Data
BA 0101	DFHBADM	BA 1	Entry	1 DMDM parameter list
BA 0102	DFHBADM	BA 1	Exit	1 DMDM parameter list
BA 0103	DFHBADM	Exc	Recovery	1 DMDM parameter list 2 Kernel error data
BA 0104	DFHBADM	Exc	Invalid format	1 DMDM parameter list
BA 0105	DFHBADM	Exc	Invalid function	1 DMDM parameter list
BA 0106	DFHBADM	Exc	Failed to release lock	1 DMDM parameter list
BA 0107	DFHBADM	Exc	Getmain for anchor block failed	1 DMDM parameter list
BA 0110	DFHBAPR	BA 1	Entry	1 BAPR parameter list 2 Process name

Table 109. Business application manager trace points (continued)

Point ID	Module	Lvl	Type	Data
BA 0111	DFHBAPR	BA 1	Exit	1 BAPR parameter list 2 Process name
BA 0112	DFHBAPR	Exc	Recovery	1 BAPR parameter list 2 Kernel error data
BA 0113	DFHBAPR	Exc	Invalid format	1 BAPR parameter list
BA 0114	DFHBAPR	Exc	Invalid function	1 BAPR parameter list
BA 0115	DFHBAPR	Exc	Failed to release lock	1 BAPR parameter list
BA 0120	DFHBAAC	BA 1	Entry	1 BAAC or BAGD parameter list 2 Activity id
BA 0121	DFHBAAC	BA 1	Exit	1 BAAC or BAGD parameter list
BA 0122	DFHBAAC	Exc	Recovery	1 BAAC or BAGD parameter list 2 Kernel error data
BA 0123	DFHBAAC	Exc	Invalid format	1 BAAC or BAGD parameter list
BA 0124	DFHBAAC	Exc	Invalid function	1 BAAC or BAGD parameter list
BA 0125	DFHBAAC	Exc	Failed to release lock	1 BAAC or BAGD parameter list
BA 0126	DFHBAAC	Exc	Invalid length	1 BAAC or BAGD parameter list
BA 0130	DFHBACR	BA 1	Entry	1 BACR parameter list
BA 0131	DFHBACR	BA 1	Exit	1 BACR parameter list
BA 0132	DFHBACR	Exc	Recovery	1 BACR parameter list 2 Kernel error data
BA 0133	DFHBACR	Exc	Invalid format	1 BACR parameter list
BA 0134	DFHBACR	Exc	Invalid function	1 BACR parameter list
BA 0135	DFHBACR	Exc	Failed to release lock	1 BACR parameter list
BA 0140	DFHBASP	BA 1	Entry	1 RMRO, RMDE or RMKP parameter list
BA 0141	DFHBASP	BA 1	Exit	1 RMRO, RMDE or RMKP parameter list

Table 109. Business application manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
BA 0142	DFHBASP	Exc	Recovery	1	RMRO, RMDE or RMKP parameter list
				2	Kernel error data
BA 0143	DFHBASP	Exc	Invalid format	1	RMRO, RMDE or RMKP parameter list
BA 0144	DFHBASP	Exc	Invalid function	1	RMRO, RMDE or RMKP parameter list
BA 0145	DFHBASP	Exc	Failed to release lock	1	RMRO, RMDE or RMKP parameter list
BA 0150	DFHBABR	BA 1	Entry	1	BABR parameter list
				2	Activity id
BA 0151	DFHBABR	BA 1	Exit	1	BABR parameter list
				2	Process name
				3	Activity id
BA 0152	DFHBABR	Exc	Recovery	1	BABR parameter list
				2	Kernel error data
BA 0153	DFHBABR	Exc	Invalid format	1	BABR parameter list
BA 0154	DFHBABR	Exc	Invalid function	1	BABR parameter list
BA 0155	DFHBABR	Exc	Invalid length	1	BABR parameter list
BA 0156	DFHBABR	Exc	Invalid buffer length	1	BABR parameter list
BA 0160	DFHBATT	BA 1	Entry	1	BATT parameter list
BA 0161	DFHBATT	BA 1	Exit	1	BATT parameter list
BA 0162	DFHBATT	Exc	Recovery	1	BATT parameter list
				2	Kernel error data
BA 0163	DFHBATT	Exc	Invalid format	1	BATT parameter list
BA 0164	DFHBATT	Exc	Invalid function	1	BATT parameter list
BA 0165	DFHBATT	Exc	Failed to lock domain	1	BATT parameter list
BA 0166	DFHBATT	Exc	Failed to unlock domain	1	BATT parameter list
BA 0167	DFHBATT	Exc	Unknown kernel error	1	BATT parameter list
BA 0170	DFHBAXM	BA 1	Entry	1	BAXM parameter list
				2	BAXM request block
BA 0171	DFHBAXM	BA 1	Exit	1	BAXM parameter list
				2	BAXM request block

Table 109. Business application manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
BA 0172	DFHBAXM	Exc	Recovery	1	BAXM parameter list
				2	Kernel error data
BA 0173	DFHBAXM	Exc	Invalid format	1	BAXM parameter list
BA 0174	DFHBAXM	Exc	Invalid function	1	BAXM parameter list
BA 0175	DFHBAXM	Exc	Failed to lock domain	1	BAXM parameter list
BA 0180	DFHBAUE	BA 1	Entry	1	APUE parameter list
BA 0181	DFHBAUE	BA 1	Exit	1	APUE parameter list
BA 0182	DFHBAUE	Exc	Recovery	1	APUE parameter list
				2	Kernel error data
BA 0183	DFHBAUE	Exc	Invalid format	1	APUE parameter list
BA 0184	DFHBAUE	Exc	Invalid function	1	APUE parameter list
BA 0185	DFHBAUE	Exc	Invalid exit point	1	APUE parameter list
BA 0190	DFHBAAC0	BA 2	Entry	1	BAAC parameter list
BA 0191	DFHBAAC0	BA 2	Exit	1	BAAC parameter list
BA 0192	DFHBAAC0	Exc	Recovery	1	BAAC parameter list
				2	Kernel error data
BA 0193	DFHBAAC0	Exc	Invalid format	1	BAAC parameter list
BA 0194	DFHBAAC0	Exc	Invalid function	1	BAAC parameter list
BA 0195	DFHBAAC0	Exc	Failed to unlock domain	1	BAAC parameter list
BA 01A0	DFHBAPR0	BA 1	Entry	1	BAPR parameter list
				2	Process name
BA 01A1	DFHBAPR0	BA 1	Exit	1	BAPR parameter list
				2	Process name
BA 01A2	DFHBAPR0	Exc	Recovery	1	BAPR parameter list
				2	Kernel error data
BA 01A3	DFHBAPR0	Exc	Invalid format	1	BAPR parameter list
BA 01A4	DFHBAPR0	Exc	Invalid function	1	BAPR parameter list
BA 01A5	DFHBAPR0	Exc	Failed to unlock domain	1	BAPR parameter list
BA 0200	DFHBAAC1	BA 1	Entry	1	DMDM parameter list
BA 0201	DFHBAAC1	BA 1	Exit	1	Response code

Table 109. Business application manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
BA 0202	DFHBAAC1	Exc	Recovery	1	Response code
				2	Kernel error data
BA 0203	DFHBAAC1	Exc	Getmain failed	1	Response code
BA 0209	DFHBAAC2	BA 1	Entry	1	Activity reference
BA 020A	DFHBAAC2	BA 1	Exit	1	Response code
BA 020B	DFHBAAC2	Exc	Recovery	1	Response code
				2	Kernel error data
BA 020C	DFHBAAC2	BA 2	Flatten activity	1	Buffer contents
				2	Buffer key
				3	Segment contents
BA 0210	DFHBAAC3	BA 1	Entry	1	Activity reference
BA 0211	DFHBAAC3	BA 1	Exit	1	Response code
BA 0212	DFHBAAC3	Exc	Recovery	1	Response code
				2	Kernel error data
BA 0220	DFHBAAC4	BA 1	Entry	1	Activity reference
BA 0221	DFHBAAC4	BA 1	Exit	1	Response code
BA 0222	DFHBAAC4	Exc	Recovery	1	Response code
				2	Kernel error data
BA 0230	DFHBAAC5	BA 1	Entry	1	Activity key
BA 0231	DFHBAAC5	BA 1	Exit	1	Response code
BA 0232	DFHBAAC5	Exc	Recovery	1	Response code
				2	Kernel error data
BA 0240	DFHBAAC6	BA 1	Entry	1	Activity reference
				2	Exit id
BA 0241	DFHBAAC6	BA 1	Exit	1	Response code
BA 0242	DFHBAAC6	Exc	Recovery	1	Response code
				2	Kernel error data
BA 0243	DFHBAAC6	Exc	Invalid exit	1	Exit id
BA 0244	DFHBAAC6	Exc	Invocation of exit failed	1	APEX parameter list
BA 0250	DFHBAA10	BA 1	Entry	1	File name
				2	Activity key
BA 0251	DFHBAA10	BA 1	Exit	1	Response code
				2	Activity record

Table 109. Business application manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
BA 0252	DFHBAA10	Exc	Recovery	1	Response code
				2	Kernel error data
BA 0260	DFHBAA11	BA 1	Entry	1	File name
				2	Activity id
BA 0261	DFHBAA11	BA 1	Exit	1	Response code
				2	Activity record
BA 0262	DFHBAA11	Exc	Recovery	1	Response code
				2	Kernel error data
BA 0270	DFHBAA12	BA 1	Entry	1	File name
				2	Process reference
				3	Activity record
				4	Event
BA 0271	DFHBAA12	BA 1	Exit	1	Response code
BA 0272	DFHBAA12	Exc	Recovery	1	Response code
				2	Kernel error data
BA 0300	DFHBACO1	BA 1	Entry	1	Response code
BA 0301	DFHBACO1	BA 1	Exit	1	Response code
BA 0302	DFHBACO1	Exc	Recovery	1	Response code
				2	Kernel error data
BA 0303	DFHBACO1	Exc	Getmain failed	1	Response code
BA 0400	DFHBAVP1	BA 2	Entry	1	Response code
BA 0401	DFHBAVP1	BA 2	Exit	1	Response code
BA 0402	DFHBAVP1	Exc	Recovery	1	Response code
				2	Kernel error data
BA 0410	DFHBAOFI	BA 2	Entry	1	Response code
BA 0411	DFHBAOFI	BA 2	Exit	1	Response code
BA 0412	DFHBAOFI	Exc	Recovery	1	Response code
				2	Kernel error data
BA 0500	DFHBAPT1	BA 1	Entry	1	Response code
BA 0501	DFHBAPT1	BA 1	Exit	1	Response code
BA 0502	DFHBAPT1	Exc	Recovery	1	Response code
				2	Kernel error data
BA 0503	DFHBAPT1	Exc	Getmain failed	1	Response code
BA 0504	DFHBAPT1	Exc	Directory create failed	1	Response code

Table 109. Business application manager trace points (continued)

Point ID	Module	Lvl	Type	Data
BA 0510	DFHBAPT2	BA 1	Entry	1 Response code 2 Reason code
BA 0511	DFHBAPT2	BA 1	Exit	1 Response code 2 Reason code
BA 0512	DFHBAPT2	Exc	Recovery	1 Response code 2 Kernel error data
BA 0520	DFHBAPT3	BA 1	Entry	1 Response code 2 Reason code
BA 0521	DFHBAPT3	BA 1	Exit	1 Response code 2 Reason code
BA 0522	DFHBAPT3	Exc	Recovery	1 Response code 2 Kernel error data
BA 0600	DFHBAAR1	BA 1	Entry	1 Response code
BA 0601	DFHBAAR1	BA 1	Exit	1 Response code
BA 0602	DFHBAAR1	Exc	Recovery	1 Response code 2 Kernel error data
BA 0603	DFHBAAR1	Exc	Getmain failed	1 Response code
BA 0610	DFHBAAR2	BA 1	Entry	1 Function 2 Audit data 3 Audit data 4 Audit data 5 Audit data 6 Audit data
BA 0611	DFHBAAR2	BA 1	Exit	1 Response code
BA 0612	DFHBAAR2	Exc	Recovery	1 Response code 2 Kernel error data
BA 0613	DFHBAAR2	Exc	Invalid parameter	1 Response code
BA 0614	DFHBAAR2	Exc	Getmain failed	1 Response code
BA 0700	DFHBALR1	BA 1	Entry	1 Response code
BA 0701	DFHBALR1	BA 1	Exit	1 Response code
BA 0702	DFHBALR1	Exc	Recovery	1 Response code 2 Kernel error data
BA 0703	DFHBALR1	Exc	Getmain failed	1 Response code
BA 0709	DFHBALR2	BA 1	Entry	1 Record key
BA 070A	DFHBALR2	BA 1	Exit	1 Response code 2 Record key

Table 109. Business application manager trace points (continued)

Point ID	Module	Lvl	Type	Data
BA 070B	DFHBALR2	Exc	Recovery	1 Response code 2 Kernel error data
BA 0710	DFHBALR3	BA 1	Entry	1 Buffer contents 2 Key 3 Sequence number
BA 0711	DFHBALR3	BA 1	Exit	1 Response code
BA 0712	DFHBALR3	Exc	Recovery	1 Response code 2 Kernel error data
BA 0719	DFHBALR4	BA 1	Entry	1 Record key
BA 071A	DFHBALR4	BA 1	Exit	1 Response code 2 Buffer contents 3 Buffer address
BA 071B	DFHBALR4	Exc	Recovery	1 Response code 2 Kernel error data
BA 0720	DFHBALR5	BA 1	Entry	1 Buffer contents
BA 0721	DFHBALR5	BA 1	Exit	1 Response code 2 Record contents
BA 0722	DFHBALR5	Exc	Recovery	1 Response code 2 Kernel error data
BA 0729	DFHBALR6	BA 1	Entry	1 Record key
BA 072A	DFHBALR6	BA 1	Exit	1 Response code
BA 072B	DFHBALR6	Exc	Recovery	1 Response code 2 Kernel error data
BA 0730	DFHBALR7	BA 1	Entry	
BA 0731	DFHBALR7	BA 1	Exit	1 Response code
BA 0732	DFHBALR7	Exc	Recovery	1 Response code 2 Kernel error data
BA 0738	DFHBALR8	BA 1	Entry	1 Reqid
BA 0739	DFHBALR8	BA 1	Exit	1 Response code 2 Record contents
BA 073A	DFHBALR8	Exc	Recovery	1 Response code 2 Kernel error data
BA 0740	DFHBALR9	BA 1	Entry	1 Reqid
BA 0741	DFHBALR9	BA 1	Exit	1 Response code

Table 109. Business application manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
BA 0742	DFHBALR9	Exc	Recovery	1	Response code
				2	Kernel error data
BA 0800	DFHBABU1	BA 1	Entry	1	Response code
BA 0801	DFHBABU1	BA 1	Exit	1	Response code
BA 0802	DFHBABU1	Exc	Recovery	1	Response code
				2	Kernel error data
BA 0803	DFHBABU1	Exc	Getmain failed	1	Response code
BA 0810	DFHBABU	BA 1	Reserve bytes entry	1	Buffer control block
				2	Number of bytes to reserve
BA 0811	DFHBABU	BA 1	Reserve bytes exit	1	Buffer control block
				2	Number of bytes reserved
				3	Pointer to first byte
				4	Buffer contents
BA 0812	DFHBABU	BA 1	Read bytes entry	1	Buffer control block
				2	Number of bytes to read
BA 0813	DFHBABU	BA 1	Read bytes exit	1	Buffer control block
				2	Number of bytes read
				3	Pointer to first byte
				4	Buffer contents

CICS catalog domain trace points

“CC” in the point ID or the level means either “GC” or “LC”, for the global and local catalog environments, respectively.

Table 110. CICS catalog domain trace points

Point ID	Module	Lvl	Type	Data	
CC 1010	DFHCCDM	CC 1	Initialization entry	1	DMDM parameter list
CC 1020	DFHCCDM	Exc	Recovery	1	Kernel error data
CC 1040	DFHCCDM	CC 1	Initialization exit	1	DMDM parameter list
CC 1B30	DFHCCDM	Exc	VSAM error	1	Report message
				2	VSAM response code
				3	VSAM error code
CC 1B40	DFHCCDM	Exc	Bad SET PHASE response	1	Response code
				2	Reason code
CC 1B50	DFHCCDM	Exc	Add lock failure	1	Response code
				2	Reason code
CC 1B60	DFHCCDM	Exc	Unlock failure	1	Response code
				2	Reason code

Table 110. CICS catalog domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
CC 2010	DFHCCCC	CC 1	Entry	1	CCCC parameter list
CC 2020	DFHCCCC	Exc	New VSAM extent		
CC 2050	DFHCCCC	CC 1	Exit	1	CCCC parameter list
CC 2070	DFHCCCC	Exc	Serialization entry error	1 2 3	CCCC parameter list Response code Reason code
CC 2080	DFHCCCC	Exc	Serialization exit error	1 2 3	CCCC parameter list Response code Reason code
CC 2090	DFHCCCC	Exc	VSAM serial lock failure	1 2 3	CCCC parameter list Response code Reason code
CC 20A0	DFHCCCC	Exc	VSAM serial unlock failure	1 2 3	CCCC parameter list Response code Reason code
CC 20B0	DFHCCCC	Exc	XC WAIT unlock failure	1 2 3	CCCC parameter list Response code Reason code
CC 20C0	DFHCCCC	Exc	XC WAIT lock failure	1 2 3	CCCC parameter list Response code Reason code
CC 2B10	DFHCCCC	Exc	Data too long for file	1	CCCC parameter list
CC 2B20	DFHCCCC	Exc	Invalid function request	1	CCCC parameter list
CC 2B30	DFHCCCC	Exc	Recovery	1 2	Kernel error data CCCC parameter list
CC 2B40	DFHCCCC	Exc	String wait unlock error	1 2 3	CCCC parameter list Response code Reason code
CC 2B41	DFHCCCC	Exc	String wait lock error	1 2 3	CCCC parameter list Response code Reason code
CC 2B42	DFHCCCC	Exc	Change mode failure	1 2 3	CCCC parameter list Response code Reason code
CC 2B43	DFHCCCC	Exc	Restore mode failure	1 2 3	CCCC parameter list Response code Reason code
CC 2B44	DFHCCCC	Exc	WAIT OLDC failure	1 2 3	CCCC parameter list Response code Reason code

Table 110. CICS catalog domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
CC 2B50	DFHCCCC	Exc	Invalid token	1	CCCC parameter list
CC 2B52	DFHCCCC	Exc	END BROWSE invalid token	1	CCCC parameter list
CC 2B53	DFHCCCC	Exc	END WRITE invalid token	1	CCCC parameter list
CC 2B54	DFHCCCC	Exc	GET NEXT invalid token	1	CCCC parameter list
CC 2B55	DFHCCCC	Exc	PUT REPLACE invalid token	1	CCCC parameter list
CC 2B56	DFHCCCC	Exc	WRITE NEXT invalid token	1	CCCC parameter list
CC 2B57	DFHCCCC	Exc	DELETE invalid token	1	CCCC parameter list
CC 2B58	DFHCCCC	Exc	Startup token in use, duplicate Startup Open		
CC 2B59	DFHCCCC	Exc	Startup token unused, not opened by Startup Open		
CC 2B5A	DFHCCCC	Exc	Startup Open and Close not valid for local catalog		
CC 2B5B	DFHCCCC	CC 2	Using Write_Next	1	Token
CC 2B5C	DFHCCCC	CC 1	Allocated token	1	Token
CC 2B60	DFHCCCC	Exc	VSAM error	1 2 3 4	VSAM response VSAM ACB VSAM RPLs current thread number
CC 2B70	DFHCCCC	Exc	Data too long for user's buffer	1	CCCC parameter list
CC 2B71	DFHCCCC	Exc	Data too long for file	1	CCCC parameter list
CC 2B72	DFHCCCC	Exc	Data too long to WRITE	1	CCCC parameter list
CC 2B73	DFHCCCC	Exc	Data too long to WRITE NEXT	1	CCCC parameter list

Directory domain trace points

Table 111. Directory domain trace entries

Point ID	Module	Lvl	Type	Data	
DD 0101	DFHDDDM	DD 1	Entry	1	DFHDDDM parameter list
DD 0102	DFHDDDM	DD 1	Exit	1	DFHDDDM parameter list
DD 0103	DFHDDDM	Exc	Invalid function	1	DFHDDDM parameter list
DD 0104	DFHDDDM	Exc	Invalid format	1	DFHDDDM parameter list
DD 0105	DFHDDDM	Exc	No storage for anchor	1	DFHDDDM parameter list
DD 0106	DFHDDDM	Exc	Unlock failed	1	DFHDDDM parameter list

Table 111. Directory domain trace entries (continued)

Point ID	Module	Lvl	Type	Data
DD 0107	DFHDDDM	Exc	Recovery entry	1 DFHDDDM parameter list 2 Kernel error data
DD 0108	DFHDDDM	Exc	Purge of DD catalog failed	1 DFHDDDM parameter list
DD 0201	DFHDDDI	DD 1	Entry	1 DFHDDDI parameter list 2 Directory name 3 Entry name
DD 0202	DFHDDDI	DD 1	Exit	1 DFHDDDI parameter list
DD 0203	DFHDDDI	Exc	Invalid function	1 DFHDDDI parameter list
DD 0204	DFHDDDI	Exc	Invalid format	1 DFHDDDI parameter list
DD 0205	DFHDDDI	Exc	Invalid directory	1 DFHDDDI parameter list
DD 0206	DFHDDDI	Exc	Invalid name length	1 DFHDDDI parameter list
DD 0207	DFHDDDI	Exc	Insufficient storage	1 DFHDDDI parameter list 2 Directory name
DD 0208	DFHDDDI	Exc	Add subpool failed	1 DFHDDDI parameter list
DD 0209	DFHDDDI	Exc	Add lock failed	1 DFHDDDI parameter list
DD 020A	DFHDDDI	Exc	Get lock failed	1 DFHDDDI parameter list 2 Directory name
DD 020B	DFHDDDI	Exc	Duplicate directory	1 DFHDDDI parameter list
DD 020C	DFHDDDI	DD 2	Delete not found	1 DFHDDDI parameter list 2 Directory name 3 Entry name
DD 020D	DFHDDDI	DD 2	Replace not found	1 DFHDDDI parameter list 2 Directory name 3 Entry name
DD 020E	DFHDDDI	DD 2	Duplicate name	1 DFHDDDI parameter list 2 Directory name 3 Entry name
DD 020F	DFHDDDI	Exc	Unlock failed	1 DFHDDDI parameter list 2 Directory name
DD 0210	DFHDDDI	Exc	Recovery unlock failed	1 DFHDDDI parameter list 2 Directory name
DD 0211	DFHDDDI	Exc	Recovery entry	1 DFHDDDI parameter list 2 Kernel error data
DD 0212	DFHDDDI	DD 2	Rehash start	1 DFHDDDI parameter list 2 Directory name 3 New hash size

Table 111. Directory domain trace entries (continued)

Point ID	Module	Lvl	Type	Data
DD 0213	DFHDDDI	DD 2	Rehash complete	1 DFHDDDI parameter list 2 Directory name
DD 0280	DFHDDDI	Exc	AVL initialization error	1 DFHDDDI parameter list
DD 0281	DFHDDDI	Exc	AVL add error	1 DFHDDDI parameter list 2 Directory name 3 Entry name
DD 0282	DFHDDDI	Exc	AVL delete error	1 DFHDDDI parameter list 2 Directory name 3 Entry name
DD 0283	DFHDDDI	Exc	AVL get error	1 DFHDDDI parameter list 2 Directory name 3 Entry name
DD 0301	DFHDDLO	DD 1	Entry	1 DFHDDLO parameter list 2 Directory name 3 Entry name
DD 0302	DFHDDLO	DD 1	Exit	1 DFHDDLO parameter list
DD 0303	DFHDDLO	Exc	Invalid function	1 DFHDDLO parameter list
DD 0304	DFHDDLO	Exc	Invalid format	1 DFHDDLO parameter list
DD 0305	DFHDDLO	Exc	Invalid directory	1 DFHDDLO parameter list
DD 0306	DFHDDLO	Exc	Recovery entry	1 DFHDDLO parameter list 2 Kernel error data
DD 0307	DFHDDLO	Exc	Lock error	1 DFHDDLO parameter list 2 Directory name
DD 0308	DFHDDLO	Exc	Unlock error	1 DFHDDLO parameter list 2 Directory name
DD 0309	DFHDDLO	Exc	Recovery unlock error	1 DFHDDLO parameter list 2 Directory name
DD 0401	DFHDDBR	DD 1	Entry	1 DFHDDBR parameter list 2 Directory name
DD 0402	DFHDDBR	DD 1	Exit	1 DFHDDBR parameter list 2 GET_NEXT = > dir name 3 GET_NEXT = > entry name
DD 0403	DFHDDBR	Exc	Invalid function	1 DFHDDBR parameter list
DD 0404	DFHDDBR	Exc	Invalid format	1 DFHDDBR parameter list
DD 0405	DFHDDBR	Exc	Invalid directory	1 DFHDDBR parameter list
DD 0406	DFHDDBR	Exc	Invalid browse	1 DFHDDBR parameter list 2 Directory name

Table 111. Directory domain trace entries (continued)

Point ID	Module	Lvl	Type	Data
DD 0407	DFHDDDBR	Exc	Invalid name	1 DFHDDDBR parameter list 2 Directory name
DD 0408	DFHDDDBR	Exc	Lock failed	1 DFHDDDBR parameter list 2 Directory name
DD 0409	DFHDDDBR	Exc	Unlock failed	1 DFHDDDBR parameter list 2 Directory name
DD 040A	DFHDDDBR	Exc	Recovery unlock failed	1 DFHDDDBR parameter list 2 Directory name
DD 040B	DFHDDDBR	Exc	Recovery entry	1 DFHDDDBR parameter list 2 Kernel error data
DD 0480	DFHDDDBR	Exc	AVL set cursor error	1 DFHDDDBR parameter list 2 Directory name 2 Browse_val
DD 0481	DFHDDDBR	Exc	AVL get current error	1 DFHDDDBR parameter list 2 Directory name 2 Browse_val
DD 0482	DFHDDDBR	Exc	AVL storage error	1 DFHDDDBR parameter list 2 Directory name

Document handler trace points

Table 112. Document handler trace points

Point ID	Module	Lvl	Type	Data
DH 0101	DFHDHDM	DH 1	Entry	1 DFHDMDM parameter list
DH 0102	DFHDHDM	DH 1	Exit	1 DFHDMDM parameter list
DH 0103	DFHDHDM	Exc	Invalid Format	1 DFHDMDM parameter list
DH 0104	DFHDHDM	Exc	Invalid Function	1 DFHDMDM parameter list
DH 0105	DFHDHDM	Exc	Recovery entered	1 DFHDMDM parameter list
DH 0106	DFHDHDM	Exc	No storage for anchor	1 DFHDMDM parameter list
DH 0107	DFHDHDM	Exc	Release lock error	1 DFHDMDM parameter list
DH 0108	DFHDHDM	Exc	Warm start error	1 DFHDMDM parameter list
DH 0120	DFHDHDH	DH 1	Entry	1 DFHDHDH parameter list
DH 0121	DFHDHDH	DH 1	Exit	1 DFHDHDH parameter list
DH 0122	DFHDHDH	Exc	Invalid Format	1 DFHDHDH parameter list
DH 0123	DFHDHDH	Exc	Invalid Function	1 DFHDHDH parameter list

Table 112. Document handler trace points (continued)

Point ID	Module	Lvl	Type	Data	
DH 0124	DFHDHHDH	Exc	Get exclusive lock error	1	DFHDHHDH parameter list
DH 0125	DFHDHHDH	Exc	Release exclusive lock error	1	DFHDHHDH parameter list
DH 0126	DFHDHHDH	Exc	Get shared lock error	1	DFHDHHDH parameter list
DH 0127	DFHDHHDH	Exc	Release shared lock error	1	DFHDHHDH parameter list
DH 0128	DFHDHHDH	Exc	Recovery release lock error	1	DFHDHHDH parameter list
DH 0129	DFHDHHDH	Exc	Recovery entered	1	DFHDHHDH parameter list
DH 012A	DFHDHHDH	Exc	Unknown kernel error code	1	DFHDHHDH parameter list
DH 0150	DFHDHHDH	Event	Validate document token	1	DCR control block
DH 0151	DFHDHHDH	Event	Locate symbol entry	1	Symbol name
DH 0152	DFHDHHDH	Event	Locate symbol exit	1 2 3	Symbol name Address of symbol value Length of symbol value
DH 0200	DFHDHSL	DH 1	Entry	1	DFHDHSL parameter list
DH 0201	DFHDHSL	DH 1	Exit	1	DFHDHSL parameter list
DH 0202	DFHDHSL	Exc	Invalid Format	1	DFHDHSL parameter list
DH 0203	DFHDHSL	Exc	Invalid Function	1	DFHDHSL parameter list
DH 0204	DFHDHSL	Exc	Get exclusive lock error	1	DFHDHSL parameter list
DH 0205	DFHDHSL	Exc	Release exclusive lock error	1	DFHDHSL parameter list
DH 0206	DFHDHSL	Exc	Get shared lock error	1	DFHDHSL parameter list
DH 0207	DFHDHSL	Exc	Release shared lock error	1	DFHDHSL parameter list
DH 0208	DFHDHSL	Exc	Recovery release lock error	1	DFHDHSL parameter list
DH 0209	DFHDHSL	Exc	Recovery entered	1	DFHDHSL parameter list
DH 020A	DFHDHSL	Exc	Unknown kernel error code	1	DFHDHSL parameter list
DH 0250	DFHDHSL	DH 2	Validate document token	1	DCR control block
DH 0251	DFHDHSL	DH 2	BBLX initialisation entry		
DH 0252	DFHDHSL	DH 2	BBLX initialisation exit	1	Symbol table address
DH 0253	DFHDHSL	DH 2	Add symbollist entry		
DH 0254	DFHDHSL	DH 2	Add symbollist exit		
DH 0255	DFHDHSL	DH 2	Add symbol entry	1 w	Symbol name Symbol value

Table 112. Document handler trace points (continued)

Point ID	Module	Lvl	Type	Data
DH 0256	DFHDHSL	DH 2	Add symbol exit	1 w Symbol name Symbol value
DH 0257	DFHDHSL	DH 2	BBLX Storage Interface entry	1 BBLX IFCB control block
DH 0258	DFHDHSL	DH 2	BBLX Storage Interface exit	1 BBLX IFCB control block
DH 0259	DFHDHSL	DH 2	BBLX Extension Storage Interface entry	1 BBLX IFCB control block
DH 025A	DFHDHSL	DH 2	BBLX Extension Storage Interface exit	1 BBLX IFCB control block
DH 0301	DFHDHRM	DH 1	Entry	1 DFHRMRO, DFHRMDE, or DFHRMKP parameter list
DH 0302	DFHDHRM	DH 1	Exit	1 DFHRMRO, DFHRMDE, or DFHRMKP parameter list
DH 0303	DFHDHRM	Exc	Recovery entered	1 DFHRMRO, DFHRMDE, or DFHRMKP parameter list
DH 0304	DFHDHRM	Exc	Invalid format	1 DFHRMRO, DFHRMDE, or DFHRMKP parameter list
DH 0305	DFHDHRM	Exc	Invalid RMRO function	1 DFHRMRO parameter list
DH 0306	DFHDHRM	Exc	Invalid RMDE function	1 DFHRMDE parameter list
DH 0307	DFHDHRM	Exc	Invalid RMKP function	1 DFHRMKP parameter list
DH 0308	DFHDHRM	Exc	Unlock error	1 DFHRMRO, DFHRMDE, or DFHRMKP parameter list
DH 0401	DFHDHTM	DH 1	Entry	1 DFHDHTM parameter list
DH 0402	DFHDHTM	DH 1	Exit	1 DFHDHTM parameter list
DH 0403	DFHDHTM	Exc	Recovery entered	1 DFHDHTM parameter list
DH 0404	DFHDHTM	Exc	Invalid Format	1 DFHDHTM parameter list
DH 0405	DFHDHTM	Exc	Invalid Function	1 DFHDHTM parameter list
DH 0406	DFHDHTM	Exc	Invalid resource type	1 DFHDHTM parameter list
DH 0407	DFHDHTM	Exc	Invalid browse token	1 DFHDHTM parameter list
DH 0408	DFHDHTM	Event	Template PDS open complete	1 DHPDC Control Block
DH 0409	DFHDHTM	Event	Template PDS BLDL complete	1 BLDL parameter list
DH 040A	DFHDHTM	Event	Template PDS I/O complete	1 2 3 4 DHTLC Control Block DHPDC Control Block IOB Control Block DECB Control Block

Table 112. Document handler trace points (continued)

Point ID	Module	Lvl	Type	Data
DH 0411	DFHDHTM	Exc	Template name in use	1 DFHDHTM parameter list
DH 0412	DFHDHTM	Exc	Catalog failure	1 DFHDHTM parameter list
DH 0413	DFHDHTM	Exc	Getmain failure	1 DFHDHTM parameter list
DH 0414	DFHDHTM	Exc	Freemain failure	1 DFHDHTM parameter list
DH 0415	DFHDHTM	Exc	Directory error	1 DFHDHTM parameter list
DH 0416	DFHDHTM	Exc	DOCTEMPLATE not found	1 DFHDHTM parameter list
DH 0417	DFHDHTM	Exc	DDNAME not found	1 DFHDHTM parameter list
DH 0418	DFHDHTM	Exc	Member not found	1 DFHDHTM parameter list
DH 0500	DFHDHPT	DH 1	Entry	1 DFHDHPT parameter list
DH 0501	DFHDHPT	DH 1	Exit	1 DFHDHPT parameter list
DH 0502	DFHDHPT	Exc	Recovery entered	1 DFHDHPT parameter list
DH 0503	DFHDHPT	Exc	Unknown kernel error code	1 DFHDHPT parameter list
DH 0600	DFHDHPB	DH 1	Entry	1 DFHDHPB parameter list
DH 0601	DFHDHPB	DH 1	Exit	1 DFHDHPB parameter list
DH 0602	DFHDHPB	Exc	Recovery entered	1 DFHDHPB parameter list
DH 0603	DFHDHPB	Exc	Unknown kernel error code	1 DFHDHPB parameter list
DH 0700	DFHDHPM	DH 1	Entry	1 DFHDHPM parameter list
DH 0701	DFHDHPM	DH 1	Exit	1 DFHDHPM parameter list
DH 0702	DFHDHPM	Exc	Recovery entered	1 DFHDHPM parameter list
DH 0703	DFHDHPM	Exc	Unknown kernel error code	1 DFHDHPM parameter list
DH 0800	DFHDHPS	DH 1	Entry	1 DFHDHPS parameter list
DH 0801	DFHDHPS	DH 1	Exit	1 DFHDHPS parameter list
DH 0802	DFHDHPS	Exc	Recovery entered	1 DFHDHPS parameter list
DH 0803	DFHDHPS	Exc	Unknown kernel error code	1 DFHDHPS parameter list
DH 0900	DFHDHPD	DH 1	Entry	1 DFHDHPD parameter list
DH 0901	DFHDHPD	DH 1	Exit	1 DFHDHPD parameter list
DH 0902	DFHDHPD	Exc	Recovery entered	1 DFHDHPD parameter list
DH 0903	DFHDHPD	Exc	Unknown kernel error code	1 DFHDHPD parameter list

Table 112. Document handler trace points (continued)

Point ID	Module	Lvl	Type	Data
DH 0A00	DFHDHPX	DH 1	Entry	1 DFHDHDDH parameter list
DH 0A01	DFHDHPX	DH 1	Exit	1 DFHDHDDH parameter list
DH 0A02	DFHDHPX	Exc	Recovery entered	1 DFHDHDDH parameter list
DH 0A03	DFHDHPX	Exc	Unknown kernel error code	1 DFHDHDDH parameter list
DH 0B00	DFHDHPU	DH 1	Entry	1 DFHDHDDH parameter list
DH 0B01	DFHDHPU	DH 1	Exit	1 DFHDHDDH parameter list
DH 0B02	DFHDHPU	Exc	Recovery entered	1 DFHDHDDH parameter list
DH 0B03	DFHDHPU	Exc	Unknown kernel error code	1 DFHDHDDH parameter list
DH 0C01	DFHDHRP	DH 1	Entry	1 DFHDHRP parameter list
DH 0C02	DFHDHRP	DH 1	Exit	1 DFHDHRP parameter list
DH 0C03	DFHDHRP	Exc	Recovery entered	1 DFHDHRP parameter list
DH 0C04	DFHDHRP	Exc	Invalid Format	1 DFHDHRP parameter list
DH 0C05	DFHDHRP	Exc	Invalid Function	1 DFHDHRP parameter list
DH 0C06	DFHDHRP	Exc	Get next error	1 DFHDHRP parameter list 1 DFHCCCC parameter list
DH 0C07	DFHDHRP	Exc	End browse error	1 DFHDHRP parameter list 1 DFHCCCC parameter list
DH 0C08	DFHDHRP	Exc	Add/replace error	1 DFHDHRP parameter list 1 DFHDHTM parameter list
DH 0D01	DFHDHUE	DH 1	Entry	1 DFHDHUE parameter list
DH 0D02	DFHDHUE	DH 1	Exit	1 DFHDHUE parameter list
DH 0D03	DFHDHUE	Exc	Recovery entered	1 DFHDHUE parameter list
DH 0D04	DFHDHUE	Exc	Invalid Format	1 DFHDHUE parameter list
DH 0D05	DFHDHUE	Exc	Invalid Function	1 DFHDHUE parameter list
DH 0D06	DFHDHUE	Exc	Get lock error	1 DFHDHUE parameter list
DH 0D07	DFHDHUE	Exc	Release lock error	1 DFHDHUE parameter list
DH 0D08	DFHDHUE	Exc	Unknown kernel error code	1 DFHDHUE parameter list

Domain manager domain trace points

Table 113. Domain manager domain trace points

Point ID	Module	Lvl	Type	Data
DM 0001	DFHDMMDM	DM 1	Entry	1 DMDM parameter list
DM 0002	DFHDMMDM	DM 1	Exit	1 DMDM parameter list
DM 0003	DFHDMIQ	DM 1	Entry	1 DMIQ parameter list
DM 0004	DFHDMIQ	DM 1	Exit	1 DMIQ parameter list
DM 0007	DFHDMDS	DM 2	Initialize call to domain	1 Domain token
DM 0008	DFHDMDS	DM 2	Quiesce call to domain	1 Domain token
DM 0009	DFHDMDS	DM 2	Domain call return	1 DMDM parameter list
DM 000A	DFHDMDS	DM 2	Domain call return	1 DMDM parameter list
DM 000C	DFHDMMDM	DM 2	Change of global phase	1 Old phase state 2 New phase state
DM 000D	DFHDMDS	DM 2	Change of global phase	1 Old phase state 2 New phase state
DM 0010	DFHDMWQ	DM 1	Entry	1 DMWQ parameter list
DM 0011	DFHDMWQ	DM 1	Exit	1 DMWQ parameter list
DM 0012	DFHDMWQ	DM 2	Domain wait	1 Caller's domain token 2 Domain being waited on 3 Phase being waited on 4 Actual phase
DM 0013	DFHDMWQ	DM 2	System wait	1 Caller's domain token 2 Phase being waited on 3 Phase state
DM 0014	DFHDMWQ	DM 2	Domain wait ended	1 Caller's domain token 2 Domain being waited on 3 Phase being waited on
DM 0015	DFHDMWQ	DM 2	System wait ended	1 Caller's domain token 2 Phase being waited on
DM 0020	DFHDMMDM	Exc	Recovery	1 DMDM parameter list 2 Kernel error data
DM 0021	DFHDMDS	Exc	Recovery	1 DSAT parameter list 2 Kernel error data
DM 0022	DFHDMWQ	Exc	Recovery	1 DMWQ parameter list 2 Kernel error data
DM 0023	DFHDMIQ	Exc	Recovery	1 DMIQ parameter list 2 Kernel error data

Table 113. Domain manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
DM 0025	DFHDMMDM	Exc	Acquire program error	1	LDLD parameter list
DM 0026	DFHDMMDM	Exc	Acquire program error	1	LDLD parameter list
DM 0027	DFHDMMDM	Exc	Acquire program error	1	LDLD parameter list
DM 0028	DFHDMMDM	Exc	Acquire program error	1	LDLD parameter list
DM 0029	DFHDMMDM	Exc	Add domain error	1	KEDD parameter list
DM 002A	DFHDMMDM	Exc	Add domain error	1	KEDD parameter list
DM 002B	DFHDMMDM	Exc	Add subpool error	1	SMAD parameter list
DM 002C	DFHDMMDM	Exc	Add record error	1	CCCC parameter list
DM 002D	DFHDMMDM	Exc	Delete record error	1	CCCC parameter list
DM 002E	DFHDMMDM	Exc	End browse error	1	CCCC parameter list
DM 002F	DFHDMMDM	Exc	End browse error	1	CCCC parameter list
DM 0030	DFHDMMDM	Exc	Get next error	1	CCCC parameter list
DM 0031	DFHDMMDM	Exc	Get next error	1	CCCC parameter list
DM 0032	DFHDMMDM	Exc	Start browse error	1	CCCC parameter list
DM 0033	DFHDMMDM	Exc	Define program error	1	LDLD parameter list
DM 0034	DFHDMMDM	Exc	Delete lock error	1	LMLM parameter list
DM 0035	DFHDMMDM	Exc	GETMAIN failure	1	SMGF parameter list
DM 0036	DFHDMMDM	Exc	Invalid domain specified	1	DMDM parameter list
DM 0037	DFHDMMDM	Exc	Invalid domain specified	1	DMDM parameter list
DM 0039	DFHDMMDM	Exc	Invalid format	1	DMDM parameter list
DM 003A	DFHDMMDM	Exc	Invalid function	1	DMDM parameter list
DM 003B	DFHDMMDM	Exc	Invalid phase specified	1	DMDM parameter list
DM 003C	DFHDMMDM	Exc	Invalid program	1	LDLD parameter list
DM 003D	DFHDMMDM	Exc	Quiesce requested while system initializing	1	DMDM parameter list
DM 003E	DFHDMMDM	Exc	Invalid set phase	1	DMDM parameter list
DM 003F	DFHDMMDM	Exc	Invalid set phase	1	DMDM parameter list
DM 0040	DFHDMMDM	Exc	Insufficient storage	1	LDLD parameter list
DM 0041	DFHDMMDM	Exc	Insufficient storage	1	LDLD parameter list

Table 113. Domain manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
DM 0042	DFHDMMDM	Exc	Program not found	1	LDLD parameter list
DM 0043	DFHDMMDM	Exc	Program not found	1	LDLD parameter list
DM 0044	DFHDMMDM	Exc	Lock error	1	LMLM parameter list
DM 0046	DFHDMMDM	Exc	Release program error	1	LDLD parameter list
DM 0047	DFHDMMDM	Exc	Store clock failure		
DM 0048	DFHDMMDM	Exc	Store clock failure		
DM 0049	DFHDMMDM	Exc	Store clock failure		
DM 004A	DFHDMMDM	Exc	Store clock failure		
DM 004B	DFHDMMDM	Exc	Invalid set phase	1	DMDM parameter list
DM 004C	DFHDMMDM	Exc	Invalid wait phase	1	DMDM parameter list
DM 004D	DFHDMMDM	Exc	Invalid set phase	1	DMDM parameter list
DM 004E	DFHDMMDM	Exc	Invalid wait phase	1	DMDM parameter list
DM 004F	DFHDMMDM	Exc	Unlock error	1	LMLM parameter list
DM 0050	DFHDMMDM	Exc	Unlock error	1	LMLM parameter list
DM 0051	DFHDMMDM	Exc	Unlock error	1	LMLM parameter list
DM 0055	DFHDMDS	Exc	Inquire domain name error	1	KEDD parameter list
DM 0056	DFHDMDS	Exc	Inquire domain name error	1	KEDD parameter list
DM 0059	DFHDMDS	Exc	Invalid format	1	DSAT parameter list
DM 005A	DFHDMDS	Exc	Invalid function	1	DSAT parameter list
DM 005B	DFHDMDS	Exc	Lock error	1	LMLM parameter list
DM 005C	DFHDMDS	Exc	Lock error	1	LMLM parameter list
DM 005D	DFHDMDS	Exc	Lock error	1	LMLM parameter list
DM 005E	DFHDMDS	Exc	Store clock failure		
DM 005F	DFHDMDS	Exc	Store clock failure		
DM 0061	DFHDMDS	Exc	Unlock error	1	LMLM parameter list
DM 0062	DFHDMDS	Exc	Unlock error	1	LMLM parameter list
DM 0063	DFHDMDS	Exc	Unlock error	1	LMLM parameter list
DM 0064	DFHDMDS	Exc	Unlock error	1	LMLM parameter list
DM 0065	DFHDMDS	Exc	Unlock error	1	LMLM parameter list
DM 0070	DFHDMWQ	Exc	GETMAIN failure	1	SMGF parameter list
DM 0071	DFHDMWQ	Exc	Invalid function	1	DMWQ parameter list

Table 113. Domain manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
DM 0072	DFHDMWQ	Exc	Invalid format	1	DMWQ parameter list
DM 0073	DFHDMWQ	Exc	Lock error	1	LMLM parameter list
DM 0074	DFHDMWQ	Exc	No element found	1	Suspend token
DM 0075	DFHDMWQ	Exc	Unlock error	1	LMLM parameter list
DM 0080	DFHDMIQ	Exc	Domain ID not found	1	DMIQ parameter list
DM 0081	DFHDMIQ	Exc	Domain name not found	1	KEDD parameter list
DM 0082	DFHDMIQ	Exc	Domain token not found	1	KEDD parameter list
DM 0083	DFHDMIQ	Exc	GETMAIN failure	1	SMGF parameter list
DM 0084	DFHDMIQ	Exc	Inquire domain name error	1	KEDD parameter list
DM 0085	DFHDMIQ	Exc	Inquire domain name error	1	KEDD parameter list
DM 0086	DFHDMIQ	Exc	Invalid domain token	1	DMIQ parameter list
DM 0087	DFHDMIQ	Exc	Invalid format	1	DMIQ parameter list
DM 0088	DFHDMIQ	Exc	Invalid function	1	DMIQ parameter list
DM 008A	DFHDMIQ	Exc	Invalid get next token	1	DMIQ parameter list
DM 008B	DFHDMIQ	Exc	Lock error	1	LMLM parameter list
DM 008C	DFHDMIQ	Exc	Unlock error	1	LMLM parameter list
DM 0090	DFHDMDM	Exc	SVC listen error	1	DMAF parameter list
DM 0091	DFHDMDM	Exc	SVC delete error	1	DMAF parameter list
DM 0092	DFHDMDM	Exc	DS attach ENF error	1	DSAT parameter list
DM 0201	DFHDMENF	DM 1	Entry	1	DSAT parameter list
DM 0202	DFHDMENF	DM 1	Exit	1	DSAT parameter list
DM 0203	DFHDMENF	Exc	Trace notify element	1	ENF notify element
DM 0204	DFHDMENF	Exc	Recovery routine	1 2	DSAT parameter list Kernel error data
DM 0205	DFHDMENF	Exc	DS attach error	1	DSAT parameter list
DM 0206	DFHDMENF	Exc	SRB detected error	1	ENF notify element
DM 0207	DFHDMENF	Exc	Invalid notify element	1	ENF notify element
DM 0208	DFHDMENF	Exc	Storage manager GETMAIN error	1	SMGF parameter list

Table 113. Domain manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
DM 0210	DFHDMEN	DM 1	Entry	1	DMEN parameter list
DM 0211	DFHDMEN	DM 1	Exit	1	DMEN parameter list
DM 0212	DFHDMEN	Exc	Recovery	1 2	DMEN parameter list Kernel error data
DM 0213	DFHDMEN	Exc	Invalid function	1	DMEN parameter list
DM 0214	DFHDMEN	Exc	Invalid format	1	Supplied parameter list

Dispatcher domain trace points

Table 114. Dispatcher domain trace points

Point ID	Module	Lvl	Type	Data	
DS 0002	DFHDSAT	DS 1	Entry	1	DSAT parameter list
DS 0003	DFHDSAT	DS 1	Exit	1	DSAT parameter list
DS 0004	DFHDSR	DS 1	Entry	1	DSSR parameter list
DS 0005	DFHDSR	DS 1	Exit	1	DSSR parameter list
DS 0006	DFHDSDM	DS 1	Entry	1	DMDM parameter list
DS 0007	DFHDSDM	DS 1	Exit	1	DMDM parameter list
DS 0008	DFHDSIT	DS 1	Entry	1	DSIT parameter list
DS 0009	DFHDSIT	DS 1	Exit	1	DSIT parameter list
DS 0010	DFHDSBR	DS 1	Entry	1	DSBR parameter list
DS 0011	DFHDSBR	DS 1	Exit	1	DSBR parameter list
DS 0012	DFHDSKE	DS 1	Entry	1	KEDS parameter list
DS 0013	DFHDSKE	DS 1	Exit	1	KEDS parameter list
DS 0014	DFHDSSTCB	DS 1	Entry	1	DSDS parameter list
DS 0015	DFHDSSTCB	DS 1	Exit	1	DSDS parameter list
DS 0016	DFHSDSDS3	DS 2	Entry	1	DSDS parameter list
DS 0017	DFHSDSDS3	DS 2	Exit	1	DSDS parameter list
DS 0018	DFHSDSDS4	DS 2	Entry	1	DSDS parameter list
DS 0019	DFHSDSDS4	DS 2	Exit	1	DSDS parameter list
DS 0020	DFHDSST	DS 1	Entry	1	STST parameter list

Table 114. Dispatcher domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
DS 0021	DFHDSST	DS 1	Exit	1	STST parameter list
DS 0022	DFHDS3	DS 2	Before MVS wait	1	Internal data
				2	Internal data
DS 0023	DFHDS3	DS 2	After MVS wait	1	Internal data
				2	Internal data
DS 0024	DFHDS3	DS 2	Set MVS STIMER	1	STIMER Interval
				2	Internal data
DS 0025	DFHDS3	DS 2	Cancel MVS STIMER	1	Internal data
DS 0026		DS 2	Before MVS GETMAIN	1	Module issuing GETMAIN
				2	Amount of storage requested
DS 0027		DS 2	After MVS GETMAIN	1	Module issuing GETMAIN
				2	Amount of storage requested
				3	Address of storage
DS 0028	DFHDSTCB	DS 2	Internal function		
DS 0029		DS 2	Free open TCB	1	Detecting module
				2	CICS name of TCB
				3	CICS token for TCB
DS 0030	DFHDSTCB	DS 2	Internal function		
DS 0031	DFHDSTCB	DS 2	Internal function		
DS 0032	DFHDS3	DS 2	Internal function		
DS 0033	DFHDSTCB	DS 2	Internal function		
DS 0034	DFHDS3	DS 2	Internal function		
DS 0038	DFHDSSM	DS 2	Storage getting short		
DS 0039	DFHDSSM	DS 2	Storage critical		
DS 0040	DFHDSSM	DS 2	Storage ok		
DS 0041		DS 2	Internal function	1	Internal data
				2	Internal data
DS 0042		DS 2	Internal function	1	Internal data
				2	Internal data
				3	Internal data
DS 0043		DS 2	Internal function	1	Internal data
				2	Internal data
				3	Internal data
DS 0044		DS 2	Internal function	1	Internal data
				2	Internal data
DS 0046		DS 2	Internal function	1	Internal data
				2	Internal data
DS 0047	DFHDSKE	Exc	Invalid format	1	Detecting module
				2	KEDS parameter list
DS 0048	DFHDSKE	Exc	Invalid function	1	Detecting module
				2	KEDS parameter list

Table 114. Dispatcher domain trace points (continued)

Point ID	Module	Lvl	Type	Data
DS 0049	DFHDSKE	Exc	Recovery	1 Detecting module 2 KEDS parameter list 3 Kernel error data
DS 0050	DFHDSAT	Exc	Invalid format	1 Detecting module 2 DSAT parameter list
DS 0051	DFHDSAT	Exc	Invalid function	1 Detecting module 2 DSAT parameter list
DS 0052	DFHDSAT	Exc	Recovery	1 Detecting module 2 DSAT parameter list 3 Kernel error data
DS 0053	DFHDSTCB	Exc	Invalid format	1 Detecting module 2 DSDS parameter list
DS 0054	DFHDSTCB	Exc	Invalid function	1 Detecting module 2 DSDS parameter list
DS 0055	DFHDSTCB	Exc	Recovery	1 Detecting module 2 DSDS parameter list 3 Kernel error data
DS 0056	DFHDSTCB	Exc	Task suspend token in use	1 Detecting module 2 Dispatcher task area 3 Suspend/resume area
DS 0057	DFHDSTCB	Exc	Store clock failure	1 Detecting module 2 What the STCK generated
DS 0058	DFHSDS3	Exc	Invalid format	1 Detecting module 2 DSDS parameter list
DS 0059	DFHSDS3	Exc	Invalid function	1 Detecting module 2 DSDS parameter list
DS 0060	DFHSDS3	Exc	Recovery	1 Detecting module 2 DSDS parameter list 3 Kernel error data
DS 0061	DFHSDS4	Exc	Invalid format	1 Detecting module 2 DSDS parameter list
DS 0062	DFHSDS4	Exc	Invalid function	1 Detecting module 2 DSDS parameter list
DS 0063	DFHSDS4	Exc	Recovery	1 Detecting module 2 DSDS parameter list 3 Kernel error data
DS 0064	DFHDSSR	Exc	Invalid format	1 Detecting module 2 DSSR parameter list
DS 0065	DFHDSSR	Exc	Invalid function	1 Detecting module 2 DSSR parameter list

Table 114. Dispatcher domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
DS 0066	DFHDSSR	Exc	Recovery	1 2 3	Detecting module DSSR parameter list Kernel error data
DS 0067	DFHDSSR	Exc	Suspend error - invalid suspend token	1 2	Detecting module DSSR parameter list
DS 0068	DFHDSSR	Exc	Suspend error - already suspended	1 2	Detecting module DSSR parameter list
DS 0069	DFHDSSR	DS 2	SUSPEND or WAIT purged	1 2 3	Detecting module DSSR parameter list Task of purged request
DS 0070	DFHDSSR	Exc	Suspend error - not resumed since last purge	1 2	Detecting module DSSR parameter list
DS 0071	DFHDSSR	Exc	Resume error - invalid suspend token	1 2	Detecting module DSSR parameter list
DS 0072	DFHDSSR	Exc	Resume error - already resumed	1 2	Detecting module DSSR parameter list
DS 0073	DFHDSSR	Exc	Resume error - purged	1 2	Detecting module DSSR parameter list
DS 0074	DFHDSSR	Exc	Delete suspend error - invalid suspend token	1 2	Detecting module DSSR parameter list
DS 0075	DFHDSSR	Exc	Delete suspend error - suspend token inuse	1 2 3	Detecting module DSSR parameter list Suspend/resume area
DS 0076	DFHDSSR	Exc	Invalid mode	1 2	Detecting module DSSR parameter list
DS 0077	DFHDSDM	Exc	Invalid format	1 2	Detecting module DMDM parameter list
DS 0078	DFHDSDM	Exc	Invalid function	1 2	Detecting module DMDM parameter list
DS 0079	DFHDSDM	Exc	Set anchor failure	1 2	Detecting module KEDD parameter list
DS 0080	DFHDSDM	Exc	Add gate failure	1 2	Detecting module KEDD parameter list
DS 0081	DFHDSDM	Exc	Add lock failure	1 2	Detecting module LMLM parameter list
DS 0082	DFHDSDM	Exc	Unlock failure	1 2	Detecting module LMLM parameter list
DS 0083	DFHDSDM	Exc	CCCC get failure	1 2	Detecting module CCCC parameter list

Table 114. Dispatcher domain trace points (continued)

Point ID	Module	Lvl	Type	Data
DS 0084	DFHDSDM	Exc	CCCC add failure	1 Detecting module 2 CCCC parameter list
DS 0085	DFHDSDM	Exc	PAGP failure	1 Detecting module 2 PAGP parameter list
DS 0086	DFHDSDM	Exc	Add subpool failure	1 Detecting module 2 SMAD parameter list
DS 0087	DFHDSDM	Exc	GETMAIN request failed	1 Detecting module 2 Amount of storage requested
DS 0088	DFHDSDM	Exc	GETMAIN request failed	1 Detecting module 2 Amount of storage requested
DS 0089	DFHDSDM	Exc	Activate mode request failed	1 Detecting module 2 DFHDMDM_ARG 3 DFHDSIT_ARG
DS 0090	DFHDSDM	Exc	GETMAIN request failed	1 Detecting module 2 Amount of storage requested
DS 0091	DFHDSDM	Exc	Wait phase error	1 Detecting module 2 DMDM parameter list
DS 0092	DFHDSDM	Exc	Wait phase error	1 Detecting module 2 DMDM parameter list
DS 0093	DFHDSDM	Exc	Wait phase error	1 Detecting module 2 DMDM parameter list
DS 0094	DFHDSDM	Exc	Recovery	1 Detecting module 2 DMDM parameter list 2 Kernel error data
DS 0095	DFHDSDM	Exc	GETMAIN request failed	1 Detecting module 2 Amount of storage requested
DS 0096	DFHDSDM	Exc	GETMAIN request failed	1 Detecting module 2 Amount of storage requested
DS 0097	DFHDSDM	Exc	Create task failure	1 Detecting module 2 Dispatcher task area 3 KEDS parameter list
DS 0098	DFHDSDM	Exc	Task reply failure	1 Detecting module 2 Dispatcher task area 3 DSAT parameter list
DS 0099	DFHDSDM	Exc	POST exit enable failure	1 Detecting module 2 Return code
DS 0100	DFHDSDM	Exc	POST exit disable failure	1 Detecting module 2 Return code

Table 114. Dispatcher domain trace points (continued)

Point ID	Module	Lvl	Type	Data
DS 0101	DFHDSIT	Exc	Lock failure	1 Detecting module 2 LMLM parameter list
DS 0102	DFHDSIT	Exc	Unlock failure	1 Detecting module 2 LMLM parameter list
DS 0103	DFHDSIT	Exc	CCCC get failure	1 Detecting module 2 CCCC parameter list
DS 0104	DFHDSIT	Exc	CCCC write failure	1 Detecting module 2 CCCC parameter list
DS 0105	DFHDSIT	Exc	Invalid function	1 Detecting module 2 DSIT parameter list
DS 0106	DFHDSIT	Exc	Recovery	1 Detecting module 2 DSIT parameter list 3 Kernel error data
DS 0107	DFHDSIT	Exc	Invalid format	1 Detecting module 2 Input format number
DS 0108	DFHDSIT	Exc	Wait interval error	1 Detecting module 2 Maximum wait interval 3 Scan delay interval
DS 0109	DFHDSIT	Exc	GETMAIN request failed	1 Detecting module 2 Amount of storage requested
DS 0110	DFHDSIT	Exc	Internal function error	1 Internal data 2 Internal data
DS 0111	DFHDSIT	Exc	GETMAIN request failed	1 Detecting module 2 Amount of storage requested
DS 0112	DFHDSIT	Exc	RESUME failure	1 Detecting module 2 DSSR parameter list
DS 0113	DFHDSSM	DS 1	Exit	1 SMNT Parameter list
DS 0114	DFHDSSM	Exc	Recovery	1 Detecting module 2 SMNT parameter list 3 Kernel error data
DS 0115	DFHDSSM	Exc	Invalid format	1 Detecting module 2 SMNT parameter list
DS 0116	DFHDSSM	Exc	Invalid function	1 Detecting module 2 SMNT parameter list
DS 0117	DFHDSBR	Exc	Invalid function	1 Detecting module 2 DSAT parameter list
DS 0118	DFHDSBR	Exc	Recovery	1 Detecting module 2 DSBR parameter list 3 Kernel error data

Table 114. Dispatcher domain trace points (continued)

Point ID	Module	Lvl	Type	Data
DS 0119	DFHDSDM	Exc	FREEMAIN request failed	1 Detecting module 2 SMGF parameter list
DS 0120	DFHDSDM	Exc	GETMAIN request failed	1 Detecting module 2 SMGF parameter list
DS 0121	DFHDSUE	DS 1	Entry	1 APUE parameter list
DS 0122	DFHDSUE	DS 1	Exit	1 APUE parameter list
DS 0123	DFHDSUE	Exc	Invalid format	1 APUE parameter list
DS 0124	DFHDSUE	Exc	Invalid function	1 APUE parameter list
DS 0125	DFHDSUE	Exc	Recovery	1 Detecting module 2 APUE parameter list 3 Kernel error data
DS 0126	DFHDSST	Exc	Invalid format	1 Detecting module 2 STST parameter list
DS 0127	DFHDSST	Exc	Invalid function	1 Detecting module 2 STST parameter list
DS 0128	DFHDSST	Exc	Recovery	1 Detecting module 2 STST parameter list 3 Kernel error data
DS 0129	DFHDSST	Exc	Buffer too short	1 STST parameter list
DS 0130	DFHDSST	Exc	Lock failure	1 Detecting module 2 LMLM parameter list
DS 0131	DFHDSDM	Exc	Statistics buffer getmain failure	1 Detecting module 2 Amount of storage
DS 0132	DFHDSDS2	DS 1	Entry	1 XMNT parameter list
DS 0133	DFHDSDS2	DS 1	Exit	1 XMNT parameter list
DS 0134	DFHDSDS2	Exc	Invalid format	1 XMNT parameter list
DS 0136	DFHDSDS2	Exc	Recovery	1 Detecting module 2 DSDS parameter list 3 Kernel error data
DS 0137	DFHDSIT	Exc	Create TCB failure	1 Detecting module 2 DFHDSIT_ARG 2 DFHKEDS_ARG
DS 0138	DFHDSIT	Exc	Invalid maxopentcbs value	1 DSIT parameter list 2 LMLM parameter list
DS 0139	DFHDSST	Exc	Unlock failure	1 Detecting module 2 LMLM parameter list

Table 114. Dispatcher domain trace points (continued)

Point ID	Module	Lvl	Type	Data
DS 0140	DFHDSDM	Exc	Wait phase error	1 Detecting module 2 DMDM parameter list
DS 0141	DFHDSDM	Exc	ADD_LOCK failure	1 Detecting module 2 LMLM parameter list
DS 0142	DFHDSDM	Exc	UNLOCK failure	1 Detecting module 2 LMLM parameter list
DS 0143	DFHDSDM	Exc	ADD_SUBPOOL failure	1 Detecting module 2 SMAD parameter list
DS 0144	DFHDSDM	Exc	Lock failure	1 Detecting module 2 LMLM parameter list
DS 0145	DFHDSM	DS 1	Entry	1 SMNT parameter list
DS 0147	DFHDS3	Exc	Invalid ECB address	1 Detecting module 2 ECB parameters 3 Dispatcher task area
DS 0148	DFHDS3	Exc	STIMER set error	1 R15
DS 0149	DFHDS3	Exc	STIMER cancel error	1 R15
DS 0150	DFHDS4	Exc	Invalid ECB address	1 Detecting module 2 ECB parameters 3 Dispatcher task area
DS 0151	DFHDSM	Exc	GETMAIN req failed	1 Detecting module 2 Amount of storage requested
DS 0152	DFHDSR	Exc	Already waiting error	1 Detecting module 2 DSSR parameter list
DS 0153	DFHDS2	Exc	No extension storage error	1 Detecting module 2 Amount of storage requested
DS 0154	DFHDSM	Exc	DSAS call failed	1 Detecting module 2 DSAS return code
DS 0155	DFHDSM	Exc	KETI call failed	1 TCB_START_TIME 2 KETI response
DS 0156	DFHDSAT	Exc	User task overflow	1 Detecting module
DS 0157	DFHDSR	Exc	Internal logic error	1 Detecting module 2 DSSR parameter list
DS 0158	DFHDSR	Exc	Internal logic error	1 Detecting module 2 DSSR parameter list
DS 0159	DFHDSR	Exc	Internal logic error	1 Detecting module 2 DSSR parameter list

Table 114. Dispatcher domain trace points (continued)

Point ID	Module	Lvl	Type	Data
DS 0160	DFHDSR	Exc	Internal logic error	1 Detecting module 2 DSSR parameter list
DS 0161	DFHDSAT	Exc	ACTIVATE_MODE failure	1 Detecting module 2 DSIT parameter list
DS 0162	DFHDSAT	Exc	ADD_TCB failure	1 Detecting module 2 DSIT parameter list
DS 0163	DFHDSAT	Exc	SUSPEND failure	1 Detecting module 2 DSSR parameter list
DS 0164	DFHDSAT	Exc	RESUME failure	1 Detecting module 2 DSSR parameter list
DS 0165	DFHDSIT	DS 2	Free dead DS_TCB	1 Dead DS_TCB
DS 0166	DFHDSIT	DS 2	Post WAIT in ESTAE exit of dead DS_TCB	1 Dead DS_TCB
DS 0167	DFHDSIT	DS 2	Pull running task from dead DS_TCB	1 Pulled TASK 2 Dead DS_TCB
DS 0168	DFHDSIT	DS 2	Pull dispatchable task from dead DS_TCB	1 Pulled TASK 2 Dead DS_TCB
# DS 0169	DFHDSIT	Exc	Delete Open TCB failed	1 DFHDSIT_ARG
# DS 0170		Exc	LOCK failure	1 Detecting module
DS 0171		Exc	UNLOCK failure	1 Detecting module
DS 0172		Exc	DELETE_TCB failure	1 Detecting module 2 DSIT parameter list
DS 0173		Exc	RESUME failure	1 Detecting module 2 DSSR parameter list
# DS 0174	DFHDS*	Exc	FREEMAIN failed for match block	1 Detecting module name 2 DFHSMGF_ARG
# DS 0175	DFHDSIT	Exc	Failed to acquire DSIT lock	1 Detecting module name 2 DFHMLM_ARG
# DS 0176	DFHDSIT	Exc	Failed to free DSIT lock	1 Detecting module name 2 DFHMLM_ARG

Dump domain trace points

Table 115. Dump domain trace points

Point ID	Module	Lvl	Type	Data
DU 0001	DFHDUDM	DU 1	Entry	1 DMDM parameter list
DU 0002	DFHDUDM	DU 1	Exit	1 DMDM parameter list

Table 115. Dump domain trace points (continued)

Point ID	Module	Lvl	Type	Data
DU 0003	DFHDUDM	Exc	Invalid call	1 DMDM parameter list 2 DU anchor block
DU 0004	DFHDUDM	Exc	Recovery	1 DMDM parameter list 2 Kernel error data
DU 0007	DFHDUDM	Exc	DUIO load failed	1 DMDM parameter list 2 DU anchor block
DU 0008	DFHDUDM	DU 1	GETMAIN DUA	1 Length required
DU 0009	DFHDUDM	DU 1	GETMAIN DUA return	1 Return code 2 Address of area
DU 000A	DFHDUDM	DU 1	GETMAIN SDT	1 Length required
DU 000B	DFHDUDM	DU 1	GETMAIN SDT return	1 Return code 2 Address of area
DU 000C	DFHDUDM	DU 1	GETMAIN TDT	1 Length required
DU 000D	DFHDUDM	DU 1	GETMAIN TDT return	1 Return code 2 Address of area
DU 000E	DFHDUDM	DU 1	GETMAIN stats buffer	1 Storage length
DU 000F	DFHDUDM	DU 1	GETMAIN stats buffer return	1 Return code 2 Storage address
DU 0101	DFHDUDU	DU 1	Entry	1 DUDU parameter list
DU 0102	DFHDUDU	DU 1	Exit	1 DUDU parameter list
DU 0103	DFHDUDU	Exc	Invalid call	1 DUDU parameter list
DU 0104	DFHDUDU	Exc	Recovery	1 DUDU parameter list 2 Kernel error data
DU 0105	DFHDUDU	Exc	Transaction dump table not initialized	1 DUDU parameter list
DU 0200	DFHDUIO	DU 2	Entry	1 DUIO parameter list
DU 0201	DFHDUIO	DU 2	Exit	1 DUIO parameter list
DU 0202	DFHDUIO	Exc	Recovery	
DU 0203	DFHDUIO	DU 2	OPEN	1 Dump data set DCB
DU 0204	DFHDUIO	DU 2	OPEN return	1 Dump data set DCB
DU 0205	DFHDUIO	DU 2	DEVTYPE	
DU 0206	DFHDUIO	DU 2	DEVTYPE return	1 DEVTYPE information
DU 0207	DFHDUIO	DU 2	GETMAIN	1 Length required

Table 115. Dump domain trace points (continued)

Point ID	Module	Lvl	Type	Data
DU 0208	DFHDUIO	DU 2	GETMAIN return	1 Address of area 2 Length of area 3 GETMAIN return code
DU 0209	DFHDUIO	DU 2	FREEMAIN	1 Open block
DU 020A	DFHDUIO	DU 2	FREEMAIN return	
DU 020B	DFHDUIO	DU 2	CLOSE	1 Dump data set DCB
DU 020C	DFHDUIO	DU 2	CLOSE return	1 Dump data set DCB
DU 020D	DFHDUIO	DU 2	FREEPOOL	1 Dump data set DCB
DU 020E	DFHDUIO	DU 2	FREEPOOL return	1 Dump data set DCB
DU 020F	DFHDUIO	DU 2	WRITE	1 Dump data set DCB
DU 0210	DFHDUIO	DU 2	WRITE return	1 Dump data set DCB
DU 0211	DFHDUIO	DU 2	CHECK	1 Dump data set DCB
DU 0212	DFHDUIO	DU 2	CHECK return	1 Dump data set DCB
DU 0214	DFHDUIO	Exc	CLOSE error	1 DUIO parameter list 2 DU anchor block 3 Open block
DU 0215	DFHDUSU	DU 2	Entry	1 DUSU parameter list
DU 0216	DFHDUSU	DU 2	Exit	1 DUSU parameter list
DU 0217	DFHDUSU	Exc	Recovery	1 DUSU parameter list 2 Kernel error data 3 DU anchor block
DU 0218	DFHDUXD	DU 2	Entry	1 DUDD parameter list 2 DUDU parameter list
DU 0219	DFHDUXD	DU 2	Exit	1 DUDD parameter list 2 DUDU parameter list
DU 021A	DFHDUXD	Exc	Recovery	1 DUDD parameter list 2 DUDU parameter list 3 Kernel error data 4 DU anchor block
DU 021B	DFHDUXW	DU 2	Entry	1 DUXW parameter list
DU 021C	DFHDUXW	DU 2	Exit	1 DUXW parameter list
DU 021D	DFHDUXW	Exc	Recovery	1 DUXW parameter list 2 Kernel error data 3 DU anchor block
DU 021E	DFHDLXDF	DU 2	Entry	1 DUXF parameter list

Table 115. Dump domain trace points (continued)

Point ID	Module	Lvl	Type	Data
DU 021F	DFHDLXDF	DU 2	Exit	1 DUXF parameter list
DU 0220	DFHDLXDF	Exc	Recovery	1 DUXF parameter list 2 DUDD parameter list 3 DUDU parameter list 4 Kernel error data 5 DU anchor block
DU 0221	DFHXRADF	DU 2	Entry	1 DUXF parameter list
DU 0222	DFHXRADF	DU 2	Exit	1 DUXF parameter list
DU 0223	DFHXRADF	Exc	Recovery	1 DUXF parameter list 2 DUDD parameter list 3 DUDU parameter list 4 Kernel error data 5 DU anchor block
DU 0224	DFHTCXDF	DU 2	Entry	1 DUXF parameter list
DU 0225	DFHTCXDF	DU 2	Exit	1 DUXF parameter list
DU 0226	DFHTCXDF	Exc	Recovery	1 DUXF parameter list 2 DUDD parameter list 3 DUDU parameter list 4 Kernel error data 5 DU anchor block
DU 0227	DFHPCXDF	DU 2	Entry	1 DUXF parameter list
DU 0228	DFHPCXDF	DU 2	Exit	1 DUXF parameter list
DU 0229	DFHPCXDF	Exc	Recovery	1 DUXF parameter list 2 DUDD parameter list 3 DUDU parameter list 4 Kernel error data 5 DU anchor block
DU 022A	DFHSAXDF	DU 2	Entry	1 DUXF parameter list
DU 022B	DFHSAXDF	DU 2	Exit	1 DUXF parameter list
DU 022C	DFHSAXDF	Exc	Recovery	1 DUXF parameter list 2 DUDD parameter list 3 DUDU parameter list 4 Kernel error data 5 DU anchor block
DU 022D	DFHFCXDF	DU 2	Entry	1 DUXF parameter list
DU 022E	DFHFCXDF	DU 2	Exit	1 DUXF parameter list

Table 115. Dump domain trace points (continued)

Point ID	Module	Lvl	Type	Data
DU 022F	DFHFCXDF	Exc	Recovery	1 DUXF parameter list 2 DUDD parameter list 3 DUDU parameter list 4 Kernel error data 5 DU anchor block
DU 0230	DFHTRXDF	DU 2	Entry	1 DUXF parameter list
DU 0231	DFHTRXDF	DU 2	Exit	1 DUXF parameter list
DU 0232	DFHTRXDF	Exc	Recovery	1 DUXF parameter list 2 DUDD parameter list 3 DUDU parameter list 4 Kernel error data 5 DU anchor block
DU 0233	DFHXDXDF	DU 2	Entry	1 DUXF parameter list
DU 0234	DFHXDXDF	DU 2	Exit	1 DUXF parameter list
DU 0235	DFHXDXDF	Exc	Recovery	1 DUXF parameter list 2 DUDD parameter list 3 DUDU parameter list 4 Kernel error data 5 DU anchor block
DU 0239	DFHDUIO	DU 2	NOTE	1 Dump data set DCB
DU 0240	DFHDUIO	DU 2	NOTE return	1 Dump data set DCB
DU 0241	DFHDUIO	DU 2	POINT	1 Dump data set DCB
DU 0242	DFHDUIO	DU 2	POINT return	1 Dump data set DCB
DU 0250	DFHDUSU	DU 2	DYNALLOC	1 DYNALLOC parameter list
DU 0251	DFHDUSU	DU 2	DYNALLOC return	1 DYNALLOC parameter list
DU 0252	DFHDUSU	DU 2	FREEMAIN DYNALLOC plist	1 DYNALLOC parameter list
DU 0253	DFHDUSU	DU 2	FREEMAIN return	
DU 0301	DFHDUSR	DU 1	Entry	1 DUSR or APUE parameter list
DU 0302	DFHDUSR	DU 1	Exit	1 DUSR or APUE parameter list
DU 0304	DFHDUSR	Exc	Recovery	1 DUSR or APUE parameter list 2 Kernel error data
DU 0305	DFHDUSR	Exc	Failed to add IEASDUMP.QUERY exit DFHDUMPX	1 DUSR parameter list 2 DAFPB 3 CSVVDYNEX ADD response
DU 0500	DFHDUDT	DU 1	Entry	1 STST or DUDT parameter list
DU 0501	DFHDUDT	DU 1	Exit	1 STST or DUDT parameter list

Table 115. Dump domain trace points (continued)

Point ID	Module	Lvl	Type	Data
DU 0502	DFHDUDT	Exc	Recovery	1 STST or DUDT parameter list 2 Kernel error data
DU 0503	DFHDUDT	Exc	Invalid format	1 STST or DUDT parameter list
DU 0504	DFHDUDT	Exc	Invalid function	1 STST or DUDT parameter list
DU 0505	DFHDUDT	Exc	Invalid function	1 STST or DUDT parameter list
DU 0600	DFHDUTM	DU 1	Entry	1 STST or DUDT parameter list
DU 0601	DFHDUTM	DU 1	Exit	1 STST or DUDT parameter list
DU 0602	DFHDUTM	Exc	Recovery	1 STST or DUDT parameter list 2 Kernel error data
DU 0603	DFHDUTM	Exc	Invalid format	1 STST or DUDT parameter list
DU 0604	DFHDUTM	Exc	Invalid function	1 STST or DUDT parameter list
DU 0605	DFHDUTM	Exc	Invalid function	1 STST or DUDT parameter list
DU 0606	DFHDUTM	Exc	Browse token not found	1 STST or DUDT parameter list
DU 0607	DFHDUTM	Exc	Browse token not found	1 STST or DUDT parameter list
DU 0608	DFHDUTM	Exc	Invalid stats requirements	1 STST or DUDT parameter list
DU 0609	DFHDUTM	DU 1	Before MVS GETMAIN	1 Storage length
DU 060A	DFHDUTM	DU 1	After MVS GETMAIN	1 GETMAIN return code
DU 060B	DFHDUTM	DU 1	Before MVS GETMAIN	1 Storage length
DU 060C	DFHDUTM	DU 1	After MVS GETMAIN	1 GETMAIN return code
DU 060D	DFHDUTM	DU 1	Before MVS GETMAIN	1 Storage length
DU 060E	DFHDUTM	DU 1	After MVS GETMAIN	1 GETMAIN return code
DU 060F	DFHDUTM	Exc	Nonzero return code from MVS GETMAIN	1 DUDT parameter list 2 Storage length
DU 0610	DFHDUTM	Exc	Nonzero return code from MVS GETMAIN	1 DUDT parameter list 2 Storage length
DU 0611	DFHDUTM	Exc	Nonzero return code from MVS GETMAIN	1 DUDT parameter list 2 Storage length

Note: The following trace points DU 0710, DU 0711, DU 0720, DU 0721, DU 0722, DU 0723, and DU 0724 are sent to the GTF trace data set and not to any other currently active trace destination.

DU 0710	DFHDUSVC		Remote SDUMPX return	1 SDUMPX parameter list 2 SDUMPX REMOTE parms 3 Up to 200 bytes of SDUMPX PROBDISC parms
---------	----------	--	----------------------	--

Table 115. Dump domain trace points (continued)

Point ID	Module	Lvl	Type	Data
DU 0711	DFHDUSVC		Invalid PROBDDESC data	1 PROBDDESC parms address 2 Up to 200 bytes of SDUMPX PROBDDESC parms
DU 0720	DFHDUMPX		Entry	1 SDUMPX exit parms (SDMSE) 2 Up to 100 bytes of SDUMPX PROBDDESC parms
DU 0721	DFHDUMPX		Exit	1 DFHDUMPX response 2 SDUMPX exit parms (SDMSE) 3 Up to 100 bytes of SDMSE_ASIDLST or SDMSE_JOBLIST
DU 0722	DFHDUMPX		IWMWQWRK call	1 Up to 200 bytes of the call to IWMWQWRK
DU 0723	DFHDUMPX		IWMWQWRK error	1 IWMWQWRK return code 2 IWMWQWRK reason 3 IWMWQWRK parameter list
DU 0724	DFHDUMPX		IWMWQWRK return	1 IWMWQWRK return code 2 IWMWQWRK reason 3 IWMWQWRK parameter list 4 Up to 100 bytes of the address space list returned by IWMWQWRK

Event Manager

Table 116. Event manager trace points

Point ID	Module	Lvl	Type	Data
EM 0101	DFHEMDM	EM 1	Entry	1 DMDM parameter list
EM 0102	DFHEMDM	EM 1	Exit	1 DMDM parameter list
EM 0103	DFHEMDM	Exc	Recovery	1 DMDM parameter list 2 Kernel error data
EM 0104	DFHEMDM	Exc	Invalid format	1 DMDM parameter list
EM 0105	DFHEMDM	Exc	Invalid function	1 DMDM parameter list
EM 0201	DFHEMEM	EM 1	Entry	1 EMEM parameter list
EM 0202	DFHEMEM	EM 1	Exit	1 EMEM parameter list
EM 0203	DFHEMEM	Exc	Recovery	1 EMEM parameter list 2 Kernel error data
EM 0204	DFHEMEM	Exc	Invalid format	1 EMEM parameter list
EM 0205	DFHEMEM	Exc	Invalid function	1 EMEM parameter list

Table 116. Event manager trace points (continued)

Point ID	Module	Lvl	Type	Data
EM 0206	DFHEMEM	Exc	Failed to unlock the domain lock	1 EMEM parameter list
EM 0207	DFHEMEM	Exc	Event pool check failed	1 EMEM parameter list 2 Event pool anchor 3 Event block 4 Subevent in error
EM 0301	DFHEMBR	EM 1	Entry	1 EMBR parameter list
EM 0302	DFHEMBR	EM 1	Exit	1 EMBR parameter list
EM 0303	DFHEMBR	Exc	Recovery	1 EMBR parameter list 2 Kernel error data
EM 0304	DFHEMBR	Exc	Invalid format	1 EMBR parameter list
EM 0305	DFHEMBR	Exc	Invalid function	1 EMBR parameter list
EM 0306	DFHEMBR	Exc	Failed to unlock the domain lock	1 EMBR parameter list
EM 0401	DFHEMBA	EM 1	Entry	1 BAGD parameter list
EM 0402	DFHEMBA	EM 1	Exit	1 BAGD parameter list
EM 0403	DFHEMBA	Exc	Recovery	1 BAGD parameter list 2 Kernel error data
EM 0404	DFHEMBA	Exc	Invalid format	1 BAGD parameter list
EM 0405	DFHEMBA	Exc	Invalid function	1 BAGD parameter list
EM 0406	DFHEMBA	Exc	Failed to unlock the domain lock	1 BAGD parameter list

External CICS interface trace points

Table 117. External CICS interface trace points

Point ID	Module	Lvl	Type	Data
EX 0001	DFHXCPRH	Exc	PIPE_ALREADY_OPEN	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Pipe token
EX 0002	DFHXCPRH	Exc	PIPE_ALREADY_CLOSED	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Pipe token

Table 117. External CICS interface trace points (continued)

Point ID	Module	Lvl	Type	Data
EX 0003	DFHXCPRH	Exc	VERIFY_BLOCK_FM ERROR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer
EX 0005	DFHXCPRH	Exc	XCPIP_FM_ERR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Pipe token
EX 0006	DFHXCPRH	Exc	IRP_IOAREA_FM_ERR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer
EX 0007	DFHXCPRH	Exc	Server Terminated	1 Caller's parameter list 2 Call type 3 Callers user name 4 Connection name 5 Target CICS applid
EX 0008	DFHXCPRH	Exc	XFRASTG1_FM_ERR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Pipe token
EX 0201	DFHXCPRH	Exc	NO_CICS_IRC_STARTED	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer
EX 0202	DFHXCPRH	Exc	NO_PIPE	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Pipe token 6 Target CICS applid
EX 0203	DFHXCPRH	Exc	NO_CICS_ON_OPEN	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Pipe token 6 Target CICS applid

Table 117. External CICS interface trace points (continued)

Point ID	Module	Lvl	Type	Data
EX 0204	DFHXCPRH	Exc	NO_CICS_ON_DPL_1	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Pipe token 6 Target CICS applid
EX 0205	DFHXCPRH	Exc	NO_CICS_ON_DPL_2	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Pipe token 6 Target CICS applid
EX 0206	DFHXCPRH	Exc	NO_CICS_ON_DPL_3	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Pipe token 6 Target CICS applid
EX 0403	DFHXCPRH	Exc	INVALID_APPL_NAME	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer
EX 0405	DFHXCPRH	Exc	PIPE_NOT_CLOSED	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Pipe token
EX 0406	DFHXCPRH	Exc	PIPE_NOT_OPEN	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Pipe token
EX 0407	DFHXCPRH	Exc	INVALID_USERID	1 Caller's parameter list 2 Call type 3 Caller's user name
EX 0408	DFHXCPRH	Exc	INVALID_UOWID	1 Caller's parameter list 2 Call type 3 Caller's user name 4 UOWID
EX 0409	DFHXCPRH	Exc	INVALID_TRANSID	1 Caller's parameter list 2 Call type 3 Caller's user name

Table 117. External CICS interface trace points (continued)

Point ID	Module	Lvl	Type	Data
EX 0414	DFHXCPRH	Exc	ABORT_RECEIVED	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Target CICS applid 5 Message to be returned
EX 0415	DFHXCPRH	Exc	INVALID_CONNECTION	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Connection name 5 Target CICS applid
EX 0416	DFHXCPRH	Exc	INVALID_CICS_RELEASE	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Target CICS applid
EX 0417	DFHXCPRH	Exc	PIPE_MUST_CLOSE	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Pipe token
EX 0418	DFHXCPRH	Exc	INVALID_PIPE_TOKEN	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Pipe token
EX 0422	DFHXCPRH	Exc	Server abended	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 DPL return area
EX 0603	DFHXCPRH	Exc	XCUSER_GM_ERROR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer
EX 0604	DFHXCPRH	Exc	XCPIPE_GM_ERROR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer
EX 0605	DFHXCPRH	Exc	VERIFY_BLOCK_GM_ERROR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer
EX 0606	DFHXCPRH	Exc	SSI_VERIFY_FAILED	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer

Table 117. External CICS interface trace points (continued)

Point ID	Module	Lvl	Type	Data
EX 0607	DFHXCPRH	Exc	SVC_CALL_FAILED	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer
EX 0608	DFHXCPRH	Exc	IRP_LOGON_FAILURE	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Target CICS applid 6 Logon name
EX 0609	DFHXCPRH	Exc	IRP_CONNECT_FAIL	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Pipe token 6 Target CICS applid
EX 0610	DFHXCPRH	Exc	IRP_DISC_FAIL	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Target CICS applid 6 Pipe token
EX 0611	DFHXCPRH	Exc	IRP_LOGOFF_FAILED	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Target CICS applid 6 Pipe token
EX 0612	DFHXCPRH	Exc	TRANSFORM_1_ERROR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer
EX 0613	DFHXCPRH	Exc	TRANSFORM_4_ERROR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer
EX 0614	DFHXCPRH	Exc	IRP_NULL_DATA	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Target CICS applid

Table 117. External CICS interface trace points (continued)

Point ID	Module	Lvl	Type	Data
EX 0615	DFHXCPRH	Exc	IRP_NEG_RESPONSE	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Target CICS applid
EX 0616	DFHXCPRH	Exc	IRP_SWITCH_PULL_ERR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Target CICS applid 6 Pipe token
EX 0617	DFHXCPRH	Exc	IRP_IOAREA_GM_ERR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer
EX 0619	DFHXCPRH	Exc	IRP_BAD_IOAREA	1 Caller's parameter list 2 Call type 3 Caller's user name 4 IOAREA address
EX 0620	DFHXCPRH	Exc	IRP_PROTOCOL_ERR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Target CICS applid 5 Pipe token
EX 0621	DFHXCPRH	Exc	PIPE_RECOVERY FAILURE	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Target CICS applid 5 Pipe token
EX 0622	DFHXCPRH	Exc	ESTAE_SETUP_FAIL	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer
EX 0623	DFHXCPRH	Exc	ESTAE_INVOKED	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 MVS abend code
EX 0624	DFHXCPRH	Exc	TIMEDOUT	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Server program name 5 Target CICS applid

Table 117. External CICS interface trace points (continued)

Point ID	Module	Lvl	Type	Data
EX 0625	DFHXCPRH	Exc	STIMER_SETUP_FAIL	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer
EX 0626	DFHXCPRH	Exc	STIMER_CANCEL_FAIL	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer
EX 0627	DFHXCPRH	Exc	INCORRECT_SVC_LEVEL	1 Caller's parameter list 2 Call type 3 Caller's user name 4 SVC instruction
EX 0628	DFHXCPRH	Exc	INCORRECT IRP Level	1 Caller's parameter list 2 Call type 3 Callers user name 4 Return codes and message ptr
EX 0629	DFHXCPRH	Exc	Server protocol error	1 Caller's parameter list 2 Call type 3 Callers user name 4 Connection name 5 Target CICS applid
EX 0800	DFHXCPRH	Exc	RESP shows LENGERR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 COMMAREA length 6 Data length
EX 0801	DFHXCPRH	Exc	RESP shows INVREQ	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 DPL options specified
EX 0802	DFHXCPRH	Exc	RESP shows PGMIDERR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Program name 5 Target CICS applid
EX 0803	DFHXCPRH	Exc	RESP shows ROLLEDBACK	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Program name 5 Target CICS applid

Table 117. External CICS interface trace points (continued)

Point ID	Module	Lvl	Type	Data
EX 0804	DFHXCPRH	Exc	RESP shows NOTAUTH	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Program name 5 Target CICS applid
EX 0805	DFHXCPRH	Exc	RESP shows SYSIDERR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Program name 5 Target CICS applid 6 DPL_Retarea
EX 0806	DFHXCPRH	Exc	RESP shows TERMERR	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Program name 5 Target CICS applid
EX 0904	DFHXCTRP	Exc	Overlength trace data field	1 XCTRP parameter list
EX 0905	DFHXCTRA	Exc	DFHXCTRA trace entry	1 User-specified data
EX 1000	DFHXCPRH	EX 1	Entry	For INIT_USER commands: 1 Caller's parameter list 2 Call type 3 Caller's user name 4 Caller's register 14 For ALLOCATE_PIPE requests: 1 Caller's parameter list 2 Call type 3 Caller's user name 4 CICS name 5 ALLOCATE options 6 Caller's register 14 For OPEN, CLOSE, and DEALLOCATE requests: 1 Caller's parameter list 2 Call type 3 Caller's user name 4 CICS name 5 Pipe token 6 Caller's register 14 For DPL requests: 1 Caller's parameter list 2 Call type 3 Caller's user name 4 CICS name 5 Pipe token 6 Program name 7 Caller's register 14

Table 117. External CICS interface trace points (continued)

Point ID	Module	Lvl	Type	Data
EX 1001	DFHXCPRH	EX 1	Exit	<p>For INIT_USER, OPEN, CLOSE, and DEALLOCATE requests:</p> <ol style="list-style-type: none"> 1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Caller's register 14 <p>For ALLOCATE requests:</p> <ol style="list-style-type: none"> 1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 Pipe token 6 Caller's register 14 <p>For DPL requests:</p> <ol style="list-style-type: none"> 1 Caller's parameter list 2 Call type 3 Caller's user name 4 Return codes and message pointer 5 DPL return area 6 Caller's register 14
EX 1010	DFHXCEIP	EX 1	Entry	<ol style="list-style-type: none"> 1 Program name 2 Target CICS applid 3 Transaction id 4 Caller's register 14 5 Up to first 100 bytes of commarea (if passed) 6 Commarea length, if commarea passed 7 Datalength, if commarea passed
EX 1011	DFHXCEIP	EX 1	Exit	<ol style="list-style-type: none"> 1 EXEC retarea 2 Program name 3 Target CICS applid 4 Transaction id 5 Caller's register 14 6 Up to first 100 bytes of commarea (if passed) 7 Commarea length, if commarea passed
EX 2000	DFHXCPRH	EX 2	IRP_LOGON	<ol style="list-style-type: none"> 1 Caller's parameter list 2 Call type 3 Caller's user name 4 Target CICS applid 5 IRP userid 6 SLCB address 7 Connection name

Table 117. External CICS interface trace points (continued)

Point ID	Module	Lvl	Type	Data
EX 2001	DFHXCPRH	EX 2	IRP_CONN	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Target CICS applid 5 IRP userid 6 IRP threadid 7 SCCB address
EX 2002	DFHXCPRH	EX 2	IRP_DISC	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Target CICS applid 5 Pipe token
EX 2003	DFHXCPRH	EX 2	IRP_LOGOFF	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Pipe token 5 IRP userid
EX 2004	DFHXCPRH	EX 2	IRP_SWITCH	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Target CICS applid 5 IRP userid 6 IRP threadid
EX 2005	DFHXCPRH	EX 2	IRP_SWITCH_DATA	1 User' appl name 2 Pipe token 3 Request header 4 Bind data 5 UOWID/USERID FMH 6 Transformed DPL request to CICS (up to 1000 bytes) 7 Final 1000 bytes of transformed DPL request
EX 2006	DFHXCPRH	EX 2	IRP_DATA	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Target CICS applid 5 Length of data returned 6 Data (first 1000 bytes) 7 Data (final 1000 bytes)
EX 2007	DFHXCPRH	EX 2	PRE_URM	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Parameters passed to DFHXCURM 5 URMINV, reason for calling URM 6 URM CICS, target CICS applid 7 URM ANCH, URM anchor point address

Table 117. External CICS interface trace points (continued)

Point ID	Module	Lvl	Type	Data
EX 2008	DFHXCPRH	EX 2	POST_URM	1 Caller's parameter list 2 Call type 3 Caller's user name 4 Parameters passed to DFHXCURM 5 URMINV, reason for calling URM 6 URMCIICS, target CICS applid 7 URMANCH, URM anchor point address
EX 3000	DFHXCEIP	Exc	ESTAE_SETUP_ERROR	1 Return area (20 bytes) 2 MVS return code
EX 3001	DFHXCEIP	Exc	ESTAE_INVOKED	1 Return area (20 bytes)
EX 3002	DFHXCEIP	Exc	INV_CTYPE_ON_INIT	1 Return area (20 bytes) 2 Call type
EX 3003	DFHXCEIP	Exc	INV_VNUM_ON_INIT	1 Return area (20 bytes) 2 Version number
EX 3004	DFHXCEIP	Exc	INV_APPL_NAME_ON INIT	1 Return area (20 bytes) 2 User name
EX 3005	DFHXCEIP	Exc	INV_CTYPE_ON_ALLOC	1 Return area (20 bytes) 2 Call type
EX 3006	DFHXCEIP	Exc	INV_VNUM_ON_ALLOC	1 Return area (20 bytes) 2 Version number
EX 3007	DFHXCEIP	Exc	INV_UTOKEN_ON ALLOC	1 Return area (20 bytes) 2 User token
EX 3008	DFHXCEIP	Exc	INV_CTYPE_ON_OPEN	1 Return area (20 bytes) 2 Call type
EX 3009	DFHXCEIP	Exc	INV_VNUM_ON_OPEN	1 Return area (20 bytes) 2 Version number
EX 3010	DFHXCEIP	Exc	INV_UTOKEN_ON_OPEN	1 Return area (20 bytes) 2 User token
EX 3011	DFHXCEIP	Exc	INV_PTOKEN_ON_OPEN	1 Return area (20 bytes) 2 Pipe token
EX 3012	DFHXCEIP	Exc	INV_CTYPE_ON_DPL	1 Return area (20 bytes) 2 Call type
EX 3013	DFHXCEIP	Exc	INV_VNUM_ON_DPL	1 Return area (20 bytes) 2 Version number
EX 3014	DFHXCEIP	Exc	INV_UTOKEN_ON_DPL	1 Return area (20 bytes) 2 User token

Table 117. External CICS interface trace points (continued)

Point ID	Module	Lvl	Type	Data	
EX 3015	DFHXCEIP	Exc	INV_PTOKEN_ON_DPL	1	Return area (20 bytes)
				2	Pipe token
EX 3017	DFHXCEIP	Exc	INV_USERID_ON_DPL	1	Return area (20 bytes)
				2	Userid
EX 3018	DFHXCEIP	Exc	PIPE_NOT_OPEN_ON DPL	1	Return area (20 bytes)
				2	Pipe token
EX 3019	DFHXCEIP	Exc	PIPE_MUST_CLOSE_ON DPL	1	Return area (20 bytes)
				2	Pipe token
EX 3020	DFHXCEIP	Exc	INV_CTYPE_ON_CLOSE	1	Return area (20 bytes)
				2	Call type
EX 3021	DFHXCEIP	Exc	INV_VNUM_ON_CLOSE	1	Return area (20 bytes)
				2	Version number
EX 3022	DFHXCEIP	Exc	INV_UTOKEN_ON CLOSE	1	Return area (20 bytes)
				2	User token
EX 3023	DFHXCEIP	Exc	INV_PTOKEN_ON CLOSE	1	Return area (20 bytes)
				2	Pipe token
EX 3024	DFHXCEIP	Exc	INV_CTYPE_ON_DEALL	1	Return area (20 bytes)
				2	Call type
EX 3025	DFHXCEIP	Exc	INV_VNUM_ON_DEALL	1	Return area (20 bytes)
				2	Version number
EX 3026	DFHXCEIP	Exc	INV_UTOKEN_ON_DEALL	1	Return area (20 bytes)
				2	User token
EX 3027	DFHXCEIP	Exc	INV_PTOKEN_ON_DEALL	1	Return area (20 bytes)
				2	Pipe token
EX 3028	DFHXCEIP	Exc	PIPE_NOT_CLOSED_ON DEALL	1	Return area (20 bytes)
				2	Pipe token
EX 3029	DFHXCEIP	Exc	XCEIP_RETRYING	1	Return area (20 bytes)
EX 8500	DFHWBSRV	Exc	HTTPD_EXTRACT failed	1	Header string
				2	HTTPD_EXTRACT return code
				3	WBA1 parameter list
EX 8501	DFHWBSRV	Exc	HTTPD_read failed	1	Read buffer
				2	HTTPD_read return code
				3	WBA1 parameter list
EX 8502	DFHWBSRV	Exc	Invalid URL	1	WBA1 parameter list
EX 8503	DFHWBSRV	Exc	Make partnership failed	1	EXCI LINK RESP
				2	EXCI link RESP2

Table 117. External CICS interface trace points (continued)

Point ID	Module	Lvl	Type	Data
EX 8504	DFHWBSRV	Exc	WBA1 exception response	1 WBA1_RESPONSE field 2 WBA1 parameter list
EX 8505	DFHWBSRV	Exc	HTTPD_set failed	1 Header name 2 Header value 3 HTTD_set return code 4 WBA1 parameter list
EX 8506	DFHWBSRV	Exc	HTTPD_write failed	1 HTTD_write string 2 HTTPD_write return code

ONC/RPC trace points

Table 118. ONC/RPC trace points

Point ID	Module	Lvl	Type	Data
FT 9E00	DFHRPC01	FT 1	Entry	None
FT 9E01	DFHRPC01	FT 1	Exit	None
FT 9E02	DFHRPC01	Exc	TRUE not found	1 RPCOM 2 EIB
FT 9E03	DFHRPC01	Exc	Invalid GWA length	1 RPCOM 2 ONC_GWA
FT 9E04	DFHRPC01	Exc	No GWA returned	1 RPCOM 2 EIB
FT 9E06	DFHRPC01	Exc	INIT EXT NOTAUTH	1 RPCOM 2 EIB
FT 9E07	DFHRPC01	Exc	INIT bad EIBRESP	1 RPCOM 2 EIB
FT 9E08	DFHRPC01	Exc	INIT bad EIBRESP2	1 RPCOM 2 EIB
FT 9E09	DFHRPC01	FT 1	INIT CRPM running	1 RPCOM
FT 9E0A	DFHRPC01	Exc	ASSIGN error	1 RPCOM 2 EIB
FT 9E0B	DFHRPC01	Exc	RECEIVE error	1 RPCOM
FT 9E0C	DFHRPC01	Exc	DUMP REG error	1 DUFT parameters
FT 9E0D	DFHRPC01	Exc	HANDLE ABEND	1 RPCOM
FT 9E0E	DFHRPC01	Exc	TRUE enabled but no CRPM	1 RPCOM
FT 9E10	DFHRPC01	Exc	Invalid startcode	1 EIB
FT 9E11	DFHRPC01	Exc	GETMAIN buffer error	1 EIB
FT 9E12	DFHRPC01	Exc	Invalid terminal	1 RPCOM

Table 118. ONC/RPC trace points (continued)

Point ID	Module	Lvl	Type	Data
FT 9E20	DFHRPC04	FT 1	Entry	1 RPCOM
FT 9E21	DFHRPC04	FT 1	Exit	1 RPCOM
FT 9E22	DFHRPC04	Exc	Update ENQ error	1 RPCOM 2 ONC_GWA 3 EIBRESP
FT 9E23	DFHRPC04	Exc	Update DEQ error	1 RPCOM 2 ONC_GWA 3 EIBRESP
FT 9E24	DFHRPC04	FT 1	Update GWA entry	1 RPCOM
FT 9E25	DFHRPC04	FT 1	Update GWA exit	1 RPCOM
FT 9E30	DFHRPC42	FT 1	Entry	1 RPCOM
FT 9E31	DFHRPC42	FT 1	Exit	1 RPCOM
FT 9E32	DFHRPC42	Exc	Inquire ESM error	1 RPCOM
FT 9E38	DFHRPC03	FT 1	Entry	1 RPCOM
FT 9E39	DFHRPC03	FT 1	Exit	1 RPCOM
FT 9E3A	DFHRPC03	Exc	ENQ error	1 RPCOM 2 ENQ response
FT 9E3B	DFHRPC03	Exc	DEQ error	1 RPCOM 2 DEQ response
FT 9E40	DFHRPC4C	FT 1	Entry	1 RPCOM
FT 9E41	DFHRPC4C	FT 1	Exit	1 RPCOM
FT 9E42	DFHRPC4C	Exc	WRITE TSQ error	1 EIB 2 RPCOM 3 Subpool token
FT 9E43	DFHRPC4C	Exc	ADDSUB invalid unit	1 SMAD parameters 2 RPCOM 3 ONC_GWA
FT 9E45	DFHRPC4C	Exc	SMAD no storage	1 SMAD parameters 2 RPCOM 3 ONC_GWA
FT 9E46	DFHRPC4C	Exc	Unexpected response	1 SMAD parameters 2 RPCOM 3 ONC_GWA
FT 9E47	DFHRPC4C	Exc	WAIT MVS error	1 DSSR parameters 2 RPCOM

Table 118. ONC/RPC trace points (continued)

Point ID	Module	Lvl	Type	Data
FT 9E48	DFHRPC4C	Exc	DSIT no storage	1 DSIT parameters 2 RPCOM
FT 9E49	DFHRPC4C	Exc	ACTIVATE mode error	1 DSIT parameters 2 RPCOM
FT 9E4A	DFHRPC4C	Exc	Error	1 EIB 2 RPCOM
FT 9E4B	DFHRPC4C	Exc	INVEXITR	1 EIB 2 RPCOM
FT 9E4D	DFHRPC4C	Exc	NOTAUTH for SPI	1 EIB 2 RPCOM
FT 9E4E	DFHRPC4C	Exc	NOTAUTH for TRUE	1 EIB 2 RPCOM
FT 9E4F	DFHRPC4C	Exc	LOAD RPC CALLER error	1 EIB 2 RPCOM
FT 9E50	DFHRPC4C	Exc	CRPM start error	1 EIB 2 RPCOM 3 ONC_GWA
FT 9E51	DFHRPC4C	Exc	Load alias list error	1 EIB 2 RPCOM
FT 9E52	DFHRPC4C	Exc	CHANGE MODE error	1 DSIT parameters 2 RPCOM 3 ONC_GWA
FT 9E53	DFHRPC4C	Exc	DSAT no storage	1 DSAT parameters 2 RPCOM
FT 9E55	DFHRPC4C	Exc	INIT RPC error	1 EIB 2 RPCOM 3 ONC_GWA
FT 9E56	DFHRPC4C	Exc	EXTRACT error	1 EIB 2 RPCOM 3 ONC_GWA
FT 9E57	DFHRPC4C	Exc	ADD XDR error	1 RPCOM 2 ONC_GWA
FT 9E58	DFHRPC4C	Exc	DUMP UPDATE error	1 DUFT parameters
FT 9E59	DFHRPC4C	Exc	Invalid GWA status	1 ONC_GWA
FT 9E5A	DFHRPC4C	Exc	Update ENQ error	1 RPCOM 2 ONC_GWA 3 EIBRESP

Table 118. ONC/RPC trace points (continued)

Point ID	Module	Lvl	Type	Data
FT 9E5B	DFHRPC4C	Exc	Update DEQ error	1 RPCOM 2 ONC_GWA 3 EIBRESP
FT 9E5C	DFHRPC05	FT 1	Entry	1 RPCOM
FT 9E5D	DFHRPC05	FT 1	Exit	1 RPCOM
FT 9E5E	DFHRPC05	Exc	ENQ error	1 RPCOM 2 ENQ response
FT 9E5F	DFHRPC05	Exc	DEQ error	1 RPCOM 2 DEQ response
FT 9E60	DFHRPC06	FT 1	Entry	1 RPCOM
FT 9E61	DFHRPC06	FT 1	Exit	1 RPCOM
FT 9E62	DFHRPC06	Exc	REGTABLE ENQ error	1 RPCOM
FT 9E63	DFHRPC06	Exc	REGTABLE DEQ error	1 RPCOM
FT 9E64	DFHRPC06	Exc	CHANGE MODE error	1 DSAT 2 RPCOM 3 ONC_GWA
FT 9E65	DFHRPC06	Exc	Unregister error	1 RPRP parameters 2 RPCOM 3 ONC_GWA
FT 9E70	DFHRPC08	FT 1	INITREG entry	1 RPCOM
FT 9E71	DFHRPC08	FT 1	INITREG exit	1 RPCOM
FT 9E72	DFHRPC08	Exc	INITREG error	1 Return code
FT 9E73	DFHRPC08	FT 1	GETREG entry	1 RPCOM 2 GETREG parameters
FT 9E74	DFHRPC08	FT 1	GETREG exit	1 RPCOM 2 GETREG parameters 3 GETREG return code
FT 9E75	DFHRPC08	Exc	GETREG LOCATE error	1 INITREG return code 2 GETREG parameters 3 GETREG return code
FT 9E76	DFHRPC08	Exc	GETREG GET error	1 INITREG return code 2 GETREG parameters 3 GETREG return code
FT 9E77	DFHRPC08	FT 1	REPREG entry	1 RPCOM 2 REGTABLE element
FT 9E78	DFHRPC08	FT 1	REPREG exit	1 RPCOM

Table 118. ONC/RPC trace points (continued)

Point ID	Module	Lvl	Type	Data
FT 9E79	DFHRPC08	Exc	REPREG error	1 RPCOM 2 REGTABLE element
FT 9E7A	DFHRPC08	FT 1	ADDREG entry	1 RPCOM 2 REGTABLE element
FT 9E7B	DFHRPC08	FT 1	ADDREG exit	1 RPCOM
FT 9E7C	DFHRPC08	Exc	ADDREG error	1 Return code 2 REGTABLE element
FT 9E7D	DFHRPC08	FT 1	Current delete entry	1 RPCOM
FT 9E7E	DFHRPC08	FT 1	Current delete exit	1 RPCOM
FT 9E7F	DFHRPC08	Exc	DELREG error	1 INITREG return code
FT 9E80	DFHRPC08	Exc	CICS ONC RPC disabled	None
FT 9E81	DFHRPC08	FT 1	LOCDEL entry	1 RPCOM
FT 9E82	DFHRPC08	FT 1	LOCDEL exit	1 RPCOM
FT 9E83	DFHRPC08	FT 1	List 4-tuple entry	1 RPCOM
FT 9E84	DFHRPC08	FT 1	List 4-tuple exit	1 4-tuple element
FT 9E85	DFHRPC08	Exc	List 4-tuple GETMAIN	1 SMGF parameters
FT 9E86	DFHRPC08	Exc	List 4-tuple FREEMAIN	1 SMGF parameters
FT 9E87	DFHRPC08	Exc	List 4-tuple cursor	1 ONC_GWA
FT 9E88	DFHRPC08	Exc	List 4-tuple get element	1 ONC_GWA
FT 9E90	DFHRPC09	FT 1	GETDEFS entry	1 RPCOM
FT 9E91	DFHRPC09	FT 1	GETDEFS exit	1 RPCOM
FT 9E92	DFHRPC09	Exc	GETDEFS read error	1 RPCOM 2 EIB
FT 9E93	DFHRPC09	Exc	GETDEFS write error	1 RPCOM 2 CICS ONC RPC definition record
FT 9E94	DFHRPC09	Exc	GETDEFS write process error	1 RPCOM 2 REGTABLE element
FT 9E95	DFHRPC09	Exc	DATAREG ENQ error	1 RPCOM 2 EIBRESP
FT 9E96	DFHRPC09	Exc	DATAREG STARTBR error	1 RPCOM 2 EIBRESP

Table 118. *ONC/RPC trace points (continued)*

Point ID	Module	Lvl	Type	Data	
FT 9E97	DFHRPC09	Exc	DATAREG READ first error	1	RPCOM
				2	EIBRESP
FT 9E98	DFHRPC09	Exc	DATAREG READNEXT error	1	RPCOM
				2	EIBRESP
FT 9E99	DFHRPC09	Exc	DATAREG READNEXT error	1	RPCOM
FT 9E9A	DFHRPC09	Exc	DATAREG ENDBR error	1	RPCOM
				2	EIBRESP
FT 9E9B	DFHRPC09	Exc	DATAREG DEQ error	1	RPCOM
				2	EIBRESP
FT 9E9C	DFHRPC09	Exc	Update READ error	1	RPCOM
				2	CICS ONC RPC definition list
FT 9E9D	DFHRPC09	Exc	Update WRITE error	1	RPCOM
				2	CICS ONC RPC definition list
FT 9EB0	DFHRPC0A	FT 1	INITRUN entry	1	RPCOM
FT 9EB1	DFHRPC0A	FT 1	INITRUN exit	1	RPCOM
FT 9EB2	DFHRPC0A	Exc	INITRUN error	1	Return code
FT 9EB3	DFHRPC0A	Exc	Listdata free error	1	SMGF parameters
FT 9EB4	DFHRPC0A	Exc	Listdata get error	1	SMGF parameters
FT 9EB5	DFHRPC0A	Exc	Listdata start browse error	1	RPCOM
				2	EIBRESP
FT 9EB6	DFHRPC0A	Exc	Listdata end browse error	1	RPCOM
				2	EIBRESP
FT 9EB7	DFHRPC0A	Exc	Listdata read first error	1	RPCOM
				2	EIBRESP
FT 9EB8	DFHRPC0A	Exc	Listdata read next error	1	RPCOM
				2	EIBRESP
FT 9EC0	DFHRPC0B	FT 1	Help panels entry	1	RPCOM
FT 9EC1	DFHRPC0B	FT 1	Help panels exit	1	RPCOM
FT 9EC2	DFHRPC0B	FT 1	DISPLAY errors entry	1	RPCOM
FT 9EC3	DFHRPC0B	FT 1	DISPLAY errors exit	1	RPCOM
FT 9EC4	DFHRPC0B	FT 1	MSGISSUE entry	1	RPCOM
FT 9EC5	DFHRPC0B	FT 1	MSGISSUE exit	1	RPCOM

Table 118. *ONC/RPC trace points (continued)*

Point ID	Module	Lvl	Type	Data
FT 9EC6	DFHRPC0B	Exc	MSGISSUE SEND MSG error	1 EIB 2 RPCOM
FT 9EC7	DFHRPC0B	Exc	MSGISSUE WRITEQ error	1 EIB 2 RPCOM
FT 9EC8	DFHRPC0B	Exc	EXTRACT exit error	1 RPCOM 2 EIB
FT 9EC9	DFHRPC0B	Exc	Invalid GWA length	1 RPCOM 2 EIB
FT 9ECA	DFHRPC0B	Exc	Invalid GWA detected	1 RPCOM 2 EIB
FT 9ECB	DFHRPC0B	Exc	Message GETMAIN error	1 EIB 2 RPCOM
FT 9ED0	DFHRPC0D	FT 1	Entry	1 RPCOM
FT 9ED1	DFHRPC0D	FT 1	Exit	1 RPCOM
FT 9EE0	DFHRPC0E	FT 1	Entry	1 RPCOM
FT 9EE1	DFHRPC0E	FT 1	Exit	1 RPCOM
FT 9EE2	DFHRPC0E	Exc	REGTABLE ENQ error	1 RPCOM
FT 9EE3	DFHRPC0E	Exc	REGTABLE DEQ error	1 RPCOM
FT 9EE4	DFHRPC0E	Exc	Getlengths LINK error	1 RPCOM
FT 9EE5	DFHRPC0E	Exc	Getlengths process error	1 RPCOM 2 Getlengths parameters
FT 9EE6	DFHRPC0E	Exc	Getlengths lengths error	1 RPCOM 2 Getlengths parameters
FT 9EE7	DFHRPC0E	Exc	XDR LOAD error	1 RPCOM 2 EIBRESP
FT 9EE8	DFHRPC0E	Exc	XDR ENQ error	1 RPCOM 2 ONC_GWA
FT 9EE9	DFHRPC0E	Exc	XDR DEQ error	1 RPCOM 2 ONC_GWA
FT 9EEA	DFHRPC0E	Exc	XDR ADD error	1 SMGF parameters 2 RPCOM 3 ONC_GWA
FT 9EEB	DFHRPC0E	Exc	CHANGE MODE error	1 DSAT parameters 2 RPCOM 3 ONC_GWA

Table 118. ONC/RPC trace points (continued)

Point ID	Module	Lvl	Type	Data
FT 9EEC	DFHRPC0E	Exc	REGISTER error	1 RPRP parameters 2 RPCOM 3 ONC_GWA
FT 9EED	DFHRPC0E	Exc	Handle abend	1 RPCOM 2 Getlengths parameters 3 EIBRESP
FT 9EF0	DFHRPC10	FT 1	Entry	1 RPCOM
FT 9EF1	DFHRPC10	FT 1	Exit	1 RPCOM
FT 9EF2	DFHRPC10	Exc	ENQ error	1 RPCOM 2 EIBRESP
FT 9EF3	DFHRPC10	Exc	DEQ error	1 RPCOM 2 EIBRESP
FT 9EF4	DFHRPC10	Exc	Start browse error	1 RPCOM
FT 9EF5	DFHRPC10	Exc	GETMAIN error	1 SMGF parameters
FT 9EF6	DFHRPC10	Exc	FREEMAIN error	1 SMGF parameters
FT 9EF7	DFHRPC10	Exc	Get next error	1 RPCOM
FT 9EF8	DFHRPC10	Exc	End browse error	1 RPCOM
FT 9EF9	DFHRPC10	Exc	Delete entry error	1 RPCOM
FT 9F02	DFHRPAS	Exc	ASSIGN CMD	1 Start code 2 EIB
FT 9F03	DFHRPAS	Exc	START CODE	1 Start code
FT 9F04	DFHRPAS	Exc	RETRIEVE CMD	1 EIB
FT 9F05	DFHRPAS	FT 1	RETRIEVE parameters	1 Actual eyecatcher 2 Expected eyecatcher
FT 9F09	DFHRPAS	FT 1	UPDATE RUNPROC	1 EIB
FT 9F0A	DFHRPAS	Exc	GWA CHECK	1 Enable time 2 GWA address 3 Alias parameters
FT 9F0B	DFHRPAS	Exc	VERIFY PASSWORD	1 Alias parameters 2 ONC_GWA
FT 9F0C	DFHRPAS	Exc	LINK TERMERR	1 EIB
FT 9F0D	DFHRPAS	Exc	LINK CMD	1 Alias parameters 2 EIB
FT 9F0E	DFHRPAS	Exc	Resource checker	1 Resource checker parameters

Table 118. ONC/RPC trace points (continued)

Point ID	Module	Lvl	Type	Data
FT 9F0F	DFHRPAS	Exc	QUERY SECURITY error	1 Client address 2 User ID 3 Alias parameters
FT 9F10	DFHRPAS	Exc	AUTH error	1 Client address 2 User ID 3 Alias parameters
FT 9F12	DFHRPAS	Exc	REPLY data error	1 EIB
FT 9F13	DFHRPAS	Exc	REPLY operation error	1 Alias parameters
FT 9F14	DFHRPAS	Exc	CHANGE MODE error	1 Alias parameters
FT 9F15	DFHRPAS	Exc	SEND REPLY	1 Alias parameters
FT 9F16	DFHRPAS	Exc	Encode LINK error	1 EIB
FT 9F17	DFHRPAS	Exc	Encode response error	1 Encode parameters
FT 9F18	DFHRPAS	Exc	RPC error	1 EIB
FT 9F19	DFHRPAS	Exc	RPC caller error	1 Alias parameters
FT 9F1A	DFHRPAS	Exc	FREEMAIN server error	1 EIB
FT 9F1B	DFHRPAS	Exc	FREEMAIN client error	1 EIB
FT 9F1C	DFHRPAS	Exc	DELRUN error	1 Alias parameters
FT 9F1D	DFHRPAS	Exc	RETURN error	1 Alias parameters
FT 9F1E	DFHRPAS	Exc	MAIN ABEND	1 Alias parameters
FT 9F1F	DFHRPAS	FT 1	Encode request	1 Encode parameters
FT 9F20	DFHRPAS	FT 1	Encode response	1 Encode parameters
FT 9F21	DFHRPAS	FT 1	Server output data	1 First 256 bytes data
FT 9F22	DFHRPAS	FT 1	Server output data	1 Next 3900 bytes data
FT 9F23	DFHRPAS	FT 1	Encode output data	1 First 256 bytes data
FT 9F24	DFHRPAS	FT 1	Encode output data	1 Next 3900 bytes data
FT 9F25	DFHRPAS	FT 1	COMMAREA	1 First 256 bytes data
FT 9F26	DFHRPAS	FT 2	COMMAREA	1 Next 3900 bytes data
FT 9F41	DFHRPRP	Exc	Invalid format	1 RPRP parameters
FT 9F42	DFHRPRP	Exc	Invalid function	1 RPRP parameters
FT 9F43	DFHRPRP	FT 1	Entry	1 RPRP parameters

Table 118. ONC/RPC trace points (continued)

Point ID	Module	Lvl	Type	Data	
FT 9F44	DFHRPRP	FT 1	Exit	1	RPRP parameters
FT 9F45	DFHRPRP	Exc	Recovery	1 2	RPRP parameters Kernel error data
FT 9F46	DFHRPRP	FT 1	Call	1 2	Preinit C arguments RPC parameters
FT 9F47	DFHRPRP	FT 1	Return	1 2	Preinit C arguments RPC parameters
FT 9F48	DFHRPRP	Exc	Invalid GWA	None	
FT 9F49	DFHRPRP	Exc	INIT error	1 2	RPRP parameters RPC parameters
FT 9F4A	DFHRPRP	Exc	No storage	None	
FT 9F4B	DFHRPRP	Exc	Not registered	None	
FT 9F4C	DFHRPRP	Exc	Socket error	1 2	RPRP parameters RPC parameters
FT 9F4D	DFHRPRP	Exc	Gethostid error	1 2	RPRP parameters ONC_GWA
FT 9F4E	DFHRPRP	Exc	Logic error	1 2	Trace point RPRP parameters
FT 9F4F	DFHRPRP	Exc	Select error	1 2	RPRP parameters RPC parameters
FT 9F50	DFHRPRP	Exc	DELETE LOCK error	1	RPRP parameters
FT 9F51	DFHRPRP	Exc	Duplicate LOCK error	1 2	RPRP parameters ONC_GWA
FT 9F52	DFHRPRP	Exc	GET LOCK error	1	RPRP parameters
FT 9F53	DFHRPRP	Exc	Bad parameter list	1 2	RPRP parameters ONC_GWA
FT 9F54	DFHRPRP	Exc	Already registered	None	
FT 9F55	DFHRPRP	Exc	svc_register error	1 2	RPRP parameters RPC parameters
FT 9F57	DFHRPRP	Exc	PMAP UNSET error	1 2	RPRP parameters RPC parameters
FT 9F58	DFHRPRP	Exc	svcupd_create error	1 2	RPRP parameters RPC parameters
FT 9F59	DFHRPRP	Exc	svctcp_create error	1 2	RPRP parameters RPC parameters
FT 9F5A	DFHRPRP	Exc	HANDLE not found	1 2	RPRP parameters RPC parameters

Table 118. ONC/RPC trace points (continued)

Point ID	Module	Lvl	Type	Data	
FT 9F5B	DFHRPRP	Exc	svc_sendreply error	1	RPRP parameters
				2	RPC parameters
FT 9F5C	DFHRPRP	Exc	Invalid aup_gids	1	RPRP parameters
				2	RPC parameters
FT 9F5D	DFHRPRP	Exc	Invalid machine name length	1	RPRP parameters
				2	RPC parameters
FT 9F5E	DFHRPRP	Exc	svc_getargs error	1	RPRP parameters
				2	RPC parameters
FT 9F5F	DFHRPRP	Exc	svc_freeargs error	1	RPRP parameters
				2	RPC parameters
FT 9F60	DFHRPRP	Exc	getsockopt error	1	RPRP parameters
				2	RPC parameters
FT 9F61	DFHRPRP	Exc	Transport handle free error	1	SMGF parameters
				2	RPC parameters
FT 9F62	DFHRPRP	Exc	Transport copy free error	1	SMGF parameters
				2	RPC parameters
FT 9F63	DFHRPRP	Exc	maxdesc unknown	1	RPRP parameters
				2	RPC parameters
FT 9F64	DFHRPRP	Exc	maxdesc too few	1	RPRP parameters
				2	RPC parameters
FT 9F65	DFHRPRP	Exc	maxdesc EFAULT	1	RPRP parameters
				2	RPC parameters
FT 9F66	DFHRPRP	Exc	maxdesc EALREADY	1	RPRP parameters
				2	RPC parameters
FT 9F67	DFHRPRP	Exc	maxdesc EINVAL	1	RPRP parameters
				2	RPC parameters
FT 9F68	DFHRPRP	Exc	maxdesc EMFILE	1	RPRP parameters
				2	RPC parameters
FT 9F69	DFHRPRP	Exc	maxdesc ENOMEM	1	RPRP parameters
				2	RPC parameters
FT 9F6A	DFHRPRP	Exc	maxdesc EIBMIUCVERR	1	RPRP parameters
				2	RPC parameters
FT 9F6B	DFHRPRP	Exc	svcerr_auth error	1	RPRP parameters
				2	RPC parameters
FT 9F6C	DFHRPRP	Exc	svcerr_decode error	1	RPRP parameters
				2	RPC parameters
FT 9F6D	DFHRPRP	Exc	svcerr_noproc error	1	RPRP parameters
				2	RPC parameters

Table 118. ONC/RPC trace points (continued)

Point ID	Module	Lvl	Type	Data
FT 9F6E	DFHRPRP	Exc	svcerr_systemerr error	1 RPRP parameters 2 RPC parameters
FT 9F6F	DFHRPRP	Exc	dfhsvc_getreqset error	1 RPRP parameters 2 RPC parameters
FT 9F81	DFHRPMS	FT 1	Exit	1 ONC_GWA
FT 9F82	DFHRPMS	FT 1	Decode request	1 Decode parameters
FT 9F83	DFHRPMS	FT 1	Decode response	1 Decode parameters
FT 9F87	DFHRPMS	Exc	Wait MVS	1 DSSR parameters 2 ONC_GWA
FT 9F90	DFHRPMS	Exc	LINK error	1 EIB 2 ONC_GWA 3 Alias parameters
FT 9F91	DFHRPMS	Exc	START error	1 EIB 2 ONC_GWA 3 Alias parameters
FT 9F93	DFHRPMS	Exc	Run error	1 RPRP parameters 2 ONC_GWA
FT 9F99	DFHRPMS	Exc	CHANGE MODE error	1 DSAT parameters 2 ONC_GWA
FT 9F9A	DFHRPMS	Exc	HANDLE decode abend	1 Decode parameters 2 ONC_GWA
FT 9F9F	DFHRPMS	Exc	CICS abend client	1 ONC_GWA
FT 9FA3	DFHRPMS	Exc	Disabled TRUE	1 EIB 2 ONC_GWA
FT 9FA4	DFHRPMS	Exc	FREEMAIN error	1 EIB
FT 9FA6	DFHRPMS	Exc	Release RPAL error	1 EIB
FT 9FAA	DFHRPMS	Exc	Decode return error	1 Decode parameters 2 ONC_GWA 3 Alias parameters
FT 9FAE	DFHRPMS	Exc	EXTRACT exit 1	1 EIB
FT 9FAF	DFHRPMS	Exc	GWA corrupt 1	1 EIB
FT 9FB0	DFHRPMS	FT 1	GETREG entry	1 GETREG parameters
FT 9FB1	DFHRPMS	FT 1	GETREG exit	1 BBLX return code 2 GETREG parameters 3 GETREG return code

Table 118. ONC/RPC trace points (continued)

Point ID	Module	Lvl	Type	Data
FT 9FB2	DFHRPMS	Exc	GETREG ENQ error	1 BBLX return code 2 GETREG parameters 3 GETREG return code
FT 9FB3	DFHRPMS	Exc	GETREG DEQ error	1 BBLX return code 2 GETREG parameters 3 GETREG return code
FT 9FB4	DFHRPMS	Exc	GETREG CURSOR error	1 BBLX return code 2 GETREG parameters 3 GETREG return code
FT 9FB5	DFHRPMS	Exc	GETREG LOCATE error	1 BBLX return code 2 GETREG parameters 3 GETREG return code
FT 9FB6	DFHRPMS	Exc	GETREG POINT error	1 BBLX return code 2 GETREG parameters 3 GETREG return code
FT 9FC2	DFHRPMS	Exc	Decode lengths	1 Decode parameters 2 ONC_GWA 3 Alias parameters
FT 9FC8	DFHRPMS	FT 1	Alias list add error	1 ONC_GWA 2 RPAL parameters
FT 9FD0	DFHRPMS	Exc	ABEND footprint	1 ONC_GWA
FT 9FD1	DFHRPMS	Exc	CICS ABEND NOCLIENT	1 ONC_GWA
FT 9FD2	DFHRPMS	FT 1	Client data	1 First 256 bytes data 2 aup_machname 3 aup_gids
FT 9FD3	DFHRPMS	FT 2	Client data	1 Next 3900 bytes data
FT 9FD4	DFHRPMS	FT 1	Decoded data	1 First 256 bytes data
FT 9FD5	DFHRPMS	FT 2	Decoded data	1 Next 3900 bytes data
FT 9FD6	DFHRPMS	Exc	Freeargs	1 RPRP parameters
FT 9FF0	DFHRPAL	FT 1	RPAL entry	1 RPAL parameters
FT 9FF1	DFHRPAL	FT 1	RPAL exit	1 RPAL parameters
FT 9FF2	DFHRPAL	Exc	Invalid format	1 RPAL parameters
FT 9FF3	DFHRPAL	Exc	Invalid function	1 RPAL parameters
FT 9FF4	DFHRPAL	Exc	Recovery	1 RPAL parameters 2 Kernel error data
FT 9FF5	DFHRPAL	Exc	Browse busy	1 RPAL parameters

Kernel domain trace points

Table 119. Kernel domain trace points

Point ID	Module	Lvl	Type	Data	
KE 0101	DFHKETI	KE 1	Entry	1	KETI parameter list
KE 0102	DFHKETI	KE 1	Exit	1	KETI parameter list
KE 0103	DFHKETI	Exc	Recovery	1 2	KETI parameter list Kernel error data
KE 0104	DFHKETI	Exc	Store clock error	1 2	KETI parameter list Store clock value
KE 0201	DFHKEDD	KE 1 ¹	Entry	1	KEDD parameter list
KE 0202	DFHKEDD	KE 1 ¹	Exit	1	KEDD parameter list
KE 0203	DFHKEDD	Exc	Recovery	1 2	KEDD parameter list Kernel error data
KE 0204	DFHKEDD	Exc	Invalid format	1	KEDD parameter list
KE 0205	DFHKEDD	Exc	Invalid function	1	KEDD parameter list
KE 0206	DFHKEDD	Exc	Invalid domain token	1	KEDD parameter list
KE 0207	DFHKEDD	Exc	Invalid entry point	1	KEDD parameter list
KE 0208	DFHKEDD	Exc	Invalid domain token	1	KEDD parameter list
KE 0209	DFHKEDD	Exc	Invalid entry point	1	KEDD parameter list
KE 020A	DFHKEDD	Exc	Invalid gate index	1	KEDD parameter list
KE 020C	DFHKEDD	Exc	Invalid domain token	1	KEDD parameter list
KE 020D	DFHKEDD	Exc	Invalid gate index	1	KEDD parameter list
KE 020E	DFHKEDD	Exc	Invalid domain token	1	KEDD parameter list
KE 020F	DFHKEDD	Exc	Invalid domain token	1	KEDD parameter list
KE 0210	DFHKEDD	Exc	Invalid domain token	1	KEDD parameter list
KE 0211	DFHKEDD	Exc	Invalid domain token	1	KEDD parameter list
KE 0212	DFHKEDD	Exc	Invalid domain token	1	KEDD parameter list
KE 0213	DFHKEDD	Exc	Invalid domain token	1	KEDD parameter list
KE 0214	DFHKEDD	Exc	Invalid entry point	1	KEDD parameter list
KE 0301	DFHKEIN	KE 1	Entry	1	KEIN parameter list
KE 0302	DFHKEIN	KE 1	Exit	1	KEIN parameter list

Table 119. Kernel domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
KE 0303	DFHKEIN	Exc	Recovery	1 2	KEIN parameter list Kernel error data
KE 0304	DFHKEIN	Exc	Invalid format	1	KEIN parameter list
KE 0305	DFHKEIN	Exc	Invalid function	1	KEIN parameter list
KE 0306	DFHKEIN	Exc ²	Insufficient storage	1	KEIN parameter list
KE 0307	DFHKEIN	Exc ²	Insufficient storage	1	KEIN parameter list
KE 0308	DFHKEIN	Exc ²	Insufficient storage	1	KEIN parameter list
KE 0309	DFHKEIN	Exc ²	Insufficient storage	1	KEIN parameter list
KE 030A	DFHKEIN	Exc ²	Insufficient storage	1	KEIN parameter list
KE 030B	DFHKEIN	Exc ²	Insufficient storage	1	KEIN parameter list
KE 030C	DFHKEIN	Exc ²	Insufficient storage	1	KEIN parameter list
KE 030D	DFHKEIN	Exc ²	MVS IDENTIFY error	1	KEIN parameter list
KE 030E	DFHKEIN	Exc ²	Internal error	1	KEIN parameter list
KE 030F	DFHKEIN	Exc ²	Internal error	1	KEIN parameter list
KE 0310	DFHKEIN	Exc ²	Internal error	1	KEIN parameter list
KE 0401	DFHKEGD	KE 1	Entry	1	KEGD or DSNT or DMDM parameter list
KE 0402	DFHKEGD	KE 1	Exit	1	KEGD or DSNT or DMDM parameter list
KE 0403	DFHKEGD	Exc	Recovery	1 2	KEGD or DSNT or DMDM parameter list Kernel error data
KE 0404	DFHKEGD	Exc	Invalid format	1	KEGD or DSNT or DMDM parameter list
KE 0405	DFHKEGD	Exc	Invalid function	1	KEGD or DSNT or DMDM parameter list
KE 0501	DFHKEDS	Exc	Recovery	1 2	KEDS parameter list Kernel error data
KE 0502	DFHKEDS	KE 1	Entry	1	KEDS parameter list
KE 0503	DFHKEDS	KE 1	Exit	1	KEDS parameter list
KE 0504	DFHKEDS	Exc	Change mode error	1 2	KEDS parameter list DSAT parameter list

Table 119. Kernel domain trace points (continued)

Point ID	Module	Lvl	Type	Data
KE 0505	DFHKEDS	Exc	Attach error	1 KEDS parameter list
KE 0506	DFHKEDS	Exc	Set dub default error	1 KEDS parameter list 2 Dub results
KE 0507	DFHKEDS	Event	Pre SVC call	1 KAFPB
KE 0508	DFHKEDS	Event	Post SVC call	1 KAFPB
KE 0509	DFHKEDS	Exc	SVC error	1 KEDS parameter list 2 KAFPB
KE 0601	DFHKEXM	KE 1	Entry	1 DFHKEXM parameter list
KE 0602	DFHKEXM	KE 1	Exit	1 DFHKEXM parameter list
KE 0603	DFHKEXM	Exc	Recovery	1 DFHKEXM parameter list 2 Kernel error data
KE 0604	DFHKEXM	Exc	Invalid format	1 Invalid parameter list
KE 0605	DFHKEXM	Exc	Invalid function	1 DFHKEXM parameter list
KE 0701	DFHKEAR	KE 1	Entry	1 DFHKEAR parameter list
KE 0702	DFHKEAR	KE 1	Exit	1 DFHKEAR parameter list
KE 0703	DFHKEAR	Exc	Recovery	1 DFHKEAR parameter list 2 Kernel error data
KE 0704	DFHKEAR	Exc	Deregister failed	1 DFHKEAR parameter list 2 ARM response 3 ARM reason
KE 0705	DFHKEAR	Exc	Waitpred failed	1 DFHKEAR parameter list 2 ARM response 3 ARM reason
KE 0706	DFHKEAR	Exc	Ready failed	1 DFHKEAR parameter list 2 ARM response 3 ARM reason
KE 0707	DFHKEAR	Exc	Waitpred timed out	1 DFHKEAR parameter list 2 ARM response 3 ARM reason
KE 0708	DFHKEAR	KE 1	Pre SVC call	1 DFHKEAR parameter list 2 KAFPB
KE 0709	DFHKEAR	KE 1	Post SVC call	1 DFHKEAR parameter list 2 KAFPB
KE 070A	DFHKEAR	Exc	SVC call error	1 DFHKEAR parameter list 2 KAFPB
KE 070B	DFHKEAR	Exc	Invalid function	1 DFHKEAR parameter list

Table 119. Kernel domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
KE 070C	DFHKEAR	Exc	Invalid format	1	DFHKEAR parameter list
KE 0801	DFHKETA	Exc	Recovery	1 2	DFHKEDS parameter list Kernel error data

¹ Functions SET_GLOBAL_TRACE, SET_DOMAIN_TRACE, and SET_TASK_TRACE are always traced from point IDs KE 0201 and KE 0202, even when KE level-1 tracing is not selected.

² Tracing from these point IDs is sent to the console, because trace domain is not yet initialized.

Loader domain trace points

Table 120. Loader domain trace points

Point ID	Module	Lvl	Type	Data	
LD 0001	DFHLDLD	LD 1	Entry	1	LDLD parameter list
LD 0002	DFHLDLD	LD 1	Exit	1	LDLD parameter list
LD 0701	DFHLDLD	Exc	Recovery	1 2	LDLD parameter list Kernel error data
LD 0801	DFHLDLD	Exc	Invalid format	1	LDLD parameter list
LD 0802	DFHLDLD	Exc	Invalid function	1	LDLD parameter list
LD 0803	DFHLDLD	Exc	Invalid parameters	1	LDLD parameter list
LD 0804	DFHLDLD	Exc	Invalid PDB	1 2	Program name PDB
LD 0806	DFHLDLD	Exc	Invalid entry point	1 2	Parameter list LDLD parameter list
LD 0807 LD 0808 LD 0809	DFHLDLD	Exc	Invalid PGM token	1 2	Parameter list LDLD parameter list
LD 0903	DFHLDLD	Exc	GETMAIN request failure	1 2	SMGF parameter list LDLD parameter list
LD 0905	DFHLDLD	Exc	ADD SUSPEND failure	1 2	DSSR parameter list LDLD parameter list
LD 0906	DFHLDLD	Exc	DELETE SUSPEND failure	1 2	DSSR parameter list LDLD parameter list
LD 0907	DFHLDLD	Exc	SUSPEND failure	1 2	DSSR parameter list LDLD parameter list
LD 0909 LD 090A	DFHLDLD	Exc	Lock failure	1 2	LMLM parameter list LDLD parameter list

Table 120. Loader domain trace points (continued)

Point ID	Module	Lvl	Type	Data
LD 090B	DFHLDLD	Exc	Unlock failure	1 LMLM parameter list
LD 090C				2 LDLD parameter list
LD 090D	DFHLDLD	Exc	INQUIRE_START failure	1 PAGP parameter list
LD 1003	DFHLDLD1	LD 1	Before SVC call	1 Authorized facility parameter list
				2 BLDL parameter list
LD 1004	DFHLDLD1	LD 1	After SVC call	1 Authorized facility parameter list
				2 BLDL parameter list
LD 1005	DFHLDLD1	LD 2	DSA compression	1 Program APE
				2 DSA name
LD 1007	DFHLDLD1	LD 2	Before issuing CSVQUERY	1 Program name
LD 1008	DFHLDLD1	LD 2	After issuing CSVQUERY	1 Program name
				2 Return code
LD 1701	DFHLDLD1	Exc	Recovery	1 LDSU parameter list
				2 Kernel error data
LD 1801	DFHLDLD1	Exc	Invalid function	1 Parameter list
				2 LDSU parameter list
				3 LDLD parameter list
LD 1802	DFHLDLD1	Exc	Bad response from SVC c	1 Authorized facility parameter list
				2 BLDL parameter list
				3 MVS abend code for the LOAD failing
				4 MVS reason code for the LOAD failing
LD 1803	DFHLDLD1	Exc	Corrupted control block	1 Control block address
				2 Control block identifier
				3 Control block contents
LD 1804	DFHLDLD1	Exc	CSVQUERY failure	1 Program name
				2 Return code
LD 1902	DFHLDLD1	Exc	State lock failure	1 LMLM parameter list
				2 LDSU parameter list
				3 LDLD parameter list
LD 1903	DFHLDLD1	Exc	APE GETMAIN failure	1 SMGF parameter list
				2 LDSU parameter list
				3 LDLD parameter list
LD 1905	DFHLDLD1	Exc	CSECTL GETMAIN failure	1 SMGF parameter list
				2 LDSU parameter list
				3 LDLD parameter list

Table 120. Loader domain trace points (continued)

Point ID	Module	Lvl	Type	Data
LD 1907	DFHLDLD1	Exc	PGM GETMAIN failure	1 SMGF parameter list 2 LDSU parameter list 3 LDLD parameter list
LD 1910	DFHLDLD1	Exc	State lock failure	1 LMLM parameter list
LD 1911				2 LDSU parameter list
LD 1912				3 LDLD parameter list
LD 1913				
LD 1914				
LD 1915	DFHLDLD1	Exc	State unlock failure	1 LMLM parameter list
LD 1916				2 LDSU parameter list
LD 1917				3 LDLD parameter list
LD 1918				
LD 1919	DFHLDLD1	Exc	Library lock failure	1 LMLM parameter list
LD 191A				2 LDSU parameter list
LD 191B				3 LDLD parameter list
LD 191C	DFHLDLD1	Exc	Library unlock failure	1 LMLM parameter list
LD 191D				2 LDSU parameter list
LD 191E				3 LDLD parameter list
LD 191F	DFHLDLD1	Exc	Library unlock failure	1 LMLM parameter list
				2 LDSU parameter list
				3 LDLD parameter list
LD 1920	DFHLDLD1	Exc	Mode change failure	1 DSAT parameter list
LD 1921				2 LDSU parameter list
				3 LDLD parameter list
LD 1922	DFHLDLD1	Exc	MVS LOAD or BLDL failure, no OS storage	1 Parameter list
				2 LDSU parameter list
				3 LDLD parameter list
LD 1923	DFHLDLD1	Exc	MVS LOAD or BLDL failure, no OS storage	1 Parameter list
				2 LDSU parameter list
				3 MVS abend code for the LOAD failing
				4 MVS reason code for the LOAD failing
LD 1924	DFHLDLD1	Exc	Library I/O error	1 Parameter list
				2 LDSU parameter list
				3 LDLD parameter list
LD 1925	DFHLDLD1	Exc	Library I/O error	1 Parameter list
				2 LDSU parameter list
				3 MVS abend code for the LOAD failing
				4 MVS reason code for the LOAD failing
LD 1926	DFHLDLD1	Exc	SVC request failure	1 Parameter list
				2 LDSU parameter list
				3 LDLD parameter list

Table 120. Loader domain trace points (continued)

Point ID	Module	Lvl	Type	Data
LD 1927	DFHLDLD1	Exc	SVC request failure	1 Parameter list 2 LDSU parameter list 3 MVS abend code for the LOAD failing 4 MVS reason code for the LOAD failing
LD 1929	DFHLDLD1	Exc	State unlock failure	1 LMLM parameter list 2 LDSU parameter list 3 LDLD parameter list
LD 192A	DFHLDLD1	Exc	Mode change failure	1 DSAT parameter list 2 LDSU parameter list 3 LDLD parameter list
LD 192B	DFHLDLD1	Exc	Library lock failure	1 LMLM parameter list 2 LDSU parameter list 3 LDLD parameter list
LD 192C	DFHLDLD1	Exc	Library unlock failure	1 LMLM parameter list 2 LDSU parameter list 3 LDLD parameter list
LD 192D	DFHLDLD1	Exc	State lock failure	1 LMLM parameter list 2 LDSU parameter list 3 LDLD parameter list
LD 2701	DFHLDLD2	Exc	Recovery	1 LDLD parameter list 2 Kernel error data 3 LDSU parameter list
LD 2901	DFHLDLD2	Exc	Catalog error	1 CCCC parameter list 2 LDLD parameter list
LD 2902	DFHLDLD2	Exc	Catalog DELETE failure	1 CCCC parameter list 2 LDLD parameter list
LD 2903	DFHLDLD2	Exc	CPE GETMAIN failure	1 SMGF parameter list 2 LDLD parameter list
LD 2909	DFHLDLD2	Exc	Catalog write failure	1 CCCC parameter list 2 LDLD parameter list
LD 3701	DFHLDLD3	Exc	Recovery	1 LDLD parameter list 2 Kernel error data 3 LDSU parameter list
LD 3901	DFHLDLD3	Exc	Catalog WRITE failure	1 LDLD parameter list 2 LDSU parameter list 2 CCCC parameter list
LD 3902	DFHLDLD3	Exc	LDBE GETMAIN failure	1 SMGF parameter list 2 LDLD parameter list

Table 120. Loader domain trace points (continued)

Point ID	Module	Lvl	Type	Data
LD 3904	DFHLDLD3	Exc	PRVMOD GETMAIN failure	1 LDLD parameter list 2 LDSU parameter list 3 SMGF parameter list
LD 3905	DFHLDLD3	Exc	Catalog error	1 LDLD parameter list 2 LDSU parameter list 3 CCCC parameter list
LD 3906	DFHLDLD3	Exc	Catalog write failure	1 LDLD parameter list 2 LDSU parameter list 3 CCCC parameter list
LD 3907	DFHLDLD3	Exc	Catalog error	1 LDLD parameter list 2 LDSU parameter list 3 CCCC parameter list
LD 3908	DFHLDLD3	Exc	Catalog write failure	1 LDLD parameter list 2 LDSU parameter list 3 CCCC parameter list
LD 3909	DFHLDLD3	Exc	Library lock failure	1 LDLD parameter list 2 LDSU parameter list 3 Lock manager parameter list
LD 390A	DFHLDLD3	Exc	Library unlock failure	1 LDLD parameter list 2 LDSU parameter list 3 Lock manager parameter list
LD 390B	DFHLDLD3	LD 1	Pre SVC call, DESERV GET	1 LAFPB parameter list 2 DESERV name descriptor
LD 390C	DFHLDLD3	LD 1	Post SVC call, DESERV GET	1 LAFPB parameter list 2 DESERV result (IGWSMDE)
LD 390D	DFHLDLD3	Exc	Post SVC, DESERV GET exception	1 LAFPB parameter list 2 DESERV buffer
LD 390E	DFHLDLD3	Exc	Mode change to RO failed	1 LDLD parameter list 2 LDSU parameter list 3 Dispatcher domain parameter list
LD 3910	DFHLDLD3	Exc	Convert long name failed	1 LDLD parameter list 2 Text of long name
LD 4001	DFHLDNT	LD 1	Entry	1 SMNT parameter list
LD 4002	DFHLDNT	LD 1	Exit	1 SMNT parameter list
LD 4701	DFHLDNT	Exc	Recovery	1 SMNT parameter list 2 Kernel error data
LD 4801	DFHLDNT	Exc	Invalid format	1 SMNT parameter list 2 Parameter list

Table 120. Loader domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
LD 4802	DFHLDNT	Exc	Invalid function	1	SMNT parameter list
				2	Parameter list
LD 4803	DFHLDNT	Exc	Invalid parameters	1	SMNT parameter list
LD 4901	DFHLDNT	Exc	State lock failure	1	SMNT parameter list
				2	LMLM parameter list
LD 4902	DFHLDNT	Exc	State unlock failure	1	SMNT parameter list
				2	LMLM parameter list
LD 5001	DFHLDST	LD 1	Entry	1	STST parameter list
LD 5002	DFHLDST	LD 1	Exit	1	STST parameter list
LD 5701	DFHLDST	Exc	Recovery	1	STST parameter list
				2	Kernel error data
LD 5801	DFHLDST	Exc	Invalid format	1	Parameter list
				2	STST parameter list
LD 5802	DFHLDST	Exc	Invalid function	1	Parameter list
				2	STST parameter list
LD 5803	DFHLDST	Exc	Invalid parameters - neither DATA(YES) nor RESET(YES)	1	Parameter list
				2	STST parameter list
LD 5901	DFHLDST	Exc	State lock failure	1	LMLM parameter list
				2	STST parameter list
LD 5902	DFHLDST	Exc	State unlock failure	1	LMLM parameter list
				2	STST parameter list
LD 6001	DFHLDDM	LD 1	Entry	1	DMDM parameter list
LD 6002	DFHLDDM	LD 1	Exit	1	DMDM parameter list
LD 6003	DFHLDDM	LD 2	Before SVC call	1	Authorized facility parameter list
LD 6004	DFHLDDM	LD 2	After SVC call	1	Authorized facility parameter list
LD 6701	DFHLDDM	Exc	Recovery	1	DMDM parameter list
				2	Kernel error data
LD 6801	DFHLDDM	Exc	Invalid format	1	DMDM parameter list
LD 6802	DFHLDDM	Exc	Invalid function	1	DMDM parameter list
LD 6803	DFHLDDM	Exc	Invalid parameters	1	DMDM parameter list
LD 6804	DFHLDDM	Exc	Bad LOB read from catalog	1	LOB
LD 6901	DFHLDDM	Exc	Define program error	1	DMDM parameter list
				2	Parameter list

Table 120. Loader domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
LD 6902	DFHLDDM	Exc	Acquire program error	1 2	DMDM parameter list Parameter list
LD 6903	DFHLDDM	Exc	Release program error	1 2	DMDM parameter list Parameter list
LD 6905	DFHLDDM	Exc	GETMAIN failure	1 2	DMDM parameter list SMGF parameter list
LD 6908	DFHLDDM	Exc	Add gate failure	1 2	DMDM parameter list KEDD parameter list
LD 6909	DFHLDDM	Exc	Get override parameters error	1 2	DMDM parameter list Parameter list
LD 690B	DFHLDDM	Exc	Catalog WRITE failure during quiesce	1 2	DMDM parameter list CCCC parameter list
LD 690D	DFHLDDM	Exc	Add control subpool failure	1 2	DMDM parameter list SMAD parameter list
LD 690E	DFHLDDM	Exc	Add APE cell subpool failure	1 2	DMDM parameter list SMAD parameter list
LD 690F	DFHLDDM	Exc	Add CSECTL subpool failure	1 2	DMDM parameter list SMAD parameter list
LD 6910	DFHLDDM	Exc	Add LDNUC subpool failure	1 2	DMDM parameter list SMAD parameter list
LD 6911	DFHLDDM	Exc	Add LDENUC subpool failure	1 2	DMDM parameter list SMAD parameter list
LD 6912	DFHLDDM	Exc	Add LDENUCRO subpool failure	1 2	DMDM parameter list SMAD parameter list
LD 6913	DFHLDDM	Exc	Add LDRES subpool failure	1 2	DMDM parameter list SMAD parameter list
LD 6914	DFHLDDM	Exc	Add LDERES subpool failure	1 2	DMDM parameter list SMAD parameter list
LD 6915	DFHLDDM	Exc	Add LDERESRO subpool failure	1 2	DMDM parameter list SMAD parameter list
LD 6916	DFHLDDM	Exc	Add LDPGM subpool failure	1 2	DMDM parameter list SMAD parameter list
LD 6917	DFHLDDM	Exc	Add LDEPGM subpool failure	1 2	DMDM parameter list SMAD parameter list
LD 6918	DFHLDDM	Exc	Add LDEPGMRO subpool failure	1 2	DMDM parameter list SMAD parameter list
LD 6919 LD 691A	DFHLDDM	Exc	Set anchor failure	1 2	DMDM parameter list KEDD parameter list

Table 120. Loader domain trace points (continued)

Point ID	Module	Lvl	Type	Data
LD 691B	DFHLDDM	Exc	Add lock failure	1 DMDM parameter list
LD 691C				2 LMLM parameter list
LD 691D	DFHLDDM	Exc	Unlock failure	1 DMDM parameter list
LD 691E				2 LMLM parameter list
LD 691F	DFHLDDM	Exc	Inquire start failure	1 DMDM parameter list
				2 PAGP parameter list
LD 6920	DFHLDDM	Exc	Add LDRESRO subpool failure	1 DMDM parameter list
				2 SMAD parameter list
LD 6921	DFHLDDM	Exc	Add LDPGMRO subpool failure	1 DMDM parameter list
				2 SMAD parameter list
LD 6922	DFHLDDM	Exc	Add LDNUCRO subpool failure	1 DMDM parameter list
				2 SMAD parameter list
LD 6923	DFHLDDM	Exc	Add CPE cell subpool failure	1 DMDM parameter list
				2 SMAD parameter list
LD 7003	DFHLDDMI	LD 1	Before SVC call	1 Authorized facility parameter list
				2 BLDL parameter list (up to first 200 bytes)
LD 7004	DFHLDDMI	LD 1	After SVC call	1 Authorized facility parameter list
				2 BLDL parameter list (up to first 200 bytes)
LD 7005	DFHLDDMI	LD 2	Before issuing CSVQUERY	1 Program name
LD 7006	DFHLDDMI	LD 2	After issuing CSVQUERY	1 Program name
				2 Return code
LD 7701	DFHLDDMI	Exc	Recovery	1 DMDM parameter list
				2 Kernel error data
LD 7801	DFHLDDMI	Exc	Bad response from SVC call	1 Authorized facility parameter list
				2 BLDL parameter list (up to first 200 bytes)
LD 7802	DFHLDDMI	Exc	Invalid PDB	1 Program name
				2 PDB
LD 7803	DFHLDDMI	Exc	CSVQUERY failure	1 Program name
				2 Return code
LD 7832	DFHLDDMI	Exc	CSVQUERY failed to locate DFHSIP	1 Program name
				2 LDSU parameter list
				3 LDLD parameter list
LD 7903	DFHLDDMI	Exc	Get override parameters error	1 Parameter list
				2 LDSU parameter list
				3 DMDM parameter list

Table 120. Loader domain trace points (continued)

Point ID	Module	Lvl	Type	Data
LD 7905	DFHLDDMI	Exc	APE GETMAIN failure	1 SMGF parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 7906	DFHLDDMI	Exc	Wait phase error	1 DMDM parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 7907	DFHLDDMI	Exc	Local catalog request error	1 CCCC parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 7908	DFHLDDMI	Exc	Global catalog request error	1 CCCC parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 7909	DFHLDDMI	Exc	DFHLDNT exception	1 KEDD parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 790A	DFHLDDMI	Exc	DFHLDST exception	1 KEDD parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 790B	DFHLDDMI	Exc	Library lock failure	1 LMLM parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 790C	DFHLDDMI	Exc	Library unlock failure	1 LMLM parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 790D	DFHLDDMI	Exc	START BROWSE failure	1 Parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 790E	DFHLDDMI	Exc	END BROWSE failure	1 Parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 790F	DFHLDDMI	Exc	CPE GETMAIN failure	1 SMGF parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 7910	DFHLDDMI	Exc	BLDL GETMAIN failure	1 SMGF parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 7912	DFHLDDMI	Exc	CSECTL GETMAIN failure	1 SMGF parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 7913	DFHLDDMI	Exc	Mode change failure	1 DSAT parameter list 2 LDSU parameter list 3 DMDM parameter list

Table 120. Loader domain trace points (continued)

Point ID	Module	Lvl	Type	Data
LD 7914	DFHLDDMI	Exc	INQUIRE START failure	1 DSAT parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 7915	DFHLDDMI	Exc	TYPE PURGE failure	1 DSAT parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 7920	DFHLDDMI	Exc	State lock failure	1 LMLM parameter list
LD 7921				2 LDSU parameter list
LD 7922				3 DMDM parameter list
LD 7923				
LD 7924				
LD 7925				
LD 7926	DFHLDDMI	Exc	State unlock failure	1 LMLM parameter list
LD 7927				2 LDSU parameter list
LD 7928				3 DMDM parameter list
LD 7929				
LD 792A				
LD 792B				
LD 792C				
LD 792D				
LD 792E				
LD 7930				DFHLDDMI
LD 7931	2 LDSU parameter list			
	3 DMDM parameter list			
LD 7932	DFHLDDMI	Exc	Lock call failed for state lock	1 LMLM parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 7933	DFHLDDMI	Exc	Unlock call failed for state lock	1 LMLM parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 7934	DFHLDDMI	Exc	ADD_SUSPEND call failed	1 DSSR parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 7935	DFHLDDMI	Exc	Library unlock failure	1 LMLM parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 7936	DFHLDDMI	Exc	DELETE_SUSPEND call failed	1 DSSR parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 7937	DFHLDDMI	Exc	GETMAIN for LDWE failed	1 SMGF parameter list 2 LDSU parameter list 3 DMDM parameter list
LD 7938	DFHLDDMI	Exc	SUSPEND call failed	1 DSSR parameter list 2 LDSU parameter list 3 DMDM parameter list

Log manager trace points

Table 121. Log manager trace points

Point ID	Module	Lvl	Type	Data
LG 0101	DFHLGDM	LG 1	Entry	1 DMDM parameter list
LG 0102	DFHLGDM	LG 1	Exit	1 DMDM parameter list
LG 0103	DFHLGDM	Exc	Recovery	1 DMDM parameter list 2 Kernel error data
LG 0104	DFHLGDM	Exc	Invalid format number	1 DMDM parameter list
LG 0105	DFHLGDM	Exc	Invalid function	1 DMDM parameter list
LG 0106	DFHLGDM	Exc	Release lock error	1 DMDM parameter list 2 LMLM parameter list
LG 0107	DFHLGDM	Exc	No storage for LGA	1 DMDM parameter list
LG 0108	DFHLGDM	Exc	Register error	1 DMDM parameter list 2 RMCD parameter list
LG 0109	DFHLGDM	Exc	Set gate error	1 DMDM parameter list 2 RMCD parameter list
LG 0110	DFHLGDM	Exc	Invalid exit id	1 DMDM parameter list
LG 0111	DFHLGDM	Exc	Get parameters failed	1 DMDM parameter list
LG 0112	DFHLGDM	Exc	Release LGUOW lock error	1 DMDM parameter list 2 LMLM parameter list
LG 0201	DFHLGGL	LG 1	Entry	1 LGGL parameter list
LG 0202	DFHLGGL	LG 1	Exit	1 LGGL parameter list
LG 0203	DFHLGGL	Exc	Recovery	1 LGGL parameter list 2 Kernel error data
LG 0204	DFHLGGL	Exc	Invalid format number	1 LGGL parameter list
LG 0205	DFHLGGL	Exc	Invalid function	1 LGGL parameter list
LG 0206	DFHLGGL	Exc	Unknown kernel error code	1 LGGL parameter list
LG 0207	DFHLGGL	Exc	Get exc lock error	1 LGGL parameter list 2 LMLM parameter list
LG 0208	DFHLGGL	Exc	Release exc lock error	1 LGGL parameter list 2 LMLM parameter list
LG 0209	DFHLGGL	Exc	Get share lock error	1 LGGL parameter list 2 LMLM parameter list
LG 020A	DFHLGGL	Exc	Release share lock error	1 LGGL parameter list 2 LMLM parameter list

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
LG 020B	DFHLGGL	Exc	Recovery release lock error	1	LGGL parameter list
				2	LMLM parameter list
LG 020C	DFHLGGL	Exc	Add subpool error	1	LGGL parameter list
LG 020D	DFHLGGL	Exc	Unknown log token	1	LGGL parameter list
LG 020E	DFHLGGL	Exc	Bad logtype	1	LGGL parameter list
LG 0211	DFHLGGL	Exc	Get share stream lock error	1	LGGL parameter list
				2	LMLM parameter list
LG 0212	DFHLGGL	Exc	Release share stream lock error	1	LGGL parameter list
				2	LMLM parameter list
LG 0213	DFHLGGL	Exc	Recovery release stream lock error	1	LGGL parameter list
				2	LMLM parameter list
LG 0214	DFHLGGL	Exc	Invalid parameters	1	LGGL parameter list
LG 0215	DFHLGGL	Exc	Glogs BBLX exception	1	LGGL parameter list
				2	BBLX exception code
LG 0216	DFHLGGL	Exc	Glogs SIF exception	1	LGGL parameter list
				2	BBLX storage exception code
LG 0217	DFHLGGL	Exc	Add uw subpool error	1	LGGL parameter list
LG 0218	DFHLGGL	Exc	Storage req purged	1	LGGL parameter list
				2	SMGF parameter list
LG 0219	DFHLGGL	Exc	Start wt browse error	1	LGGL parameter list
				2	RMWT parameter list
LG 0220	DFHLGGL	Exc	Get next wt error	1	LGGL parameter list
				2	RMWT parameter list
LG 022A	DFHLGGL	Exc	End wt browse error	1	LGGL parameter list
				2	RMWT parameter list
LG 022B	DFHLGGL	Exc	MVS write error	1	LGGL parameter list
				2	LGLB parameter list
LG 022C	DFHLGGL	Exc	SMF write error	1	LGGL parameter list
				2	LGLB parameter list
LG 022D	DFHLGGL	Exc	MVS force error	1	LGGL parameter list
				2	LGLB parameter list
LG 022E	DFHLGGL	Exc	SMF force error	1	LGGL parameter list
				2	LGLB parameter list
LG 0231	DFHLGGL	Exc	Get share SMF lock error	1	LGGL parameter list
				2	LMLM parameter list

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
LG 0232	DFHLGGL	Exc	Release share SMF lock error	1	LGGL parameter list
				2	LMLM parameter list
LG 0233	DFHLGGL	Exc	Recovery release SMF lock error	1	LGGL parameter list
				2	LMLM parameter list
LG 0234	DFHLGGL	Exc	Get exc LGUOW lock error	1	LGGL parameter list
				2	LMLM parameter list
LG 0235	DFHLGGL	Exc	Release exc LGUOW lock error	1	LGGL parameter list
				2	LMLM parameter list
LG 0236	DFHLGGL	Exc	Recovery release LGUOW lock error	1	LGGL parameter list
				2	LMLM parameter list
LG 0301	DFHLGJN	LG 1	Entry	1	LGJN parameter list
LG 0302	DFHLGJN	LG 1	Exit	1	LGJN parameter list
LG 0303	DFHLGJN	Exc	Recovery	1	LGJN parameter list
				2	Kernel error data
LG 0304	DFHLGJN	Exc	Invalid format number	1	LGJN parameter list
LG 0305	DFHLGJN	Exc	Invalid function	1	LGJN parameter list
LG 0306	DFHLGJN	Exc	Unknown kernel error code	1	LGJN parameter list
LG 0307	DFHLGJN	Exc	Get exc lock error	1	LGJN parameter list
				2	LMLM parameter list
LG 0308	DFHLGJN	Exc	Release exc lock error	1	LGJN parameter list
				2	LMLM parameter list
LG 0309	DFHLGJN	Exc	Get share lock error	1	LGJN parameter list
				2	LMLM parameter list
LG 030A	DFHLGJN	Exc	Release share lock error	1	LGJN parameter list
				2	LMLM parameter list
LG 030B	DFHLGJN	Exc	Recovery release lock error	1	LGJN parameter list
				2	LMLM parameter list
LG 030C	DFHLGJN	Exc	Add subpool error	1	LGJN parameter list
LG 030D	DFHLGJN	Exc	Journals BBLX exception	1	LGJN parameter list
				2	BBLX exception code
LG 030E	DFHLGJN	Exc	Journals SIF exception	1	LGJN parameter list
				2	BBLX storage exception code
LG 030F	DFHLGJN	Exc	Browses BBLX exception	1	LGJN parameter list
				2	BBLX exception code
LG 0310	DFHLGJN	Exc	Browses SIF exception	1	LGJN parameter list
				2	BBLX storage exception code

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
LG 0311	DFHLGJN	Exc	Get share stream lock error	1	LGJN parameter list
				2	LMLM parameter list
LG 0313	DFHLGJN	Exc	Recovery release stream lock error	1	LGJN parameter list
				2	LMLM parameter list
LG 0314	DFHLGJN	LG 1	Journal defined	1	LGJN parameter list
LG 0315	DFHLGJN	Exc	Stream failed	1	LGJN parameter list
				2	Journal name
LG 0316	DFHLGJN	Exc	Invalid journal status	1	LGJN parameter list
				2	LGJI Journal info data area
LG 0317	DFHLGJN	Exc	LD match error	1	LGJN parameter list
				2	LGLD parameter list
LG 0318	DFHLGJN	Exc	Invalid set status	1	LGJN parameter list
LG 0319	DFHLGJN	Exc	Catalog write error	1	LGJN parameter list
				2	CCCC parameter list
LG 0320	DFHLGJN	Exc	Catalog delete error	1	LGJN parameter list
				2	CCCC parameter list
LG 0321	DFHLGJN	Exc	Journal conn error	1	LGJN parameter list
				2	LGST parameter list
LG 0322	DFHLGJN	Exc	Enqueue error	1	LGJN parameter list
				2	NQED parameter list
LG 0323	DFHLGJN	Exc	Dequeue error	1	LGJN parameter list
				2	NQED parameter list
LG 0324	DFHLGJN	Exc	Add enqpool error	1	LGJN parameter list
				2	NQNQ parameter list
LG 0325	DFHLGJN	LG 1	Journal discarded	1	LGJN parameter list
LG 0326	DFHLGJN	Exc	Get share SMF lock error	1	LGJN parameter list
				2	LMLM parameter list
LG 0327	DFHLGJN	Exc	Get exc SMF lock error	1	LGJN parameter list
				2	LMLM parameter list
LG 0328	DFHLGJN	Exc	Release exc SMF lock error	1	LGJN parameter list
				2	LMLM parameter list
LG 0329	DFHLGJN	Exc	Recovery release SMF lock error	1	LGJN parameter list
				2	LMLM parameter list
LG 032A	DFHLGJN	Exc	SMF conn error	1	LGJN parameter list
				2	LGLB parameter list
LG 0401	DFHLGLD	LG 1	Entry	1	LGLD parameter list

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
LG 0402	DFHLGLD	LG 1	Exit	1	LGLD parameter list
LG 0403	DFHLGLD	Exc	Recovery	1 2	LGLD parameter list Kernel error data
LG 0404	DFHLGLD	Exc	Invalid format number	1	LGLD parameter list
LG 0405	DFHLGLD	Exc	Invalid function	1	LGLD parameter list
LG 0406	DFHLGLD	Exc	Unknown kernel error code	1	LGLD parameter list
LG 0407	DFHLGLD	Exc	Get exc lock error	1 2	LGLD parameter list LMLM parameter list
LG 0408	DFHLGLD	Exc	Release exc lock error	1 2	LGLD parameter list LMLM parameter list
LG 0409	DFHLGLD	Exc	Get share lock error	1 2	LGLD parameter list LMLM parameter list
LG 040A	DFHLGLD	Exc	Release share lock error	1 2	LGLD parameter list LMLM parameter list
LG 040B	DFHLGLD	Exc	Recovery release lock error	1 2	LGLD parameter list LMLM parameter list
LG 040C	DFHLGLD	Exc	Add subpool error	1	LGLD parameter list
LG 040D	DFHLGLD	Exc	Journalmodels BBLX exception	1 2	LGLD parameter list BBLX exception code
LG 040E	DFHLGLD	Exc	Journalmodels SIF exception	1 2	LGLD parameter list BBLX storage exception code
LG 040F	DFHLGLD	Exc	Browses BBLX exception	1 2	LGLD parameter list BBLX exception code
LG 0410	DFHLGLD	Exc	Browses SIF exception	1 2	LGLD parameter list BBLX storage exception code
LG 0411	DFHLGLD	LG 1	Journalmodel installed	1	LGLD parameter list
LG 0412	DFHLGLD	LG 1	Journalmodel replaced	1	LGLD parameter list
LG 0413	DFHLGLD	Exc	Catalog write error	1 2	LGLD parameter list CCCC parameter list
LG 0414	DFHLGLD	Exc	Catalog delete error	1 2	LGLD parameter list CCCC parameter list
LG 0415	DFHLGLD	LG 1	Journalmodel discarded	1	LGLD parameter list
LG 0501	DFHLGST	LG 1	Entry	1	LGST parameter list
LG 0502	DFHLGST	LG 1	Exit	1	LGST parameter list

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 0503	DFHLGST	Exc	Recovery	1 LGST parameter list 2 Kernel error data
LG 0504	DFHLGST	Exc	Invalid format number	1 LGST parameter list
LG 0505	DFHLGST	Exc	Invalid function	1 LGST parameter list
LG 0506	DFHLGST	Exc	Unknown kernel error code	1 LGST parameter list
LG 0507	DFHLGST	Exc	Get exc lock error	1 LGST parameter list 2 LMLM parameter list
LG 0508	DFHLGST	Exc	Release exc lock error	1 LGST parameter list 2 LMLM parameter list
LG 0509	DFHLGST	Exc	Get share lock error	1 LGST parameter list 2 LMLM parameter list
LG 050A	DFHLGST	Exc	Release share lock error	1 LGST parameter list 2 LMLM parameter list
LG 050B	DFHLGST	Exc	Recovery release lock error	1 LGST parameter list 2 LMLM parameter list
LG 050C	DFHLGST	Exc	Add subpool error	1 LGST parameter list
LG 050D	DFHLGST	Exc	Streams BBLX exception	1 LGST parameter list 2 BBLX exception code
LG 050E	DFHLGST	Exc	Streams SIF exception	1 LGST parameter list 2 BBLX storage exception code
LG 050F	DFHLGST	Exc	Add stream lock error	1 LGST parameter list 2 LMLM parameter list
LG 0510	DFHLGST	Exc	Get exc stream lock error	1 LGST parameter list 2 LMLM parameter list
LG 0511	DFHLGST	Exc	Release exc stream lock error	1 LGST parameter list 2 LMLM parameter list
LG 0513	DFHLGST	Exc	Get cond stream lock error	1 LGST parameter list 2 LMLM parameter list
LG 0514	DFHLGST	LG 1	Stream defined	1 LGST parameter list 2 IXGINVNT return code 3 IXGINVNT reason code 4 IXGINVNT parameter list 5 IXGINVNT answer area 6 Log stream name 7 Model log stream name

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 0515	DFHLGST	Exc	Stream define error	1 LGST parameter list 2 IXGINVNT return code 3 IXGINVNT reason code 4 IXGINVNT parameter list 5 IXGINVNT answer area 6 Log stream name 7 Model log stream name
LG 0516	DFHLGST	Exc	Release share stream lock error	1 LGST parameter list 2 LMLM parameter list
LG 0517	DFHLGST	LG 1	Stream define input	1 LGST parameter list 2 IXGINVNT parameter list 3 IXGINVNT answer area 4 Log stream name 5 Model log stream name
LG 0518	DFHLGST	Exc	Enqueue error	1 LGST parameter list 2 NQED parameter list
LG 0519	DFHLGST	Exc	Dequeue error	1 LGST parameter list 2 NQED parameter list
LG 051A	DFHLGST	Exc	Add enqpool error	1 LGST parameter list 2 NQEQ parameter list
LG 0520	DFHLGST	Exc	Add browses subpool error	1 LGST parameter list
LG 0521	DFHLGST	Exc	Browses BBLX exception	1 LGST parameter list 2 BBLX exception code
LG 0522	DFHLGST	Exc	Browses SIF exception	1 LGST parameter list 2 BBLX storage exception code
LG 0523	DFHLGST	Exc	Recovery release stream lock error	1 LGST parameter list 2 LMLM parameter list
LG 0524	DFHLGST	Exc	Connect error	1 LGST parameter list 2 LGLB parameter list
LG 0525	DFHLGST	Exc	Exit rejected define	1 LGST parameter list 2 APEX parameter list
LG 0526	DFHLGST	LG 1	Wait for stream lock	1 LGST parameter list 2 Stream lock token
LG 0527	DFHLGST	Exc	Start wt browse error	1 LGST parameter list 2 RMWT parameter list
LG 0528	DFHLGST	Exc	Get next wt error	1 LGST parameter list 2 RMWT parameter list
LG 0529	DFHLGST	Exc	End wt browse error	1 LGST parameter list 2 RMWT parameter list

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 052A	DFHLGST	Exc	Get exc LGUOW lock error	1 LGST parameter list 2 LMLM parameter list
LG 052B	DFHLGST	Exc	Release exc LGUOW lock error	1 LGST parameter list 2 LMLM parameter list
LG 052C	DFHLGST	Exc	Recovery release LGUOW lock error	1 LGST parameter list 2 LMLM parameter list
LG 0601	DFHLGPA	LG 1	Entry	1 LGPA parameter list
LG 0602	DFHLGPA	LG 1	Exit	1 LGPA parameter list
LG 0603	DFHLGPA	Exc	Recovery	1 LGPA parameter list 2 Kernel error data
LG 0604	DFHLGPA	Exc	Invalid format number	1 LGPA parameter list
LG 0605	DFHLGPA	Exc	Invalid function	1 LGPA parameter list
LG 0701	DFHLGSC	LG 1	Entry	1 STST parameter list
LG 0702	DFHLGSC	LG 1	Exit	1 STST parameter list
LG 0703	DFHLGSC	Exc	Recovery	1 STST parameter list 2 Kernel error data
LG 0704	DFHLGSC	Exc	Invalid format number	1 STST parameter list
LG 0705	DFHLGSC	Exc	Invalid function	1 STST parameter list
LG 0706	DFHLGSC	Exc	Invalid parameters	1 STST parameter list
LG 2001	DFHL2LBG	LG 1	Entry	1 LGLB parameter list
LG 2002	DFHL2LBG	LG 1	Exit	1 LGLB parameter list
LG 2003	DFHL2LBG	Exc	Recovery	1 LGLB parameter list 2 Kernel error data
LG 2004	DFHL2LBG	Exc	Invalid format	1 LGLB parameter list
LG 2005	DFHL2LBG	Exc	Invalid function	1 LGLB parameter list
LG 2006	DFHL2LBG	Exc	Stream lock fail	1 LGLB parameter list
LG 2007	DFHL2LBG	Exc	Stream unlock fail	1 LGLB parameter list
LG 2008	DFHL2LBG	Exc	Unknown kernel error	1 LGLB parameter list
LG 2101	DFHL2CCG	LG 1	Entry	1 LGCC parameter list
LG 2102	DFHL2CCG	LG 1	Exit	1 LGCC parameter list

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 2103	DFHL2CCG	Exc	Recovery	1 LGCC parameter list 2 Kernel error data
LG 2104	DFHL2CCG	Exc	Invalid format	1 LGCC parameter list
LG 2105	DFHL2CCG	Exc	Invalid function	1 LGCC parameter list
LG 2106	DFHL2CCG	Exc	Stream lock fail	1 LGCC parameter list
LG 2107	DFHL2CCG	Exc	Stream unlock fail	1 LGCC parameter list
LG 2108	DFHL2CCG	Exc	Chain lock fail	1 LGCC parameter list
LG 2109	DFHL2CCG	Exc	Chain unlock fail	1 LGCC parameter list
LG 210A	DFHL2CCG	Exc	Unknown kernel error	1 LGCC parameter list
LG 2201	DFHL2WFG	LG 1	Entry	1 LGWF parameter list
LG 2202	DFHL2WFG	LG 1	Exit	1 LGWF parameter list
LG 2203	DFHL2WFG	Exc	Recovery	1 LGWF parameter list 2 Kernel error data
LG 2204	DFHL2WFG	Exc	Invalid format	1 LGWF parameter list
LG 2205	DFHL2WFG	Exc	Invalid function	1 LGWF parameter list
LG 2206	DFHL2WFG	Exc	Stream lock fail	1 LGWF parameter list
LG 2207	DFHL2WFG	Exc	Stream unlock fail	1 LGWF parameter list
LG 2208	DFHL2WFG	Exc	Chain lock fail	1 LGWF parameter list
LG 2209	DFHL2WFG	Exc	Chain unlock fail	1 LGWF parameter list
LG 220A	DFHL2WFG	Exc	Unknown kernel error	1 LGWF parameter list
LG 2301	DFHL2CBG	LG 1	Entry	1 LGCB parameter list
LG 2302	DFHL2CBG	LG 1	Exit	1 LGCB parameter list
LG 2303	DFHL2CBG	Exc	Recovery	1 LGCB parameter list 2 Kernel error data
LG 2304	DFHL2CBG	Exc	Invalid format	1 LGCB parameter list
LG 2305	DFHL2CBG	Exc	Invalid function	1 LGCB parameter list
LG 2306	DFHL2CBG	Exc	Stream lock fail	1 LGCB parameter list
LG 2307	DFHL2CBG	Exc	Stream unlock fail	1 LGCB parameter list
LG 2308	DFHL2CBG	Exc	Chain lock fail	1 LGCB parameter list

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
LG 2309	DFHL2CBG	Exc	Chain unlock fail	1	LGCB parameter list
LG 230A	DFHL2CBG	Exc	Unknown kernel error	1	LGCB parameter list
LG 2401	DFHL2BAG	LG 1	Entry	1	LGBA parameter list
LG 2402	DFHL2BAG	LG 1	Exit	1	LGBA parameter list
LG 2403	DFHL2BAG	Exc	Recovery	1 2	LGBA parameter list Kernel error data
LG 2404	DFHL2BAG	Exc	Invalid format	1	LGBA parameter list
LG 2405	DFHL2BAG	Exc	Invalid function	1	LGBA parameter list
LG 2406	DFHL2BAG	Exc	Stream lock fail	1	LGBA parameter list
LG 2407	DFHL2BAG	Exc	Stream unlock fail	1	LGBA parameter list
LG 2408	DFHL2BAG	Exc	Chain lock fail	1	LGBA parameter list
LG 2409	DFHL2BAG	Exc	Chain unlock fail	1	LGBA parameter list
LG 240A	DFHL2BAG	Exc	Unknown kernel error	1	LGBA parameter list
LG 2501	DFHL2MVG	LG 1	Entry	1	LGMV parameter list
LG 2502	DFHL2MVG	LG 1	Exit	1	LGMV parameter list
LG 2503	DFHL2MVG	Exc	Recovery	1 2	LGMV parameter list Kernel error data
LG 2504	DFHL2MVG	Exc	Invalid format	1	LGMV parameter list
LG 2505	DFHL2MVG	Exc	Invalid function	1	LGMV parameter list
LG 2506	DFHL2MVG	Exc	Stream lock fail	1	LGMV parameter list
LG 2507	DFHL2MVG	Exc	Stream unlock fail	1	LGMV parameter list
LG 2508	DFHL2MVG	Exc	Chain lock fail	1	LGMV parameter list
LG 2509	DFHL2MVG	Exc	Chain unlock fail	1	LGMV parameter list
LG 250A	DFHL2MVG	Exc	Unknown kernel error	1	LGMV parameter list
LG 2601	DFHL2SRG	LG 1	Entry	1	LGSR parameter list
LG 2602	DFHL2SRG	LG 1	Exit	1	LGSR parameter list
LG 2603	DFHL2SRG	Exc	Recovery	1 2	LGSR parameter list Kernel error data
LG 2604	DFHL2SRG	Exc	Invalid format	1	LGSR parameter list

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
LG 2605	DFHL2SRG	Exc	Invalid function	1	LGSR parameter list
LG 2701	DFHL2HB	LG 2	Entry	1	DSAT parameter list
LG 2702	DFHL2HB	LG 2	Exit	1	DSAT parameter list
LG 2703	DFHL2HB	Exc	Recovery	1 2	DSAT parameter list Kernel error data
LG 2704	DFHL2HB	Exc	Invalid format	1	DSAT parameter list
LG 2705	DFHL2HB	Exc	Invalid function	1	DSAT parameter list
LG 2706	DFHL2HB	Exc	Unknown kernel error	1	DSAT parameter list
LG 2707	DFHL2HB	Exc	Heartbeat start error	1	DSAT parameter list
LG 2708	DFHL2HB	Exc	DSIT inq ICV	1 2	Response code Reason code
LG 2709	DFHL2HB	Exc	Heartbeat interrupt	1	None
LG 270A	DFHL2HB	Exc	DS resume error	1	DSAT parameter list
LG 270B	DFHL2HB	Exc	DS suspend error	1	DSAT parameter list
LG 3010	DFHL2CH1	LG 2	Entry	None	
LG 3011	DFHL2CH1	LG 2	Exit	1	Response
LG 3012	DFHL2CH1	Exc	No storage for class data	1	Response
LG 3013	DFHL2CH1	Exc	Recovery entered	1	Kernel error data
LG 3018	DFHL2CH2	LG 2	Entry	None	
LG 3019	DFHL2CH2	LG 2	Exit	1	Response
LG 301A	DFHL2CH2	Exc	Chain add lock failure	1	Response
LG 301B	DFHL2CH2	Exc	Chain unlock failure	1	Response
LG 301C	DFHL2CH2	Exc	Recovery entered	1	Kernel error data
LG 301D	DFHL2CH2	Exc	Domain lock failure	1	Response
LG 301E	DFHL2CH2	Exc	Domain unlock failure	1	Response
LG 301F	DFHL2CH2	Exc	Unknown kernel error	1	Response
LG 3020	DFHL2CH3	LG 2	Entry	None	
LG 3021	DFHL2CH3	LG 2	Exit	1	Response
LG 3022	DFHL2CH3	Exc	Invalid during browse all	1	Response

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
LG 3023	DFHL2CH3	Exc	Recovery entered	1	Kernel error data
				1	Response
				1	Response
				1	Response
LG 3030	DFHL2CH4	LG 2	Entry	None	
LG 3031	DFHL2CH4	LG 2	Exit	1	Response
LG 3032	DFHL2CH4	Exc	Fork to dummy secondary	1	Response
LG 3033	DFHL2CH4	Exc	Invalid record type	1	Response
LG 3034	DFHL2CH4	Exc	Read bad exc	1	Response
LG 3035	DFHL2CH4	Exc	Recovery entered	1	Kernel error data
LG 3036	DFHL2CH4	Exc	Stream lock failure	1	Response
LG 3037	DFHL2CH4	Exc	Stream unlock failure	1	Response
LG 3038	DFHL2CH4	Exc	Chain lock failure	1	Response
LG 3039	DFHL2CH4	Exc	Chain unlock failure	1	Response
LG 303A	DFHL2CH4	Exc	Unknown kernel error	1	Response
LG 3040	DFHL2CH5	LG 2	Entry	None	
LG 3041	DFHL2CH5	LG 2	Exit	1	Response
LG 3042	DFHL2CH5	Exc	Invalid in browse all	1	Response
LG 3043	DFHL2CH5	Exc	Recovery entered	1	Kernel error data
				1	Response
				1	Response
				1	Response
LG 3050	DFHL2CHA	LG 2	Entry	None	
LG 3051	DFHL2CHA	LG 2	Exit	1	Response
LG 3052	DFHL2CHA	Exc	Recovery entered	1	Kernel error data
LG 3053	DFHL2CHA	Exc	Stream lock failure	1	Response
LG 3054	DFHL2CHA	Exc	Stream unlock failure	1	Response
LG 3055	DFHL2CHA	Exc	Unknown kernel error	1	Response
LG 3052	DFHL2CHA	Exc	Invalid in browse all	1	Response
LG 3058	DFHL2CHN	LG 2	Entry	None	
LG 3059	DFHL2CHN	LG 2	Exit	1	Response
LG 305A	DFHL2CHN	Exc	Recovery entered	1	Kernel error data
LG 3052	DFHL2CHN	Exc	Invalid record type	1	Response

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
LG 305C	DFHL2CHN	Exc	Stream lock failure	1	Response
LG 305D	DFHL2CHN	Exc	Stream unlock failure	1	Response
LG 305E	DFHL2CHN	Exc	Unknown kernel error	1	Response
LG 3060	DFHL2CHL	LG 2	Entry	None	
LG 3061	DFHL2CHL	LG 2	Exit	1	Response
LG 3062	DFHL2CHL	Exc	Recovery entered	1	Kernel error data
LG 3068	DFHL2CHH	LG 2	Entry	None	
LG 3069	DFHL2CHH	LG 2	Exit	1	Response
LG 306A	DFHL2CHH	Exc	Recovery entered	1	Kernel error data
LG 3070	DFHL2CHG	LG 2	Entry	None	
LG 3071	DFHL2CHG	LG 2	Exit	1	Response
LG 3072	DFHL2CHG	Exc	Recovery entered	1	Kernel error data
LG 3078	DFHL2CHI	LG 2	Entry	None	
LG 3079	DFHL2CHI	LG 2	Exit	1	Response
LG 307A	DFHL2CHI	Exc	Recovery entered	1	Kernel error data
LG 3080	DFHL2CHR	LG 2	Entry	None	
LG 3081	DFHL2CHR	LG 2	Exit	1	Response
LG 3082	DFHL2CHR	Exc	Recovery entered	1	Kernel error data
LG 3088	DFHL2CHS	LG 2	Entry	None	
LG 3089	DFHL2CHS	LG 2	Exit	1	Response
LG 308A	DFHL2CHS	Exc	Recovery entered	1	Kernel error data
LG 308B	DFHL2CHS	Exc	Domain lock failure	1	Response
LG 308C	DFHL2CHS	Exc	Domain unlock failure	1	Response
LG 308D	DFHL2CHS	Exc	Unknown kernel error	1	Response
LG 3090	DFHL2CHE	LG 2	Entry	None	
LG 3091	DFHL2CHE	LG 2	Exit	1	Response
LG 3092	DFHL2CHE	Exc	Recovery entered	1	Kernel error data
LG 3093	DFHL2CHE	Exc	Stream lock failure	1	Response
LG 3094	DFHL2CHE	Exc	Stream unlock failure	1	Response
LG 3095	DFHL2CHE	Exc	Unknown kernel error	1	Response
LG 3098	DFHL2CHM	LG 2	Entry	None	
LG 3099	DFHL2CHM	LG 2	Exit	1	Response

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 309A	DFHL2CHM	Exc	Recovery entered	1 Kernel error data
LG 309B	DFHL2CHM	Exc	Stream lock failure	1 Response
LG 309C	DFHL2CHM	Exc	Stream unlock failure	1 Response
LG 309D	DFHL2CHM	Exc	Chain lock failure	1 Response
LG 309E	DFHL2CHM	Exc	Chain unlock failure	1 Response
LG 309F	DFHL2CHM	Exc	Unknown kernel error	1 Response
LG 30A0	DFHL2CHM	Exc	Unexpected log record type	1 Response
LG 3311	DFHL2SL1	LG 2	Entry	1 SystemLog response
LG 3312	DFHL2SL1	LG 2	Exit	1 SystemLog response
LG 3313	DFHL2SL1	Exc	Recovery entered	1 Kernel error data
LG 3314	DFHL2SL1	Exc	No storage for class data	1 SystemLog response
LG 3321	DFHL2SLN	LG 2	Entry	1 Journal name 2 BrowseableStream token 3 SystemLog response
LG 3322	DFHL2SLN	LG 2	Exit	1 Journal name 2 BrowseableStream token 3 SystemLog response
LG 3323	DFHL2SLN	Exc	Recovery entered	1 Journal name 2 Kernel error data
LG 3324	DFHL2SLN	Exc	DFHLGJN open failure	1 Journal name 2 BrowseableStream token 3 SystemLog response 4 DFHLGJN parameter list
LG 3325	DFHL2SLN	Exc	System log open disaster	1 Journal name 2 BrowseableStream token 3 SystemLog response
LG 3326	DFHL2SLN	Exc	System log is SMF	1 Journal name 2 BrowseableStream token 3 SystemLog response
LG 3327	DFHL2SLN	Exc	System log open error	1 Journal name 2 BrowseableStream token 3 SystemLog response
LG 3331	DFHL2SLE	LG 2	Entry	1 BrowseableStream token 2 Failure type 3 Operation 4 SystemLog response

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 3332	DFHL2SLE	LG 2	Exit	1 BrowseableStream token 2 Failure type 3 Operation 4 SystemLog response
LG 3333	DFHL2SLE	Exc	Recovery entered	1 BrowseableStream token 2 Failure type 3 Operation 4 Kernel error data
LG 3334	DFHL2SLE	Exc	System log access failure	1 BrowseableStream token 2 Failure type 3 Operation 4 SystemLog response
LG 3335	DFHL2SLE	Exc	Lost data from system log	1 BrowseableStream token 2 Failure type 3 Operation 4 SystemLog response
LG 3336	DFHL2SLE	Exc	Bad system log block size	1 BrowseableStream token 2 Failure type 3 Operation 4 SystemLog response
LG 3337	DFHL2SLE	Exc	System log access disaster	1 BrowseableStream token 2 Failure type 3 Operation 4 SystemLog response
LG 3338	DFHL2SLE	Exc	Bad BrowseableStream token	1 BrowseableStream token 2 Failure type 3 Operation 4 SystemLog response
LG 3339	DFHL2SLE	Exc	DFHDSSR suspend failure	1 BrowseableStream token 2 Failure type 3 Operation 4 SystemLog response 5 DFHDSSR parameter list
LG 333A	DFHL2SLE	Exc	Data not found on log	1 BrowseableStream token 2 Failure type 3 Operation 4 SystemLog response
LG 333B	DFHL2SLE	Exc	Attach CSQC failure	1 BrowseableStream token 2 Failure type 3 Operation 4 SystemLog response 5 DFHXMAT parameter list
LG 333C	DFHL2SLE	Exc	Domain lock failure	1 BrowseableStream token 2 Failure type 3 Operation 4 SystemLog response

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 333D	DFHL2SLE	Exc	Domain unlock failure	1 BrowseableStream token 2 Failure type 3 Operation 4 SystemLog response
LG 333E	DFHL2SLE	Exc	Unknown kernel error	1 BrowseableStream token 2 Failure type 3 Operation 4 SystemLog response
LG 3401	DFHL2SRC	Exc	Invalid Stream object	1 Stream object 2 Stream response 3 Module name
LG 3402	DFHL2SRC	Exc	Bad buffer switch state	1 Stream object 2 Stream response 3 Module name
LG 3403	DFHL2SRC	Exc	Bad current buffer state	1 Stream object 2 Stream response 3 Module name
LG 3404	DFHL2SRC	Exc	Bad previous buffer state	1 Stream object 2 Stream response 3 Module name
LG 3405	DFHL2SRC	Exc	Block restore failure	1 Stream object 2 Stream response 3 Module name
LG 3406	DFHL2SRC	Exc	Block read failure	1 Stream object 2 Stream response 3 Module name
LG 3407	DFHL2SRC	Exc	Block wait write failure	1 Stream object 2 Stream response 3 Module name
LG 3408	DFHL2SRC	Exc	Buffer too small for data	1 Stream object 2 Stream response 3 Module name
LG 3409	DFHL2SRC	LG 2	Buffer switch	1 Stream object 2 Stream response 3 Module name
LG 340A	DFHL2SRC	LG 2	Append	1 Stream object 2 Stream response 3 Module name
LG 340B	DFHL2SRC	LG 2	Append result	1 Stream object 2 Stream response 3 Stream reason 4 Module name

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 340C	DFHL2SRC	LG 2	Force result	1 Stream object 2 Stream response 3 Stream reason 4 Module name
LG 340D	DFHL2SRC	LG 2	Force current buffer	1 Stream object 2 Stream response 3 Module name
LG 340E	DFHL2SRC	LG 2	Force previous buffer	1 Stream object 2 Stream response 3 Module name
LG 340F	DFHL2SRC	LG 2	Read result	1 Stream object 2 Stream response 3 Stream reason 4 Module name
LG 3411	DFHL2SR1	LG 2	Entry	1 Stream response
LG 3412	DFHL2SR1	LG 2	Exit	1 Stream response
LG 3413	DFHL2SR1	Exc	Recovery entered	1 Kernel error data
LG 3414	DFHL2SR1	Exc	No storage for class data	1 Stream response
LG 3421	DFHL2SR2	LG 2	Entry	1 Stream object 2 Log stream (MVS) or journal (SMF) 3 System log indicator 4 MVS or SMF log 5 Stream response 6 Stream reason
LG 3422	DFHL2SR2	LG 2	Exit	1 Stream object 2 Log stream (MVS) or journal (SMF) 3 System log indicator 4 MVS or SMF log 5 Stream response 6 Stream reason
LG 3423	DFHL2SR2	Exc	Recovery entered	1 Stream object 2 Log stream (MVS) or journal (SMF) 3 System log indicator 4 MVS or SMF log 5 Kernel error data
LG 3424	DFHL2SR2	Exc	HardStream connect failure	1 Stream object 2 Log stream (MVS) or journal (SMF) 3 System log indicator 4 MVS or SMF log 5 Stream response 6 Stream reason

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 3425	DFHL2SR2	Exc	Stream unlock failure	1 Stream object 2 Log stream (MVS) or journal (SMF) 3 System log indicator 4 MVS or SMF log 5 Stream response 6 Stream reason
LG 3426	DFHL2SR2	Exc	Unknown kernel error	1 Stream object 2 Log stream (MVS) or journal (SMF) 3 System log indicator 4 MVS or SMF log 5 Stream response 6 Stream reason
LG 3427	DFHL2SR2	Exc	Domain lock failure	1 Stream object 2 Log stream (MVS) or journal (SMF) 3 System log indicator 4 MVS or SMF log 5 Stream response 6 Stream reason
LG 3428	DFHL2SR2	Exc	Domain unlock failure	1 Stream object 2 Log stream (MVS) or journal (SMF) 3 System log indicator 4 MVS or SMF log 5 Stream response 6 Stream reason
LG 3431	DFHL2SR3	LG 2	Entry	1 Stream object 2 Stream response
LG 3432	DFHL2SR3	LG 2	Exit	1 Stream object 2 Stream response
LG 3433	DFHL2SR3	Exc	Recovery entered	1 Stream object 2 Kernel error data
LG 3434	DFHL2SR3	Exc	Domain lock failure	1 Stream object 2 Stream response
LG 3435	DFHL2SR3	Exc	Domain unlock failure	1 Stream object 2 Stream response
LG 3436	DFHL2SR3	Exc	Unknown kernel error	1 Stream object 2 Stream response
LG 3441	DFHL2SR4	LG 2	Entry	1 Stream response
LG 3442	DFHL2SR4	LG 2	Exit	1 Stream response
LG 3443	DFHL2SR4	Exc	Recovery entered	1 Kernel error data

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
LG 3444	DFHL2SR4	Exc	Domain lock failure	1	Stream response
LG 3445	DFHL2SR4	Exc	Domain unlock failure	1	Stream response
LG 3446	DFHL2SR4	Exc	Unknown kernel error	1	Stream response
LG 3447	DFHL2SR4	Exc	Invalid stats buffer	1	Stream response
LG 3451	DFHL2SR5	LG 2	Entry	1	Stream response
LG 3452	DFHL2SR5	LG 2	Exit	1	Stream response
LG 3453	DFHL2SR5	Exc	Recovery entered	1	Kernel error data
LG 3454	DFHL2SR5	Exc	Stream lock failure	1	Stream response
LG 3455	DFHL2SR5	Exc	Unknown kernel error	1	Stream response
LG 3480	DFHL2SRC	LG 2	Collect statistics	1 2 3	Stream object Stream response Module name
LG 3481	DFHL2SRC	LG 2	Reset statistics	1 2 3	Stream object Stream response Module name
LG 3490	DFHL2SRC	LG 2	Start read result	1 2 3 4	Stream object Stream response Stream reason Module name
LG 3491	DFHL2SRC	LG 2	Start read	1 2 3	Stream object Stream response Module name
LG 3492	DFHL2SRC	LG 2	End read	1 2 3	Stream object Stream response Module name
LG 3493	DFHL2SRC	LG 2	Delete all	1 2 3	Stream object Stream response Module name
LG 3494	DFHL2SRC	LG 2	Restore result	1 2 3 4	Stream object Stream response Stream reason Module name
LG 3495	DFHL2SRC	LG 2	Suspend	1 2 3	Stream object Stream response Module name
LG 3496	DFHL2SRC	LG 2	Deferred flush suspend	1 2 3	Stream object Stream response Module name

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 3497	DFHL2SRC	LG 2	Woken from suspend	1 Stream object 2 Stream response 3 Module name
LG 3498	DFHL2SRC	LG 2	Woken from deferred flush	1 Stream object 2 Stream response 3 Module name
LG 3499	DFHL2SRC	LG 2	Start write	1 Stream object 2 Stream response 3 Module name
LG 349A	DFHL2SRC	LG 2	Wait write	1 Stream object 2 Stream response 3 Module name
LG 349B	DFHL2SRC	LG 2	Delete history	1 Stream object 2 Stream response 3 Module name
LG 349C	DFHL2SRC	LG 2	Read	1 Stream object 2 Stream response 3 Module name
LG 349D	DFHL2SRC	LG 2	Restore	1 Stream object 2 Stream response 3 Module name
LG 349E	DFHL2SRC	LG 2	Force	1 Stream object 2 Stream response 3 Module name
LG 349F	DFHL2SRC	Exc	Block start read failure	1 Stream object 2 Stream response 3 Module name
LG 3501	DFHL2BSC	LG 2	Append event	1 BrowseableStream instance 2 BrowseableStream response 3 Module name
LG 3502	DFHL2BSC	LG 2	Append result event	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason 4 Module name
LG 3503	DFHL2BSC	LG 2	Read event	1 BrowseableStream instance 2 BrowseableStream response 3 Module name
LG 3504	DFHL2BSC	LG 2	Read result event	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason 4 Module name

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 3505	DFHL2BSC	LG 2	Restore event	1 BrowseableStream instance 2 BrowseableStream response 3 Module name
LG 3506	DFHL2BSC	LG 2	Restore result event	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason 4 Module name
LG 3507	DFHL2BSC	LG 2	Start browse event	1 BrowseableStream instance 2 BrowseableStream response 3 Module name
LG 3508	DFHL2BSC	LG 2	End browse event	1 BrowseableStream instance 2 BrowseableStream response 3 Module name
LG 3511	DFHL2BS1	LG 2	Entry	1 BrowseableStream response
LG 3512	DFHL2BS1	LG 2	Exit	1 BrowseableStream response
LG 3513	DFHL2BS1	Exc	Recovery	1 Kernel error data
LG 3514	DFHL2BS1	Exc	No storage for class	1 BrowseableStream response
LG 3521	DFHL2BS2	LG 2	Entry	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason
LG 3522	DFHL2BS2	LG 2	Exit	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason
LG 3523	DFHL2BS2	Exc	Recovery	1 BrowseableStream instance 2 Kernel error data
LG 3524	DFHL2BS2	Exc	Domain lock failure	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason
LG 3525	DFHL2BS2	Exc	Domain unlock failure	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason
LG 3526	DFHL2BS2	Exc	Unknown kernel error	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason
LG 3531	DFHL2BS3	LG 2	Entry	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason
LG 3532	DFHL2BS3	LG 2	Exit	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 3533	DFHL2BS3	Exc	Recovery	1 BrowseableStream instance 2 Kernel error data
LG 3534	DFHL2BS3	Exc	Domain lock failure	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason
LG 3535	DFHL2BS3	Exc	Domain unlock failure	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason
LG 3536	DFHL2BS3	Exc	Unknown kernel error	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason
LG 3541	DFHL2BS4	LG 2	Entry	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason
LG 3542	DFHL2BS4	LG 2	Exit	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason
LG 3543	DFHL2BS4	Exc	Recovery	1 BrowseableStream instance 2 Kernel error data
LG 3544	DFHL2BS4	Exc	Stream lock failure	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason
LG 3545	DFHL2BS4	Exc	Unknown kernel error	1 BrowseableStream instance 2 BrowseableStream response 3 BrowseableStream reason
LG 3601	DFHL2BL1	LG 2	Entry	1 Block response
LG 3602	DFHL2BL1	LG 2	Exit	1 Block response
LG 3603	DFHL2BL1	Exc	Recovery entered	1 Block response 2 Kernel error data
LG 3604	DFHL2BL1	Exc	No storage for class data	1 Block response
LG 3605	DFHL2BLC	Exc	SOR record write failure	1 Block response 2 Module name
LG 3607	DFHL2BLC	Exc	No storage for buffer	1 Block response 2 Module name
LG 3608	DFHL2BLC	Exc	No storage for read cursor	1 Block response 2 Module name
LG 3609	DFHL2BLC	Exc	Bad read by block number	1 Block response 2 Module name

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 360A	DFHL2BLC	LG 2	Read	1 Block response 2 Block reason 3 Read Block object 4 Address of read Block 5 Target block object 6 Address of target Block 7 Module name
LG 360B	DFHL2BLC	LG 2	Read result	1 Block response 2 Block reason 3 Read Block object 4 Address of read Block 5 Module name
LG 360C	DFHL2BL2	LG 2	Entry	1 Block response 2 Block reason 3 MVS block id 4 Record index in buffer
LG 360D	DFHL2BL2	LG 2	Exit	1 Block response 2 Block reason 3 MVS block id 4 Record index in buffer
LG 360E	DFHL2BL2	Exc	Recovery entered	1 Block response 2 Kernel error data
LG 360F	DFHL2BL2	Exc	Get current block failure	1 Block response
LG 3610	DFHL2BLC	LG 2	Hold	1 Block response 2 Address of block 3 Use count 4 Module name
LG 3611	DFHL2BLC	LG 2	Release	1 Block response 2 Address of block 3 Use count 4 Module name
LG 3612	DFHL2BLC	LG 2	Unflatten	1 Block response 2 Block reason 3 Block object 4 Address of block 5 Module name
LG 3613	DFHL2BLC	LG 2	Append	1 Data length 2 Block reason 3 Block object 4 Address of block 5 Module name
LG 3614	DFHL2BLC	LG 2	Start read	1 Block response 2 Block reason 3 Block object 4 Address of block 5 Module name

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 3615	DFHL2BLC	LG 2	End read	1 Block response 2 Block reason 3 Block object 4 Address of block 5 Module name
LG 3616	DFHL2BLC	LG 2	Start write	1 Block response 2 Block reason 3 Block object 4 Address of block 5 Module name
LG 3617	DFHL2BLC	LG 2	Wait write	1 Block response 2 Block reason 3 Block object 4 Address of block 5 Module name
LG 3618	DFHL2BLC	LG 2	Wait write result	1 Block response 2 Block reason 3 Block object 4 Address of block 5 Module name
LG 3619	DFHL2BLC	Exc	Block already trimmed	1 Block response 2 Read Blockid 3 Target Blockid
LG 3620	DFHL2BLC	Exc	Lost_log_block	1 Block response 2 Missing Blockid 3 Chain History Point
LG 3700	DFHL2HSC	LG 2	Get current block before	1 HardStream object 2 Module name
LG 3701	DFHL2HSC	LG 2	Get current block after	1 HardStream object 2 Module name
LG 3702	DFHL2HSC	LG 2	Collect HardStream stats	1 HardStream object 2 Module name
LG 3703	DFHL2HSC	LG 2	Reset HardStream stats	1 HardStream object 2 Module name
LG 3710	DFHL2HS2	LG 2	Severe error	1 Kernel error data 2 HardStream object 3 Module global working storage
LG 3711	DFHL2HS2	LG 2	Entry	1 Log stream name 2 System log indicator 3 Log type 4 Journal name

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 3712	DFHL2HS2	LG 2	Exit	<ol style="list-style-type: none"> 1 HardStream response 2 HardStream reason 3 HardStream object
LG 3713	DFHL2HS2	LG 2	IXGCONN before	<ol style="list-style-type: none"> 1 Log stream name 2 HardStream object 3 Module global working storage
LG 3714	DFHL2HS2	LG 2	IXGCONN after	<ol style="list-style-type: none"> 1 MVS logger return code 2 MVS logger reason code 3 MVS logger answer area 4 MVS logger log stream token 5 Maximum log stream size 6 HardStream object
LG 3715	DFHL2HS2	Exc	Connect exception	<ol style="list-style-type: none"> 1 MVS logger return code 2 MVS logger reason code 3 HardStream object 4 Module global working storage 5 MVS logger answer area
LG 3716	DFHL2HS2	LG 2	IXGCONN after more	<ol style="list-style-type: none"> 1 System log flag 2 DASD-only flag 3 Structure name 4 Retention period 5 Auto delete flag
LG 3720	DFHL2HS3	LG 2	Severe error	<ol style="list-style-type: none"> 1 Kernel error data 2 HardStream object 3 Module global working storage
LG 3721	DFHL2HS3	LG 2	Entry	<ol style="list-style-type: none"> 1 HardStream object
LG 3722	DFHL2HS3	LG 2	Exit	<ol style="list-style-type: none"> 1 HardStream response 2 HardStream reason 3 HardStream object
LG 3723	DFHL2HS3	LG 2	IXGCONN DISCONNECT before	<ol style="list-style-type: none"> 1 Log stream name 2 Hardlogger log stream token 3 HardStream object 4 Module global working storage
LG 3724	DFHL2HS3	LG 2	IXGCONN DISCONNECT after	<ol style="list-style-type: none"> 1 MVS logger return code 2 MVS logger reason code 3 MVS logger answer area 4 HardStream object

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 3725	DFHL2HS3	Exc	Disconnect exception	1 MVS logger return code 2 MVS logger reason code 3 HardStream object 4 Module global working storage 5 MVS logger answer area
LG 3730	DFHL2HS4	LG 2	Severe error	1 Kernel error data 2 HardStream object 3 Module global working storage
LG 3731	DFHL2HS4	LG 2	Entry	1 HardStream object
LG 3732	DFHL2HS4	LG 2	Exit	1 HardStream response 2 HardStream reason 3 HardStream object 4 Module global working storage
LG 3733	DFHL2HS4	LG 2	IXGDELET ALL before	1 MVS logger log stream name 2 MVS logger log stream token 3 HardStream object
LG 3734	DFHL2HS4	LG 2	IXGDELET ALL after	1 MVS logger return code 2 MVS logger reason code 3 MVS logger answer area 4 HardStream object
LG 3735	DFHL2HS4	Exc	Delete all exception	1 MVS logger return code 2 MVS logger reason code 3 HardStream object 4 Module global working storage 5 MVS logger answer area
LG 3740	DFHL2HS5	LG 2	Severe error	1 Kernel error data 2 HardStream object 3 Module global working storage
LG 3741	DFHL2HS5	LG 2	Entry	1 HardStream object 2 MVS logger block id
LG 3742	DFHL2HS5	LG 2	Exit	1 HardStream response 2 HardStream reason 3 HardStream object 4 Module global working storage
LG 3743	DFHL2HS5	LG 2	IXGDELET RANGE before	1 MVS logger log stream name 2 MVS logger log stream token 3 MVS logger block id 4 HardStream object

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 3744	DFHL2HS5	LG 2	IXGDELET RANGE after	1 MVS logger return code 2 MVS logger reason code 3 MVS logger answer area 4 HardStream object
LG 3745	DFHL2HS5	Exc	Delete history exception	1 MVS logger return code 2 MVS logger reason code 3 HardStream object 4 Module global working storage 5 MVS logger block id 6 MVS logger answer area
LG 3750	DFHL2HSF	LG 2	Severe error	1 Kernel error data 2 HardStream object 3 Module global working storage
LG 3751	DFHL2HSC	LG 2	Start write before	1 HardStream object 2 Output buffer address 3 Output buffer length 4 Module name
LG 3752	DFHL2HSC	LG 2	Start write after	1 HardStream object 2 Module name
LG 3753	DFHL2HSC	LG 2	Wait write before	1 HardStream object 2 Module name
LG 3754	DFHL2HSC	LG 2	Wait write after	1 HardStream object 2 HardStream response 3 HardStream reason 4 Module name
LG 3755	DFHL2HSF	LG 2	Entry	1 HardStream object 2 Suspend indicator 3 MVS logger return code 4 MVS logger reason code
LG 3756	DFHL2HSF	LG 2	Exit	1 HardStream response 2 HardStream reason 3 HardStream object 4 Module global working storage
LG 3757	DFHL2HSC	LG 2	IXGWRITE before	1 MVS logger log stream name 2 MVS logger log stream token 3 Output buffer length 4 ECB 5 HardStream object 6 Output buffer data 7 Module name

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 3758	DFHL2HSF	LG 2	IXGWRITE before	1 MVS logger log stream name 2 MVS logger log stream token 3 Output buffer length 4 ECB 5 HardStream object 6 Output buffer data 7 Module name
LG 3759	DFHL2HSC	LG 2	IXGWRITE after	1 MVS logger return code 2 MVS logger reason code 3 MVS logger answer area 4 MVS logger block id 5 MVS logger block timestamp 6 HardStream object 7 Module name
LG 375A	DFHL2HSF	LG 2	IXGWRITE after	1 MVS logger return code 2 MVS logger reason code 3 MVS logger answer area 4 MVS logger block id 5 MVS logger block timestamp 6 HardStream object 7 Module name
LG 375B	DFHL2HSF	Exc	IXGWRITE exception	1 MVS logger return code 2 MVS logger reason code 3 HardStream object 4 Module global working storage 5 Output buffer length 6 Output buffer data 7 MVS logger answer area
LG 375C	DFHL2HSC	LG 2	SMF write before	1 SMF function 2 lgafpb block 3 HardStream object 4 Output buffer data 5 Module name
LG 375D	DFHL2HSC	LG 2	SMF write after	1 SMF response 2 lgafpb block 3 HardStream object 4 Module name
LG 375E	DFHL2HSC	Exc	SMF write exception	1 SMF function 2 SMF response 3 lgafpb block 4 HardStream object 5 Output buffer data 6 Module name
LG 3760	DFHL2HS7	LG 2	Severe error	1 Kernel error data 2 HardStream object 3 Module global working storage
LG 3761	DFHL2HS7	LG 2	Entry	1 HardStream object

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 3762	DFHL2HS7	LG 2	Exit	<ul style="list-style-type: none"> 1 HardStream response 2 HardStream reason 3 MVS logger browse token 4 HardStream object 5 Module global working storage
LG 3763	DFHL2HS7	LG 2	IXGBRWSE START before	<ul style="list-style-type: none"> 1 MVS logger log stream name 2 MVS logger log stream token 3 HardStream object
LG 3764	DFHL2HS7	LG 2	IXGBRWSE START after	<ul style="list-style-type: none"> 1 MVS logger return code 2 MVS logger reason code 3 MVS logger browse token 4 MVS logger answer area 5 HardStream object
LG 3765	DFHL2HS7	Exc	Start read block exception	<ul style="list-style-type: none"> 1 MVS logger return code 2 MVS logger reason code 3 HardStream object 4 Module global working storage 5 MVS logger answer area
LG 3770	DFHL2HS8	LG 2	Severe error	<ul style="list-style-type: none"> 1 Kernel error data 2 HardStream object 3 Module global working storage
LG 3771	DFHL2HS8	LG 2	Entry	<ul style="list-style-type: none"> 1 HardStream object 2 MVS logger browse token 3 MVS logger block id 4 Input buffer address 5 Input buffer length
LG 3772	DFHL2HS8	LG 2	Exit	<ul style="list-style-type: none"> 1 HardStream response 2 HardStream reason 3 HardStream object
LG 3773	DFHL2HS8	LG 2	IXGBRWSE READBLOCK before	<ul style="list-style-type: none"> 1 MVS logger log stream name 2 MVS logger log stream token 3 MVS logger browse token 4 MVS logger block id 5 Input buffer address 6 Input buffer length 7 HardStream object
LG 3774	DFHL2HS8	LG 2	IXGBRWSE READBLOCK after	<ul style="list-style-type: none"> 1 MVS logger return code 2 MVS logger reason code 3 MVS logger answer area 4 ECB 5 HardStream object 6 Input buffer data

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 3775	DFHL2HS8	Exc	Read block exception	1 MVS logger return code 2 MVS logger reason code 3 HardStream object 4 Module global working storage 5 MVS logger browse token 6 MVS logger answer area
LG 3780	DFHL2HS9	LG 2	Severe error	1 Kernel error data 2 HardStream object 3 Module global working storage
LG 3781	DFHL2HS9	LG 2	Entry	1 HardStream object 2 MVS logger browse token
LG 3782	DFHL2HS9	LG 2	Exit	1 HardStream response 2 HardStream reason 3 HardStream object 4 Module global working storage
LG 3783	DFHL2HS9	LG 2	IXGBRWSE END before	1 MVS logger log stream name 2 MVS logger log stream token 3 MVS logger browse token 4 HardStream object
LG 3784	DFHL2HS9	LG 2	IXGBRWSE END after	1 MVS logger return code 2 MVS logger reason code 3 MVS logger answer area 4 HardStream object
LG 3785	DFHL2HS9	Exc	End read block exception	1 MVS logger return code 2 MVS logger reason code 3 HardStream object 4 Module global working storage 5 MVS logger browse token 6 MVS logger answer area
LG 3790	DFHL2HS6	LG 2	Severe error	1 Kernel error data 2 HardStream object 3 Module global working storage
LG 3791	DFHL2HS6	LG 2	Entry	1 HardStream object
LG 3792	DFHL2HS6	LG 2	Exit	1 HardStream response 2 HardStream reason 3 MVS logger browse token 4 HardStream object 5 Module global working storage

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 3793	DFHL2HS6	LG 2	IXGBRWSE START before	<ol style="list-style-type: none"> 1 MVS logger log stream name 2 MVS logger log stream token 3 HardStream object
LG 3794	DFHL2HS6	LG 2	IXGBRWSE START after	<ol style="list-style-type: none"> 1 MVS logger return code 2 MVS logger reason code 3 MVS logger browse token 4 MVS logger answer area 5 HardStream object
LG 3795	DFHL2HS6	Exc	Start readcursor exception	<ol style="list-style-type: none"> 1 MVS logger return code 2 MVS logger reason code 3 HardStream object 4 Module global working storage 5 MVS logger answer area
LG 37A0	DFHL2HSG	LG 2	Severe error	<ol style="list-style-type: none"> 1 Kernel error data 2 HardStream object 3 Module global working storage
LG 37A1	DFHL2HSG	LG 2	Entry	<ol style="list-style-type: none"> 1 HardStream object 2 MVS logger browse token
LG 37A2	DFHL2HSG	LG 2	Exit	<ol style="list-style-type: none"> 1 HardStream response 2 HardStream reason 3 MVS logger browse token 4 HardStream object 5 Module global working storage
LG 37A3	DFHL2HSG	LG 2	IXGBRWSE READCURSOR before	<ol style="list-style-type: none"> 1 MVS logger log stream name 2 MVS logger log stream token 3 MVS logger browse token 4 HardStream object
LG 37A4	DFHL2HSG	LG 2	IXGBRWSE READCURSOR after	<ol style="list-style-type: none"> 1 MVS logger return code 2 MVS logger reason code 3 MVS logger answer area 4 MVS logger block id 5 ECB 6 HardStream object 7 Input buffer data
LG 37A5	DFHL2HSG	Exc	Read cursor exception	<ol style="list-style-type: none"> 1 MVS logger return code 2 MVS logger reason code 3 HardStream object 4 Module global working storage 5 MVS logger browse token 6 MVS logger answer area
LG 37B0	DFHL2HSJ	LG 2	Severe error	<ol style="list-style-type: none"> 1 Kernel error data 2 HardStream object 3 Module global working storage

Table 121. Log manager trace points (continued)

Point ID	Module	Lvl	Type	Data
LG 37B1	DFHL2HSJ	LG 2	Entry	1 HardStream object 2 MVS logger browse token
LG 37B2	DFHL2HSJ	LG 2	Exit	1 HardStream response 2 HardStream reason 3 HardStream object 4 Module global working storage
LG 37B3	DFHL2HSJ	LG 2	IXGBRWSE END before	1 MVS logger log stream name 2 MVS logger log stream token 3 MVS logger browse token 4 HardStream object
LG 37B4	DFHL2HSJ	LG 2	IXGBRWSE END after	1 MVS logger return code 2 MVS logger reason code 3 MVS logger answer area 4 HardStream object
LG 37B5	DFHL2HSJ	Exc	End read cursor exception	1 MVS logger return code 2 MVS logger reason code 3 HardStream object 4 Module global working storage 5 MVS logger browse token 6 MVS logger answer area
LG 3801	DFHL2DM	LG 1	Entry	1 DMDM parameter list
LG 3802	DFHL2DM	LG 1	Exit	1 DMDM parameter list
LG 3803	DFHL2DM	Exc	Recovery	1 DMDM parameter list 2 Kernel error data
LG 3804	DFHL2DM	Exc	Invalid format	1 DMDM parameter list
LG 3805	DFHL2DM	Exc	Invalid function	1 DMDM parameter list
LG 3901	DFHL2OFI	LG 1	Entry	1 Response code
LG 3902	DFHL2OFI	LG 1	Exit	1 Response code
LG 3903	DFHL2OFI	Exc	Recovery	1 Response code 2 Kernel error data
LG 3A01	DFHL2VP1	LG 1	Entry	1 Response code
LG 3A02	DFHL2VP1	LG 1	Exit	1 Response code
LG 3A03	DFHL2VP1	Exc	Recovery	1 Response code 2 Kernel error data

Lock manager domain trace points

Table 122. Lock manager domain trace points

Point ID	Module	Lvl	Type	Data
LM 0001	DFHLMMDM	LM 1	Entry	1 DMDM parameter list
LM 0002	DFHLMMDM	LM 1	Exit	1 DMDM parameter list
LM 0003	DFHLMMLM	LM 1	Entry	1 LMLM parameter list 2 Lock name
LM 0004	DFHLMMLM	LM 1	Exit	1 LMLM parameter list 2 Lock name
LM 0005	DFHLMDS	LM 1	Entry	1 DSNT parameter list
LM 0006	DFHLMDS	LM 1	Exit	1 DSNT parameter list
LM 0009	DFHLMIQ	LM 1	Entry	1 LMIQ parameter list
LM 000A	DFHLMIQ	LM 1	Exit	1 LMIQ parameter list
LM 000C	DFHLMMDM	LM 1	Before MVS GETMAIN	1 Amount of storage
LM 000D	DFHLMMLM	LM 1	Before MVS GETMAIN	1 Amount of storage
LM 000E	DFHLMDS	LM 1	Before MVS GETMAIN	1 Amount of storage
LM 000F	DFHLMIQ	LM 1	Before MVS GETMAIN	1 Amount of storage
LM 0010	DFHLMMLM	LM 2	About to do exclusive wait	1 Waiting task 2 Lock owning task 3 Lock name
LM 0011	DFHLMMLM	LM 2	Exclusive wait ended	1 Waiting task 2 Lock owning task 3 Lock name
LM 0014	DFHLMMLM	LM 2	About to do shared wait	1 Waiting task 2 Lock owning task 3 Lock name
LM 0015	DFHLMMLM	LM 2	Shared wait ended	1 Waiting task 2 Lock owning task 3 Lock name
LM 0020	DFHLMMDM	Exc	Recovery	1 DMDM parameter list 2 Kernel error data
LM 0021	DFHLMMLM	Exc	Recovery	1 LMLM parameter list 2 Kernel error data
LM 0022	DFHLMDS	Exc	Recovery	1 DSNT parameter list 2 Kernel error data
LM 0024	DFHLMIQ	Exc	Recovery	1 LMIQ parameter list 2 Kernel error data

Table 122. Lock manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
LM 0032	DFHLMMDM	Exc	Invalid format	1	DMDM parameter list
LM 0033	DFHLMMDM	Exc	Invalid function	1	DMDM parameter list
LM 0034	DFHLMMDM	Exc	Insufficient storage	1	Amount of storage
LM 0035	DFHLMMDM	Exc	Insufficient storage	1	Amount of storage
LM 0036	DFHLMMDM	Exc	Insufficient storage	1	Amount of storage
LM 0037	DFHLMMDM	Exc	Insufficient storage	1	Amount of storage
LM 0040	DFHLMMLM	Exc	Add lock error	1 2	Lock name Internal data
LM 0041	DFHLMMLM	Exc	Invalid format	1	LMLM parameter list
LM 0042	DFHLMMLM	Exc	Invalid function	1	LMLM parameter list
LM 0043	DFHLMMLM	Exc	Insufficient storage	1	Amount of storage
LM 0044	DFHLMMLM	Exc	Insufficient storage	1	Amount of storage
LM 0045	DFHLMMLM	Exc	Invalid lock token	1	LMLM parameter list
LM 0047	DFHLMMLM	Exc	Task requesting lock purged	1	LMLM parameter list
LM 0050	DFHLMDS	Exc	Insufficient storage	1	Amount of storage
LM 0051	DFHLMDS	Exc	Invalid format	1	DSNT parameter list
LM 0070	DFHLMIQ	Exc	Insufficient storage	1	Amount of storage
LM 0071	DFHLMIQ	Exc	Invalid format	1	LMIQ parameter list
LM 0072	DFHLMIQ	Exc	Invalid function	1	LMIQ parameter list
LM 0073	DFHLMIQ	Exc	Invalid browse token	1	LMIQ parameter list
LM 0074	DFHLMIQ	Exc	Invalid browse token	1	LMIQ parameter list

For further possible trace points, see "Trace points in common subroutines" on page 35.

Message domain trace points

Table 123. Message domain trace points

Point ID	Module	Lvl	Type	Data	
ME 0101	DFHMEDM	ME 1	Entry	1	DMDM parameter list
ME 0102	DFHMEDM	ME 1	Exit	1	DMDM parameter list

Table 123. Message domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
ME 0103	DFHMEDM	Exc	Invalid format	1	DMDM parameter list
ME 0104	DFHMEDM	Exc	Invalid function	1	DMDM parameter list
ME 0105	DFHMEDM	Exc	Gate add failed	1	KEDD parameter list
ME 0106	DFHMEDM	Exc	Gate add failed	1	KEDD parameter list
ME 0107	DFHMEDM	Exc	MVS GETMAIN failed	1	GETMAIN return code
ME 0108	DFHMEDM	Exc	SET ANCHOR failed	1	KEDD parameter list
ME 0109	DFHMEDM	Exc	MVS LOAD failed	1 2	LOAD abend code LOAD reason code
ME 0110	DFHMEDM	Exc	Severe error detected	1	DMDM parameter list
ME 0111	DFHMEDM	ME 1	About to do MVS GETMAIN	1	Storage length
ME 0112	DFHMEDM	ME 1	MVS GETMAIN complete	1 2	Storage address GETMAIN return code
ME 0113	DFHMEDM	ME 1	About to do MVS LOAD	1	Module name
ME 0114	DFHMEDM	ME 1	MVS LOAD complete	1	LOAD address
ME 0115	DFHMEDM	Exc	Recovery routine entered	1 2	DMDM parameter list Kernel error data
ME 0116	DFHMEDM	Exc	Add for APUE gate failed	1	Kernel parameter list
ME 0201	DFHMESR	ME 1	Entry	1	MESR parameter list
ME 0202	DFHMESR	ME 1	Exit	1	MESR parameter list
ME 0203	DFHMESR	Exc	Invalid format	1	MESR parameter list
ME 0204	DFHMESR	Exc	Invalid function	1	MESR parameter list
ME 0205	DFHMESR	Exc	Recovery routine entered	1 2	MESR parameter list Kernel error data
ME 0206	DFHMESR	Exc	Invalid APUE function id	1	APUE parameter list
ME 0301	DFHMEME	ME 1	Entry	1	MEME parameter list
ME 0302	DFHMEME	ME 1	Exit	1	MEME parameter list
ME 0303	DFHMEME	Exc	Invalid format	1	MEME parameter list
ME 0304	DFHMEME	Exc	Invalid function	1	MEME parameter list
ME 0305	DFHMEME	Exc	Recovery routine entered	1 2	MEME parameter list Kernel error data

Table 123. Message domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
ME 0307	DFHMEME	Exc	Message module not found	1 2	MEME parameter list Anchor block
ME 0308	DFHMEIN	Exc	Invalid message module	1 2	Message module header MEIN parameter list
ME 0309	DFHMEIN	Exc	Message not found	1 2	MEIN parameter list Message module header
ME 0310	DFHMEIN	Exc	Message set not found	1 2	MEIN parameter list Message module header
ME 0312	DFHMEME	ME 1	About to do MVS GETMAIN	1	Storage length
ME 0313	DFHMEME	ME 1	MVS GETMAIN complete	1 2	Storage address GETMAIN return code
ME 0314	DFHMEME	ME 1	About to do MVS FREEMAIN	1 2	Addr of storage to free Length of storage to free
ME 0315	DFHMEME	ME 1	MVS FREEMAIN complete	1	FREEMAIN return code
ME 0316	DFHMEIN	Exc	Destination missing from message definition	1	Field which should be destination
ME 0317	DFHMEIN	Exc	Invalid message definition component type	1 2 3	Message ptr and length MSG_ID ptr and length Component type and length if present
ME 0318	DFHMEME	Exc	Message too long for WTOR	1 2	Maximum WTOR length Message buffer
ME 0322	DFHMEME	Exc	Invalid CONVERSE destination	1	MEME parameter list
ME 0324	DFHMEME	Exc	Invalid SEND destination	1	MEME parameter list
ME 0328	DFHMEME	Exc	Exception response from transient data call	1 2	Message prefix TDTD parameters
ME 0329	DFHMEME	Exc	First write to transient data queue failed	1 2	Message prefix TDTD parameters
ME 0330	DFHMEME	Exc	Subsequent write to transient data queue fail	1 2	Message prefix TDTD parameters
ME 0332	DFHMEME	Exc	Reply index not specified	1	MEME parameter list
ME 0333	DFHMEME	Exc	Reply buffer not specified	1	MEME parameter list
ME 0334	DFHMEME	Exc	Reply index not specified	1	MEME parameter list
ME 0335	DFHMEME	Exc	Reply buffer not specified	1	MEME parameter list
ME 0336	DFHMEME	Exc	User exit route codes error	1	User exit route codes array

Table 123. Message domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
ME 0337	DFHMEME	Exc	User-exit TD queue names error	1	User EXIT_ID queues array
ME 0340	DFHMEME	Exc	GETMAIN for formatting message failed	1	GETMAIN return code
ME 0341	DFHMEME	Exc	GETMAIN for building message failed	1	GETMAIN return code
ME 0342	DFHMEME	Exc	GETMAIN for user exit failed	1	GETMAIN return code
ME 0343	DFHMEME	Exc	GETMAIN for rebuilding message in English failed	1	GETMAIN return code
ME 0344	DFHMEME	Exc	GETMAIN for SYMREC failed	1	GETMAIN return code
ME 0401	DFHMEBU	ME 2	Entry	1	MEBU parameter list
ME 0402	DFHMEBU	ME 2	Exit	1	MEBU parameter list
ME 0403	DFHMEBU	Exc	Invalid format	1	MEBU parameter list
ME 0404	DFHMEBU	Exc	Invalid function	1	MEBU parameter list
ME 0405	DFHMEBU1	Exc	Invalid element	1 2	Message being built MEBU parameter list
ME 0406	DFHMEBU1	Exc	Invalid template	1 2	Message being built MEBU parameter list
ME 0407	DFHMEBU	Exc	Maximum replies exceeded	1 2	Message being built MEBU parameter list
ME 0408	DFHMEBU1	Exc	Bad insert number ID	1 2	Message being built MEBU parameter list
ME 0409	DFHMEBU1	Exc	Bad insert format	1 2	Message being built MEBU parameter list
ME 0410	DFHMEBU1	Exc	Special insert format	1 2	Message being built MEBU parameter list
ME 0411	DFHMEBU1	Exc	Optional insert not found	1 2	Data found MEBU parameter list
ME 0412	DFHMEBU1	Exc	Specified insert not found	1 2	Data found MEBU parameter list
ME 0413	DFHMEBU1	Exc	Date specification error	1 2	Message being built MEBU parameter list
ME 0414	DFHMEBU1	Exc	Date specification error	1 2	Message being built MEBU parameter list
ME 0415	DFHMEBU1	Exc	Invalid decimal number	1 2	Message being built MEBU parameter list
ME 0416	DFHMEBU1	Exc	Invalid date insert	1 2	Message being built MEBU parameter list

Table 123. Message domain trace points (continued)

Point ID	Module	Lvl	Type	Data
ME 0417	DFHMEBU1	Exc	Invalid time insert	1 Message being built 2 MEBU parameter list
ME 0418	DFHMEBU1	Exc	Invalid optional insert	1 Message being built 2 MEBU parameter list
ME 0419	DFHMEBU1	Exc	Invalid time format specification	1 Message being built 2 MEBU parameter list
ME 0420	DFHMEBU1	Exc	Symptom string overflow	1 Symptom string being built 2 Length of data added 3 Data added
ME 0421	DFHMEBU1	Exc	Invalid symptom string template	1 Symptom string being built 2 Symptom string template
ME 0501	DFHMEIN	ME 2	Entry	1 MEIN parameter list
ME 0502	DFHMEIN	ME 2	Exit	1 MEIN parameter list
ME 0503	DFHMEIN	Exc	Invalid format	1 MEIN parameter list
ME 0504	DFHMEIN	Exc	Invalid function	1 MEIN parameter list
ME 0601	DFHMEWT	ME 2	Entry	1 MEIN parameter list
ME 0602	DFHMEWT	ME 2	Exit	1 MEIN parameter list
ME 0603	DFHMEWT	Exc	Invalid format	1 MEIN parameter list
ME 0604	DFHMEWT	Exc	Invalid function	1 MEIN parameter list
ME 0605	DFHMEWT	Exc	WTOR message too long	1 MEIN parameter list
ME 0606	DFHMEWT	ME 1	Before WTOR SVC call	1 SVC parameter list
ME 0607	DFHMEWT	ME 1	After WTOR SVC call	1 SVC parameter list

For further possible trace points, see "Trace points in common subroutines" on page 35.

Monitoring domain trace points

Table 124. Monitoring domain trace points

Point ID	Module	Lvl	Type	Data
MN 0101	DFHMNDM	MN 1	Entry	1 DMDM parameter list
MN 0102	DFHMNDM	MN 1	Exit	1 DMDM parameter list
MN 0103	DFHMNDM	Exc	Recovery	1 DMDM parameter list 2 Kernel error data
MN 0104	DFHMNDM	Exc	Invalid format	1 DMDM parameter list

Table 124. Monitoring domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
MN 0105	DFHMNDM	Exc	Invalid function	1	DMDM parameter list
MN 0106	DFHMNDM	Exc	Domain already initialized	1 2	DMDM parameter list MN domain global storage area
MN 0107	DFHMNDM	Exc	Catalog READ error	1	CCCC parameter list
MN 0108	DFHMNDM	Exc	Wait phase initialization error	1	DMDM parameter list
MN 0109	DFHMNDM	Exc	Wait phase termination error	1	DMDM parameter list
MN 0110	DFHMNDM	Exc	Add MNSR gate error	1	KEDD parameter list
MN 0111	DFHMNDM	Exc	Add APUE gate error	1	KEDD parameter list
MN 0112	DFHMNDM	Exc	Add STST gate error	1	KEDD parameter list
MN 0113	DFHMNDM	Exc	Add MNMN gate error	1	KEDD parameter list
MN 0114	DFHMNDM	Exc	Delete MNSR gate error	1	KEDD parameter list
MN 0115	DFHMNDM	Exc	Delete APUE gate error	1	KEDD parameter list
MN 0116	DFHMNDM	Exc	Delete STST gate error	1	KEDD parameter list
MN 0117	DFHMNDM	Exc	Delete MNMN gate error	1	KEDD parameter list
MN 0118	DFHMNDM	Exc	Set anchor error	1	KEDD parameter list
MN 0119	DFHMNDM	Exc	Delete program error	1	LDLD parameter list
MN 0120	DFHMNDM	Exc	LM LOCK call failed	1	LMLM parameter list
MN 0121	DFHMNDM	Exc	LM UNLOCK call failed	1	LMLM parameter list
MN 0122	DFHMNDM	Exc	Acquire program failed	1	LDLD parameter list
MN 0123	DFHMNDM	Exc	Define program failed	1	LDLD parameter list
MN 0124	DFHMNDM	Exc	Acquire program failed	1	LDLD parameter list
MN 0125	DFHMNDM	Exc	PA domain call failed	1	PAGP parameter list
MN 0126	DFHMNDM	Exc	Allocate subpool failed	1	SMAD parameter list
MN 0128	DFHMNDM	Exc	Allocate subpool failed	1	SMAD parameter list
MN 0129	DFHMNDM	Exc	GETMAIN request failed	1	SMGF parameter list
MN 0130	DFHMNDM	Exc	GETMAIN request failed	1	SMGF parameter list
MN 0131	DFHMNDM	Exc	GETMAIN request failed	1	SMGF parameter list
MN 0132	DFHMNDM	Exc	GETMAIN request failed	1	SMGF parameter list

Table 124. Monitoring domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
MN 0133	DFHMNDM	Exc	GETMAIN request failed	1	SMGF parameter list
MN 0134	DFHMNDM	Exc	GETMAIN request failed	1	SMGF parameter list
MN 0135	DFHMNDM	Exc	GETMAIN request failed	1	SMGF parameter list
MN 0136	DFHMNDM	Exc	Set kernel error	1	KEGD parameter list
MN 0137	DFHMNDM	Exc	PA INQUIRE START error	1	PAGP parameter list
MN 0138	DFHMNDM	Exc	SMGF Getmain PB Array error	1	SMGF parameter list
MN 0139	DFHMNDM	Exc	TISR Notify error	1	TISR parameter list
MN 0140	DFHMNDM	Exc	TISR Cancel error	1	TISR parameter list
MN 0141	DFHMNDM	Exc	KEDD Add_Gate error for TISR	1	KEDD parameter list
MN 0142	DFHMNDM	Exc	KEDD Delete_Gate error for TISR	1	KEDD parameter list
MN 0143	DFHMNDM	Exc	KEDD Add_Gate error for XMNT	1	KEDD parameter list
MN 0144	DFHMNDM	Exc	KEDD Delete_Gate error for XMNT	1	KEDD parameter list
MN 0145	DFHMNDM	Exc	LMLM Lock error	1	LMLM parameter list
MN 0146	DFHMNDM	Exc	KEDD Add_Gate error for MNXM	1	KEDD parameter list
MN 0147	DFHMNDM	Exc	KEDD Delete_Gate error for MNXM	1	KEDD parameter list
MN 0148	DFHMNDM	Exc	SMGF Getmain Performance record error	1	SMGF parameter list
MN 0201	DFHMNMN	MN 1	Entry	1	MNMN parameter list
MN 0202	DFHMNMN	MN 1	Exit	1	MNMN parameter list
MN 0203	DFHMNMN	Exc	Recovery	1 2	MNMN parameter list Kernel error data
MN 0204	DFHMNMN	Exc	Invalid format	1	MNMN parameter list
MN 0205	DFHMNMN	Exc	Invalid function	1	MNMN parameter list
MN 0206	DFHMNMN	Exc	Set kernel error	1	KEGD parameter list
MN 0207	DFHMNMN	Exc	Read CPU time error	1	KEDS parameter list
MN 0208	DFHMNMN	Exc	Reset CPU time error	1	KEDS parameter list
MN 0209	DFHMNMN	Exc	Invoke user exit error	1	APEX parameter list
MN 0215	DFHMNMN	Exc	Invalid token error	1 2	MNMN parameter list TMA
MN 0216	DFHMNMN	Exc	Point definition error	1	MNMN parameter list

Table 124. Monitoring domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
MN 0217	DFHMNMN	Exc	Point definition error	1	MNMN parameter list
MN 0218	DFHMNMN	Exc	Point definition error	1	MNMN parameter list
MN 0219	DFHMNMN	Exc	Unknown EMP option	1 2	MNMN parameter list EMP option
MN 0220	DFHMNMN	Exc	Clock start error — already running	1 2	MNMN parameter list TMA
MN 0221	DFHMNMN	Exc	Clock stop error — not running	1 2	MNMN parameter list TMA
MN 0222	DFHMNMN	Exc	LM LOCK call failed	1	LMLM parameter list
MN 0223	DFHMNMN	Exc	LM UNLOCK call failed	1	LMLM parameter list
MN 0224	DFHMNMN	Exc	Invalid data	1	MNMN parameter list
MN 0226	DFHMNMN	Exc	Data1 not specified	1 2	MNMN parameter list MCT operation
MN 0227	DFHMNMN	Exc	Data2 not specified	1 2	MNMN parameter list MCT operation
MN 0228	DFHMNMN	Exc	XMIQ Inq_Transaction error	1	XMIQ parameter list
MN 0301	DFHMNSR	MN 1	Entry	1	MNSR parameter list
MN 0302	DFHMNSR	MN 1	Exit	1	MNSR parameter list
MN 0303	DFHMNSR	Exc	Recovery	1 2	MNSR parameter list Kernel error data
MN 0304	DFHMNSR	Exc	Invalid format	1	MNSR parameter list
MN 0305	DFHMNSR	Exc	Invalid function	1	MNSR parameter list
MN 0306	DFHMNSR	Exc	Acquire program failed	1	LDLD parameter list
MN 0307	DFHMNSR	Exc	Acquire program failed	1	LDLD parameter list
MN 0308	DFHMNSR	Exc	Define program failed	1	LDLD parameter list
MN 0309	DFHMNSR	Exc	Delete program error	1	LDLD parameter list
MN 0310	DFHMNSR	Exc	LM LOCK call failed	1	LMLM parameter list
MN 0311	DFHMNSR	Exc	LM UNLOCK call failed	1	LMLM parameter list
MN 0312	DFHMNSR	Exc	Set kernel error	1	KEGD parameter list
MN 0313	DFHMNSR	Exc	KEGD Inq_Kernel error	1	KEGD parameter list
MN 0314	DFHMNSR	Exc	TISR Cancel error	1	TISR parameter list

Table 124. Monitoring domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
MN 0315	DFHMNSR	Exc	TISR Notify error	1	TISR parameter list
MN 0401	DFHMNST	MN 1	Entry	1	STST parameter list
MN 0402	DFHMNST	MN 1	Exit	1	STST parameter list
MN 0403	DFHMNST	Exc	Recovery	1 2	STST parameter list Kernel error data
MN 0404	DFHMNST	Exc	Invalid format	1	STST parameter list
MN 0405	DFHMNST	Exc	Invalid function	1	STST parameter list
MN 0406	DFHMNST	Exc	LM LOCK call failed	1	LMLM parameter list
MN 0407	DFHMNST	Exc	LM UNLOCK call failed	1	LMLM parameter list
MN 0408	DFHMNST	Exc	GETMAIN request failed	1	SMGF parameter list
MN 0409	DFHMNST	Exc	FREEMAIN request failed	1	SMGF parameter list
MN 0410	DFHMNST	Exc	Requested monitoring data unavailable	1	MNMN parameter list
MN 0501	DFHMNSU	MN 1	Entry	1	MNSU parameter list
MN 0502	DFHMNSU	MN 1	Exit	1	MNSU parameter list
MN 0503	DFHMNSU	Exc	Recovery	1 2	MNSU parameter list Kernel error data
MN 0504	DFHMNSU	Exc	Invalid format	1	MNSU parameter list
MN 0505	DFHMNSU	Exc	Invalid function	1	MNSU parameter list
MN 0506	DFHMNSU	Exc	Catalog WRITE error	1	CCCC parameter list
MN 0507	DFHMNSU	MN 1	About to make SVC request	1	Authorized facility parameter block
MN 0508	DFHMNSU	MN 1	Return from SVC request	1	Authorized facility parameter block
MN 0509	DFHMNSU	Exc	SVC call failed	1	Authorized facility parameter block
MN 0510	DFHMNSU	Exc	Invalid PB_Token	1	MNSU parameter list
MN 0511	DFHMNSU	Exc	Already connected to WLM	1	MNSU parameter list
MN 0601	DFHMNUE	MN 1	Entry	1	APUE parameter list
MN 0602	DFHMNUE	MN 1	Exit	1	APUE parameter list
MN 0603	DFHMNUE	Exc	Recovery	1 2	APUE parameter list Kernel error data

Table 124. Monitoring domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
MN 0604	DFHMNUE	Exc	Invalid format	1	APUE parameter list
MN 0605	DFHMNUE	Exc	Invalid function	1	APUE parameter list
MN 0607	DFHMNUE	Exc	LM LOCK call failed	1	LMLM parameter list
MN 0608	DFHMNUE	Exc	LM UNLOCK call failed	1	LMLM parameter list
MN 0701	DFHMNSVC	MN 3	Entry	1	Authorized facility parameter block
MN 0702	DFHMNSVC	MN 3	Exit	1	Authorized facility parameter block
MN 0801	DFHMNTI	MN 1	Entry	1	TISR parameter list
MN 0802	DFHMNTI	MN 1	Exit	1	TISR parameter list
MN 0803	DFHMNTI	Exc	Recovery	1 2	TISR parameter list Kernel error data
MN 0806	DFHMNTI	Exc	LMLM Lock error	1	LMLM parameter list
MN 0807	DFHMNTI	Exc	LMLM Unlock error	1	LMLM parameter list
MN 0808	DFHMNTI	Exc	KEDS Reset_Time error	1	KEDS parameter list
MN 0809	DFHMNTI	Exc	Clock start error	1 2	TISR parameter list Transaction monitoring area
MN 0810	DFHMNTI	Exc	Clock Stop error	1 2	TISR parameter list Transaction monitoring area
MN 0811	DFHMNTI	Exc	APEX Invoke_User_Exit error	1	APEX parameter list
MN 0812	DFHMNTI	Exc	DSAT Change_Mode error	1	DSAT parameter list
MN 0813	DFHMNTI	Exc	DSBR Inq_Task error	1	DSBR parameter list
MN 0814	DFHMNTI	Exc	XMIQ Start_Browse error	1	XMIQ parameter list
MN 0815	DFHMNTI	Exc	XMIQ Get_Next error	1	XMIQ parameter list
MN 0816	DFHMNTI	Exc	XMIQ End_Browse error	1	XMIQ parameter list
MN 0901	DFHMNNT	MN 1	Entry	1	XMNT parameter list
MN 0902	DFHMNNT	MN 1	Exit	1	XMNT parameter list
MN 0903	DFHMNNT	Exc	Recovery	1 2	XMNT parameter list Kernel error data
MN 0904	DFHMNNT	Exc	Invalid format	1	Invalid parameter list
MN 0905	DFHMNNT	Exc	LM Lock call failed	1	LMLM parameter list

Table 124. Monitoring domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
MN 0906	DFHMNNT	Exc	LM Unlock call failed	1	LMLM parameter list
MN 0A01	DFHMNXM	MN 1	Entry	1	MNXM parameter list
MN 0A02	DFHMNXM	MN 1	Exit	1	MNXM parameter list
MN 0A03	DFHMNXM	Exc	Recovery	1 2	MNXM parameter list Kernel error data
MN 0A04	DFHMNXM	Exc	Invalid format	1	MNXM parameter list
MN 0A05	DFHMNXM	Exc	Invalid function	1	MNXM parameter list
MN 0A06	DFHMNXM	Exc	Set kernel error	1	KEGD parameter list
MN 0A08	DFHMNXM	Exc	Reset CPU time error	1	KEDS parameter list
MN 0A09	DFHMNXM	Exc	Invoke user exit error	1	APEX parameter list
MN 0A12	DFHMNXM	Exc	GETMAIN request failed	1	SMGF parameter list
MN 0A13	DFHMNXM	Exc	FREEMAIN request failed	1 2	SMGF parameter list Area to be freed
MN 0A15	DFHMNXM	Exc	Invalid token error	1 2	MNMN parameter list Transaction monitoring area
MN 0A21	DFHMNXM	Exc	Clock stop error—not running	1 2	MNXM parameter list Transaction monitoring area
MN 0A22	DFHMNXM	Exc	LM LOCK call failed	1	LMLM parameter list
MN 0A23	DFHMNXM	Exc	LM UNLOCK call failed	1	LMLM parameter list

Enqueue domain trace points

Table 125. Enqueue domain trace points

Point ID	Module	Lvl	Type	Data	
NQ 0101	NQDM	NQ 1	Entry	1	DMDM parameter list
NQ 0102	NQDM	NQ 1	Exit	1	DMDM parameter list
NQ 0103	NQDM	Exc	Recovery	1 2	DMDM parameter list Kernel error data
NQ 0104	NQDM	Exc	Invalid format	1	Invalid parameter list
NQ 0105	NQDM	Exc	Invalid function	1	DMDM parameter list
NQ 0106	NQDM	Exc	Failure to add general subpool	1 2	DMDM parameter list SMAD parameter list

Table 125. Enqueue domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
NQ 0107	NQDM	Exc	No storage for anchor	1	DMDM parameter list
				2	SMGF parameter list
NQ 0108	NQDM	Exc	LMLM Unlock error	1	DMDM parameter list
				2	LMLM parameter list
NQ 0109	NQDM	Exc	NQ client register failure	1	DMDM parameter list
				2	RMCD parameter list
NQ 010A	NQDM	Exc	Failure to add NQPL subpool	1	DMDM parameter list
				2	SMAD parameter list
NQ 010B	NQDM	Exc	Failure to add NQEA subpool	1	DMDM parameter list
				2	SMAD parameter list
NQ 010C	NQDM	Exc	No storage for statistics buffer	1	DMDM parameter list
				2	SMGF parameter list
NQ 010D	NQDM	Exc	Failure to add NQRN subpool	1	DMDM parameter list
				2	SMAD parameter list
NQ 010E	NQDM	Exc	Failure to create NQRN directory	1	DMDM parameter list
				2	DDDI parameter list
NQ 010F	NQDM	Exc	Failure waiting for global catalog to initialize	1	DMDM parameter list
NQ 0201	NQNQ	NQ 1	Entry	1	NQNQ or RMRO parameter list
				2	NQ work token (RMRO) or Enqueue argument1 (NQNQ)
				3	Enqueue argument2 (NQNQ)
NQ 0202	NQNQ	NQ 1	Exit	1	NQNQ or RMRO parameter list
				2	NQ work token (RMRO only)
NQ 0203	NQNQ	Exc	Recovery	1	NQNQ or RMRO parameter list
				2	Kernel error data
NQ 0204	NQNQ	Exc	Invalid format	1	Invalid parameter list
NQ 0205	NQNQ	Exc	Invalid function	1	NQNQ parameter list
NQ 0206	NQNQ	Exc	Invalid call to DFHNQNQ	1	NQNQ parameter list
NQ 0207	NQNQ	Exc	Invalid call to DFHNQNQ	1	NQNQ parameter list
NQ 0208	NQNQ	Exc	Failure to getmain an NQPL control block	1	NQNQ parameter list
				2	SMGF parameter list
NQ 0209	NQNQ	Exc	Enqueue pool already exists	1	NQNQ parameter list
NQ 020A	NQNQ	Exc	Failure on MVS freemain of an NQEA control block	1	NQNQ or RMRO parameter list
				2	RC from MVS FREEMAIN

Table 125. Enqueue domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
NQ 020B	NQNQ	Exc	RMUW Inquire_unit of work_Id error	1	RMRO parameter list
				2	RMUW parameter list
NQ 020C	NQNQ	Exc	Invalid pool token	1	NQEQ parameter list
				2	Storage addressed by token
NQ 020D	NQNQ	Exc	Deactivate for transaction enqueue	1	NQEQ parameter list
				2	NQEA control block
NQ 020E	NQEQ	Exc	Deactivate for enqueue not owned by caller	1	NQEQ parameter list
NQ 020F	NQEQ	Exc	Deactivate for retained enqueue	1	NQEQ parameter list
				2	NQEA control block
NQ 0210	NQEQ	Exc	Failure to getmain an NQEA control block	1	NQEQ parameter list
				2	SMGF parameter list
NQ 0211	NQEQ	Exc	Failure on MVS getmain for NQEA control block	1	NQEQ parameter list
				2	RC from MVS GETMAIN
NQ 0212	NQEQ	Exc	Enqueue locked error	1	NQEQ parameter list
				2	NQEA control block
NQ 0213	NQEQ	Exc	Enqueue active error	1	NQEQ parameter list
				2	NQEA control block
NQ 0214	NQEQ	Exc	Invalid call to DFHNQEQ	1	NQEQ parameter list
NQ 0215	NQEQ	Exc	RMUW Inquire_unit of work_ error	1	NQEQ parameter list
				2	RMUW parameter list
NQ 0216	NQEQ	Exc	Invalid call to DFHNQEQ	1	NQEQ parameter list
NQ 0217	NQEQ	Exc	Incompatible shunt action	1	RMRO parameter list
				2	NQEA control block
				3	Shunt action
NQ 0301	NQED	NQ 1	Entry	1	NQED parameter list
				2	Enqueue argument1
				3	Enqueue argument2
NQ 0302	NQED	NQ 1	Exit	1	NQED parameter list
NQ 0303	NQED	Exc	Recovery	1	NQED parameter list
				2	Kernel error data
NQ 0304	NQED	Exc	Invalid format	1	Invalid parameter 1
NQ 0305	NQED	Exc	Invalid function	1	NQED parameter list
NQ 0306	NQED	Exc	Failure to getmain an NQEA control block	1	NQED parameter list
				2	SMGF parameter list
NQ 0307	NQED	Exc	Failure on MVS getmain for NQEA control block	1	NQED parameter list
				2	RC from MVS GETMAIN

Table 125. Enqueue domain trace points (continued)

Point ID	Module	Lvl	Type	Data
NQ 0308	NQED	Exc	Failure on MVS freemain of an NQEA control block	1 NQED parameter list 2 RC from MVS FREEMAIN
NQ 0309	NQED	Exc	RMUW Inquire_unit of work_Id error	1 NQED parameter list 2 RMUW parameter list
NQ 030A	NQED	Exc	Internal logic error	1 NQED parameter list 2 NQPL control block 3 NQEA control block
NQ 030B	NQED	Exc	Internal logic error	1 NQED parameter list 2 NQPL control block 3 NQEA control block
NQ 030C	NQED	Exc	Internal logic error	1 NQED parameter list 2 NQPL control block 3 NQEA control block
NQ 030D	NQED	Exc	Dequeue for retained enqueue	1 NQED parameter list 2 NQEA control block
NQ 030E	NQED	Exc	Dequeue for enqueue not owned	1 NQED parameter list 2 NQEA control block (if any)
NQ 030F	NQED	Exc	Invalid pool token	1 NQED parameter list 2 Storage addressed by token
NQ 0310	NQED	Exc	Invalid call to DFHNQED	1 NQED parameter list
NQ 0311	NQED	NQ 1	Entry	1 Resource name 2 Response area
NQ 0312	NQED	NQ 1	Exit	1 Resource name 2 Response area
NQ 0313	NQED	NQ 1	Entry	1 Resource name
NQ 0314	NQED	NQ 1	Exit	1 Resource name 2 Response area
NQ 0401	NQIB	NQ 1	Entry	1 NQIB parameter list
NQ 0402	NQIB	NQ 1	Exit	1 NQIB parameter list
NQ 0403	NQIB	Exc	Recovery	1 NQIB parameter list 2 Kernel error data
NQ 0404	NQIB	Exc	Invalid format	1 Invalid parameter list
NQ 0405	NQIB	Exc	Invalid function	1 NQIB parameter list
NQ 0406	NQIB	Exc	Failure to getmain an NQB control block	1 NQIB parameter list 2 SMGF parameter list
NQ 0407	NQIB	Exc	RMUW Inquire_unit of work error	1 NQIB parameter list 2 RMUW parameter list

Table 125. Enqueue domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
NQ 0408	NQIB	Exc	Invalid browse token	1	NQIB parameter list
				2	Storage addressed by token
NQ 0409	NQIB	Exc	Failure to getmain an NQOX control block	1	NQIB parameter list
				2	SMGF parameter list
NQ 040A	NQIB	Exc	Internal logic error	1	NQIB parameter list
				2	Full NQOX control block
NQ 040B	NQIB	Exc	Failure to getmain an NQWX control block	1	NQIB parameter list
				2	SMGF parameter list
NQ 040C	NQIB	Exc	Internal logic error	1	NQIB parameter list
NQ 040D	NQIB	Exc	Inquire unit of work token error	1	NQIB parameter list
				2	RMUW parameter list
NQ 040E	NQIB	Exc	Invalid stable enqueue browse		
NQ 0501	NQST	NQ 1	Entry	1	STST parameter list
NQ 0502	NQST	NQ 1	Exit	1	STST parameter list
NQ 0503	NQST	Exc	Recovery	1	STST parameter list
				2	Kernel error data
NQ 0504	NQST	Exc	Invalid format	1	Invalid parameter list
NQ 0505	NQST	Exc	Invalid function	1	STST parameter list
NQ 0506	NQST	Exc	Caller's buffer too small	1	STST parameter list
				2	Size of required buffer
NQ 0601	NQRN	NQ 1	Exit	1	NQRN parameter list
NQ 0602	NQRN	NQ 1	Exit	1	NQRN parameter list
NQ 0603	NQRN	Exc	Invalid format	1	NQRN parameter list
NQ 0604	NQRN	Exc	Invalid function	1	NQRN parameter list
NQ 0605	NQRN	Exc	Recovery	1	NQRN parameter list
NQ 0608	NQRN	Exc	ENQMODEL getmain failure	1	NQRN parameter list
				2	SMGF parameter list
NQ FF50	NQIE	NQ 1	Entry	1	NQIE parameter list
NQ FF51	NQIE	NQ 1	Exit	1	NQIE parameter list
NQ FF52	NQIE	Exc	Recovery	1	NQIE parameter list
NQ FF53	NQIE	Exc	Invalid format	1	NQIE parameter list

Table 125. Enqueue domain trace points (continued)

Point ID	Module	Lvl	Type	Data
NQ FF54	NQIE	Exc	Invalid function	1 NQIE parameter list
NQ FF55	NQIQ	Exc	Invalid pool token	1 NQIQ parameter list
NQ FF56	NQIQ	Exc	Invalid enqueue	1 NQIQ parameter list

Parameter manager domain trace points

Table 126. Parameter manager domain trace points

Point ID	Module	Lvl	Type	Data
PA 0101	DFHPAGP	PA 1	Entry	1 PAGP parameter list
PA 0102	DFHPAGP	PA 1	Exit	1 PAGP parameter list
PA 0103	DFHPAGP	PA 2	Before WTOR	1 PAGP parameter list 2 Operator's reply
PA 0104	DFHPAGP	PA 2	After WTOR	1 PAGP parameter list 2 Operator's reply
PA 0111	DFHPAGP	Exc	Invalid PAGP parameter list	1 PAGP parameter list
PA 0112	DFHPAGP	Exc	Invalid format number in parameter list	1 PAGP parameter list
PA 0113	DFHPAGP	Exc	Invalid function	1 PAGP parameter list
PA 0114	DFHPAGP	Exc	Invalid requesting domain	1 PAGP parameter list
PA 0115	DFHPAGP	Exc	Unable to transfer SIT to AP	1 PAGP parameter list 2 APAP parameter list
PA 0116	DFHPAGP	Exc	Recovery	1 PAGP parameter list 2 Kernel error data
PA 0201	DFHPADM	PA 1	Entry	1 DMDM parameter list
PA 0202	DFHPADM	PA 1	Exit	1 DMDM parameter list
PA 0211	DFHPADM	Exc	Invalid format number in parameter list	1 DMDM parameter list
PA 0212	DFHPADM	Exc	Invalid function	1 DMDM parameter list
PA 0213	DFHPADM	Exc	Recovery	1 DMDM parameter list 2 Kernel error data
PA 0401	DFHPASY	PA 1	Entry	1 PASY parameter list
PA 0402	DFHPASY	PA 1	Exit	1 PASY parameter list

Program manager domain trace points

Table 127. Program manager domain trace entries

Point ID	Module	Lvl	Type	Data
PG 0101	DFHPGDM	PG 1	Entry	1 DFHDMDM parameter list
PG 0102	DFHPGDM	PG 1	Exit	1 DFHDMDM parameter list
PG 0103	DFHPGDM	Exc	Recovery	1 DFHDMDM parameter list 2 Kernel error data
PG 0104	DFHPGDM	Exc	Invalid format	1 DFHDMDM parameter list
PG 0105	DFHPGDM	Exc	Invalid function	1 DFHDMDM parameter list
PG 0106	DFHPGDM	Exc	LMLM Unlock error	1 DFHDMDM parameter list 2 DFHLMLM parameter list 2 DFHSMAD parameter list
PG 0108	DFHPGDM	Exc	LDLD DEFINE or ACQUIRE failed	1 DFHDMDM parameter list 2 DFHLDLDD parameter list
PG 0109	DFHPGDM	Exc	LDLD RELEASE failed	1 DFHDMDM parameter list 2 DFHLDLDD parameter list
PG 010A	DFHPGDM	Exc	Getmain failed	1 DFHDMDM parameter list 2 DFHSMGF parameter list
PG 010B	DFHPGDM	Exc	INQUIRE_ACCESS_TOKEN failed	1 DFHDMDM parameter list 2 DFHSMR parameter list
PG 010C	DFHPGDM	Exc	INQUIRE_STORAGE_PROTECT failed	1 DFHDMDM parameter list 2 DFHSMR parameter list
PG 010D	DFHPGDM	Exc	INQUIRE_START failed	1 DFHDMDM parameter list 2 DFHPAGP parameter list
PG 010E	DFHPGDM	Exc	GET_PARAMETERS failed	1 DFHDMDM parameter list 2 DFHPAGP parameter list
PG 010F	DFHPGDM	Exc	WAIT_PHASE failed	1 DFHDMDM parameter list (call to DFHPGDM) 2 DFHDMDM parameter list (call to WAIT_PHASE)
PG 0110	DFHPGDM	Exc	SET_PHASE failed	1 DFHDMDM parameter list (call to DFHPGDM) 2 DFHDMDM parameter list (call to SET_PHASE)
PG 0111	DFHPGDM	Exc	CREATE_DIRECTORY failed	1 DFHDMDM parameter list 2 DFHDDDI parameter list
PG 0112	DFHPGDM	Exc	ADD_GATE failed	1 DFHDMDM parameter list 2 DFHKEDD parameter list

Table 127. Program manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data
PG 0113	DFHPGDM	Exc	INQUIRE_KERNEL failed	1 DFHDMDM parameter list 2 DFHKEGD parameter list
PG 0114	DFHPGDM	Exc	INQ_ISOL_TOKEN failed	1 DFHDMDM parameter list
PG 0201	DFHPGRP	PG 1	Entry	1 DFHPGRP parameter list
PG 0202	DFHPGRP	PG 1	Exit	1 DFHPGRP parameter list
PG 0203	DFHPGRP	Exc	Recovery	1 DFHPGRP parameter list 2 Kernel error data
PG 0204	DFHPGRP	Exc	Invalid format	1 DFHPGRP parameter list
PG 0205	DFHPGRP	Exc	Invalid function	1 DFHPGRP parameter list
PG 0206	DFHPGRP	Exc	DEFINE_PROGRAM failed	1 DFHPGRP parameter list 2 DFHPGDD parameter list
PG 0207	DFHPGRP	Exc	CCCC GET_NEXT failed	1 DFHPGRP parameter list 2 DFHCCCC parameter list
PG 0208	DFHPGRP	Exc	CCCC END_BROWSE failed	1 DFHPGRP parameter list 2 DFHCCCC parameter list
PG 020A	DFHPGRP	Exc	GET_PGLOCK error	1 DFHPGRP parameter list
PG 020B	DFHPGRP	Exc	RECOVERY_RELEASE_PGLOCK error	1 DFHPGRP parameter list
PG 020C	DFHPGRP	Exc	RELEASE_PGLOCK error	1 DFHPGRP parameter list
PG 020D	DFHPGRP	Exc	GETMAIN_PGWE error	1 DFHPGRP parameter list
PG 020E	DFHPGRP	Exc	SUSPEND error	1 DFHPGRP parameter list
PG 020F	DFHPGRP	Exc	LOCATE_PPTE error	1 DFHPGRP parameter list
PG 0300	DFHPGDD	PG 1	Entry	1 DFHPGDD parameter list
PG 0301	DFHPGDD	PG 1	Exit	1 DFHPGDD parameter list
PG 0302	DFHPGDD	Exc	Recovery	1 DFHPGDD parameter list
PG 0303	DFHPGDD	Exc	Invalid function	1 DFHPGDD parameter list
PG 0304	DFHPGDD	Exc	Invalid format	1 DFHPGDD parameter list 2 DFHDDLO parameter list
PG 0305	DFHPGDD	PG 1	Entry	1 DFHPGDD parameter list
PG 0306	DFHPGDD	Exc	Getmain failure	1 DFHPGDD parameter list 2 DFHSMGF parameter list
PG 0307	DFHPGDD	Exc	Define program failure	1 DFHPGDD parameter list 2 DFHLDLD parameter list

Table 127. Program manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
PG 030C	DFHPGDD	Exc	Get pglock error	1	DFHPGDD parameter list
				2	DFHLMMLM parameter list
PG 030D	DFHPGDD	Exc	Recovery release pglock error	1	DFHPGDD parameter list
				2	DFHLMMLM parameter list
PG 030E	DFHPGDD	Exc	Recovery pglock error	1	DFHPGDD parameter list
				2	DFHLMMLM parameter list
PG 030F	DFHPGDD	Exc	Add entry failure	1	DFHPGDD parameter list
				2	DFHDDDI parameter list
PG 0310	DFHPGDD	Exc	Catalog failure	1	DFHPGDD parameter list
				2	DFHDDDI parameter list
PG 0311	DFHPGDD	Exc	Inquire system failure	1	DFHPGDD parameter list
				2	DFHSAIQ parameter list
PG 0312	DFHPGDD	Exc	Getmain PGWE error	1	DFHPGDD parameter list
PG 0313	DFHPGDD	Exc	Suspend error	1	DFHPGDD parameter list
PG 0314	DFHPGDD	Exc	Locate_ppte_error	1	DFHPGDD parameter list
				2	DFHDDLO parameter list
PG 0401	DFHPGAQ	PG 1	Entry	1	DFHPGAQ parameter list
PG 0402	DFHPGAQ	PG 1	Exit	1	DFHPGAQ parameter list
PG 0403	DFHPGAQ	Exc	Recovery	1	DFHPGAQ parameter list
				2	Kernel error data
PG 0404	DFHPGAQ	Exc	Invalid function	1	DFHPGAQ parameter list
PG 0406	DFHPGAQ	Exc	Get pglock error	1	DFHPGAQ parameter list
				2	DFHLMMLM parameter list
PG 0407	DFHPGAQ	Exc	Recovery release pglock error	1	DFHPGAQ parameter list
				2	DFHLMMLM parameter list
PG 0408	DFHPGAQ	Exc	Release pglock error	1	DFHPGAQ parameter list
				2	DFHLMMLM parameter list
PG 0409	DFHPGAQ	Exc	Invalid autoinstall state	1	DFHPGAQ parameter list
PG 040A	DFHPGAQ	Exc	Invalid catalog state	1	DFHPGAQ parameter list
PG 040B	DFHPGAQ	Exc	Invalid autoinstall exit	1	DFHPGAQ parameter list
PG 040C	DFHPGAQ	Exc	Invalid_languages_ available	1	DFHPGAQ parameter list
PG 0500	DFHPGIS	PG 1	Entry	1	DFHPGIS parameter list
PG 0501	DFHPGIS	PG 1	Exit	1	DFHPGIS parameter list

Table 127. Program manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
PG 0502	DFHPGIS	Exc	Recovery	1	DFHPGIS parameter list
PG 0503	DFHPGIS	Exc	Invalid function	1	DFHPGIS parameter list
PG 0504	DFHPGIS	Exc	Invalid format	1 2	DFHPGIS parameter list DFHDDLO parameter list
PG 0506	DFHPGIS	Exc	Inquire program failure	1 2	DFHPGIS parameter list DFHLDDL parameter list
PG 0507	DFHPGIS	Exc	Define program failure	1 2	DFHPGIS parameter list DFHLDDL parameter list
PG 0508	DFHPGIS	Exc	Refresh program failure	1 2	DFHPGIS parameter list DFHLDDL parameter list
PG 0509	DFHPGIS	Exc	Start browse failure	1 2	DFHPGIS parameter list DFHDDBR parameter list
PG 050A	DFHPGIS	Exc	Get next entry failure	1 2	DFHPGIS parameter list DFHDDBR parameter list
PG 050B	DFHPGIS	Exc	End browse failure	1 2	DFHPGIS parameter list DFHDDBR parameter list
PG 050C	DFHPGIS	Exc	Get pglock error	1 2	DFHPGIS parameter list DFHMLM parameter list
PG 050D	DFHPGIS	Exc	Recovery release pglock error	1 2	DFHPGIS parameter list DFHMLM parameter list
PG 050E	DFHPGIS	Exc	Recovery pglock error	1 2	DFHPGIS parameter list DFHMLM parameter list
PG 050F	DFHPGIS	Exc	Getmain failure	1 2	DFHPGIS parameter list DFHCCCC parameter list
PG 0510	DFHPGIS	Exc	Getmain PGWE failure	1 2	DFHPGIS parameter list DFHSMGF parameter list
PG 0511	DFHPGIS	Exc	Suspend error	1 2	DFHPGIS parameter list DFHDSSR parameter list
PG 0512	DFHPGIS	Exc	Locate_ppte_error	1 2	DFHPGIS parameter list DFHDDLO parameter list
PG 0601	DFHPGLD	PG 1	Entry	1	DFHPGLD parameter list
PG 0602	DFHPGLD	PG 1	Exit	1	DFHPGLD parameter list
PG 0603	DFHPGLD	Exc	Recovery	1 2	DFHPGLD parameter list Kernel error data
PG 0604	DFHPGLD	Exc	Invalid function	1	DFHPGLD parameter list
PG 0606	DFHPGLD	Exc	Inquire transaction token error	1	DFHPGLD parameter list

Table 127. Program manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
PG 0607	DFHPGLD	Exc	Inquire transaction token error	1	DFHPGLD parameter list
PG 0608	DFHPGLD	Exc	Inquire transaction token error	1	DFHPGLD parameter list
PG 0609	DFHPGLD	Exc	Security check error	1 2	DFHPGLD parameter list DFHXSRC parameter list
PG 060A	DFHPGLD	Exc	Get pglock error	1 2	DFHPGLD parameter list DFHMLM parameter list
PG 060B	DFHPGLD	Exc	Recovery release pglock error	1 2	DFHPGLD parameter list DFHMLM parameter list
PG 060C	DFHPGLD	Exc	Release pglock error	1 2	DFHPGLD parameter list DFHMLM parameter list
PG 060D	DFHPGLD	Exc	Getmain error	1 2	DFHPGLD parameter list DFHSMGF parameter list
PG 060F	DFHPGLD	Exc	Suspend error	1 2	DFHPGLD parameter list DFHDSSR parameter list
PG 0610	DFHPGLD	Exc	Acquire program error	1 2	DFHPGLD parameter list DFHLDLD parameter list
PG 0611	DFHPGLD	Exc	Release program error	1 2	DFHPGLD parameter list DFHLDLD parameter list
PG 0612	DFHPGLD	Exc	Getmain failure	1 2	DFHPGLD parameter list DFHSMGF parameter list
PG 0613	DFHPGLD	Exc	Define program error	1 2	DFHPGLD parameter list on entry DFHPGLD parameter list on exit
PG 0614	DFHPGLD	Exc	Locate_ppte_error	1 2	DFHPGLD parameter list DFHDDLO parameter list
PG 0700	DFHPGHM	PG 1	Entry	1	DFHPGHM parameter list
PG 0701	DFHPGHM	PG 1	Exit	1	DFHPGHM parameter list
PG 0702	DFHPGHM	Exc	Recovery	1 2	DFHPGHM parameter list Kernel error data
PG 0704	DFHPGHM	Exc	Invalid function	1	DFHPGHM parameter list
PG 0705	DFHPGHM	Exc	Missing parameter	1	DFHPGHM parameter list
PG 0801	DFHPGXM	PG 1	Entry	1	DFHPGXM parameter list
PG 0802	DFHPGXM	PG 1	Exit	1	DFHPGXM parameter list
PG 0803	DFHPGXM	Exc	Recovery	1 2	DFHPGXM parameter list Kernel error data

Table 127. Program manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
PG 0804	DFHPGXM	Exc	Invalid function	1	DFHPGXM parameter list
PG 0806	DFHPGXM	Exc	Get pglock error	1 2	DFHPGXM parameter list DFHLMLM parameter list
PG 0807	DFHPGXM	Exc	Recovery release pglock error	1 2	DFHPGXM parameter list DFHLMLM parameter list
PG 0808	DFHPGXM	Exc	Release pglock error	1 2	DFHPGXM parameter list DFHLMLM parameter list
PG 0809	DFHPGXM	Exc	Release program error	1 2	DFHPGXM parameter list DFHLDLD parameter list
PG 0901	DFHPGPG	PG 1	Entry	1	DFHPGPG parameter list
PG 0902	DFHPGPG	PG 1	Exit	1	DFHPGPG parameter list
PG 0903	DFHPGPG	Exc	Recovery	1 2	DFHPGPG parameter list Kernel error data
PG 0904	DFHPGPG	Exc	Invalid function	1	DFHPGPG parameter list
PG 0909	DFHPGPG	Exc	Inquire transaction token error	1 2	DFHPGPG parameter list DFHXMIQ parameter list
PG 090D	DFHPGPG	Exc	Set terminal error	1 2	DFHPGPG parameter list DFHTFIQ parameter list
PG 0911	DFHPGPG	Exc	Clear labels error	1 2	DFHPGPG parameter list DFHPGHM parameter list
PG 0913	DFHPGPG	Exc	Get pglock error	1 2	DFHPGPG parameter list DFHLMLM parameter list
PG 0914	DFHPGPG	Exc	Recovery release pglock error	1 2	DFHPGPG parameter list DFHLMLM parameter list
PG 0915	DFHPGPG	Exc	Release pglock error	1 2	DFHPGPG parameter list DFHLMLM parameter list
PG 0917	DFHPGPG	Exc	Suspend error	1 2	DFHPGPG parameter list DFHDSSR parameter list
PG 0918	DFHPGPG	Exc	Acquire program error	1 2	DFHPGPG parameter list DFHLDLD parameter list
PG 0919	DFHPGPG	Exc	Getmain PGWE error	1 2	DFHPGPG parameter list DFHSMGF parameter list
PG 091A	DFHPGPG	Exc	Define program error	1 2	DFHPGPG parameter list on entry DFHPGPG parameter list on exit

Table 127. Program manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data
PG 091C	DFHPGPG	Exc	Release program error	1 DFHPGPG parameter list 2 DFHLDLD parameter list
PG 091D	DFHPGPG	Exc	Locate_ppte_error	1 DFHPGPG parameter list 2 DFHDDLO parameter list
PG 0A01	DFHPGLU	PG 1	Entry	1 DFHPGLU parameter list 2 COMMAREA passed to DFHPGLU
PG 0A02	DFHPGLU	PG 1	Exit	1 DFHPGLU parameter list
PG 0A03	DFHPGLU	Exc	Recovery	1 DFHPGLU parameter list 2 Kernel error data
PG 0A04	DFHPGLU	Exc	Invalid function	1 DFHPGLU parameter list
PG 0A06	DFHPGLU	Exc	Inquire transaction token error	1 DFHPGLD parameter list
PG 0A07	DFHPGLU	Exc	Inquire transaction token error	1 DFHPGLD parameter list
PG 0A08	DFHPGLU	Exc	Clear labels error	1 DFHPGLU parameter list 2 DFHPGHM parameter list
PG 0A0D	DFHPGLU	Exc	Get pglock error	1 DFHPGLU parameter list 2 DFHMLM parameter list
PG 0A0E	DFHPGLU	Exc	Recovery release pglock error	1 DFHPGLU parameter list 2 DFHMLM parameter list
PG 0A0F	DFHPGLU	Exc	Release pglock error	1 DFHPGLU parameter list 2 DFHMLM parameter list
PG 0A11	DFHPGLU	Exc	Suspend error	1 DFHPGLU parameter list 2 DFHDSSR parameter list
PG 0A12	DFHPGLU	Exc	Acquire program error	1 DFHPGLU parameter list 2 DFHLDLD parameter list
PG 0A13	DFHPGLU	Exc	Getmain PGWE error	1 DFHPGLU parameter list 2 DFHSMGF parameter list
PG 0A14	DFHPGLU	Exc	Release program error	1 DFHPGLU parameter list 2 DFHLDLD parameter list
PG 0A15	DFHPGLU	Exc	PG level incorrect	1 DFHPGLU parameter list
PG 0A16	DFHPGLU	Exc	Define program error	1 DFHPGLU parameter list on entry 2 DFHPGLU parameter list on exit
PG 0A17	DFHPGLU	Exc	Locate_ppte_error	1 DFHPGLU parameter list 2 DFHDDLO parameter list
PG 0B01	DFHPGLK	PG 1	Entry	1 DFHPGLK parameter list

Table 127. Program manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
PG 0B02	DFHPGLK	PG 1	Exit	1	DFHPGLK parameter list
PG 0B03	DFHPGLK	Exc	Recovery	1 2	DFHPGLK parameter list Kernel error data
PG 0B04	DFHPGLK	Exc	Invalid function	1	DFHPGLK parameter list
PG 0B06	DFHPGLK	Exc	Inquire transaction token error	1	DFHPGLK parameter list
PG 0B07	DFHPGLK	Exc	Inquire transaction token error	1	DFHPGLK parameter list
PG 0B08	DFHPGLK	Exc	PG level incorrect	1	DFHPGLK parameter list
PG 0B09	DFHPGLK	Exc	Clear labels error	1 2	DFHPGLK parameter list DFHPGHM parameter list
PG 0B0C	DFHPGLK	Exc	Get pglock error	1 2	DFHPGLK parameter list DFHMLM parameter list
PG 0B0D	DFHPGLK	Exc	Recovery release pglock error	1 2	DFHPGLK parameter list DFHMLM parameter list
PG 0B0E	DFHPGLK	Exc	Release pglock error	1 2	DFHPGLK parameter list DFHMLM parameter list
PG 0B10	DFHPGLK	Exc	Suspend error	1 2	DFHPGLK parameter list DFHDSR parameter list
PG 0B11	DFHPGLK	Exc	Acquire program error	1 2	DFHPGLK parameter list DFHLDLD parameter list
PG 0B12	DFHPGLK	Exc	Release program error	1 2	DFHPGLK parameter list DFHLDLD parameter list
PG 0B13	DFHPGLK	Exc	Getmain PGWE error	1 2	DFHPGLK parameter list DFHSMGF parameter list
PG 0B14	DFHPGLK	Exc	Define program error	1 2	DFHPGLK parameter list on entry DFHPGLK parameter list on exit
PG 0B15	DFHPGLK	Exc	Locate_ppte_error	1 2	DFHPGLK parameter list DFHDDLO parameter list
PG 0C01	DFHPGEX	PG 1	Entry	1	DFHPGEX parameter list
PG 0C02	DFHPGEX	PG 1	Exit	1	DFHPGEX parameter list
PG 0C03	DFHPGEX	Exc	Recovery	1 2	DFHPGEX parameter list Kernel error data
PG 0C04	DFHPGEX	Exc	Invalid function	1	DFHPGEX parameter list
PG 0C06	DFHPGEX	Exc	Getmain error	1 2	DFHPGEX parameter list DFHSMGF parameter list

Table 127. Program manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data
PG 0C08	DFHPGEX	Exc	Get pglock error	1 DFHPGEX parameter list 2 DFHLMMLM parameter list
PG 0C09	DFHPGEX	Exc	Recovery release pglock error	1 DFHPGEX parameter list 2 DFHLMMLM parameter list
PG 0C10	DFHPGEX	Exc	Define program error	1 DFHPGEX parameter list on entry 2 DFHPGEX parameter list on exit
PG 0C0A	DFHPGEX	Exc	Release pglock error	1 DFHPGEX parameter list 2 DFHLMMLM parameter list
PG 0C0C	DFHPGEX	Exc	Suspend error	1 DFHPGEX parameter list 2 DFHDSSR parameter list
PG 0C0D	DFHPGEX	Exc	Acquire program error	1 DFHPGEX parameter list 2 DFHLDLD parameter list
PG 0C0E	DFHPGEX	Exc	Getmain PGWE error	1 DFHPGEX parameter list 2 DFHSMGF parameter list
PG 0C0F	DFHPGEX	Exc	Release program error	1 DFHPGEX parameter list 2 DFHLDLD parameter list
PG 0C11	DFHPGEX	Exc	Locate_ppte_error	1 DFHPGEX parameter list on entry 2 DFHPDEX parameter list on exit
PG 0E01	DFHPGAI	PG 2	Entry	1 DFHPGAI parameter list
PG 0E02	DFHPGAI	PG 2	Exit	1 DFHPGAI parameter list
PG 0E03	DFHPGAI	Exc	Recovery	1 DFHPGAI parameter list 2 Kernel error data
PG 0E04	DFHPGAI	Exc	Invalid function	1 DFHPGAI parameter list
PG 0E06	DFHPGAI	PG 1	User exit entry	1 None
PG 0E07	DFHPGAI	PG 1	User exit exit	1 None
PG 0E08	DFHPGAI	Exc	Get pglock error	1 DFHPGAI parameter list 2 DFHLMMLM parameter list
PG 0E09	DFHPGAI	Exc	Recovery release pglock error	1 DFHPGAI parameter list 2 DFHLMMLM parameter list
PG 0E0A	DFHPGAI	Exc	Release pglock error	1 DFHPGAI parameter list 2 DFHLMMLM parameter list

Table 127. Program manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
PG 0E0B	DFHPGAI	Exc	GETMAIN pgwe error	1	DFHPGAI parameter list on entry
				2	DFHPGAI parameter list on exit
PG 0E0C	DFHPGAI	Exc	Suspend error	1	DFHPGAI parameter list on entry
				2	DFHPGAI parameter list on exit
PG 0E0D	DFHPGAI	Exc	Inquire_model_error	1	DFHPGAI parameter list
				2	DFHLDLD parameter list
PG 0E0E	DFHPGAI	Exc	Locate_ppte_error	1	DFHPGAI parameter list
				2	DFHDDLO parameter list
PG 0E0F	DFHPGAI	Exc	Define_program_error	1	DFHPGAI parameter list
				2	DFHPGDD parameter list
PG 0E10	DFHPGAI	Exc	Unknown_urm_error	1	DFHPGAI parameter list
				2	DFHPGLU parameter list
PG 0E11	DFHPGAI	Exc	Invalid parameter	1	DFHPGAI parameter list on entry
PG 0F01	DFHPGST	PG 1	Entry	1	DFHSTST parameter list
PG 0F02	DFHPGST	PG 1	Exit	1	DFHSTST parameter list
PG 0F03	DFHPGST	Exc	Recovery	1	DFHSTST parameter list
				2	Kernel error data
PG 0F04	DFHPGST	Exc	Invalid function	1	DFHSTST parameter list
PG 0F06	DFHPGST	Exc	Get pglock error	1	DFHSTST parameter list
				2	DFHMLM parameter list
PG 0F07	DFHPGST	Exc	Recovery release pglock error	1	DFHSTST parameter list
				2	DFHMLM parameter list
PG 0F08	DFHPGST	Exc	Release pglock error	1	DFHSTST parameter list
				2	DFHMLM parameter list
PG 1001	DFHPGUE	PG 1	Entry	1	DFHPGUE parameter list
PG 1002	DFHPGUE	PG 1	Exit	1	DFHPGUE parameter list
PG 1003	DFHPGUE	Exc	Recovery	1	DFHPGUE parameter list
PG 1004	DFHPGUE	Exc	Invalid function	1	DFHPGUE parameter list
PG 1005	DFHPGUE	Exc	Invalid format	1	DFHPGUE parameter list

Table 127. Program manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
PG 1006	DFHPGUE	Exc	Get_pglock_error	1	DFHPGUE parameter list on entry
				2	DFHPGUE parameter list on exit
PG 1007	DFHPGUE	Exc	Recovery release pglock error	1	DFHPGUE parameter list on entry
				2	DFHPGUE parameter list on exit
PG 1008	DFHPGUE	Exc	Release pglock error	1	DFHPGUE parameter list on entry
				2	DFHPGUE parameter list on exit
PG 1101	DFHPGLE	PG 1	Entry	1	DFHPGLE parameter list
PG 1102	DFHPGLE	PG 1	Exit	1	DFHPGLE parameter list
PG 1103	DFHPGLE	Exc	Recovery	1	DFHPGLE parameter list
				2	Kernel error data
PG 1104	DFHPGLE	Exc	Invalid function	1	DFHPGLE parameter list
PG 1108	DFHPGLE	Exc	Inquire access error	1	DFHPGLE parameter list
				2	DFHSMR parameter list
PG 1109	DFHPGLE	Exc	Inquire transaction token error	1	DFHPGLE parameter list
				2	DFHXMIQ parameter list
PG 110D	DFHPGLE	Exc	Set terminal error	1	DFHPGLE parameter list
				2	DFHTFIQ parameter list
PG 1111	DFHPGLE	Exc	Clear labels error	1	DFHPGLE parameter list
				2	DFHPGHM parameter list
PG 1112	DFHPGLE	Exc	Security check error	1	DFHPGLE parameter list
				2	DFHXSRC parameter list
PG 1113	DFHPGLE	Exc	Get pglock error	1	DFHPGLE parameter list
				2	DFHLMLM parameter list
PG 1114	DFHPGLE	Exc	Recovery release pglock error	1	DFHPGLE parameter list
				2	DFHLMLM parameter list
PG 1115	DFHPGLE	Exc	Release pglock error	1	DFHPGLE parameter list
				2	DFHLMLM parameter list
PG 1117	DFHPGLE	Exc	Suspend error	1	DFHPGLE parameter list
				2	DFHDSSR parameter list
PG 1118	DFHPGLE	Exc	Acquire program error	1	DFHPGLE parameter list
				2	DFHLDLD parameter list
PG 1119	DFHPGLE	Exc	Getmain PGWE error	1	DFHPGLE parameter list
				2	DFHSMGF parameter list

Table 127. Program manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data
PG 111C	DFHPGLE	Exc	Release program error	1 DFHPGLE parameter list 2 DFHLDLD parameter list
PG 111D	DFHPGLE	Exc	Define program error	1 DFHPGLE parameter list on entry 2 DFHPGLE parameter list on exit
PG 111E	DFHPGLE	Exc	Locate_ptte_error	1 DFHPGLE parameter list 2 DFHDDLO parameter list
PG 1201	DFHPGRE	PG 1	Entry	1 DFHPGRE parameter list
PG 1202	DFHPGRE	PG 1	Exit	1 DFHPGRE parameter list
PG 1203	DFHPGRE	Exc	Recovery	1 DFHPGRE parameter list 2 Kernel error data
PG 1204	DFHPGRE	Exc	Invalid function	1 DFHPGRE parameter list
PG 1209	DFHPGRE	Exc	Inquire transaction token error	1 DFHPGRE parameter list 2 DFHXMIQ parameter list
PG 120D	DFHPGRE	Exc	Set terminal error	1 DFHPGRE parameter list 2 DFHTFIQ parameter list
PG 120F	DFHPGRE	Exc	Invalid return request	1 DFHPGRE parameter list
PG 1301	DFHPGXE	PG 1	Entry	1 DFHPGXE parameter list
PG 1302	DFHPGXE	PG 1	Exit	1 DFHPGXE parameter list
PG 1303	DFHPGXE	Exc	Recovery	1 DFHPGXE parameter list 2 Kernel error data
PG 1304	DFHPGXE	Exc	Invalid function	1 DFHPGXE parameter list
PG 1308	DFHPGXE	Exc	Inquire access error	1 DFHPGXE parameter list 2 DFHSMSR parameter list
PG 1309	DFHPGXE	Exc	Inquire transaction token error	1 DFHPGXE parameter list 2 DFHXMIQ parameter list
PG 130D	DFHPGXE	Exc	Set terminal error	1 DFHPGXE parameter list 2 DFHTFIQ parameter list
PG 1312	DFHPGXE	Exc	Security check error	1 DFHPGXE parameter list 2 DFHXSRC parameter list
PG 1313	DFHPGXE	Exc	Get pglock error	1 DFHPGXE parameter list 2 DFHMLM parameter list
PG 1314	DFHPGXE	Exc	Recovery release pglock error	1 DFHPGXE parameter list 2 DFHMLM parameter list

Table 127. Program manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
PG 1315	DFHPGXE	Exc	Release pglock error	1	DFHPGXE parameter list
				2	DFHLMMLM parameter list
PG 1317	DFHPGXE	Exc	Suspend error	1	DFHPGXE parameter list
				2	DFHDSSR parameter list
PG 1318	DFHPGXE	Exc	Acquire program error	1	DFHPGXE parameter list
				2	DFHLDLD parameter list
PG 1319	DFHPGXE	Exc	Getmain PGWE error	1	DFHPGXE parameter list
				2	DFHSMGF parameter list
PG 131C	DFHPGXE	Exc	Release program error	1	DFHPGXE parameter list
				2	DFHLDLD parameter list
PG 131D	DFHPGXE	Exc	Define program error	1	DFHPGXE parameter list on entry
				2	DFHPGXE parameter list on exit
PG 131E	DFHPGXE	Exc	Locate_ppte_error	1	DFHPGXE parameter list
				2	DFHDDLO parameter list

Recovery Manager

Table 128. Recovery manager trace points

Point ID	Module	Lvl	Type	Data	
RM 0101	DFHRMDM	RM 1	Entry	1 DMDM parameter list	
RM 0102	DFHRMDM	RM 1	Exit	1 DMDM parameter list	
RM 0103	DFHRMDM	Exc	Recovery	1	DMDM parameter list
				2	Kernel error data
RM 0104	DFHRMDM	Exc	Invalid format	1 DMDM parameter list	
RM 0105	DFHRMDM	Exc	Invalid function	1 DMDM parameter list	
RM 0106	DFHRMDM	Exc	Unlock error	1 DMDM parameter list	
RM 0106	DFHRMDM	Exc	Unlock error	1 DMDM parameter list	
RM 0107	DFHRMDM	Exc	Getmain failed for anchor block	1 DMDM parameter list	
RM 0108	DFHRMDM	Exc	Unknown start type specified	1 DMDM parameter list	
RM 0109	DFHRMDM	Exc	No catalog record	1 DMDM parameter list	
RM 010A	DFHRMDM	RM 2	Next auto start catalog record found	1 Start parameter	
RM 010B	DFHRMDM	RM 2	Next auto start catalog record missing	1 Start parameter	
RM 010C	DFHRMDM	RM 2	Next auto start catalog record incorrect	1 Start parameter	

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data
RM 010D	DFHRMDM	RM 2	Next auto start catalog record invalid	1 Start parameter
RM 010E	DFHRMDM	Exc	Next start catalog record is NORESTART	1 DMDM parameter list
RM 010F	DFHRMDM	Exc	AUTODIAG override termination	1 DMDM parameter list
RM 0111	DFHRMCD1	RM 2	Entry	1 Response code
RM 0112	DFHRMCD1	RM 2	Exit	1 Response code
RM 0113	DFHRMCD1	Exc	Recovery	1 Kernel error data
RM 0114	DFHRMCD1	Exc	Getmain failed	1 Response code
RM 0119	DFHRMCD2	RM 2	Entry	1 Response code
RM 011A	DFHRMCD2	RM 2	Exit	1 Response code
RM 011B	DFHRMCD1	Exc	Recovery	1 Kernel error data
RM 0121	DFHRMCD	RM 1	Entry	1 RMCD parameter list
RM 0122	DFHRMCD	RM 1	Exit	1 RMCD parameter list
RM 0123	DFHRMCD	Exc	Recovery	1 RMCD parameter list 2 Kernel error data
RM 0124	DFHRMCD	Exc	Invalid format	1 RMCD parameter list
RM 0125	DFHRMCD	Exc	Invalid function	1 RMCD parameter list
RM 0126	DFHRMCD	RM 1	Call client	1 Client name 2 Local UOW id
RM 0127	DFHRMCD	Exc	Client directory not recovered	1 RMCD parameter list
RM 0128	DFHRMCD	Exc	Client directory not recovered	1 RMCD parameter list
RM 0130	DFHRMCI2	RM 2	Entry	1 Client name 2 Domain id 3 Domain gate id 4 Response code
RM 0131	DFHRMCI2	RM 2	Exit	1 Client name 2 Domain id 3 Domain gate id 4 Response code
RM 0132	DFHRMCI2	Exc	Recovery	1 Kernel error data
RM 0133	DFHRMCI2	Exc	Lock error	1 Client name 2 Domain id 3 Domain gate id 4 Response code

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data
RM 0134	DFHRMCI2	Exc	Unlock error	1 Client name 2 Domain id 3 Domain gate id 4 Response code
RM 0135	DFHRMCI2	Exc	Unknown Kernel error code	1 Client name 2 Domain id 3 Domain gate id 4 Response code
RM 0138	DFHRMCI3	RM 2	Entry	1 Client name 2 Response code
RM 0139	DFHRMCI3	RM 2	Exit	1 Client name 2 Response code
RM 013A	DFHRMCI3	Exc	Recovery	1 Kernel error data
RM 013B	DFHRMCI3	Exc	Lock error	1 Client name 2 Response code
RM 013C	DFHRMCI3	Exc	Unlock error	1 Client name 2 Response code
RM 013D	DFHRMCI3	Exc	Unknown Kernel error code	1 Client name 2 Response code
RM 0140	DFHRMCI4	RM 2	Entry	1 Client name 2 RMDE parameter list 3 Response code
RM 0141	DFHRMCI4	RM 2	Exit	1 Client name 2 RMDE parameter list 3 Response code
RM 0142	DFHRMCI4	Exc	Recovery	1 Kernel error data
RM 0143	DFHRMCI4	Exc	Lock error	1 Client name 2 RMDE parameter list 3 Response code
RM 0144	DFHRMCI4	Exc	Unlock error	1 Client name 2 RMDE parameter list 3 Response code
RM 0145	DFHRMCI4	Exc	Unknown Kernel error code	1 Client name 2 RMDE parameter list 3 Response code
RM 0161	DFHRMNM	RM 1	Entry	1 RMNM parameter list 2 Log name 3 Remote access id
RM 0162	DFHRMNM	RM 1	Exit	1 RMNM parameter list 2 Log name 3 Remote access id

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data
RM 0163	DFHRMNM	Exc	Recovery	1 RMNM parameter list 2 Kernel error data
RM 0164	DFHRMNM	Exc	Invalid format	1 RMNM parameter list 2 Log name 3 Remote access id
RM 0165	DFHRMNM	Exc	Invalid function	1 RMNM parameter list 2 Log name 3 Remote access id
RM 0166	DFHRMNM1	RM 1	Entry	1 Response code
RM 0167	DFHRMNM1	RM 1	Exit	1 Response code
RM 0168	DFHRMNM1	Exc	Recovery	1 Response code
RM 0169	DFHRMNM1	Exc	Getmain failed	1 RMNM parameter list 2 Log name 3 Remote access id
RM 016A	DFHRMNS1	RM 1	Entry	1 Response code
RM 016B	DFHRMNS1	RM 1	Exit	1 Response code
RM 016C	DFHRMNS1	Exc	Recovery	1 Response code
RM 016D	DFHRMNS1	Exc	Getmain failed	1 Response code
RM 0171	DFHRMNS2	RM 1	Entry	1 Response code 2 Client name
RM 0172	DFHRMNS2	RM 1	Exit	1 Response code
RM 0173	DFHRMNS1	Exc	Recovery	1 Response code
RM 0201	DFHRMUW	RM 1	Entry	1 RMUW parameter list 2 Local UOW id
RM 0202	DFHRMUW	RM 1	Exit	1 RMUW parameter list
RM 0203	DFHRMCI4	Exc	Recovery	1 RMUW parameter list 2 Kernel error data
RM 0204	DFHRMUW	Exc	Invalid format	1 RMUW parameter list
RM 0205	DFHRMUW	Exc	Invalid function	1 RMUW parameter list
RM 0206	DFHRMUW	Exc	Lock error	1 RMUW parameter list
RM 0207	DFHRMUW	Exc	Unlock error	1 RMUW parameter list
RM 0208	DFHRMUW	Exc	Unknown Kernel error code	1 RMUW parameter list
RM 0209	DFHRMUC	RM 1	Remote UOW creation	1 Remote UOW id

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
RM 020A	DFHRMUW DFHRMUO	RM 1	Increment remote UOW id	1	Remote UOW id
RM 020B	DFHRMUO	Exc	Perform commit failure	1	RMUW parameter list
RM 020C	DFHRMUW	Exc	Perform commit error	1	RMUW parameter list
RM 0211	DFHRMUW1	RM 2	Entry	1	Response code
RM 0212	DFHRMUW1	RM 2	Exit	1	Response code
RM 0213	DFHRMUW1	Exc	Recovery	1 1	Response code Kernel error data
RM 0219	DFHRMUW2	RM 2	Entry	1	Response code
RM 021A	DFHRMUW2	RM 2	Exit	1	Response code
RM 021B	DFHRMUW2	Exc	Recovery	1 2	Response code Kernel error data
RM 021C	DFHRMUW2	Exc	Lock error	1	Response code
RM 021D	DFHRMUW2	Exc	Unlock error	1	Response code
RM 021E	DFHRMUW2	Exc	Unknown Kernel error code	1	Response code
RM 0221	DFHRMUWU	RM 2	Entry	1	Response code
RM 0222	DFHRMUWU	RM 2	Exit	1	Response code
RM 0223	DFHRMUWU	Exc	Recovery	1 2	Response code Kernel error data
RM 0224	DFHRMUWU	Exc	Lock error	1	Response code
RM 0225	DFHRMUWU	Exc	Unlock error	1	Response code
RM 0226	DFHRMUWU	Exc	Unknown Kernel error code	1	Response code
RM 022A	DFHRMUWL	RM 2	Entry	1	Response code
RM 022B	DFHRMUWL	RM 2	Exit	1	Response code
RM 022C	DFHRMUWL	Exc	Recovery	1 2	Response code Kernel error data
RM 022D	DFHRMUWL	Exc	Lock error	1	Response code
RM 022E	DFHRMUWL	Exc	Unlock error	1	Response code
RM 022F	DFHRMUWL	Exc	Unknown Kernel error code	1	Response code
RM 0231	DFHRMRO	RM 1	Entry	1	RMRE or RMKD parameter list

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data
RM 0232	DFHRMRO	RM 1	Exit	1 RMRE or RMKD parameter list
RM 0233	DFHRMRO	Exc	Recovery	1 RMRE or RMKD parameter list 2 Kernel error data
RM 0234	DFHRMRO	Exc	Invalid format	1 RMRE or RMKD parameter list
RM 0235	DFHRMRO	Exc	Invalid function	1 RMRE or RMKD parameter list
RM 0236	DFHRMRO	Exc	Lock error	1 RMRE or RMKD parameter list
RM 0237	DFHRMRO	Exc	Unlock error	1 RMRE or RMKD parameter list
RM 0238	DFHRMRO	Exc	Unknown Kernel error code	1 RMRE or RMKD parameter list
RM 0241	DFHRMRO1	RM 2	Entry	1 Response code
RM 0242	DFHRMRO1	RM 2	Exit	1 Response code
RM 0243	DFHRMRO1	Exc	Recovery	1 Response code 2 Kernel error data
RM 0251	DFHRMROO	RM 2	Entry	1 Response code
RM 0252	DFHRMROO	RM 2	Exit	1 Response code
RM 0253	DFHRMROO	Exc	Recovery	1 Response code 2 Kernel error data
RM 0254	DFHRMROO	Exc	Lock error	1 Response code
RM 0255	DFHRMROO	Exc	Unlock error	1 Response code
RM 0256	DFHRMROO	Exc	Unknown Kernel error code	1 Response code
RM 0271	DFHRMOFI	RM 2	Entry	1 Response code
RM 0272	DFHRMOFI	RM 2	Exit	1 Response code
RM 0273	DFHRMOFI	Exc	Recovery	1 Response code 2 Kernel error data
RM 0281	DFHRMVP1	RM 2	Entry	1 Response code
RM 0282	DFHRMVP1	RM 2	Exit	1 Response code
RM 0283	DFHRMVP1	Exc	Recovery	1 Response code 2 Kernel error data

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
RM 0291	DFHRMUWW	RM 2	Entry	1	Response code
RM 0292	DFHRMUWW	RM 2	Exit	1	Response code
RM 0293	DFHRMUWW	Exc	Recovery	1 2	Response code Kernel error data
RM 02A1	DFHRMUWF	RM 2	Entry	1	Response code
RM 02A2	DFHRMUWF	RM 2	Exit	1	Response code
RM 02A3	DFHRMUWF	Exc	Recovery	1 2	Response code Kernel error data
RM 02B1	DFHRMUWB	RM 2	Entry	1	Response code
RM 02B2	DFHRMUWB	RM 2	Exit	1	Response code
RM 02B3	DFHRMUWB	Exc	Recovery	1 2	Response code Kernel error data
RM 02B4	DFHRMUWB	Exc	Truncated log record detected	1	Log record
RM 02C1	DFHRMSLO	RM 2	Entry	1	Response code
RM 02C2	DFHRMSLO	RM 2	Exit	1	Response code
RM 02C3	DFHRMSLO	Exc	Recovery	1 2	Response code Kernel error data
RM 02D1	DFHRMSLL	RM 2	Entry	1	Response code
RM 02D2	DFHRMSLL	RM 2	Exit	1	Response code
RM 02D3	DFHRMSLL	Exc	Recovery	1 2	Response code Kernel error data
RM 02E1	DFHRMSLW	RM 2	Entry	1 2	Response code Remark
RM 02E2	DFHRMSLW	RM 2	Exit	1	Response code
RM 02E3	DFHRMSLW	Exc	Recovery	1 2	Response code Kernel error data
RM 02F1	DFHRMSLF	RM 2	Entry	1	Response code
RM 02F2	DFHRMSLF	RM 2	Exit	1	Response code
RM 02F3	DFHRMSLF	Exc	Recovery	1 2	Response code Kernel error data

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data
RM 0301	DFHRMLN	RM 1	Entry	1 RMLN parameter list 2 Access id 3 Log name 4 Link id 5 UOW id
RM 0302	DFHRMLN	RM 1	Exit	1 RMLN parameter list 2 Access id 3 Log name 4 Link id 5 UOW id
RM 0303	DFHRMLN	Exc	Recovery	1 RMLN parameter list 2 Kernel error data
RM 0304	DFHRMLN	Exc	Invalid format	1 RMLN parameter list 2 Access id 3 Log name 4 Link id 5 UOW id
RM 0305	DFHRMLN	Exc	Invalid function	1 RMLN parameter list 2 Access id 3 Log name 4 Link id 5 UOW id
RM 0306	DFHRMLN	Exc	Lock error	1 RMLN parameter list 2 Access id 3 Log name 4 Link id 5 UOW id
RM 0307	DFHRMLN	Exc	Unlock error	1 RMLN parameter list 2 Access id 3 Log name 4 Link id 5 UOW id
RM 0308	DFHRMLN	Exc	Unknown Kernel error code	1 RMLN parameter list 2 Access id 3 Log name 4 Link id 5 UOW id
RM 0309	DFHRMLN	RM 1	Call client	1 Client name 2 Local UOW id
RM 030A	DFHRMLN	RM 2	Link set empty	1 Link set
RM 030B	DFHRMLN	RM 2	Link set not empty	1 Link set
RM 0311	DFHRMLK1	RM 2	Entry	1 Response code
RM 0312	DFHRMLK1	RM 2	Exit	1 Response code

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data
RM 0313	DFHRMLK1	Exc	Recovery	1 Response code 2 Kernel error data
RM 0314	DFHRMLK1	Exc	Getmain failed	1 Response code
RM 0321	DFHRMLK2	RM 2	Entry	1 RMLN parameter list 2 Access id 3 Log name 4 Link id 5 UOW id
RM 0322	DFHRMLK2	RM 2	Exit	1 RMLN parameter list 2 Access id 3 Log name 4 Link id 5 UOW id
RM 0323	DFHRMLK2	Exc	Recovery	1 RMLN parameter list 2 Kernel error data
RM 0324	DFHRMLK2	Exc	Lock error	1 RMLN parameter list 2 Access id 3 Log name 4 Link id 5 UOW id
RM 0325	DFHRMLK2	Exc	Unlock error	1 RMLN parameter list 2 Access id 3 Log name 4 Link id 5 UOW id
RM 0326	DFHRMLK2	Exc	Unknown Kernel error code	1 RMLN parameter list 2 Access id 3 Log name 4 Link id 5 UOW id
RM 0331	DFHRMLK3	RM 2	Entry	1 Response code
RM 0332	DFHRMLK3	RM 2	Exit	1 Response code
RM 0333	DFHRMLK3	Exc	Recovery	1 Response code 2 Kernel error data
RM 0334	DFHRMLK3	Exc	Lock error	1 Response code
RM 0335	DFHRMLK3	Exc	Unlock error	1 Response code
RM 0336	DFHRMLK3	Exc	Unknown Kernel error code	1 Response code
RM 0341	DFHRMLK4	RM 2	Entry	1 Response code
RM 0342	DFHRMLK4	RM 2	Exit	1 Response code

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data
RM 0343	DFHRMLK4	Exc	Recovery	1 Response code 2 Kernel error data
RM 0344	DFHRMLK4	Exc	Lock error	1 Response code
RM 0345	DFHRMLK4	Exc	Unlock error	1 Response code
RM 0346	DFHRMLK4	Exc	Unknown Kernel error code	1 Response code
RM 0347	DFHRMLK4	RM 2	Link set empty	1 Link set
RM 0348	DFHRMLK4	RM 2	Link set not empty	1 Link set
RM 034A	DFHRMLK5	RM 2	Entry	1 Response code
RM 034B	DFHRMLK5	RM 2	Exit	1 Response code
RM 034C	DFHRMLK5	Exc	Lock error	1 Response code 2 Kernel error data
RM 0351	DFHRMLSP	RM 2	Entry	1 Transaction continue - Y/N 2 Read only - Y/N
RM 0352	DFHRMLSP	RM 2	Exit	1 Transaction continue - Y/N 2 Read only - Y/N 3 Composite vote 4 Response code
RM 0353	DFHRMLSP	Exc	Recovery	1 Kernel error data
RM 0354	DFHRMLSP	Exc	Lock error	1 Response code
RM 0355	DFHRMLSP	Exc	Unlock error	1 Response code
RM 0356	DFHRMLSP	Exc	Unknown Kernel error code	1 Response code
RM 0357	DFHRMLSP	RM 1	Call client	1 Client name 2 Local UOW id
RM 0361	DFHRMLSD	RM 2	Entry	1 Transaction continue - Y/N 2 Read only - Y/N
RM 0362	DFHRMLSD	RM 2	Exit	1 Transaction continue - Y/N 2 Read only - Y/N 3 Composite vote 4 Response code
RM 0363	DFHRMLSD	Exc	Recovery	1 Kernel error data
RM 0364	DFHRMLSD	Exc	Lock error	1 Response code
RM 0365	DFHRMLSD	Exc	Unlock error	1 Response code
RM 0366	DFHRMLSD	Exc	Unknown Kernel error code	1 Response code

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data
RM 0367	DFHRMLSD	Exc	Perform commit failure	1 Response code
RM 0368	DFHRMLSD	RM 1	Call client	1 Client name 2 Local UOW id
RM 0371	DFHRMLSO	RM 2	Entry	1 Transaction continue - Y/N 2 Vote 3 Restart - Y/N
RM 0372	DFHRMLSO	RM 2	Exit	1 Response code 2 Links present - Y/N
RM 0373	DFHRMLSO	Exc	Recovery	1 Kernel error data
RM 0374	DFHRMLSO	Exc	Lock error	1 Response code
RM 0375	DFHRMLSO	Exc	Unlock error	1 Response code
RM 0376	DFHRMLSO	Exc	Unknown Kernel error code	1 Response code
RM 0377	DFHRMLSO	Exc	Perform commit failure	1 Response code
RM 0378	DFHRMLSO	RM 1	Call client	1 Client name 2 Local UOW id
RM 0379	DFHRMLSO	RM 2	Link set empty	1 Link set
RM 037A	DFHRMLSO	RM 2	Link set not empty	1 Link set
RM 0381	DFHRMLSS	RM 2	Entry	1 Response code
RM 0382	DFHRMLSS	RM 2	Exit	1 Response code
RM 0383	DFHRMLSS	Exc	Recovery	1 Kernel error data
RM 0384	DFHRMLSS	Exc	Lock error	1 Response code
RM 0385	DFHRMLSS	Exc	Unlock error	1 Response code
RM 0386	DFHRMLSS	Exc	Unknown Kernel error code	1 Response code
RM 0387	DFHRMLSS	Exc	Perform shunt failure	1 Response code
RM 0388	DFHRMLSS	RM 1	Call client	1 Client name 2 Local UOW id
RM 0389	DFHRMLSS	RM 2	Link set empty	1 Link set
RM 038A	DFHRMLSS	RM 2	Link set not empty	1 Link set
RM 0391	DFHRMLSU	RM 2	Entry	1 Response code
RM 0392	DFHRMLSU	RM 2	Exit	1 Response code
RM 0393	DFHRMLSU	Exc	Recovery	1 Kernel error data

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
RM 0394	DFHRMLSU	Exc	Lock error	1	Response code
RM 0395	DFHRMLSU	Exc	Unlock error	1	Response code
RM 0396	DFHRMLSU	Exc	Unknown Kernel error code	1	Response code
RM 0397	DFHRMLSU	Exc	Perform unshunt failure	1	Response code
RM 0398	DFHRMLSU	RM 1	Call client	1 2	Client name Local UOW id
RM 03A1	DFHRML1D	RM 2	Entry	1	Response code
RM 03A2	DFHRML1D	RM 2	Exit	1	Response code
RM 03A3	DFHRML1D	Exc	Recovery	1 2	Response code Kernel error data
RM 03A4	DFHRML1D	Exc	Lock error	1	Response code
RM 03A5	DFHRML1D	Exc	Unlock error	1	Response code
RM 03A6	DFHRML1D	Exc	Unknown Kernel error code	1	Response code
RM 03B1	DFHRMLSF	RM 2	Entry	1	Response code
RM 03B2	DFHRMLSF	RM 2	Exit	1	Response code
RM 03B3	DFHRMLSF	Exc	Recovery	1 2	Response code Kernel error data
RM 03B4	DFHRMLSF	Exc	Lock error	1	Response code
RM 03B5	DFHRMLSF	Exc	Unlock error	1	Response code
RM 03B6	DFHRMLSF	Exc	Unknown Kernel error code	1	Response code
RM 03C1	DFHRMLKQ	RM 2	Entry	1 2	Response code Client name
RM 03C2	DFHRMLKQ	RM 2	Exit	1 2	Response code Client name
RM 03C3	DFHRMLKQ	Exc	Recovery	1 2	Response code Kernel error data
RM 03C4	DFHRMLKQ	Exc	Lock error	1	Response code
RM 03C5	DFHRMLKQ	Exc	Unlock error	1	Response code
RM 03C6	DFHRMLKQ	Exc	Unknown Kernel error code	1	Response code
RM 0401	DFHRMSL2	RM 2	Entry	1	Response code
RM 0402	DFHRMSL2	RM 2	Exit	1	Response code

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data
RM 0403	DFHRMSL2	Exc	Recovery	1 Response code 2 Kernel error data
RM 0404	DFHRMSL2	Exc	Start chain browse failed	
RM 0411	DFHRMSL3	RM 2	Entry	1 Response code
RM 0412	DFHRMSL3	RM 2	Exit	1 Response code
RM 0413	DFHRMSL3	Exc	Recovery	1 Response code 2 Kernel error data
RM 0414	DFHRMSL3	Exc	Truncated log record	1 Log record
RM 0415	DFHRMSL3	Exc	Chain browse read failed	
RM 0421	DFHRMSL4	RM 2	Entry	1 Response code
RM 0422	DFHRMSL4	RM 2	Exit	1 Response code
RM 0423	DFHRMSL4	Exc	Recovery	1 Response code 2 Kernel error data
RM 0431	DFHRMSL1	RM 2	Entry	1 Response code
RM 0432	DFHRMSL1	RM 2	Exit	1 Response code
RM 0433	DFHRMSL1	Exc	Recovery	1 Response code 2 Kernel error data
RM 0441	DFHRMRO2	RM 2	Entry	1 Response code
RM 0442	DFHRMRO2	RM 2	Exit	1 Response code
RM 0443	DFHRMRO2	Exc	Recovery	1 Response code 2 Kernel error data
RM 0444	DFHRMRO2	Exc	Bad response from client	1 Response code
RM 0445	DFHRMRO2	Exc	Lock error	1 Response code
RM 0446	DFHRMRO2	Exc	Unlock error	1 Response code
RM 0447	DFHRMRO2	Exc	Unknown Kernel error code	1 Response code
RM 0448	DFHRMRO2	RM 1	Call client	1 Client name 2 Local UOW id
RM 0451	DFHRMRO3	RM 2	Entry	1 Response code
RM 0452	DFHRMRO3	RM 2	Exit	1 Response code
RM 0453	DFHRMRO3	Exc	Recovery	1 Response code 2 Kernel error data
RM 0454	DFHRMRO3	Exc	Truncated log record	1 Log record

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
RM 0455	DFHRMRO3	Exc	Log record with inconsistent lengths	1	Log record
RM 0456	DFHRMRO3	Exc	Bad response from client	1	Response code
RM 0457	DFHRMRO3	Exc	Lock error	1	Response code
RM 0458	DFHRMRO3	Exc	Unlock error	1	Response code
RM 0459	DFHRMRO3	Exc	Unknown Kernel error code	1	Response code
RM 0460	DFHRMRO3	RM 1	Call client	1 2	Client name Local UOW id
RM 0461	DFHRMRO4	RM 2	Entry	1	Response code
RM 0462	DFHRMRO4	RM 2	Exit	1	Response code
RM 0463	DFHRMRO4	Exc	Recovery	1 2	Response code Kernel error data
RM 0464	DFHRMRO4	Exc	Bad response from client	1	Response code
RM 0465	DFHRMRO4	Exc	Lock error	1	Response code
RM 0466	DFHRMRO4	Exc	Unlock error	1	Response code
RM 0467	DFHRMRO3	Exc	Unknown Kernel error code	1	Response code
RM 0468	DFHRMRO4	RM 1	Call client	1 2	Client name Local UOW id
RM 0471	DFHRMROS	RM 2	Entry		
RM 0472	DFHRMROS	RM 2	Exit		
RM 0473	DFHRMROS	Exc	Recovery	1	Kernel error data
RM 0474	DFHRMROS	Exc	Bad response from client		
RM 0475	DFHRMROS	RM 1	Call client	1 2	Client name Local UOW id
RM 0481	DFHRMROU	RM 2	Entry		
RM 0482	DFHRMROU	RM 2	Exit		
RM 0483	DFHRMROS	Exc	Recovery	1	Kernel error data
RM 0484	DFHRMROU	Exc	Bad response from client		
RM 0485	DFHRMROU	RM 1	Call client	1 2	Client name Local UOW id
RM 0491	DFHRMUWV	RM 2	Entry	1	Response code
RM 0492	DFHRMUWV	RM 2	Exit	1	Response code
RM 0493	DFHRMUWV	Exc	Recovery	1 2	Response code Kernel error data
RM 04A1	DFHRMROV	RM 2	Entry	1	Response code

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
RM 04A2	DFHRMROV	RM 2	Exit	1	Response code
RM 04A3	DFHRMROV	Exc	Recovery	1	Response code
				2	Kernel error data
RM 04B1	DFHRMXNE	RM 2	Entry	1	Response code
RM 04B2	DFHRMXNE	RM 2	Exit	1	Response code
RM 04B3	DFHRMXNE	Exc	Recovery	1	Response code
				2	Kernel error data
RM 04C1	DFHRMUWE	RM 2	Entry	1	Response code
RM 04C2	DFHRMUWE	RM 2	Exit	1	Response code
RM 04C3	DFHRMUWE	Exc	Recovery	1	Response code
				2	Kernel error data
RM 04C4	DFHRMUWE	Exc	Lock error	1	Response code
RM 04C5	DFHRMUWE	Exc	Unlock error	1	Response code
RM 04C6	DFHRMUWE	Exc	Unknown Kernel error code	1	Response code
RM 04C7	DFHRMUWE	RM 2	Unshunt UOW	1	UOW
				2	Unshunt request
RM 04D1	DFHRMUWP	RM 2	Entry	1	Response code
RM 04D2	DFHRMUWP	RM 2	Exit	1	Response code
RM 04D3	DFHRMUWP	Exc	Recovery	1	Response code
				2	Kernel error data
RM 04D4	DFHRMUWP	Exc	Perform commit error	1	Response code
RM 04D5	DFHRMUWP	RM 1	Call client	1	Client name
				2	Local UOW id
RM 04E1	DFHRMUWH	RM 2	Entry	1	Response code
				2	UOW token
				3	Held - Y/N
RM 04E2	DFHRMUWH	RM 2	Exit	1	Response code
				2	UOW token
				3	Held - Y/N
RM 04E3	DFHRMUWH	Exc	Recovery	1	Response code
				2	Kernel error data
RM 04E4	DFHRMUWH	Exc	Lock error	1	Response code
RM 04E5	DFHRMUWH	Exc	Unlock error	1	Response code

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
RM 04E6	DFHRMUWH	Exc	Unknown Kernel error code	1	Response code
RM 04F1	DFHRMUW0	RM 2	Entry	1	Response code
RM 04F2	DFHRMUW0	RM 2	Exit	1	Response code
RM 04F3	DFHRMUW0	Exc	Recovery	1 2	Response code Kernel error data
RM 04F4	DFHRMUW0	Exc	Lock error	1	Response code
RM 04F5	DFHRMUW0	Exc	Unlock error	1	Response code
RM 04F6	DFHRMUW0	Exc	Unknown Kernel error code	1	Response code
RM 0601	DFHRMUWN	RM 2	Entry	1	Response code
RM 0602	DFHRMUWN	RM 2	Exit	1	Response code
RM 0603	DFHRMUWN	Exc	Recovery	1 2	Response code Kernel error data
RM 0604	DFHRMUWN	Exc	Lock error	1	Response code
RM 0605	DFHRMUWN	Exc	Unlock error	1	Response code
RM 0606	DFHRMUWN	Exc	Unknown Kernel error code	1	Response code
RM 0611	DFHRMUWQ	RM 2	Entry	1	Response code
RM 0612	DFHRMUWQ	RM 2	Exit	1	Response code
RM 0613	DFHRMUWQ	Exc	Recovery	1 2	Response code Kernel error data
RM 0614	DFHRMUWQ	Exc	Lock error	1	Response code
RM 0615	DFHRMUWQ	Exc	Unlock error	1	Response code
RM 0616	DFHRMUWQ	Exc	Unknown Kernel error code	1	Response code
RM 0617	DFHRMUWQ	Exc	Perform commit error	1	Response code
RM 0618	DFHRMUWQ	RM 1	Call client	1 2	Client name Local UOW id
RM 0621	DFHRMUWS	RM 2	Entry	1 2	Vote Return code
RM 0622	DFHRMUWS	RM 2	Exit	1 2	Vote Return code
RM 0623	DFHRMUWS	Exc	Recovery	1 2	Response code Kernel error data

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
RM 0624	DFHRMUWS	Exc	Lock error	1	Vote
				2	Return code
RM 0625	DFHRMUWS	Exc	Unlock error	1	Vote
				2	Return code
RM 0626	DFHRMUWS	Exc	Unknown Kernel error code	1	Vote
				2	Return code
RM 0631	DFHRMUWJ	RM 2	Entry	1	Response code
RM 0632	DFHRMUWJ	RM 2	Exit	1	Response code
RM 0633	DFHRMUWJ	Exc	Recovery	1	Response code
				2	Kernel error data
RM 0634	DFHRMUWJ	Exc	Lock error	1	Response code
RM 0635	DFHRMUWJ	Exc	Unlock error	1	Response code
RM 0636	DFHRMUWJ	Exc	Unknown Kernel error code	1	Response code
RM 0641	DFHRMU1S	RM 2	Entry	1	Response code
RM 0642	DFHRMU1S	RM 2	Exit	1	Response code
RM 0643	DFHRMU1S	Exc	Recovery	1	Response code
				2	Kernel error data
RM 0644	DFHRMU1S	Exc	Lock error	1	Response code
RM 0645	DFHRMU1S	Exc	Unlock error	1	Response code
RM 0646	DFHRMU1S	Exc	Unknown Kernel error code	1	Response code
RM 0651	DFHRMU1D	RM 2	Entry	1	Response code
RM 0652	DFHRMU1D	RM 2	Exit	1	Response code
				2	UOW instance
RM 0653	DFHRMU1D	Exc	Recovery	1	Response code
				2	Kernel error data
RM 0654	DFHRMU1D	Exc	Lock error	1	Response code
RM 0655	DFHRMU1D	Exc	Unlock error	1	Response code
RM 0656	DFHRMU1D	Exc	Unknown Kernel error code	1	Response code
RM 0657	DFHRMU1D	Exc	Truncated log record	1	Log record
RM 0658	DFHRMU1D	Exc	Unknown type of UOW log record	1	Log record
RM 0659	DFHRMU1D	Exc	Unexpected keypoint log record	1	Log record

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
RM 0661	DFHRMU1E	RM 2	Entry	1	Response code
RM 0662	DFHRMU1E	RM 2	Exit	1	Response code
RM 0663	DFHRMU1E	Exc	Recovery	1 2	Response code Kernel error data
RM 0664	DFHRMU1E	Exc	Lock error	1	Response code
RM 0665	DFHRMU1E	Exc	Unlock error	1	Response code
RM 0666	DFHRMU1E	Exc	Unknown Kernel error code	1	Response code
RM 0667	DFHRMU1E	Exc	Incomplete UOW	1	UOW instance
RM 0671	DFHRMU1C	RM 2	Entry	1	Response code
RM 0672	DFHRMU1C	RM 2	Exit	1	Response code
RM 0673	DFHRMU1C	Exc	Recovery	1 2	Response code Kernel error data
RM 0674	DFHRMU1C	Exc	UOW chain token already set	1	Response code
RM 0681	DFHRMR1S	RM 2	Entry	1	Response code
RM 0682	DFHRMR1S	RM 2	Exit	1	Response code
RM 0683	DFHRMR1S	Exc	Recovery	1 2	Response code Kernel error data
RM 0684	DFHRMR1S	Exc	Lock error	1	Response code
RM 0685	DFHRMR1S	Exc	Unlock error	1	Response code
RM 0686	DFHRMR1S	Exc	Unknown Kernel error code	1	Response code
RM 0687	DFHRMR1S	Exc	Start delivery failed	1	Response code
RM 0691	DFHRMR1D	RM 2	Entry	1	Response code
RM 0692	DFHRMR1D	RM 2	Exit	1	Response code
RM 0693	DFHRMR1D	Exc	Recovery	1 2	Response code Kernel error data
RM 0694	DFHRMR1D	Exc	Lock error	1	Response code
RM 0695	DFHRMR1D	Exc	Unlock error	1	Response code
RM 0696	DFHRMR1D	Exc	Unknown Kernel error code	1	Response code
RM 0697	DFHRMR1D	Exc	Truncated log record	1	Log record
RM 0698	DFHRMR1D	Exc	Delivery of non-UOW related log record failed	1	Response code

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
RM 0699	DFHRMR1D	Exc	Unrecognised type of log record	1	Response code
RM 0699	DFHRMR1D	Exc	Unrecognised type of log record	1	Response code
RM 069A	DFHRMR1D	Exc	Delivery of UOW related log record failed	1	Response code
RM 069B	DFHRMR1D	Exc	Deliver forget failed	1	Response code
RM 069C	DFHRMR1D	RM 1	Call client	1 2	Client name Local UOW id
RM 06A1	DFHRMR1E	RM 2	Entry	1	Response code
RM 06A2	DFHRMR1E	RM 2	Exit	1	Response code
RM 06A3	DFHRMR1E	Exc	Recovery	1 2	Response code Kernel error data
RM 06A4	DFHRMR1E	Exc	Lock error	1	Response code
RM 06A5	DFHRMR1E	Exc	Unlock error	1	Response code
RM 06A6	DFHRMR1E	Exc	Unknown Kernel error code	1	Response code
RM 06A7	DFHRMR1E	Exc	End delivery failed	1	Response code
RM 06A8	DFHRMR1E	RM 1	Call client	1 2	Client name Local UOW id
RM 06B1	DFHRMSL5	RM 2	Entry	1	Response code
RM 06B2	DFHRMSL5	RM 2	Exit	1	Response code
RM 06B3	DFHRMSL5	Exc	Recovery	1 2	Response code Kernel error data
RM 06B4	DFHRMSL5	Exc	Lock error	1	Response code
RM 06B5	DFHRMSL5	Exc	Unlock error	1	Response code
RM 06B6	DFHRMSL5	Exc	Unknown Kernel error code	1	Response code
RM 06B7	DFHRMSL5	Exc	Truncated log record	1	Log record
RM 06B8	DFHRMSL5	Exc	No owner for log record	1	Log record
RM 06B9	DFHRMSL5	Exc	Truncated log from chain	1	Log record
RM 06BA	DFHRMSL5	Exc	No owner for log record from chain	1	Log record
RM 06BB	DFHRMSL5	Exc	Empty system log		
RM 06C1	DFHRMU1R	RM 2	Entry	1	Response code
RM 06C2	DFHRMU1R	RM 2	Exit	1	Response code

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data
RM 06C3	DFHRMU1R	Exc	Recovery	1 Response code 2 Kernel error data
RM 06C4	DFHRMU1R	Exc	Lock error	1 Response code
RM 06C5	DFHRMU1R	Exc	Unlock error	1 Response code
RM 06C6	DFHRMU1R	Exc	Unknown Kernel error code	1 Response code
RM 06D1	DFHRMU1U	RM 2	Entry	1 Response code
RM 06D2	DFHRMU1U	RM 2	Exit	1 Response code
RM 06D3	DFHRMU1U	Exc	Recovery	1 Response code 2 Kernel error data
RM 06D4	DFHRMU1U	Exc	Lock error	1 Response code
RM 06D5	DFHRMU1U	Exc	Unlock error	1 Response code
RM 06D6	DFHRMU1U	Exc	Unknown Kernel error code	1 Response code
RM 06E1	DFHRMSL	RM 1	Entry	1 RMSL parameter list
RM 06E2	DFHRMSL	RM 1	Exit	1 RMSL parameter list
RM 06E3	DFHRMSL	Exc	Recovery	1 RMSL parameter list 2 Kernel error data
RM 06E4	DFHRMSL	Exc	Lock error	1 RMSL parameter list
RM 06E5	DFHRMSL	Exc	Unlock error	1 RMSL parameter list
RM 06E6	DFHRMSL	Exc	Unknown Kernel error code	1 RMSL parameter list
RM 06E7	DFHRMSL	Exc	Invalid format	1 RMSL parameter list
RM 06E8	DFHRMSL	Exc	Invalid function	1 RMSL parameter list
RM 06F1	DFHRMSL6	RM 2	Entry	1 Response code
RM 06F2	DFHRMSL6	RM 2	Exit	1 Response code
RM 06F3	DFHRMSL6	Exc	Recovery	1 Response code 2 Kernel error data
RM 06F4	DFHRMSL6	Exc	Lock error	1 Response code
RM 06F5	DFHRMSL6	Exc	Unlock error	1 Response code
RM 06F6	DFHRMSL6	Exc	Unknown Kernel error code	1 Response code
RM 0801	DFHRMSL7	RM 2	Entry	1 Response code
RM 0802	DFHRMSL7	RM 2	Exit	1 Response code

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data
RM 0803	DFHRMSL7	Exc	Recovery	1 Response code 2 Kernel error data
RM 0804	DFHRMSL7	Exc	Lock error	1 Response code
RM 0805	DFHRMSL7	Exc	Unlock error	1 Response code
RM 0806	DFHRMSL7	Exc	Unknown Kernel error code	1 Response code
RM 0811	DFHRMR1K	RM 2	Entry	1 Response code
RM 0812	DFHRMR1K	RM 2	Exit	1 Response code
RM 0813	DFHRMR1K	Exc	Recovery	1 Response code 2 Kernel error data
RM 0814	DFHRMR1K	Exc	Lock error	1 Response code
RM 0815	DFHRMR1K	Exc	Unlock error	1 Response code
RM 0816	DFHRMR1K	Exc	Unknown Kernel error code	1 Response code
RM 0817	DFHRMR1K	Exc	Take keypoint failed	1 Response code
RM 0818	DFHRMR1K	Exc	Call client	1 Client name 2 Local UOW id
RM 0821	DFHRMXN2	RM 2	Entry	1 Response code
RM 0822	DFHRMXN2	RM 2	Exit	1 Response code
RM 0823	DFHRMXN2	Exc	Recovery	1 Response code 2 Kernel error data
RM 0824	DFHRMXN2	Exc	Lock error	1 Response code
RM 0825	DFHRMXN2	Exc	Unlock error	1 Response code
RM 0826	DFHRMXN2	Exc	Unknown Kernel error code	1 Response code
RM 0831	DFHRMXN4	RM 2	Entry	1 Response code
RM 0832	DFHRMXN4	RM 2	Exit	1 Response code
RM 0833	DFHRMXN4	Exc	Recovery	1 Response code 2 Kernel error data
RM 0834	DFHRMXN4	Exc	Lock error	1 Response code
RM 0835	DFHRMXN4	Exc	Unlock error	1 Response code
RM 0836	DFHRMXN4	Exc	Unknown Kernel error code	1 Response code
RM 083A	DFHRMXN5	RM 2	Entry	1 Response code

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
RM 083B	DFHRMXN5	RM 2	Exit	1	Response code
RM 083C	DFHRMXN5	Exc	Recovery	1 2	Response code Kernel error data
RM 0841	DFHRMU1K	RM 2	Entry	1	Response code
RM 0842	DFHRMU1K	RM 2	Exit	1	Response code
RM 0843	DFHRMU1K	Exc	Recovery	1 2	Response code Kernel error data
RM 0844	DFHRMU1K	Exc	Lock error	1	Response code
RM 0845	DFHRMU1K	Exc	Unlock error	1	Response code
RM 0846	DFHRMU1K	Exc	Unknown Kernel error code	1	Response code
RM 0848	DFHRMU1G	RM 2	Entry	1	Response code
RM 0849	DFHRMU1G	RM 2	Exit	1	Response code
RM 084A	DFHRMU1G	Exc	Recovery	1 2	Response code Kernel error data
RM 084B	DFHRMU1G	Exc	Lock error	1	Response code
RM 084C	DFHRMU1G	Exc	Unlock error	1	Response code
RM 084D	DFHRMU1G	Exc	Unknown Kernel error code	1	Response code
RM 0851	DFHRMU1J	RM 2	Entry	1	Response code
RM 0852	DFHRMU1J	RM 2	Exit	1	Response code
RM 0853	DFHRMU1J	Exc	Recovery	1 2	Response code Kernel error data
RM 0854	DFHRMU1J	Exc	Lock error	1	Response code
RM 0855	DFHRMU1J	Exc	Unlock error	1	Response code
RM 0856	DFHRMU1J	Exc	Unknown Kernel error code	1	Response code
RM 0861	DFHRMUW3	RM 2	Entry	1	Response code
RM 0862	DFHRMUW3	RM 2	Exit	1	Response code
RM 0863	DFHRMUW3	Exc	Recovery	1 2	Response code Kernel error data
RM 0864	DFHRMUW3	Exc	Lock error	1	Response code
RM 0865	DFHRMUW3	Exc	Unlock error	1	Response code

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data	
RM 0866	DFHRMUW3	Exc	Unknown Kernel error code	1	Response code
RM 0871	DFHRMSLJ	RM 2	Entry	1	Response code
RM 0872	DFHRMSLJ	RM 2	Exit	1	Response code
RM 0873	DFHRMSLJ	Exc	Recovery	1 2	Response code Kernel error data
RM 0874	DFHRMSLJ	Exc	Lock error	1	Response code
RM 0875	DFHRMSLJ	Exc	Unlock error	1	Response code
RM 0876	DFHRMSLJ	Exc	Unknown Kernel error code	1	Response code
RM 0881	DFHRMSLV	RM 2	Entry	1	Response code
RM 0882	DFHRMSLV	RM 2	Exit	1	Response code
RM 0883	DFHRMSLV	Exc	Recovery	1 2	Response code Kernel error data
RM 0891	DFHRMU1Q	RM 1	Entry	1	TISR Parameter list
RM 0892	DFHRMU1Q	RM 1	Exit	1	TISR parameter list
RM 0893	DFHRMU1Q	Exc	Recovery	1 2	TISR parameter list Kernel error data
RM 0894	DFHRMU1Q	Exc	Invalid format	1	TISR parameter list
RM 0895	DFHRMU1Q	Exc	Invalid function	1	TISR parameter list
RM 08A1	DFHRMU1V	RM 2	Entry	1	Response code
RM 08A2	DFHRMU1V	RM 2	Exit	1	Response code
RM 08A3	DFHRMU1V	Exc	Recovery	1 2	Response code Kernel error data
RM 08A4	DFHRMU1V	Exc	Lock error	1	Response code
RM 08A5	DFHRMU1V	Exc	Unlock error	1	Response code
RM 08A6	DFHRMU1V	Exc	Unknown Kernel error code	1	Response code
RM 08A7	DFHRMU1V	Exc	Request notify failure	1	Response code
RM 08B1	DFHRMU1W	RM 2	Entry	1	Response code
RM 08B2	DFHRMU1W	RM 2	Exit	1	Response code
RM 08B3	DFHRMU1W	Exc	Recovery	1 2	Response code Kernel error data

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data
RM 08B4	DFHRMU1W	Exc	Lock error	1 Response code
RM 08B5	DFHRMU1W	Exc	Unlock error	1 Response code
RM 08B6	DFHRMU1W	Exc	Unknown Kernel error code	1 Response code
RM 08B7	DFHRMU1W	Exc	Cancel notify failure	1 Response code
RM 08C1	DFHRMU1F	RM 2	Entry	1 Response code
RM 08C2	DFHRMU1F	RM 2	Exit	1 Response code
RM 08C3	DFHRMU1F	Exc	Recovery	1 Response code 2 Kernel error data
RM 08C4	DFHRMU1F	Exc	Lock error	1 Response code
RM 08C5	DFHRMU1F	Exc	Unlock error	1 Response code
RM 08C6	DFHRMU1F	Exc	Unknown Kernel error code	1 Response code
RM 08D1	DFHRMU1L	RM 1	Entry	1 XMPP parameter list
RM 08D2	DFHRMU1L	RM 1	Exit	1 XMPP parameter list
RM 08D3	DFHRMU1L	Exc	Recovery	1 XMPP parameter list 2 Kernel error data
RM 08D4	DFHRMU1L	Exc	Invalid format	1 XMPP parameter list
RM 08D5	DFHRMU1L	Exc	Invalid function	1 XMPP parameter list
RM 08E1	DFHRMU1N	RM 2	Entry	1 Response code
RM 08E2	DFHRMU1N	RM 2	Exit	1 Response code
RM 08E3	DFHRMU1N	Exc	Recovery	1 Response code 2 Kernel error data
RM 08E4	DFHRMU1N	Exc	Lock error	1 Response code
RM 08E5	DFHRMU1N	Exc	Unlock error	1 Response code
RM 08E6	DFHRMU1N	Exc	Unknown Kernel error code	1 Response code
RM 08F1	DFHRMST1	RM 2	Entry	1 Response code
RM 08F2	DFHRMST1	RM 2	Exit	1 Response code
RM 08F3	DFHRMST1	Exc	Recovery	1 Response code 2 Kernel error data
RM 0A01	DFHRMST	RM 1	Entry	1 STST parameter list
RM 0A02	DFHRMST	RM 1	Exit	1 STST parameter list

Table 128. Recovery manager trace points (continued)

Point ID	Module	Lvl	Type	Data
RM 0A03	DFHRMST	Exc	Recovery	1 STST parameter list 2 Kernel error data
RM 0A04	DFHRMST	Exc	Invalid format	1 STST parameter list
RM 0A05	DFHRMST	Exc	Invalid function	1 STST parameter list
RM 0A06	DFHRMST	Exc	Statistics buffer too small	1 STST parameter list
RM F209	DFHRMUW	RM 1	Call client	1 Client name 2 Local UOW id
RM F20B	DFHRMUO	Exc	Call client	1 Client name 2 Local UOW id
RM FA01	DFHRMUC	RM 1	Entry	1 RMUW parameter list 2 Local UOW id
RM FA02	DFHRMUC	RM 1	Exit	1 RMUW parameter list
RM FA03	DFHRMUC	Exc	Recovery	1 RMUW parameter list 1 Kernel error data
RM FA04	DFHRMUC	Exc	Lock error	1 RMUW parameter list
RM FA05	DFHRMUC	Exc	Unlock error	1 RMUW parameter list
RM FA06	DFHRMUC	Exc	Unknown Kernel error code	1 RMUW parameter list
RM FA11	DFHRMUO	RM 1	Entry	1 RMUW parameter list
RM FA12	DFHRMUO	RM 1	Exit	1 RMUW parameter list
RM FA13	DFHRMUO	Exc	Recovery	1 RMUW parameter list 1 Kernel error data
RM FA14	DFHRMUO	Exc	Lock error	1 RMUW parameter list
RM FA15	DFHRMUO	Exc	Unlock error	1 RMUW parameter list
RM FA16	DFHRMUO	Exc	Unknown Kernel error code	1 RMUW parameter list

RRMS domain trace points

Table 129. RRMS domain trace entries

Point ID	Module	Lvl	Type	Data
RX 0101	DFHRXDM	1	Entry	1 RXDM parameter list
RX 0102	DFHRXDM	1	Exit	1 RXDM parameter list
RX 0103	DFHRXDM	Exc	Invalid format	1 RXDM parameter list
RX 0104	DFHRXDM	Exc	Invalid function	1 RXDM parameter list

Table 129. RRMS domain trace entries (continued)

Point ID	Module	Lvl	Type	Data
RX 0105	DFHRXDM	Exc	GETMAIN failure	1 RXDM parameter list
RX 0106	DFHRXDM	Exc	Inquire error	1 RXDM parameter list
RX 0107	DFHRXDM	Exc	INQUIRE LOGNAME error	1 RXDM parameter list
RX 0108	DFHRXDM	Exc	SET LOGNAME error	1 RXDM parameter list
RX 0109	DFHRXDM	Exc	COMPARE LOGNAME error	1 RXDM parameter list
RX 010A	DFHRXDM	1	Event - start notification task	None
RX 010B	DFHRXDM	1	Event - end notification task	None
RX 010C	DFHRXDM	1	Event - start resynchronization task	None
RX 010C	DFHRXDM	1	Event - start resynchronization task	None
RX 010D	DFHRXDM	1	Event - End resynchronization task	None
RX 010E	DFHRXDM	1	Event - Start restart task	None
RX 010F	DFHRXDM	1	Event - End restart task	None
RX 0110	DFHRXDM	1	Event - start RRS failure task	None
RX 0111	DFHRXDM	1	Event - end RRS failure task	None
RX 0112	DFHRXDM	1	Event - start resolving unmatched UOW links	None
RX 0113	DFHRXDM	1	Event - End resolving unmatched UOW links	None
RX 0114	DFHRXDM	1	Event - Initialize unit of recovery for resynchronization	1 Unit of recovery ID
RX 0115	DFHRXDM	1	Event - begin resynchronization of unit of recovery	1 Unit of recovery ID
RX 0116	DFHRXDM	1	Event - end resynchronization of unit of recovery	1 Unit of recovery ID
RX 0201	DFHRXDM	1	Before CICS SVC	1 SVC parameter list
RX 0202	DFHRXDM	1	After CICS SVC	1 SVC parameter list 2 SVC return code
RX 0203	DFHRXDM	Exc	Error in CICS SVC	1 SVC parameter list 2 SVC return code
RX 0211	DFHRXUW	1	GETBefore CICS SVC	1 SVC parameter list
RX 0212	DFHRXUW	1	After CICS SVC	1 SVC parameter list 2 SVC return code
RX 0213	DFHRXUW	Exc	Error in CICS SVC	1 SVC parameter list 2 SVC return code
RX 0301	DFHRXDM	1	Notification exit event	None

Table 129. RRMS domain trace entries (continued)

Point ID	Module	Lvl	Type	Data
RX 0302	DFHRXDM	1	Resync ECB posted	None
RX 0302	DFHRXDM	1	Entry	1 RXUW parameter list
RX 0402	DFHRXUW	1	Exit	1 RXUW parameter list
RX 0403	DFHRXUW	Exc	Invalid format	1 RXUW parameter list
RX 0404	DFHRXUW	Exc	Invalid function	1 RXUW parameter list
RX 0405	DFHRXUW	Exc	UR not added	1 RXUW parameter list
RX 0406	DFHRXUW	Exc	RRMS error	1 RXUW parameter list
RX 0407	DFHRXUW	Exc	Wrong pass token	1 RXUW parameter list
RX 0408	DFHRXUW	Exc	Express interest error	1 RXUW parameter list
RX 0409	DFHRXUW	Exc	Add link error	1 RXUW parameter list
RX 040A	DFHRXUW	Exc	Userid inconsistent	1 Incorrect userid 2 Expected userid
RX 040B	DFHRXUW	Exc	TRANSID inconsistent	1 Incorrect transaction id 2 Expected transaction id
RX 040C	DFHRXUW	Exc	Client address invalid	1 Client address
RX 040D	DFHRXUW	Exc	RRMS not open	None
RX 040E	DFHRXDM	1	Set logical unit of work identifier	1 Logical unit of work identifier
RX 0501	DFHRXXRM	1	Entry	1 Exit Number 2 Unit of Recovery ID 3 Exit flags For EXIT_FAILED exit: Failed Exit number Exit Failure reason Abend code or return code Abend reason code
RX 0502	DFHRXXRM	1	Exit	1 Exit number 2 Unit of Recovery ID 3 Exit return code
RX 0601	DFHRXXRG	1	Entry	1 Exit number 2 Global data 3 Reason exit is driven
RX 0602	DFHRXXRG	1	Exit	1 Exit number 2 Exit return code
RX 0701	DFHRXSVC	1	Call to RRMS	1 RRMS service 2 RRMS return code

Scheduler domain trace points

Table 130. Scheduler domain trace points

Point ID	Module	Lvl	Type	Data
SH 0101	DFHSHDM	SH 1	Entry	1 DMDM parameter list
SH 0102	DFHSHDM	SH 1	Exit	1 DMDM parameter list
SH 0103	DFHSHDM	Exc	Recovery	1 DMDM parameter list 2 Kernel error data
SH 0104	DFHSHDM	Exc	Invalid format	1 DMDM parameter list
SH 0105	DFHSHDM	Exc	Invalid function	1 DMDM parameter list
SH 0106	DFHSHDM	Exc	Failed to unlock the domain	1 DMDM parameter list
SH 0107	DFHSHDM	Exc	Getmain failed	1 DMDM parameter list
SH 0111	DFHSHRQ	SH 1	Entry	1 SHRQ parameter list
SH 0112	DFHSHRQ	SH 1	Exit	1 SHRQ parameter list
SH 0113	DFHSHRQ	Exc	Recovery	1 SHRQ parameter list 2 Kernel error data
SH 0114	DFHSHRQ	Exc	Invalid format	1 SHRQ parameter list
SH 0115	DFHSHRQ	Exc	Invalid function	1 SHRQ parameter list
SH 0116	DFHSHRQ	Exc	Failed to unlock the domain	1 SHRQ parameter list
SH 0117	DFHSHRQ	SH 2	Getmain failed	1 Flattened record 2 Schedule request
SH 0121	DFHSHXM	SH 1	Entry	1 XMAC parameter list 2 Client request block
SH 0122	DFHSHXM	SH 1	Exit	1 XMAC parameter list 2 Client request block
SH 0123	DFHSHXM	Exc	Recovery	1 XMAC parameter list 2 Kernel error data
SH 0124	DFHSHXM	Exc	Invalid format	1 XMAC parameter list
SH 0125	DFHSHXM	Exc	Invalid function	1 XMAC parameter list
SH 0126	DFHSHXM	Exc	Failed to unlock the domain	1 XMAC parameter list
SH 0131	DFHSHRM	SH 1	Entry	1 RMRO, RMDE or RMKP parameter list
SH 0132	DFHSHRM	SH 1	Exit	1 RMRO, RMDE or RMKP parameter list

Table 130. Scheduler domain trace points (continued)

Point ID	Module	Lvl	Type	Data
SH 0133	DFHSHRM	Exc	Recovery	1 RMRO, RMDE or RMKP parameter list 2 Kernel error data
SH 0134	DFHSHRM	Exc	Invalid format	1 RMRO, RMDE or RMKP parameter list
SH 0135	DFHSHRM	Exc	Invalid function	1 RMRO parameter list
SH 0136	DFHSHRM	Exc	Invalid function	1 RMDE parameter list
SH 0137	DFHSHRM	Exc	Invalid function	1 RMKP parameter list
SH 0138	DFHSHRM	Exc	Unrecognised log record	1 RMDE parameter list
SH 0139	DFHSHRM	Exc	Multiple log record	1 RMDE parameter list
SH 0141	DFHSHRT	SH 1	Entry	1 SHRT parameter list
SH 0142	DFHSHRT	SH 1	Exit	1 SHRT parameter list
SH 0143	DFHSHRT	Exc	Recovery	1 SHRT parameter list 2 Kernel error data
SH 0144	DFHSHRT	Exc	Invalid format	1 SHRT parameter list
SH 0145	DFHSHRT	Exc	Invalid function	1 SHRT parameter list
SH 0146	DFHSHRT	Exc	Failed to unlock the domain	1 SHRT parameter list
SH 0151	DFHSHPR	SH 1	Entry	1 SHPR parameter list
SH 0152	DFHSHPR	SH 1	Exit	1 SHPR parameter list
SH 0153	DFHSHPR	Exc	Recovery	1 SHPR parameter list 2 Kernel error data
SH 0154	DFHSHPR	Exc	Invalid format	1 SHPR parameter list
SH 0155	DFHSHPR	Exc	Invalid function	1 SHPR parameter list
SH 0166	DFHSHPR	Exc	Failed to unlock the domain	1 SHPR parameter list
SH 0161	DFHSHRR	SH 1	Entry	1 SHRR parameter list
SH 0162	DFHSHRR	SH 1	Exit	1 SHRR parameter list
SH 0163	DFHSHRR	Exc	Recovery	1 SHRR parameter list 2 Kernel error data
SH 0164	DFHSHRR	Exc	Invalid format	1 SHRR parameter list
SH 0165	DFHSHRR	Exc	Invalid function	1 SHRR parameter list
SH 0166	DFHSHRR	Exc	Failed to unlock the domain	1 SHRR parameter list

Table 130. Scheduler domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
SH 0201	DFHSHVP1	SH 1	Entry	1	Response code
SH 0202	DFHSHVP1	SH 1	Exit	1	Response code
SH 0203	DFHSHVP1	Exc	Recovery	1 2	Response code Kernel error data
SH 0301	DFHSHOFI	SH 1	Entry	1	Response code
SH 0302	DFHSHOFI	SH 1	Exit	1	Response code
SH 0303	DFHSHOFI	Exc	Recovery	1 2	Response code Kernel error data
SH 0401	DFHSHRE1	SH 2	Entry	1	Response code
SH 0402	DFHSHRE1	SH 2	Exit	1	Response code
SH 0403	DFHSHRE1	Exc	Getmain failed	1	Response code
SH 0404	DFHSHRE1	Exc	Recovery	1 2	Response code Kernel error data
SH 0501	DFHSHRT1	SH 2	Entry	1	Response code
SH 0502	DFHSHRT1	SH 2	Exit	1	Response code
SH 0503	DFHSHRT1	Exc	Recovery	1 2	Response code Kernel error data
SH 0504	DFHSHRT1	Exc	PAGP Get parameters call failed	1	Response code
SH 0505	DFHSHRT1	Exc	Getmain failed	1	Response code
SH 0511	DFHSHRT2	SH 2	Entry	1	Response code
SH 0512	DFHSHRT2	SH 2	Exit	1	Response code
SH 0513	DFHSHRT2	Exc	Recovery	1 2	Response code Kernel error data
SH 0514	DFHSHRT2	Exc	Failed to link to the routing URM	1	Response code
SH 0601	DFHSHQP	Exc	Failed to add request to pending queue	1	SHPR parameter list
SH 0602	DFHSHQP	Exc	Getmain failed	1	SHPR parameter list
SH 0603	DFHSHQP	Exc	Delete of a request from the pending queue failed	1	SHPQ parameter
SH 0701	DFHSHTI	SH 1	Entry	1	TISR parameter list
SH 0702	DFHSHTI	SH 1	Exit	1	TISR parameter list
SH 0703	DFHSHTI	Exc	Recovery	1 2	TISR parameter list Kernel error data

Table 130. Scheduler domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
SH 0704	DFHSHTI	Exc	Invalid function	1	SHTI parameter list
SH 0705	DFHSHTI	Exc	Invalid format	1	TISR parameter list
SH 0801	DFHSHRQ1	SH 1	Entry	1	Response code
SH 0802	DFHSHRQ1	SH 1	Exit	1	Response code
SH 0803	DFHSHRQ1	Exc	Recovery	1 2	Response code Kernel error data
SH 0804	DFHSHRQ1	Exc	Getmain failed	1	Response code

Storage manager domain trace points

Table 131. Storage manager domain trace points

Point ID	Module	Lvl	Type	Data	
SM 0101	DFHSMMDM	SM 1	Entry	1	DMDM parameter list
SM 0102	DFHSMMDM	SM 1	Exit	1	DMDM parameter list
SM 0103	DFHSMMDM	Exc	Recovery	1 2	DMDM parameter list Kernel error data
SM 0104	DFHSMMDM	Exc	Insufficient MVS storage for SMA	1 2	DMDM parameter list Storage requested
SM 0109	DFHSMMDM	Exc	Insufficient MVS storage for SCA	1 2	DMDM parameter list Storage requested
SM 010A	DFHSMMDM	Exc	Insufficient MVS storage for SCQ	1 2	DMDM parameter list Storage requested
SM 010C	DFHSMMDM	Exc	MVS store clock failure	1	DMDM parameter list
SM 010D	DFHSMMDM	Exc	Insufficient MVS storage for STAB	1 2	DMDM parameter list Storage requested
SM 010E	DFHSMMDM	Exc	Insufficient storage SMX	1 2	DMDM parameter list Storage length
SM 010F	DFHSMMDM	Exc	Invalid format	1	DMDM parameter list
SM 0110	DFHSMMDM	Exc	Invalid function	1	DMDM parameter list
SM 0111	DFHSMMDM	Exc	DSALIMIT GETMAIN request failure	1 2	DMDM parameter list Storage length
SM 0112	DFHSMMDM	Exc	EDSALIMIT GETMAIN request failure	1 2	DMDM parameter list Storage length
SM 0113	DFHSMMDM	Exc	DSALIMIT default GETMAIN failure	1 2	DMDM parameter list Storage length

Table 131. Storage manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data
SM 0114	DFHSMDM	Exc	EDSALIMIT default GETMAIN failure	1 DMDM parameter list 2 Storage length
SM 0115	DFHSMDM	Exc	SVC call failed	1 SMAF parameter list 2 Kernel error code 3 Kernel error reason
SM 0201	DFHSMAD	SM 1	Entry	1 SMAD parameter list
SM 0202	DFHSMAD	SM 1	Exit	1 SMAD parameter list
SM 0203	DFHSMAD	Exc	Recovery	1 SMAD parameter list 2 Kernel error data
SM 0204	DFHSMAD	Exc	Invalid format	1 SMAD parameter list
SM 0205	DFHSMAD	Exc	Invalid function	1 SMAD parameter list
SM 0206	DFHSMAD	Exc	Insufficient MVS storage	1 SMAD parameter list
SM 0207	DFHSMAD	Exc	Subpool not empty	1 SMAD parameter list
SM 0208	DFHSMAD	Exc	Invalid subpool token	1 SMAD parameter list
SM 0301	DFHSMGF	SM 1	Entry	1 SMGF parameter list 2 SCA name
SM 0302	DFHSMGF	SM 1	Exit	1 SMGF parameter list 2 SCA name
SM 0303	DFHSMGF	Exc	Recovery	1 SMGF parameter list 2 Kernel error data
SM 0304	DFHSMGF	Exc	Invalid function	1 SMGF parameter list 2 SCA name
SM 0305	DFHSMGF	Exc	Invalid address	1 SMGF parameter list 2 SCA name
SM 0306	DFHSMGF	Exc	Insufficient MVS storage	1 SMGF parameter list 2 SCA name
SM 030A	DFHSMGF	Exc	Insufficient storage	1 SMGF parameter list 2 SCA name
SM 030B	DFHSMGF	Exc	Storage zone check fail	1 SMGF parameter list 2 Address of storage element 3 First 16 bytes of storage element 4 Last 16 bytes of storage element
SM 030C	DFHSMGF	Exc	Invalid initial image	1 SMGF parameter list 2 SCA name

Table 131. Storage manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
SM 030D	DFHSMGF	Exc	Quickcell GETMAIN invalid QPF	1 2	SMGF parameter list SCA name
SM 030E	DFHSMGF	Exc	Quickcell FREEMAIN invalid QPH	1 2	SMGF parameter list SCA name
SM 030F	DFHSMGF	Exc	Quickcell FREEMAIN QPF already free	1 2	SMGF parameter list SCA name
SM 0310	DFHSMGF	Exc	Quickcell FREEMAIN invalid free chain	1 2	SMGF parameter list SCA name
SM 0311	DFHSMGF	Exc	Invalid storage class GETMAIN	1	SMGF parameter list
SM 0312	DFHSMGF	Exc	Invalid storage class FREEMAIN	1	SMGF parameter list
SM 0313	DFHSMGF	Exc	No transaction environment GETMAIN	1	SMGF parameter list
SM 0314	DFHSMGF	Exc	No transaction environment FREEMAIN	1	SMGF parameter list
SM 0315	DFHSMGF	Exc	Invalid FREEMAIN address stg class	1	SMGF parameter list
SM 0316	DFHSMGF	Exc	Pages not owned free chain	1 2	SMGF parameter list SCA name
SM 0317	DFHSMGF	Exc	Next SCF overlay free chain	1 2	SMGF parameter list SCA name
SM 0318	DFHSMGF	Exc	Previous SCF overlay free chain	1 2	SMGF parameter list SCA name
SM 0319	DFHSMGF	Exc	Stg violation PCT increment failure	1	SMGF parameter list
SM 031C	DFHSMGF	SM 1	EXIT - storage freeze active	1 2	SMGF parameter list Element address
SM 0401	DFHSMRSR	SM 1	Entry	1	SMSR parameter list
SM 0402	DFHSMRSR	SM 1	Exit	1	SMSR parameter list
SM 0403	DFHSMRSR	Exc	Recovery	1 2	SMSR parameter list Kernel error data
SM 0404	DFHSMRSR	Exc	Invalid format	1	SMSR parameter list
SM 0405	DFHSMRSR	Exc	Invalid function	1	SMSR parameter list
SM 0406	DFHSMRSR	Exc	Lock error	1	SMSR parameter list
SM 0407	DFHSMRSR	Exc	Unlock error	1	SMSR parameter list
SM 0601	DFHSMCCI	SM 1	Entry	1	SMMC parameter list
SM 0602	DFHSMCCI	SM 1	Exit	1	SMMC parameter list

Table 131. Storage manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data
SM 0603	DFHSMCI	Exc	Recovery	1 SMMC parameter list 2 Kernel error data
SM 0801	DFHMSY	SM 1	Entry	1 DSAT parameter list
SM 0802	DFHMSY	SM 1	Exit	1 DSAT parameter list
SM 0803	DFHMSY	Exc	Recovery	1 DSAT parameter list 2 Kernel error data
SM 0804	DFHMSY	Exc	Invalid format	1 DSAT parameter list
SM 0805	DFHMSY	Exc	Invalid function	1 DSAT parameter list
SM 0808	DFHMSY	SM 1	Before SM system task suspend	
SM 0809	DFHMSY	SM 1	After SM system task resume	
SM 080A	DFHMSY	Exc	Short on storage in named DSA	1 DSA name (CDSA, UDSA, SDSA, RDSA, ESDSA, ECDSA, EUDSA, ERDSA) 2 Number of free bytes in this DSA 3 Number of cushion bytes in this DSA 4 Number of tasks suspended for storage in this DSA
SM 080B	DFHMSY	Exc	No longer short on storage in named DSA	1 DSA name (CDSA, UDSA, SDSA, RDSA, ESDSA, ECDSA, EUDSA, ERDSA) 2 Number of free bytes in this DSA 3 Number of cushion bytes in this DSA 4 Number of tasks suspended for storage in this DSA
SM 0901	DFHSMCK	SM 1	Entry	1 SMCK parameter list
SM 0902	DFHSMCK	SM 1	Exit	1 SMCK parameter list
SM 0903	DFHSMCK	Exc	Recovery	1 SMCK parameter list 2 Kernel error data
SM 0904	DFHSMCK	Exc	Invalid format	1 SMCK parameter list
SM 0905	DFHSMCK	Exc	Invalid function	1 SMCK parameter list
SM 0906	DFHSMCK	Exc	Lock error	1 SMCK parameter list
SM 0907	DFHSMCK	Exc	Unlock error	1 SMCK parameter list

Table 131. Storage manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
SM 090A	DFHSMCK	Exc	SAA check failed for TP storage	1	SMCK parameter list
				2	Address of storage element
				3	First 16 bytes of storage element
				4	Last 16 bytes of storage element
SM 0910	DFHSMCK	Exc	SAA address not on 8-byte boundary	1	Parameter list
				2	Subpool name
				3	SAA address
SM 0911	DFHSMCK	Exc	SAA address not in DSA	1	Parameter list
				2	Subpool name
				3	SAA address
SM 0912	DFHSMCK	Exc	SAA address not in page owned by subpool	1	Parameter list
				2	Subpool name
				3	SAA address
SM 0913	DFHSMCK	Exc	Length in SAA zero	1	Parameter list
				2	Subpool name
				3	SAA storage, 16 bytes (code should use length of TPE)
SM 0914	DFHSMCK	Exc	Length in SAA not multiple	1	Parameter list
				2	Subpool name
				3	SAA storage, 16 bytes (code should use length of TPE)
SM 0915	DFHSMCK	Exc	Duplicate SAA not in DSA	1	Parameter list
				2	Subpool name
				3	SAA storage, 16 bytes (code should use length of TPE)
SM 0916	DFHSMCK	Exc	Length in SAA invalid	1	Parameter list
				2	Subpool name
				3	SAA storage, 16 bytes (code should use length of TPE)
SM 0917	DFHSMCK	Exc	Storage class in SAA invalid	1	Parameter list
				2	Subpool name
				3	SAA storage, 16 bytes (code should use length of TPE)
SM 0930	DFHSMCK	Exc	SAA recovered	1	SMCK parameter list
				2	Initial SAA before recovery
				3	Doubleword of storage following initial SAA
				4	Doubleword of storage preceding duplicate SAA
				5	Duplicate SAA before recovery
				6	Initial SAA after recovery
				7	Duplicate SAA after recovery

Table 131. Storage manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data
SM 0931	DFHSMCK	Exc	SAA In TCTTE recovered	1 SMCK parameter list 2 Address of TCTTE 3 TCTTETI 4 TIOA chain header before recovery 5 TIOA chain header after recovery
SM 0932	DFHSMCK	Exc	Storage zone check failed	1 SMCK parameter list 2 Subpool name 3 Address of storage 4 First 128 bytes of storage element 5 Last 16 bytes of storage element
SM 0933	DFHSMCK	Exc	Loop in TIOA chain	1 SMCK parameter list
SM 0934	DFHSMCK	Exc	Storage check zones recovered	1 SMCK parameter list 2 Leading check zone before recovery 3 First 8 bytes of storage element 4 Last 8 bytes of storage element 5 Trailing check zone before recovery 6 Leading check zone after recovery 7 Trailing check zone after recovery
SM 0935	DFHSMCK	Exc	Stg violation PCT increment failure	1 SMCK parameter list
SM 0936	DFHSMCK	Exc	Stg violation TCT increment failure	1 SMCK parameter list
SM 0A01	DFHSMST	SM 1	Entry	1 STST parameter list
SM 0A02	DFHSMST	SM 1	Exit	1 STST parameter list
SM 0A03	DFHSMST	Exc	Recovery	1 STST parameter list 2 Kernel error data
SM 0A04	DFHSMST	Exc	Invalid format	1 STST parameter list
SM 0A05	DFHSMST	Exc	Invalid function	1 STST parameter list
SM 0A06	DFHSMST	Exc	Invalid parameters	1 STST parameter list
SM 0A07	DFHSMST	Exc	Lock error	1 STST parameter list
SM 0A08	DFHSMST	Exc	Unlock error	1 STST parameter list
SM 0A09	DFHSMST	Exc	Invalid buffer	1 STST parameter list
SM 0C01	DFHSMMG	SM 1	Entry	1 SMMG parameter list

Table 131. Storage manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
SM 0C02	DFHSMMG	SM 1	Exit	1	SMMG parameter list
SM 0C03	DFHSMMG	Exc	Recovery	1 2	SMMG parameter list Kernel error data
SM 0C04	DFHSMMG	Exc	Invalid TCTTE_ADDRESS parm	1	SMMG parameter list
SM 0C05	DFHSMMG	Exc	Invalid STORAGE_CLASS parm	1	SMMG parameter list
SM 0C06	DFHSMMG	Exc	Invalid length for CICS24 storage	1	SMMG parameter list
SM 0C08	DFHSMMG	Exc	Invalid length for SHARED_CICS24	1	SMMG parameter list
SM 0C09	DFHSMMG	Exc	Invalid length for TP storage	1	SMMG parameter list
SM 0C0A	DFHSMMG	Exc	MVS GETMAIN failed	1	SMMG parameter list
SM 0C0B	DFHSMMG	Exc	Invalid length for USER24 storage	1	SMMG parameter list
SM 0C0C	DFHSMMG	Exc	GETMAIN with SUSPEND(NO) failed	1	SMMG parameter list
SM 0C0E	DFHSMMG	Exc	Invalid length for USER storage	1	SMMG parameter list
SM 0C11	DFHSMMG	Exc	Invalid length for SHARED_USER24	1	SMMG parameter list
SM 0C12	DFHSMMG	Exc	Invalid length for SHARED_USER	1	SMMG parameter list
SM 0C13	DFHSMMG	Exc	Function is not GETMAIN	1	SMMG parameter list
SM 0C14	DFHSMMG	Exc	Invalid length for CICS storage	1	SMMG parameter list
SM 0C15	DFHSMMG	Exc	Invalid length for SHARED_CICS storage	1	SMMG parameter list
SM 0C16	DFHSMMG	Exc	Invalid length for TASK storage	1	SMMG parameter list
SM 0C17	DFHSMMG	Exc	Invalid length for TASK24 storage	1	SMMG parameter list
SM 0C18	DFHSMMG	Exc	Invalid length for CICS24_SAA storage	1	SMMG parameter list
SM 0C19	DFHSMMG	Exc	Invalid length for SHARED_CICS24_SAA storage	1	SMMG parameter list
SM 0C1A	DFHSMMG	Exc	No transaction environment FREEMAIN	1	SMMC parameter list
SM 0D01	DFHSMMF	SM 1	Entry	1	SMMF parameter list
SM 0D02	DFHSMMF	SM 1	Exit	1 2 3	SMMF parameter list Storage class First 8 bytes of storage element
SM 0D03	DFHSMMF	Exc	Recovery	1	SMMF parameter list

Table 131. Storage manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data
SM 0D05	DFHSMMF	Exc	SAA check failed during FREEMAIN of terminal storage	1 SMMF parameter list 2 Storage address 3 Leading SAA plus user data. Total min length is 24 bytes, max is truncated to 128 bytes 4 Last 8 bytes of user data plus 8-byte trailing SAA
SM 0D06	DFHSMMF	Exc	FREEMAIN address not multiple of 8	1 SMMF parameter list
SM 0D07	DFHSMMF	Exc	FREEMAIN address out of range	1 SMMF parameter list
SM 0D08	DFHSMMF	Exc	Invalid FREEMAIN address	1 SMMF parameter list
SM 0D09	DFHSMMF	Exc	TCTTE_ADDRESS not supplied	1 SMMF parameter list
SM 0D0A	DFHSMMF	Exc	TERMINAL storage address not found	1 SMMF parameter list
SM 0D0C	DFHSMMF	Exc	Invalid FREEMAIN address	1 SMMF parameter list
SM 0D0D	DFHSMMF	Exc	MVS GETMAIN failed	1 SMMF parameter list
SM 0D10	DFHSMMF	Exc	Not FREEMAIN function	1 SMMF parameter list
SM 0D11	DFHSMMF	Exc	Storage zone check failed	1 SMMC parameter list 2 Address of storage element 3 First 16 bytes of storage element 4 Last 16 bytes of storage element
SM 0D12	DFHSMMF	Exc	Invalid exec key	1 SMMF parameter list
SM 0D13	DFHSMMF	Exc	Attempted to freemain storage not owned by storage subpool	1 SMMF parameter list
SM 0D14	DFHSMMF	Exc	Next SCF has been overlayed	1 SMMF parameter list
SM 0D15	DFHSMMF	Exc	Previous SCF has been overlayed	1 SMMF parameter list
SM 0D17	DFHSMMF	Exc	Stg violation TCT increment failure	1 SMMC parameter list
SM 0D18	DFHSMMF	Exc	No transaction environment FREEMAIN	1 SMMC parameter list
SM 0D19	DFHSMMF	SM 1	EXIT - storage freeze active	1 SMMC parameter list 2 Element address 3 Storage class
SM 0E01	DFHSMMC2	SM 1	Entry	1 SMMC2 parameter list
SM 0E02	DFHSMMC2	SM 1	Exit	1 SMMC2 parameter list
SM 0E03	DFHSMMC2	Exc	Recovery	1 SMMC2 parameter list 2 Kernel error data
SM 0E04	DFHSMMC2	Exc	Invalid function	1 SMMC2 parameter list

Table 131. Storage manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
SM 0E05	DFHSMC2	SM 1	Event - FREEMAIN element	1	Address
SM 0E06	DFHSMC2	Exc	Invalid storage element for TP storage	1 2 3 4	SMMC2 parameter list Address of leading SAA First 16 bytes of storage element Last 16 bytes of storage element
SM 0E08	DFHSMC2	Exc	MVS GETMAIN failed	1	SMMC2 parameter list
SM 0E0A	DFHSMC2	Exc	Invalid address passed to FREEMAIN subroutine	1	SMMC2 parameter list
SM 0E0B	DFHSMC2	Exc	Storage zone check failed	1 2 3 4	SMMC parameter list Address of storage element First 16 bytes of storage element Last 16 bytes of storage element
SM 0E0D	DFHSMC2	Exc	Pages not owned	1	SMMC2 parameter list
SM 0E0E	DFHSMC2	Exc	Next SCF overlay	1	SMMC2 parameter list
SM 0E0F	DFHSMC2	Exc	Previous SCF overlay	1	SMMC2 parameter list
SM 0E10	DFHSMC2	Exc	Stg violation PCT increment failure	1	SMMC parameter list
SM 0E11	DFHSMC2	Exc	Stg violation TCT increment failure	1	SMMC parameter list
SM 0E12	DFHSMC2	SM 1	No transaction environment	1	SMCC parameter list
SM 0F01	DFHSMAR	Exc	Entry	1	SMAR parameter list
SM 0F02	DFHSMAR	SM 1	Exit	1 2 3	SMAR parameter list SMX address SMX contents
SM 0F03	DFHSMAR	Exc	Recovery	1 2	SMAR parameter list Kernel error data
SM 0F04	DFHSMAR	Exc	Invalid format	1	SMAR parameter list
SM 0F05	DFHSMAR	Exc	Invalid function	1	SMAR parameter list
SM 0F06	DFHSMAR	Exc	XMIQ call failed (set_transaction_token)	1	SMAR parameter list
SM 0F07	DFHSMAR	Exc	XMIQ call failed (inquire_transaction)	1	SMAR parameter list
SM 0F08	DFHSMAR	Exc	XMIQ call failed (inquire_transaction_token)	1	SMAR parameter list
SM 0F09	DFHSMAR	Exc	Insufficient storage for SCAs	1	SMAR parameter list
SM 0F0A	DFHSMAR	Exc	Insufficient storage for SCQs	1	SMAR parameter list

Table 131. Storage manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data
SM 0F0B	DFHSMAR	Exc	Insufficient storage for SMXs	1 SMAR parameter list
# SM 0F0C	DFHSMAR	Exc	Storage check failure	1 SMAR parameter list
#				2 Address of storage element
#				3 Length of storage element
#				4 First 512 bytes (max) of storage element
#				5 Last 512 bytes (max) of storage element
#				6 Data preceding storage element (1K max)
#				7 Data following storage element (1K max)
#				
SM 0F0D	DFHSMAR	SM 1	FREEMAIN storage element	1 Storage address
				2 Storage class
				3 First double word
SM 0F0E	DFHSMAR	Exc	Storage violation (PCT increment failure)	1 SMAR parameter list
SM 0F0F	DFHSMAR	Exc	Storage violation (TCTTE increment failure)	1 SMAR parameter list
SM 1001	DFHSMSQ	SM 1	Entry	1 SMSQ parameter list
SM 1002	DFHSMSQ	SM 1	Exit	1 SMSQ parameter list
SM 1003	DFHSMSQ	Exc	Recovery	1 SMSQ parameter list
				2 Kernel error data
SM 1004	DFHSMSQ	Exc	Invalid format	1 SMSQ parameter list
SM 1005	DFHSMSQ	Exc	Invalid function	1 SMSQ parameter list
SM 1006	DFHSMSQ	Exc	Inquire suspend failure (DSSR)	1 SMSQ parameter list
SM 1007	DFHSMSQ	Exc	Pre-suspend for storage	1 SMSQ parameter list
				2 SQE
SM 1008	DFHSMSQ	Exc	Post-suspend for storage	1 SMSQ parameter list
				2 SQE
SM 1009	DFHSMSQ	Exc	GETMAIN failure for SQE	1 SMSQ parameter list
SM 1101	DFHSMPP	SM 2	Entry	1 SMPP parameter list
SM 1102	DFHSMPP	SM 2	Exit	1 SMPP parameter list
SM 1103	DFHSMPP	Exc	Recovery	1 SMPP parameter list
				2 Kernel error data
SM 1104	DFHSMPP	Exc	Invalid format	1 SMPP parameter list
SM 1105	DFHSMPP	Exc	Invalid function	1 SMPP parameter list
SM 1106	DFHSMPP	Exc	Insufficient storage for PPA	1 SMPP parameter list

Table 131. Storage manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
SM 1107	DFHSMPP	Exc	Insufficient storage for PPX	1	SMPQ parameter list
SM 1109	DFHSMPP	Exc	Insufficient storage for SAT	1	SMPQ parameter list
SM 110D	DFHSMPP	Exc	Insufficient storage for CTN	1	SMPQ parameter list
SM 110E	DFHSMPP	SM 2	Delete empty extent	1 2 3 4	DSA name PPX address Extent start address Extent end address
SM 110F	DFHSMPP	SM 2	Before SVC call	1	SMAF parameter list
SM 1110	DFHSMPP	SM 2	After SVC call	1	SMAF parameter list
SM 1111	DFHSMPP	Exc	Freemain DSALIMIT storage failed	1	SMPQ parameter list
SM 1112	DFHSMPP	Exc	SVC call failed	1	SMAF parameter list
SM 1201	DFHSMPP	SM 2	Entry	1	SMPQ parameter list
SM 1202	DFHSMPP	SM 2	Exit	1	SMPQ parameter list
SM 1203	DFHSMPP	Exc	Recovery	1 2	SMPQ parameter list Kernel error data
SM 1204	DFHSMPP	Exc	Invalid format for SAT	1	SMPQ parameter list
SM 1205	DFHSMPP	Exc	Invalid function for SAT	1	SMPQ parameter list
SM 1206	DFHSMPP	Exc	Insufficient storage for req	1 2 2	SMPQ parameter list Subpool name DSA name
SM 1207	DFHSMPP	Exc	Invalid address	1	SMPQ parameter list
SM 1208	DFHSMPP	Exc	Insufficient storage for CTN	1	SMPQ parameter list
SM 1209	DFHSMPP	SM 2	Before SVC call	1	SMAF parameter list
SM 120A	DFHSMPP	SM 2	After SVC call	1	SMAF parameter list
SM 120B	DFHSMPP	Exc	SVC call failed	1	SMPQ parameterlist
SM 3001	DFHSMPP	SM 2	Entry	1	SMSU parameter list
SM 3002	DFHSMPP	SM 2	Exit	1	SMSU parameter list
SM 3003	DFHSMPP	Exc	Recovery	1 2	SMSU parameter list Kernel error data
SM 3004	DFHSMPP	Exc	Invalid function	1	SMSU parameter list
SM 3005	DFHSMPP	Exc	Invalid format	1	SMSU parameter list

Table 131. Storage manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
SM 3006	DFHSMSU	Exc	MVS getmain SUA failure	1	SMSU parameter list
SM 3007	DFHSMSU	Exc	ALESERV add failure	1	SMSU parameter list
SM 3008	DFHSMSU	Exc	Invalid TCB for allocate	1	SMSU parameter list
SM 3009	DFHSMSU	SM 2	Event - pre subspace create	1	SMSU parameter list
SM 300A	DFHSMSU	SM 2	Event - post subspace create	1	SMSU parameter list
SM 300B	DFHSMSU	Exc	Create subspace failure	1	SMSU parameter list
SM 300C	DFHSMSU	Exc	Invalid TCB for delete subspace	1	SMSU parameter list
SM 300D	DFHSMSU	SM 2	Event - pre subspace delete	1	SMSU parameter list
SM 300E	DFHSMSU	SM 2	Event - post subspace delete	1	SMSU parameter list
SM 300F	DFHSMSU	Exc	Delete subspace failure	1	SMSU parameter list
SM 3011	DFHSMSU	Exc	Assign failure	1	SMSU parameter list
SM 3013	DFHSMSU	Exc	Add subspace for steal failure	1	SMSU parameter list
SM 3014	DFHSMSU	Exc	ACESERV add failure	1	SMSU parameter list
SM 3016	DFHSMSU	Exc	Delete subspace failure	1	SMSU parameter list
SM 3018	DFHSMSU	Exc	Event - steal ALET	1 2	SUA stealer SUA victim
SM 3019	DFHSMSU	Exc	Unassign failure	1	SMSU parameter list
SM 301A	DFHSMSU	Exc	Invalid format	1	SMSU parameter list
SM 301B	DFHSMSU	Exc	Invalid parameter list format	1	SMSU parameter list
SM 301C	DFHSMSU	SM 2	Event - pre-ASSIGN	1 2	page address Number of pages
SM 301D	DFHSMSU	SM 2	Event - post-ASSIGN	1	ASSIGN RC
SM 301E	DFHSMSU	SM 2	Event - pre-UNASSIGN	1 2	page address Number of pages
SM 301F	DFHSMSU	SM 2	Event - post-UNASSIGN	1	UNASSIGN RC
SM 3020	DFHSMSU	Exc	Change mode failure (2)	1	SMSU parameter list
SM 3021	DFHSMSU	Exc	Invalid TCB for release subspace	1	SMSU parameter list
SM 3022	DFHSMSU	Exc	ASSIGN failure abend	1	SMSU parameter list
SM 3023	DFHSMSU	Exc	UNASSIGN failure abend	1	SMSU parameter list

Table 131. Storage manager domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
SM 3025	DFHSMSTU	Exc	No ALET to steal	1	SMSU parameter list
SM 3026	DFHSMSTU	Exc	SVC call failure	1	SMSU parameter list
SM 3027	DFHSMSTU	SM 2	Unassign multiple storage ranges	1 2 3 4	SUA address List of storage ranges Number of storage ranges SUA contents
SM F101	DFHSMSCP	SM 1	Entry	1	SM overlay for TCA
SM F102	DFHSMSCP	SM 1	Exit	1 2	SM overlay for TCA on entry SM overlay for TCA on exit
SM F104	DFHSMSCP	Exc	Invalid request	1	SM overlay for TCA

Socket domain

Table 132. Socket domain trace points

Point ID	Module	Lvl	Type	Data	
SO 0101	DFHSODM	SO 1	Entry	1	DMDM parameter list
SO 0102	DFHSODM	SO 1	Exit	1	DMDM parameter list
SO 0103	DFHSODM	Exc	Recovery	1 2	DMDM parameter list Kernel error data
SO 0104	DFHSODM	Exc	Invalid format	1	DMDM parameter list
SO 0105	DFHSODM	Exc	Invalid function	1	DMDM parameter list
SO 0106	DFHSODM	Exc	Exclusive lock error	1 2	DMDM parameter list LMLM parameter list
SO 0107	DFHSODM	Exc	Exclusive unlock error	1 2	DMDM parameter list LMLM parameter list
SO 0108	DFHSODM	Exc	Storage error	1	DMDM parameter list
SO 0109	DFHSODM	Exc	Shared lock error	1 2	DMDM parameter list LMLM parameter list
SO 0110	DFHSODM	Exc	Shared unlock error	1 2	DMDM parameter list LMLM parameter list
SO 0111	DFHSODM	Exc	Recovery release lock error	1 2	DMDM parameter list LMLM parameter list
SO 0112	DFHSODM	Exc	Dispatcher error	1	DMDM parameter list
SO 0113	DFHSODM	Exc	Directory manager error	1	DMDM parameter list

Table 132. Socket domain trace points (continued)

Point ID	Module	Lvl	Type	Data
SO 0201	DFH SOCK	SO 1	Entry	1 SOCK parameter list 2 Send : sent data
SO 0202	DFH SOCK	SO 1	Exit	1 SOCK parameter list 2 Receive : received data
SO 0203	DFH SOCK	Exc	Recovery	1 SOCK parameter list 2 Kernel error data
SO 0204	DFH SOCK	Exc	Invalid format	1 SOCK parameter list
SO 0205	DFH SOCK	Exc	Invalid function	1 SOCK parameter list
SO 0206	DFH SOCK	Exc	Exclusive lock error	1 SOCK parameter list 2 LMLM parameter list
SO 0207	DFH SOCK	Exc	Exclusive unlock error	1 SOCK parameter list 2 LMLM parameter list
SO 0208	DFH SOCK	Exc	Getmain error	1 SMGF parameter list
SO 0209	DFH SOCK	SO 2	Before asyncio	1 bpx_interface 2 LTE 3 STE 4 AioCb
SO 0210	DFH SOCK	SO 2	After asyncio	1 bpx_interface 2 LTE 3 STE 4 AioCb
SO 0211	DFH SOCK	Exc	Asyncio error	1 bpx_interface 2 LTE 3 STE 4 AioCb
SO 0212	DFH SOCK	SO 2	Before select	1 bpx_interface 2 LTE 3 Read_List 4 Write_List 5 Exception_List 6 ECB
SO 0213	DFH SOCK	SO 2	After select	1 bpx_interface 2 LTE 3 Read_List 4 Write_List 5 Exception_List 6 ECB
SO 0214	DFH SOCK	Exc	Select error	1 bpx_interface 2 LTE 3 Read_List 4 Write_List 5 Exception_List 6 ECB

Table 132. Socket domain trace points (continued)

Point ID	Module	Lvl	Type	Data
SO 0215	DFH SOCK	SO 2	Before socket	1 bpx_interface 2 LTE
SO 0216	DFH SOCK	SO 2	After socket	1 bpx_interface 2 LTE
SO 0217	DFH SOCK	Exc	Socket error	1 bpx_interface 2 LTE
SO 0218	DFH SOCK	SO 2	Before bind	1 bpx_interface 2 LTE 3 Sockaddr
SO 0219	DFH SOCK	SO 2	After bind	1 bpx_interface 2 LTE 3 Sockaddr
SO 0220	DFH SOCK	Exc	Bind error	1 bpx_interface 2 LTE 3 Sockaddr
SO 0221	DFH SOCK	SO 2	Before listen	1 bpx_interface 2 LTE
SO 0222	DFH SOCK	SO 2	After listen	1 bpx_interface 2 LTE
SO 0223	DFH SOCK	Exc	Listen error	1 bpx_interface 2 LTE
SO 0224	DFH SOCK	SO 2	Before accept	1 bpx_interface 2 LTE 3 STE 4 Sockaddr
SO 0225	DFH SOCK	SO 2	After accept	1 bpx_interface 2 LTE 3 STE 4 Sockaddr
SO 0226	DFH SOCK	Exc	Accept error	1 bpx_interface 2 LTE 3 STE 4 Sockaddr
SO 0227	DFH SOCK	SO 2	Before getclientid	1 bpx_interface 2 LTE 3 Clientid
SO 0228	DFH SOCK	SO 2	After getclientid	1 bpx_interface 2 LTE 3 Clientid
SO 0229	DFH SOCK	Exc	Getclientid error	1 bpx_interface 2 LTE 3 Clientid

Table 132. Socket domain trace points (continued)

Point ID	Module	Lvl	Type	Data
SO 0231	DFH SOCK	SO 2	Before takesocket	1 bpx_interface 2 LTE 3 STE 4 Clientid
SO 0232	DFH SOCK	SO 2	After takesocket	1 bpx_interface 2 LTE 3 STE 4 Clientid
SO 0233	DFH SOCK	Exc	Takesocket error	1 bpx_interface 2 LTE 3 STE 4 Clientid
SO 0234	DFH SOCK	SO 2	Before givesocket	1 bpx_interface 2 LTE 3 STE 4 Clientid
SO 0235	DFH SOCK	SO 2	After givesocket	1 bpx_interface 2 LTE 3 STE 4 Clientid
SO 0236	DFH SOCK	Exc	Givesocket error	1 bpx_interface 2 LTE 3 STE 4 Clientid
SO 0237	DFH SOCK	SO 2	Before close	1 bpx_interface 2 LTE 3 STE
SO 0238	DFH SOCK	SO 2	After close	1 bpx_interface 2 LTE 3 STE
SO 0239	DFH SOCK	Exc	Close error	1 bpx_interface 2 LTE 3 STE
SO 0240	DFH SOCK	SO 2	Before setsockopt	1 bpx_interface 2 LTE 3 option_data
SO 0241	DFH SOCK	SO 2	After setsockopt	1 bpx_interface 2 LTE 3 option_data
SO 0242	DFH SOCK	Exc	Setsockopt error	1 bpx_interface 2 LTE 3 option_data
SO 0243	DFH SOCK	Exc	Socket in use	1 SOCK parameter list

Table 132. Socket domain trace points (continued)

Point ID	Module	Lvl	Type	Data
SO 0244	DFH SOCK	Exc	Attach error	1 STE
				2 LTE
SO 0245	DFH SOCK	SO 2	IO wait posted for termination	1 STE
SO 0246	DFH SOCK	Exc	Unknown session token	1 SOCK parameter list
SO 0247	DFH SOCK	Exc	IO error	1 SOCK parameter list
SO 0248	DFH SOCK	Exc	DSSR wait error	1 SOCK parameter list
SO 0249	DFH SOCK	SO 2	Immclose requested	
SO 0250	DFH SOCK	SO 2	Register requested	
SO 0251	DFH SOCK	SO 2	Deregister requested	
SO 0252	DFH SOCK	SO 2	Quiesce requested	
SO 0253	DFH SOCK	SO 2	Terminate requested	
SO 0254	DFH SOCK	Exc	Unknown post code	1 bpx_interface
				2 LTE
				3 ECB
SO 0255	DFH SOCK	SO 2	Before gethostname	1 bpx_interface
				2 Name
SO 0256	DFH SOCK	SO 2	After gethostname	1 bpx_interface
				2 Name
SO 0257	DFH SOCK	Exc	Gethostname error	1 bpx_interface
				2 Name
SO 0258	DFH SOCK	SO 2	TCP/IP inactive	
SO 0260	DFH SOCK	SO 2	Listen subroutine entry	1 SOCK parameter list
SO 0261	DFH SOCK	SO 2	Listen subroutine exit	1 SOCK parameter list
SO 0262	DFH SOCK	Exc	EIO received	1 bpx_interface
				2 LTE
				3 Read_List
				4 Write_List
				5 Exception List
				6 ECB
SO 0263	DFH SOCK	Exc	Accept EIO received	1 bpx_interface
				2 LTE
				3 STE
				4 Sockaddr
SO 0270	DFH SOCK	Exc	Shared lock error	1 SOCK parameter list
				2 LMLM parameter list
SO 0271	DFH SOCK	Exc	Shared unlock error	1 SOCK parameter list
				2 LMLM parameter list
SO 0272	DFH SOCK	Exc	Recovery release lock error	1 SOCK parameter list
				2 LMLM parameter list

Table 132. Socket domain trace points (continued)

Point ID	Module	Lvl	Type	Data
SO 0273	DFH SOCK	Exc	Unknown KE error code	1 SOCK parameter list
SO 0274	DFH SOCK	Exc	Asynco function error	1 bpx_interface 2 LTE 3 STE 4 AioCb
SO 0275	DFH SOCK	Exc	Getmain for STE failure	
SO 0280	DFH SOCK	SO 2	Before iwmsrsrg	1 iw m_parameters
SO 0281	DFH SOCK	SO 2	After iwmsrsrg	1 iw m_parameters
SO 0282	DFH SOCK	Exc	Iwmsrsrg error	1 iw m_parameters
SO 0283	DFH SOCK	SO 2	Before iwmsrdrs	1 iw m_parameters
SO 0284	DFH SOCK	SO 2	After iwmsrdrs	1 iw m_parameters
SO 0285	DFH SOCK	Exc	Iwmsrdrs error	1 iw m_parameters
SO 0290	DFH SOCK	SO 1	Initialize timer entry	
SO 0291	DFH SOCK	SO 1	Initialize timer exit	
SO 0292	DFH SOCK	SO 1	Timer event	
SO 0293	DFH SOCK	SO 1	Monitor data put entry	
SO 0294	DFH SOCK	SO 1	Monitor data put exit	
SO 0295	DFH SOCK	SO 1	Cancel timer entry	
SO 0296	DFH SOCK	SO 1	Cancel timer exit	
SO 0297	DFH SOCK	SO 2	Connection count increment	1 Tcpi service name 2 New connection count
SO 0298	DFH SOCK	SO 2	Connection count decrement	1 Tcpi service name 2 New connection count
SO 0299	DFH SOCK	SO 2	Asynco wakeup	1 LTE 2 STE 3 AioRv 4 AioRc 5 AioRsn
SO 029A	DFH SOCK	SO 2	Before sigprocmask	1 bpx_interface 2 How 3 New_signal_mask 4 Old_signal_mask
SO 029B	DFH SOCK	SO 2	After sigprocmask	1 bpx_interface 2 How 3 New_signal_mask 4 Old_signal_mask
SO 029C	DFH SOCK	Exc	Sigprocmask error	1 bpx_interface 2 How 3 New_signal_mask 4 Old_signal_mask
SO 0301	DFH SORD	SO 1	Entry	1 SORD parameter list

Table 132. Socket domain trace points (continued)

Point ID	Module	Lvl	Type	Data
SO 0302	DFHSORD	SO 1	Exit	1 SORD parameter list
SO 0303	DFHSORD	Exc	Recovery	1 SORD parameter list 2 Kernel error data
SO 0304	DFHSORD	Exc	Invalid format	1 SORD parameter list
SO 0305	DFHSORD	Exc	Invalid function	1 SORD parameter list
SO 0306	DFHSORD	Exc	Lock error	1 SORD parameter list 2 LMLM parameter list
SO 0307	DFHSORD	Exc	Unlock error	1 SORD parameter list 2 LMLM parameter list
SO 0308	DFHSORD	Exc	Storage error	1 SMGF parameter list
SO 0401	DFHSOIS	SO 1	Entry	1 SOIS parameter list
SO 0402	DFHSOIS	SO 1	Exit	1 SOIS parameter list
SO 0403	DFHSOIS	Exc	Recovery	1 SOIS parameter list 2 Kernel error data
SO 0404	DFHSOIS	Exc	Invalid format	1 SOIS parameter list
SO 0405	DFHSOIS	Exc	Invalid function	1 SOIS parameter list
SO 0406	DFHSOIS	Exc	Exclusive lock error	1 SOIS parameter list 2 LMLM parameter list
SO 0407	DFHSOIS	Exc	Exclusive unlock error	1 SOIS parameter list 2 LMLM parameter list
SO 0408	DFHSOIS	Exc	Shared lock error	1 SOIS parameter list 2 LMLM parameter list
SO 0409	DFHSOIS	Exc	Shared unlock error	1 SOIS parameter list 2 LMLM parameter list
SO 0410	DFHSOIS	Exc	Recovery unlock error	1 SOIS parameter list 2 LMLM parameter list
SO 0411	DFHSOIS	Exc	Storage error	1 SMGF parameter list
SO 0412	DFHSOIS	Exc	Unknown KE error code	
SO 0413	DFHSOIS	Exc	CEEPIPI error	1 c_interface
SO 0414	DFHSOIS	Exc	Gethostbyaddr error	1 c_interface
SO 0415	DFHSOIS	Exc	Gethostid error	1 c_interface
SO 0416	DFHSOIS	SO 2	Before CEEPIPI	1 c_interface 2 pipi_table 3 init_sub_dp : runopts

Table 132. Socket domain trace points (continued)

Point ID	Module	Lvl	Type	Data
SO 0417	DFHSOIS	SO 2	After CEEPIPI	1 c_interface 2 pipi_table 3 init_sub_dp : runopts
SO 0418	DFHSOIS	Exc	Dispatcher error	1 SOIS parameter list
SO 0419	DFHSOIS	Exc	Dub error	1 dub_results
SO 0420	DFHSOIS	SO 2	Before sigprocmask	1 bpx_interface 2 How 3 New_signal_mask 3 Old_signal_mask
SO 0421	DFHSOIS	SO 2	After sigprocmask	1 bpx_interface 2 How 3 New_signal_mask 3 Old_signal_mask
SO 0422	DFHSOIS	Exc	Sigprocmask error	1 bpx_interface 2 How 3 New_signal_mask 3 Old_signal_mask
SO 0501	DFHSOUE	SO 1	Entry	1 SOUE parameter list
SO 0502	DFHSOUE	SO 1	Exit	1 SOUE parameter list
SO 0503	DFHSOUE	Exc	Recovery	1 SOUE parameter list 2 Kernel error data
SO 0504	DFHSOUE	Exc	Invalid function	1 SOUE parameter list
SO 0505	DFHSOUE	Exc	Invalid format	1 SOUE parameter list
SO 0506	DFHSOUE	Exc	Lock error	1 SOUE parameter list 2 LMLM parameter list
SO 0507	DFHSOUE	Exc	Unlock error recovery	1 SOUE parameter list 2 LMLM parameter list
SO 0508	DFHSOUE	Exc	Release lock error	1 SOUE parameter list 2 LMLM parameter list
SO 0509	DFHSOUE	Exc	Recovery release lock error	1 SOUE parameter list 2 LMLM parameter list
SO 050A	DFHSOUE	Exc	Unknown KE error code	
SO 0601	DFHSOAD	SO 1	Entry	1 SOAD parameter list
SO 0602	DFHSOAD	SO 1	Exit	1 SOAD parameter list
SO 0603	DFHSOAD	Exc	Recovery	1 SOAD parameter list 2 Kernel error data
SO 0604	DFHSOAD	Exc	Invalid format	1 SOAD parameter list

Table 132. Socket domain trace points (continued)

Point ID	Module	Lvl	Type	Data
SO 0605	DFHSOAD	Exc	Invalid function	1 SOAD parameter list
SO 0606	DFHSOAD	Exc	Unlock error recovery	1 SOAD parameter list 2 LMLM parameter list
SO 0607	DFHSOAD	Exc	Storage error	1 SMGF parameter list
SO 0701	DFHSOTB	SO 1	Entry	1 SOTB parameter list
SO 0702	DFHSOTB	SO 1	Exit	1 SOTB parameter list
SO 0703	DFHSOTB	Exc	Recovery	1 SOTB parameter list 2 Kernel error data
SO 0704	DFHSOTB	Exc	Invalid format	1 SOTB parameter list
SO 0705	DFHSOTB	Exc	Invalid function	1 SOTB parameter list
SO 0706	DFHSOTB	Exc	Unlock error recovery	1 SOTB parameter list 2 LMLM parameter list
SO 0707	DFHSOTB	Exc	Storage error	1 SMGF parameter list
SO 0801	DFHSEOSE	SO 1	Entry	1 SOSE parameter list
SO 0802	DFHSEOSE	SO 1	Exit	1 SOSE parameter list
SO 0803	DFHSEOSE	Exc	Recovery	1 SOSE parameter list 2 Kernel error data
SO 0804	DFHSEOSE	Exc	Invalid format	1 SOSE parameter list
SO 0805	DFHSEOSE	Exc	Invalid function	1 SOSE parameter list
SO 0806	DFHSEOSE	Exc	Lock error	1 SOSE parameter list 2 LMLM parameter list
SO 0807	DFHSEOSE	Exc	Unlock error	1 SOSE parameter list 2 LMLM parameter list
SO 0808	DFHSEOSE	Exc	Storage error	1 SMGF parameter list
SO 0809	DFHSEOSE	SO 2	Before CEEPIPI	1 gsk_interface
SO 080A	DFHSEOSE	SO 2	After CEEPIPI	1 gsk_interface
SO 080B	DFHSEOSE	Exc	CEEPIPI error	1 gsk_interface
SO 080C	DFHSEOSE	Exc	GSK error	1 gsk_interface
SO 080D	DFHSEOSE	Exc	Getmain error	
SO 080E	DFHSEOSE	Exc	Repository error	
SO 080F	DFHSEOSE	Exc	Directory error	1 SOSE parameter list
SO 0901	DFHSOXM	SO 1	Entry	1 XMXM parameter list

Table 132. Socket domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
SO 0902	DFHSOXM	SO 1	Exit	1	MXM parameter list
SO 0903	DFHSOXM	Exc	Invalid function	1	MXM Parameter list
SO 0904	DFHSOXM	Exc	Invalid format	1	MXM parameter list
SO 0905	DFHSOXM	Exc	Recovery	1 2	MXM parameter list Kernel error data
SO 0A01	DFHSOST	SO 1	Entry	1	STST parameter list
SO 0A02	DFHSOST	SO 1	Exit	1	STST parameter list
SO 0A03	DFHSOST	Exc	Recovery	1 2	STST parameter list Kernel error data
SO 0A04	DFHSOST	Exc	Invalid format	1	STST parameter list
SO 0A05	DFHSOST	Exc	Invalid function	1	STST parameter list
SO 0A06	DFHSOST	Exc	Exclusive lock error	1 2	STST parameter list LMLM parameter list
SO 0A07	DFHSOST	Exc	Exclusive unlock error	1 2	STST parameter list LMLM parameter list
SO 0A08	DFHSOST	Exc	Shared lock error	1 2	STST parameter list LMLM parameter list
SO 0A09	DFHSOST	Exc	Shared unlock error	1 2	STST parameter list LMLM parameter list
SO 0A10	DFHSOST	Exc	Recovery release lock error	1 2	STST parameter list LMLM parameter list
SO 0A11	DFHSOST	Exc	Getmain error	1	SMGF parameter list
SO 0A12	DFHSOST	Exc	Unknown kernel error code	1 2	STST parameter list Kernel error data
SO 0A13	DFHSOST	Exc	Invalid parameters	1	STST parameter list
SO 0B01	DFHSOTI	SO 1	Entry	1	SO anchor block
SO 0B02	DFHSOTI	SO 1	Exit	1	SO anchor block
SO 0B03	DFHSOTI	SO 1	Before posting listener		
SO 0B04	DFHSOTI	SO 1	After posting listener		
SO 0B05	DFHSOTI	Exc	Recovery entry	1 2	SO anchor block Kernel error data
SO 0B06	DFHSOTI	Exc	Recovery exit	1 2	SO anchor block Kernel error data

Statistics domain trace points

Table 133. Statistics domain trace points

Point ID	Module	Lvl	Type	Data	
ST 0001	DFHSTDM	ST 1	Entry	1	DMDM parameter list
ST 0002	DFHSTDM	ST 1	Exit	1	DMDM parameter list
ST 0003	DFHSTST	ST 1	Entry	1	STST parameter list
ST 0004	DFHSTST	ST 1	Exit	1	STST parameter list
ST 0005	DFHSTTI	ST 1	Entry	1	TISR parameter list
ST 0006	DFHSTTI	ST 1	Exit	1	TISR parameter list
ST 0007	DFHSTUE	ST 1	Entry	1	APUE parameter list
ST 0008	DFHSTUE	ST 1	Exit	1	APUE parameter list
ST 000E	DFHSTST	ST 1	SMF call		
ST 000F	DFHSTST	ST 1	SMF return		
ST 0010	DFHSTST	ST 2	SMF call	1 2	SAFPB SMF record
ST 0011	DFHSTST	ST 2	SMF return	1 2	SAFPB SMF record
ST 0012	DFHSTST	ST 2	Statistics record to be written to SMF	1	Statistics record
ST 0020	DFHSTDM	Exc	Recovery	1 2	DMDM parameter list Kernel error data
ST 0021	DFHSTST	Exc	Recovery	1 2	STST parameter list Kernel error data
ST 0022	DFHSTTI	Exc	Recovery	1 2	TISR parameter list Kernel error data
ST 0023	DFHSTUE	Exc	Recovery	1 2	APUE parameter list Kernel error data
ST 0024	DFHSTDM	Exc	Inquire start error	1	PAGP parameter list
ST 0025	DFHSTDM	Exc	Add subpool error	1	SMAD parameter list
ST 0026	DFHSTDM	Exc	Already initialized	1 2	DMDM parameter list Anchor block
ST 0027	DFHSTDM	Exc	Catalog get error	1	CCCC parameter list
ST 0028	DFHSTDM	Exc	Catalog write error	1	CCCC parameter list
ST 0029	DFHSTDM	Exc	Delete lock error	1	LMLM parameter list
ST 002A	DFHSTDM	Exc	GETMAIN request failed	1	SMGF parameter list

Table 133. Statistics domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
ST 002B	DFHSTDM	Exc	GETMAIN request failed	1	SMGF parameter list
ST 002C	DFHSTDM	Exc	GETMAIN request failed	1	SMGF parameter list
ST 002D	DFHSTDM	Exc	GETMAIN request failed	1	SMGF parameter list
ST 002E	DFHSTDM	Exc	Invalid format	1	DMDM parameter list
ST 002F	DFHSTDM	Exc	Invalid function	1	DMDM parameter list
ST 0030	DFHSTDM	Exc	Notify TOD error	1	TISR parameter list
ST 0032	DFHSTDM	Exc	Quiesce error—statistics domain not initialized	1 2	DMDM parameter list Anchor block
ST 0033	DFHSTDM	Exc	Store clock error		
ST 0035	DFHSTDM	Exc	Unlock error	1	LMLM parameter list
ST 0036	DFHSTDM	Exc	Wait phase error	1	DMDM parameter list
ST 0037	DFHSTDM	Exc	Wait phase error	1	DMDM parameter list
ST 0038	DFHSTDM	Exc	Wait phase error	1	DMDM parameter list
ST 0039	DFHSTDM	Exc	Lock error	1	LMLM parameter list
ST 003A	DFHSTUE	Exc	Invalid exit point	1	APUE parameter list
ST 003B	DFHSTUE	Exc	Invalid format	1	APUE parameter list
ST 003C	DFHSTUE	Exc	Invalid function	1	APUE parameter list
ST 003D	DFHSTUE	Exc	Lock error	1	LMLM parameter list
ST 003E	DFHSTUE	Exc	Unlock error	1	LMLM parameter list
ST 0040	DFHSTTI	Exc	Invalid format	1	TISR parameter list
ST 0041	DFHSTTI	Exc	Invalid function	1	TISR parameter list
ST 0042	DFHSTTI	Exc	Lock error	1	LMLM parameter list
ST 0043	DFHSTTI	Exc	Unlock error	1	LMLM parameter list
ST 0044	DFHSTTI	Exc	Unlock error	1	LMLM parameter list
ST 0046	DFHSTST	Exc	Cancel request notify error	1	TISR parameter list
ST 0047	DFHSTST	Exc	Cancel request notify error	1	TISR parameter list
ST 0048	DFHSTST	Exc	Cancel request notify error	1	TISR parameter list
ST 0049	DFHSTST	Exc	Cancel request notify error	1	TISR parameter list
ST 004A	DFHSTST	Exc	Cancel request notify error	1	TISR parameter list

Table 133. Statistics domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
ST 004B	DFHSTST	Exc	Cancel request notify error	1	TISR parameter list
ST 004C	DFHSTST	Exc	Catalog write failure	1	CCCC parameter list
ST 004D	DFHSTST	Exc	Collect statistics error	1	STST parameter list
ST 004E	DFHSTST	Exc	Invalid collect option	1	STST parameter list
ST 004F	DFHSTST	Exc	Invalid data format	1	STST parameter list
ST 0050	DFHSTST	Exc	Invalid EOD	1	STST parameter list
ST 0051	DFHSTST	Exc	Invalid format	1	STST parameter list
ST 0052	DFHSTST	Exc	Invalid function	1	STST parameter list
ST 0053	DFHSTST	Exc	Invalid interval	1	STST parameter list
ST 0054	DFHSTST	Exc	Invalid request	1	STST parameter list
ST 0055	DFHSTST	Exc	Invoke user exit error	1	APEX parameter list
ST 0056	DFHSTST	Exc	Invoke user exit error	1	APEX parameter list
ST 0057	DFHSTST	Exc	Global lock error	1	LMLM parameter list
ST 0058	DFHSTST	Exc	Notify TOD error	1	TISR parameter list
ST 0059	DFHSTST	Exc	SMF error	1 2	SAFPB SMF record
ST 005A	DFHSTST	Exc	Store clock error		
ST 005B	DFHSTST	Exc	Store clock error		
ST 005C	DFHSTST	Exc	Store clock error		
ST 005D	DFHSTST	Exc	Global unlock error	1	LMLM parameter list
ST 005E	DFHSTST	Exc	Unlock error	1	LMLM parameter list
ST 005F	DFHSTST	Exc	User exit purge error	1	APEX parameter list
ST 0060	DFHSTST	Exc	Cancel request notify error	1	TISR parameter list
ST 0061	DFHSTST	Exc	Store clock error		
ST 0062	DFHSTST	Exc	Invalid reset request	1	STST parameter list
ST 0063	DFHSTST	Exc	Invalid use of RECORDNOW or RESETNOW	1	STST parameter list
ST 0064	DFHSTST	Exc	Cancel request, notify error	1	TISR parameter list
ST 0065	DFHSTST	Exc	GETMAIN request failed for USS buffer	1	SMGF parameter list
ST 0066	DFHSTST	Exc	FREEMAIN request failed for USS buffer	1	SMGF parameter list
ST 0067	DFHSTST	Exc	USS lock error	1	LMLM parameter list

Table 133. Statistics domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
ST 0068	DFHSTST	Exc	Invoke user exit error while processing USS chain	1	APEX parameter list
ST 0069	DFHSTST	Exc	USS unlock error	1	LMLM parameter list
ST 0070	DFHSTST	Exc	Parameter manager GET PARAMETERS call failed	1	PAGP parameter list

Timer domain trace points

Table 134. Timer domain trace points

Point ID	Module	Lvl	Type	Data	
TI 0001	DFHTIDM	TI 1	Entry	1	DMDM parameter list
TI 0002	DFHTIDM	TI 1	Exit	1	DMDM parameter list
TI 0050	DFHTIDM	Exc	Invalid domain call	1	DMDM parameter list
TI 0051	DFHTIDM	Exc	Invalid format number	1	DMDM parameter list
TI 0060	DFHTIDM	Exc	Recovery	1 2	DMDM parameter list Kernel error data
TI 0100	DFHTISR	TI 1	Entry	1	TISR, KETI, or DSAT parameter list
TI 0101	DFHTISR	TI 1	Exit	1	TISR, KETI, or DSAT parameter list
TI 0150	DFHTISR	Exc	Invalid domain call	1	TISR, KETI, or DSAT parameter list
TI 0151	DFHTISR	Exc	Invalid format number	1	TISR, KETI, or DSAT parameter list
TI 0152	DFHTISR	Exc	Invalid interval	1	TISR parameter list
TI 0153	DFHTISR	Exc	Invalid token	1	TISR parameter list
TI 0154	DFHTISR	Exc	Input TOD too late	1	TISR parameter list
TI 0160	DFHTISR	Exc	Recovery	1 2	TISR parameter list Kernel error data
TI 0161	DFHTISR	Exc	Store clock error	1 2	TISR, KETI, or DSAT parameter list Store clock value
TI 0162	DFHTISR	Exc	Unable to attach task	1 2	DSAT parameter list Timer request element

Trace domain trace points

Table 135. Trace domain trace points

Point ID	Module	Lvl	Type	Data
TR 0001	DFHTRDM	TR 1	Entry	1 DMDM parameter list
TR 0002	DFHTRDM	TR 1	Exit	1 DMDM parameter list
TR 0003	DFHTRDM	Exc	Recovery	1 DMDM parameter list 2 Kernel error data
TR 0004	DFHTRDM	Exc	DFHTRAP activation failed	1 DMDM parameter list 2 TRSR parameter list
TR 0101	DFHTRPT	Exc	Overlength entry	1 Calling domain index 2 TRPT parameter list
TR 0102	DFHTRPT	Exc	Bad data passed	1 Calling domain index 2 TRPT parameter list 3 Kernel error data
TR 0103	DFHTRPT	n/a	DFHTRAP requested entry	1 User specified data 2 User specified data 3 User specified data
TR 0201	DFHTRSR	TR 1	Entry	1 TRSR or KETI parameter list
TR 0202	DFHTRSR	TR 1	Exit	1 TRSR or KETI parameter list
TR 0203 ¹	DFHTRSR	Exc	Recovery	1 TRSR parameter list 2 Kernel error data
TR 0204	DFHTRSR	Exc	Invalid function	1 TRSR or KETI parameter list
TR 0205	DFHTRSR	Exc	Aux open failed	1 TRSR parameter list 2 TR anchor block 3 DCB
TR 0206	DFHTRSR	Exc	Aux buffer GETMAIN failed	1 TRSR parameter list
TR 0207	DFHTRSR	Exc	DFHTRAO load failed	1 TRSR parameter list
TR 0208	DFHTRSR	Exc	Invalid autoswitch status	1 TRSR parameter list
TR 0209	DFHTRSR	Exc	Table size increase failed	1 TRSR parameter list
TR 0220	DFHTRSR	TR 1	Before aux buffer GETMAIN	1 GETMAIN return code 2 Address of aux buffer
TR 0221	DFHTRSR	TR 1	After aux buffer GETMAIN	
TR 0230	DFHTRSR		TR time reset	1 New time base
TR 0301	DFHTRSU	TR 1	Entry	1 TRSU parameter list
TR 0302	DFHTRSU	TR 1	Exit	1 TRSU parameter list
TR 0304	DFHTRSU	Exc	GTF buffer GETMAIN failed	1 TRSU parameter list

¹ The function time-base-reset is always traced from Point ID TR 0203, even when TR level 1 tracing is not selected.

Temporary storage domain trace points

Table 136. Temporary storage domain trace points

Point ID	Module	Lvl	Type	Data	
TS 0101	DFHTSDM	TS 1	Entry	1	DMDM parameter list
TS 0102	DFHTSDM	TS 1	Exit	1	DMDM parameter list
TS 0103	DFHTSDM	Exc	Recovery entered	1 2	DMDM parameter list Kernel error data
TS 0104	DFHTSDM	Exc	Invalid format	1	DMDM parameter list
TS 0105	DFHTSDM	Exc	Invalid function	1	DMDM parameter list
TS 0201	DFHTSQR	TS 1	Entry	1	TSQR parameter list
TS 0202	DFHTSQR	TS 1	Exit	1	TSQR parameter list
TS 0203	DFHTSQR	Exc	Recovery entered	1 2	TSQR parameter list Kernel error data
TS 0204	DFHTSQR	Exc	Invalid format	1	TSQR parameter list
TS 0205	DFHTSQR	Exc	Invalid function	1	TSQR parameter list
TS 0206	DFHTSQR	Exc	Unlock error in recovery	1	TSQR parameter list
TS 0301	DFHTSPT	TS 1	Entry	1	TSPT parameter list
TS 0302	DFHTSPT	TS 1	Exit	1	TSPT parameter list
TS 0303	DFHTSPT	Exc	Recovery entered	1 2	TSPT parameter list Kernel error data
TS 0304	DFHTSPT	Exc	Invalid format	1	TSPT parameter list
TS 0305	DFHTSPT	Exc	Invalid function	1	TSPT parameter list
TS 0306	DFHTSPT	Exc	Unlock error in recovery	1	TSPT parameter list
TS 0401	DFHTSRM	TS 1	Entry	1	RMRO/RMDE/RMKP parameter list
TS 0402	DFHTSRM	TS 1	Exit	1	RMRO/RMDE/RMKP parameter list
TS 0403	DFHTSRM	Exc	Recovery entered	1 2	RMRO/RMDE/RMKP parameter list Kernel error data
TS 0404	DFHTSRM	Exc	Invalid format	1	RMRO/RMDE/RMKP parameter list

Table 136. Temporary storage domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
TS 0405	DFHTSRM	Exc	RMRO invalid function	1	RMRO/RMDE/RMKP parameter list
TS 0406	DFHTSRM	Exc	RMDE invalid function	1	RMRO/RMDE/RMKP parameter list
TS 0407	DFHTSRM	Exc	RMKP invalid function	1	RMRO/RMDE/RMKP parameter list
TS 0408	DFHTSRM	Exc	Unlock error recovery	1	RMRO/RMDE/RMKP parameter list
TS 0409	DFHTSRM	Exc	TSIC invalid function	1	RMRO/RMDE/RMKP parameter list
TS 040A	DFHTSRM	Exc	Queue recovery error 1	1	RMRO/RMDE/RMKP parameter list
TS 040B	DFHTSRM	Exc	Queue recovery error 2	1	RMRO/RMDE/RMKP parameter list
TS 040C	DFHTSRM	Exc	Section recovery error 1	1	RMRO/RMDE/RMKP parameter list
TS 040D	DFHTSRM	Exc	Section recovery error 2	1	RMRO/RMDE/RMKP parameter list
TS 040E	DFHTSRM	Exc	Section recovery error 3	1	RMRO/RMDE/RMKP parameter list
TS 040F	DFHTSRM	Exc	Invalid log record	1	RMRO/RMDE/RMKP parameter list
TS 0410	DFHTSRM	Exc	Invalid indoubt operation	1	RMRO/RMDE/RMKP parameter list
TS 0501	DFHTSST	TS 1	Entry	1	STST parameter list
TS 0502	DFHTSST	TS 1	Exit	1	STST parameter list
TS 0503	DFHTSST	Exc	Recovery entered	1 2	STST parameter list Kernel error data
TS 0504	DFHTSST	Exc	Invalid format	1	STST parameter list
TS 0505	DFHTSST	Exc	Invalid function	1	STST parameter list
TS 0506	DFHTSST	Exc	Unlock error in recovery	1	STST parameter list
TS 0507	DFHTSST	Exc	Statistics buffer too small	1	STST parameter list
TS 0601	DFHTSSR	TS 1	Entry	1	TSSR parameter list
TS 0602	DFHTSSR	TS 1	Exit	1	TSSR parameter list

Table 136. Temporary storage domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
TS 0603	DFHTSSR	Exc	Recovery entered	1 2	TSSR parameter list Kernel error data
TS 0604	DFHTSSR	Exc	Invalid format	1	TSSR parameter list
TS 0605	DFHTSSR	Exc	Invalid function	1	TSSR parameter list
TS 0606	DFHTSSR	Exc	Unlock error in recovery	1	TSSR parameter list
TS 0607	DFHTSSR	Exc	Invalid exit point	1	TSSR parameter list
TS 0701	DFHTSBR	TS 1	Entry	1	TSBR parameter list
TS 0702	DFHTSBR	TS 1	Exit	1	TSBR parameter list
TS 0703	DFHTSBR	Exc	Recovery entered	1 2	TSBR parameter list Kernel error data
TS 0704	DFHTSBR	Exc	Invalid format	1	TSBR parameter list
TS 0705	DFHTSBR	Exc	Invalid function	1	TSBR parameter list
TS 0706	DFHTSBR	Exc	Unlock error in recovery	1	TSBR parameter list
TS 0801	DFHTSWQ	TS 1	Entry	1	TSWQ parameter list
TS 0802	DFHTSWQ	TS 1	Exit	1	TSWQ parameter list
TS 0803	DFHTSWQ	Exc	Recovery entered	1 2	TSWQ parameter list Kernel error data
TS 0804	DFHTSWQ	Exc	Invalid format	1	TSWQ parameter list
TS 0805	DFHTSWQ	Exc	Invalid function	1	TSWQ parameter list
TS 0806	DFHTSWQ	Exc	Unlock error in recovery	1	TSWQ parameter list
TS 0807	DFHTSWQ	Exc	DSSR inquire suspend	1	TSWQ parameter list
TS 0808	DFHTSWQ	Exc	Before suspend	1 2	TSWQ parameter list TSW control block
TS 0809	DFHTSWQ	Exc	After suspend	1 2	TSWQ parameter list TSW control block
TS 0901	DFHTSAM	TS 1	Entry	1	TSAM parameter list
TS 0902	DFHTSAM	TS 1	Exit	1	TSAM parameter list
TS 0903	DFHTSAM	Exc	Recovery entered	1 2	TSAM parameter list Kernel error data
TS 0904	DFHTSAM	Exc	Invalid format	1	TSAM parameter list
TS 0905	DFHTSAM	Exc	Invalid function	1	TSAM parameter list

Table 136. Temporary storage domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
TS 0906	DFHTSAM	Exc	1310 abend 1	1	TSAM parameter list
TS 0907	DFHTSAM	Exc	1310 abend 2	1	TSAM parameter list
TS 0908	DFHTSAM	Exc	1310 abend 3	1	TSAM parameter list
TS 0909	DFHTSAM	Exc	1310 abend 4	1	TSAM parameter list
TS 090A	DFHTSAM	Exc	1310 abend 5	1	TSAM parameter list
TS 090B	DFHTSAM	Exc	1310 abend 6	1	TSAM parameter list
TS 090C	DFHTSAM	Exc	1310 abend 7	1	TSAM parameter list
TS 090D	DFHTSAM	Exc	1310 abend 8	1	TSAM parameter list
TS 090E	DFHTSAM	Exc	1310 abend 9	1	TSAM parameter list
TS 090F	DFHTSAM	Exc	1310 abend 10	1	TSAM parameter list
TS 0910	DFHTSAM	Exc	1310 abend 11	1	TSAM parameter list
TS 0A01	DFHTSSH	TS 1	Entry	1	TSSH parameter list
TS 0A02	DFHTSSH	TS 1	Exit	1	TSSH parameter list
TS 0A03	DFHTSSH	Exc	Recovery entered	1 2	TSSH parameter list Kernel error data
TS 0A04	DFHTSSH	Exc	Invalid format	1	TSSH parameter list
TS 0A05	DFHTSSH	Exc	Invalid function	1	TSSH parameter list
TS 0A06	DFHTSSH	Exc	Unlock error in recovery	1	TSSH parameter list
TS 0A07	DFHTSSH	Exc	Before server connect	1	TSSH parameter list
TS 0A08	DFHTSSH	Exc	After server connect	1	TSSH parameter list
TS 0A09	DFHTSSH	Exc	Before query server	1	TSSH parameter list
TS 0A0A	DFHTSSH	Exc	After query server	1	TSSH parameter list
TS 0A0B	DFHTSSH	Exc	Before server request	1	TSSH parameter list
TS 0A0C	DFHTSSH	Exc	After server request	1	TSSH parameter list
TS 0A0D	DFHTSSH	Exc	Before server close	1 2	Pool name Connect token
TS 0A0E	DFHTSSH	Exc	After server close	1 2 3	Pool name Connect token Close return code
TS 0B01	DFHTSAD	TS 1	Entry	1	TSAD parameter list

Table 136. Temporary storage domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
TS 0B02	DFHTSAD	TS 1	Exit	1	TSAD parameter list
TS 0B03	DFHTSAD	Exc	Recovery entered	1 2	TSAD parameter list Kernel error data
TS 0B04	DFHTSAD	Exc	Invalid format	1	TSAD parameter list
TS 0B05	DFHTSAD	Exc	Invalid function	1	TSAD parameter list
TS 0B06	DFHTSAD	Exc	Unlock error in recovery	1	TSAD parameter list
TS 0C01	DFHTSMB	TS 1	Entry	1	TSMB parameter list
TS 0C02	DFHTSMB	TS 1	Exit	1	TSMB parameter list
TS 0C03	DFHTSMB	Exc	Recovery entered	1 2	TSMB parameter list Kernel error data
TS 0C04	DFHTSMB	Exc	Invalid format	1	TSMB parameter list
TS 0C05	DFHTSMB	Exc	Invalid function	1	TSMB parameter list
TS 0C06	DFHTSMB	Exc	Unlock error in recovery	1	TSMB parameter list

User domain trace points

Table 137. User domain trace entries

Point ID	Module	Lvl	Type	Data	
US 0101	DFHUSDM	US 1	Entry	1	DFHUSDM parameter list
US 0102	DFHUSDM	US 1	Exit	1	DFHUSDM parameter list
US 0103	DFHUSDM	Exc	Recovery	1 2	DFHUSDM parameter list Kernel error data
US 0104	DFHUSDM	Exc	Invalid format	1	DFHUSDM parameter list
US 0105	DFHUSDM	Exc	Invalid function	1	DFHUSDM parameter list
US 0106	DFHUSDM	Exc	Unlock error	1	DFHUSDM parameter list
US 0107	DFHUSDM	Exc	No storage for USA	1	DFHUSDM parameter list
US 0108	DFHUSDM	Exc	Get parms failed	1	DFHUSDM parameter list
US 0201	DFHUSIS	US 1	Entry	1	DFHUSIS parameter list
US 0202	DFHUSIS	US 1	Exit	1	DFHUSIS parameter list
US 0203	DFHUSIS	Exc	Recovery	1 2	DFHUSIS parameter list Kernel error data
US 0204	DFHUSIS	Exc	Invalid format	1	DFHUSIS parameter list

Table 137. User domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
US 0205	DFHUSIS	Exc	Invalid function	1	DFHUSIS parameter list
US 0206	DFHUSIS	Exc	No inquire parameters	1	DFHUSIS parameter list
US 0207	DFHUSIS	Exc	No set parameters	1	DFHUSIS parameter list
US 0208	DFHUSIS	Exc	Lock error	1	DFHUSIS parameter list
US 0209	DFHUSIS	Exc	Unlock error	1	DFHUSIS parameter list
US 020A	DFHUSIS	Exc	Unlock error recovery	1	DFHUSIS parameter list
US 0301	DFHUSAD	US 1	Entry	1	DFHUSAD parameter list
US 0302	DFHUSAD	US 1	Exit	1	DFHUSAD parameter list
US 0303	DFHUSAD	Exc	Recovery	1 2	DFHUSAD parameter list Kernel error data
US 0304	DFHUSAD	Exc	Invalid format	1	DFHUSAD parameter list
US 0305	DFHUSAD	Exc	Invalid function	1	DFHUSAD parameter list
US 0306	DFHUSAD	Exc	Lock error	1	DFHUSAD parameter list
US 0307	DFHUSAD	Exc	Unlock error	1	DFHUSAD parameter list
US 0308	DFHUSAD	Exc	Unlock error recovery	1	DFHUSAD parameter list
US 0309	DFHUSAD	Exc	Exception unknown	1	DFHUSAD parameter list
US 030A	DFHUSAD	Exc	Extract failed	1	DFHUSAD parameter list
US 030B	DFHUSAD	Exc	Invalid parameters	1	DFHUSAD parameter list
US 030C	DFHUSAD	Exc	User not in directory	1	DFHUSAD parameter list
US 030D	DFHUSAD	Exc	User dir add duplicate	1	DFHUSAD parameter list
US 030E	DFHUSAD	Exc	User dir add error	1	DFHUSAD parameter list
US 030F	DFHUSAD	Exc	User dir del error	1	DFHUSAD parameter list
US 0310	DFHUSAD	Exc	Invalid security token	1	DFHUSAD parameter list
US 0311	DFHUSAD	Exc	Use count error	1	DFHUSAD parameter list
US 0312	DFHUSAD	Exc	DFHUSER deq failure	1	DFHUSAD parameter list
US 0313	DFHUSAD	Exc	Invalid UDB pointer	1	DFHUSAD parameter list
US 0314	DFHUSAD	Exc	Add timeout failure	1	DFHUSAD parameter list
US 0315	DFHUSAD	Exc	Del timeout failure	1	DFHUSAD parameter list

Table 137. User domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
US 0316	DFHUSAD	Exc	Del expired failure	1	DFHUSAD parameter list
US 0317	DFHUSAD	Exc	Invalid DCE state	1	DFHUSAD parameter list
US 0318	DFHUSAD	Exc	DCE exception unknown	1	DFHUSAD parameter list
US 0401	DFHUSXM	US 1	Entry	1	DFHUSXM parameter list
US 0402	DFHUSXM	US 1	Exit	1	DFHUSXM parameter list
US 0403	DFHUSXM	Exc	Recovery	1 2	DFHUSXM parameter list Kernel error data
US 0404	DFHUSXM	Exc	Invalid format	1	DFHUSXM parameter list
US 0405	DFHUSXM	Exc	Invalid function	1	DFHUSXM parameter list
US 0406	DFHUSXM	Exc	Lock error	1	DFHUSXM parameter list
US 0407	DFHUSXM	Exc	Unlock error	1	DFHUSXM parameter list
US 0408	DFHUSXM	Exc	Unlock error recovery	1	DFHUSXM parameter list
US 0409	DFHUSXM	Exc	GETMAIN failure	1	DFHUSXM parameter list
US 040A	DFHUSXM	Exc	DIRMAN failure	1	DFHUSXM parameter list
US 040B	DFHUSXM	Exc	Tran use count max	1	DFHUSXM parameter list
US 040C	DFHUSXM	Exc	Tran use count neg	1	DFHUSXM parameter list
US 040D	DFHUSXM	Exc	Tran use count low	1	DFHUSXM parameter list
US 040E	DFHUSXM	Exc	Invalid security token	1	DFHUSXM parameter list
US 040F	DFHUSXM	Exc	Token type error	1	DFHUSXM parameter list
US 0410	DFHUSXM	Exc	Invalid transaction token	1	DFHUSXM parameter list
US 0411	DFHUSXM	Exc	Already added security	1	DFHUSXM parameter list
US 0412	DFHUSXM	Exc	No principal UDB pointer	1	DFHUSXM parameter list
US 0413	DFHUSXM	Exc	USAD error	1	DFHUSXM parameter list
US 0501	DFHUSFL	US 1	Entry	1	DFHUSFL parameter list
US 0502	DFHUSFL	US 1	Exit	1	DFHUSFL parameter list
US 0503	DFHUSFL	Exc	Recovery	1 2	DFHUSFL parameter list Kernel error data
US 0504	DFHUSFL	Exc	Invalid format	1	DFHUSFL parameter list
US 0505	DFHUSFL	Exc	Invalid function	1	DFHUSFL parameter list

Table 137. User domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
US 0506	DFHUSFL	Exc	Lock error	1	DFHUSFL parameter list
US 0507	DFHUSFL	Exc	Unlock error	1	DFHUSFL parameter list
US 0508	DFHUSFL	Exc	Unlock error recovery	1	DFHUSFL parameter list
US 0509	DFHUSFL	Exc	Exception unknwn	1	DFHUSFL parameter list
US 050B	DFHUSFL	Exc	User not in directory	1	DFHUSFL parameter list
US 050C	DFHUSFL	Exc	User dir add duplicate	1	DFHUSFL parameter list
US 050D	DFHUSFL	Exc	Unflatten user error	1	DFHUSFL parameter list
US 050E	DFHUSFL	Exc	User dir del error	1	DFHUSFL parameter list
US 050F	DFHUSFL	Exc	Invalid security token	1	DFHUSFL parameter list
US 0510	DFHUSFL	Exc	Use count error	1	DFHUSFL parameter list
US 0511	DFHUSFL	Exc	DFHUSER deq failure	1	DFHUSFL parameter list
US 0512	DFHUSFL	Exc	Invalid UDB pointer	1	DFHUSFL parameter list
US 0513	DFHUSFL	Exc	Del timeout failure	1	DFHUSFL parameter list
US 0601	DFHUSST	US 1	Entry	1	DFHUSST parameter list
US 0602	DFHUSST	US 1	Exit	1	DFHUSST parameter list
US 0603	DFHUSST	Exc	Recovery	1 2	DFHUSST parameter list Kernel error data
US 0604	DFHUSST	Exc	Invalid format	1	DFHUSST parameter list
US 0605	DFHUSST	Exc	Invalid function	1	DFHUSST parameter list
US 0606	DFHUSST	Exc	Lock error	1	DFHUSST parameter list
US 0607	DFHUSST	Exc	Unlock error	1	DFHUSST parameter list
US 0608	DFHUSST	Exc	Unlock error recovery	1	DFHUSST parameter list
US 0701	DFHUSTI	US 1	Entry	1	DFHUSTI parameter list
US 0702	DFHUSTI	US 1	Exit	1	DFHUSTI parameter list
US 0703	DFHUSTI	Exc	Recovery	1 2	DFHUSTI parameter list Kernel error data
US 0704	DFHUSTI	Exc	Invalid format	1	DFHUSTI parameter list
US 0705	DFHUSTI	Exc	Invalid function	1	DFHUSTI parameter list
US 0706	DFHUSTI	Exc	Lock error	1	DFHUSTI parameter list

Table 137. User domain trace entries (continued)

Point ID	Module	Lvl	Type	Data
US 0707	DFHUSTI	Exc	Unlock error	1 DFHUSTI parameter list
US 0708	DFHUSTI	Exc	Unlock error recovery	1 DFHUSTI parameter list
US 0709	DFHUSTI	Exc	Exception unknown	1 DFHUSTI parameter list
US 070A	DFHUSTI	Exc	Invalid UDB pointer	1 DFHUSTI parameter list
US 070B	DFHUSTI	Exc	Add queue entry error	1 DFHUSTI parameter list
US 070C	DFHUSTI	Exc	Already in queue	1 DFHUSTI parameter list
US 070D	DFHUSTI	Exc	Del queue entry error	1 DFHUSTI parameter list
US 070E	DFHUSTI	Exc	Get queue entry error	1 DFHUSTI parameter list
US 070F	DFHUSTI	Exc	Queue entry in use	1 DFHUSTI parameter list
US 0710	DFHUSTI	Exc	Set queue entry error	1 DFHUSTI parameter list
US 0711	DFHUSTI	Exc	Timer interval req failure	1 DFHUSTI parameter list
US 0712	DFHUSTI	Exc	Timer cancel req failure	1 DFHUSTI parameter list
US 0713	DFHUSTI	Exc	UTQ is empty	1 DFHUSTI parameter list
US 0801	DFHUSDE	US 1	Entry	1 DFHUSDE parameter list
US 0802	DFHUSDE	US 1	Exit	1 DFHUSDE parameter list
US 0803	DFHUSDE	Exc	Recovery	1 DFHUSDE parameter list
US 0804	DFHUSDE	Exc	Invalid format	1 DFHUSDE parameter list
US 0805	DFHUSDE	Exc	Invalid function	1 DFHUSDE parameter list
US 0806	DFHUSDE	Exc	DFHUSER deq failed	1 DFHUSDE parameter list
US 0807	DFHUSDE	Exc	Exception unknown	1 DFHUSDE parameter list
US 0808	DFHUSDE	Exc	Lock error	1 DFHUSDE parameter list
US 0809	DFHUSDE	Exc	Unlock error	1 DFHUSDE parameter list
US 080A	DFHUSDE	Exc	Unlock error recovery	1 DFHUSDE parameter list

Web domain trace points

Table 138. Web domain trace points

Point ID	Module	Lvl	Type	Data
WB 0100	DFHWBDM	WB 1	Entry	1 WBDM parameter list
WB 0101	DFHWBDM	WB 1	Exit	1 WBDM parameter list

Table 138. Web domain trace points (continued)

Point ID	Module	Lvl	Type	Data	
WB 0102	DFHWBDM	Exc	Recovery	1	WBDM parameter list
WB 0103	DFHWBDM	Exc	Invalid format	1	DMDM parameter list
WB 0104	DFHWBDM	Exc	Invalid function	1	DMDM parameter list
WB 0105	DFHWBDM	Exc	Release lock error	1 2	DMDM parameter list LMLM parameter list
WB 0107	DFHWBDM	Exc	No storage for anchor block	1	DMDM parameter list
WB 0108	DFHWBDM	Exc	Get parameters failed	1	DMDM parameter list
WB 0200	DFHWBGP	Entry		1	WBGP parameter list
WB 0201	DFHWBGP	Exit		1	WBGP parameter list
WB 0202	DFHWBGP	Exc	Recovery	1	WBGP parameter list
WB 0203	DFHWBGP	Exc	Invalid format	1	WBGP parameter list
WB 0204	DFHWBGP	Exc	Invalid function	1	WBGP parameter list
WB 0300	DFHWBAP	Entry		1 2	WBAP parameter list Client codepage
WB 0301	DFHWBAP	Exit		1 2	WBAP parameter list Client codepage
WB 0302	DFHWBAP	Exc	Recovery	1	WBAP parameter list
WB 0303	DFHWBAP	Exc	Invalid format	1	WBAP parameter list
WB 0304	DFHWBAP	Exc	Invalid function	1	WBAP parameter list
WB 0305	DFHWBAP	Exc	Unlock error recovery	1	WBAP parameter list
WB 0410	DFHWBRQ	Event	Inbound HTTP request	1	HTTP request headers
WB 0411	DFHWBSR	Exc	TSQ put header failed	1	WRB
WB 0412	DFHWBRQ	Exc	TS put request body failed	1	WRB
WB 0413	DFHWBSR	Exc	No repository token returned	1	WRB
WB 0414	DFHWBSR	Event	Before call to Analyzer	1	Analyzer parameter list
WB 0415	DFHWBSR	Event	After call to Analyzer	1	Analyzer parameter list
WB 0416	DFHWBSR	Data	HTTP request body	1	HTTP request body
# WB 04B0	DFHWBBMS	WB1	Entry	1	WBTC parameter list
#					
# WB 04B1	DFHWBBMS	WB1	Exit	1	WBTC parameter list
#					

Table 138. Web domain trace points (continued)

Point ID	Module	Lvl	Type	Data
# WB 04B2	DFHWBBMS	Exc	Recovery entered	1 WBTC parameter list
#				2 Kernel error data
#				
# WB 04B4	DFHWBBMS	Exc	Invalid function	1 WBTC parameter list
#				
# WB 04B7	DFHWBBMS	Exc	BMS map not found	1 WBTC parameter list
#				
# WB 04B8	DFHWBBMS	Exc	BMS ADSD not found	1 WBTC parameter list
#				
# WB 04B9	DFHWBBMS	Exc	Template manager error	1 WBTC parameter list
#				
WB 0500	DFHWBSR	Entry		1 WBSR parameter list
WB 0501	DFHWBSR	Exit		1 WBSR parameter list
WB 0502	DFHWBSR	Exc	Invalid format	1 WBSR parameter list
WB 0503	DFHWBSR	Exc	Invalid function	1 WBSR invalid function
WB 0600	DFHWBXM	Entry		1 XMAC parameter list
WB 0601	DFHWBXM	Exit		1 XMAC parameter list
WB 0602	DFHWBXM	Exc	Invalid format	1 XMAC parameter list
WB 0603	DFHWBXM	Exc	Invalid function	1 XMAC parameter list
WB 0604	DFHWBXM	Exc	Recovery	1 XMAC parameter list
WB 4109	DFHWBLT	Exc	Trigger partner failed	1 WBST parameter list
WB 4654	DFHWBST	Exc	Directory browse error	1 WBST parameter list
				2 DDBR parameter list
# WB FF60	DFHWBQM	Entry		1 WBQM parameter list
#				
# WB FF61	DFHWBQM	Exit		1 WBQM parameter list
#				
# WB FF62	DFHWBQM	Exc	Recovery	1 WBQM parameter list
#				
# WB FF63	DFHWBQM	Exc	Invalid format	1 WBAP parameter list
#				
# WB FF64	DFHWBQM	Exc	Invalid function	1 WBQM parameter list
#				
# WB FF65	DFHWBQM	Exc	Invalid parameter	1 WBQM parameter list
#				
# WB FF66	DFHWBQM	Exc	TS queue error	1 WBQM parameter list
#				

Transaction manager domain trace points

Table 139. Transaction manager domain trace entries

Point ID	Module	Lvl	Type	Data
XM 0101	DFHXMDM	XM 1	Entry	1 DMDM parameter list

Table 139. Transaction manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
XM 0102	DFHXMDM	XM 1	Exit	1	DMDM parameter list
XM 0103	DFHXMDM	Exc	Recovery	1 2	DMDM parameter list Kernel error data
XM 0104	DFHXMDM	Exc	Invalid format	1	Invalid parameter list
XM 0105	DFHXMDM	Exc	Invalid function	1	DMDM parameter list
XM 0106	DFHXMDM	Exc	LMLM Unlock error	1	DMDM parameter list
XM 0107	DFHXMDM	Exc	No storage for anchor	1	DMDM parameter list
XM 0108	DFHXMDM	Exc	No storage for subpool	1	DMDM parameter list
XM 0109	DFHXMDM	Exc	No storage for subpool	1	DMDM parameter list
XM 010A	DFHXMDM	Exc	PAGP Inquire_Start error	1	DMDM parameter list
XM 010B	DFHXMDM	Exc	DDDI Create_Directory error	1	DMDM parameter list
XM 010C	DFHXMDM	Exc	DDDI Create_Directory error	1	DMDM parameter list
XM 010D	DFHXMDM	Exc	DDDI Create_Directory error	1	DMDM parameter list
XM 010E	DFHXMDM	Exc	No storage for subpool	1	DMDM parameter list
XM 010F	DFHXMDM	Exc	DDDI Create_Directory error	1	DMDM parameter list
XM 0110	DFHXMDM	Exc	No storage for subpool	1	DMDM parameter list
XM 0111	DFHXMDM	Exc	No storage for transaction	1	DMDM parameter list
XM 0112	DFHXMDM	Exc	CCCC Get error	1	DMDM parameter list
XM 0113	DFHXMDM	Exc	PAGP Get_Parameters error	1	DMDM parameter list
XM 0114	DFHXMDM	Exc	Internal logic error	1	DMDM parameter list
XM 0115	DFHXMDM	Exc	XMSR Set_MXT error	1	DMDM parameter list
XM 0116	DFHXMDM	Exc	XMCL Add_Tclass error	1	DMDM parameter list
XM 0117	DFHXMDM	Exc	DMDM Wait_Phase error	1	DMDM parameter list
XM 0118	DFHXMDM	Exc	No storage for buffer	1	DMDM parameter list
XM 0119	DFHXMDM	Exc	Insufficient 24-bit storage	1	DMDM parameter list
XM 0201	DFHXMXD	XM 1	Entry	1	XXXD parameter list
XM 0202	DFHXMXD	XM 1	Exit	1	XXXD parameter list
XM 0203	DFHXMXD	Exc	Recovery	1 2	XXXD parameter list Kernel error data

Table 139. Transaction manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
XM 0204	DFHXXMXD	Exc	Invalid format	1	Invalid parameter list
XM 0205	DFHXXMXD	Exc	Invalid function	1	XXMXD parameter list
XM 0206	DFHXXMXD	Exc	SMGF getmain error	1 2	XXMXD parameter list SMGF parameter list
XM 0207	DFHXXMXD	Exc	SMGF getmain error	1 2	XXMXD parameter list SMGF parameter list
XM 0208	DFHXXMXD	Exc	Invalid call to XXMXD	1	XXMXD parameter list
XM 0209	DFHXXMXD	Exc	Invalid call to XXMXD	1	XXMXD parameter list
XM 020A	DFHXXMXD	Exc	Invalid call to XXMXD	1	XXMXD parameter list
XM 020B	DFHXXMXD	Exc	Invalid call to XXMXD	1	XXMXD parameter list
XM 020C	DFHXXMXD	Exc	Invalid call to XXMXD	1	XXMXD parameter list
XM 020D	DFHXXMXD	Exc	Invalid call to XXMXD	1	XXMXD parameter list
XM 020E	DFHXXMXD	Exc	DDLO Locate error	1 2	XXMXD parameter list DDLO parameter list
XM 020F	DFHXXMXD	Exc	KEGD Inquire_Kernel error	1 2	XXMXD parameter list KEGD parameter list
XM 0210	DFHXXMXD	Exc	Bad catalog record length	1 2	XXMXD parameter list Expected length
XM 0211	DFHXXMXD	Exc	DDDI Add_Entry error	1 2	XXMXD parameter list DDDI parameter list
XM 0212	DFHXXMXD	Exc	DDDI Replace_Data error	1 2	XXMXD parameter list DDDI parameter list
XM 0213	DFHXXMXD	Exc	LMLM Lock error	1 2	XXMXD parameter list LMLM parameter list
XM 0214	DFHXXMXD	Exc	LMLM Unlock error	1 2	XXMXD parameter list LMLM parameter list
XM 0215	DFHXXMXD	Exc	DDLO Locate error	1 2	XXMXD parameter list DDLO parameter list
XM 0216	DFHXXMXD	Exc	DDDI Add_Entry error	1 2	XXMXD parameter list DDDI parameter list
XM 0217	DFHXXMXD	Exc	DDDI Replace_Data error	1 2	XXMXD parameter list DDDI parameter list
XM 0218	DFHXXMXD	Exc	DDLO Locate error	1 2	XXMXD parameter list DDLO parameter list

Table 139. Transaction manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data
XM 0219	DFHXMXD	Exc	DDDI Add_Entry error	1 XMXD parameter list 2 DDDI parameter list
XM 021A	DFHXMXD	Exc	DDDI Replace_Data error	1 XMXD parameter list 2 DDDI parameter list
XM 021B	DFHXMXD	Exc	Update lock error	1 XMXD parameter list 2 DSSR or LMLM parameter list
XM 021C	DFHXMXD	Exc	Update unlock error	1 XMXD parameter list 2 DSSR parameter list
XM 021D	DFHXMXD	Exc	Invalid trandef token	1 XMXD parameter list 2 Trandef instance
XM 021E	DFHXMXD	XM 2	Trandef on exit	1 Trandef instance 2 Trandef static
XM 021F	DFHXMXD	Exc	Lock held on exit	1 XMXD parameter list
XM 0220	DFHXMXD	Exc	Invalid call to XMXD	1 XMXD parameter list
XM 0301	DFHXMRP	XM 1	Entry	1 XMRP parameter list
XM 0302	DFHXMRP	XM 1	Exit	1 XMRP parameter list
XM 0303	DFHXMRP	Exc	Recovery	1 XMRP parameter list 2 Kernel error data
XM 0304	DFHXMRP	Exc	Invalid format	1 Invalid parameter list
XM 0305	DFHXMRP	Exc	Invalid function	1 XMRP parameter list
XM 0306	DFHXMRP	Exc	CCCC Get_Next error	1 XMRP parameter list 2 CCCC parameter list
XM 0307	DFHXMRP	Exc	XMXD Add_Replace_Trandef error	1 XMRP parameter list 2 XMXD parameter list
XM 0308	DFHXMRP	Exc	XMCL Add_Replace_Tclass error	1 XMRP parameter list 2 XMCL parameter list
XM 0401	DFHXMLD	XM 1	Entry	1 XMLD parameter list
XM 0402	DFHXMLD	XM 1	Exit	1 XMLD parameter list
XM 0403	DFHXMLD	Exc	Recovery	1 XMLD parameter list 2 Kernel error data
XM 0404	DFHXMLD	Exc	Invalid format	1 Invalid parameter list
XM 0405	DFHXMLD	Exc	Invalid function	1 XMLD parameter list
XM 0406	DFHXMLD	Exc	DDLO Locate error	1 XMLD parameter list 2 DDLO parameter list

Table 139. Transaction manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
XM 0407	DFHXMLD	Exc	DDLO Locate error	1	XMLD parameter list
				2	DDLO parameter list
XM 0408	DFHXMLD	Exc	Invalid call to XMLD	1	XMLD parameter list
				2	Trandef instance
XM 0409	DFHXMLD	Exc	LMLM Lock error	1	XMLD parameter list
				2	LMLM parameter list
XM 040A	DFHXMLD	Exc	LMLM Unlock error	1	XMLD parameter list
				2	LMLM parameter list
XM 040B	DFHXMLD	Exc	Invalid TPName length	1	XMLD parameter list
				2	Invalid length
XM 040C	DFHXMLD	Exc	Invalid trandef token	1	XMLD parameter list
				2	Trandef instance
XM 040D	DFHXMLD	XM 2	Trandef on exit	1	Trandef instance
				2	Trandef static
XM 040E	DFHXMLD	Exc	Lock held on exit	1	XMLD parameter list
XM 0501	DFHXMBD	XM 1	Entry	1	XMBD parameter list
XM 0502	DFHXMBD	XM 1	Exit	1	XMBD parameter list
XM 0503	DFHXMBD	Exc	Recovery	1	XMBD parameter list
				2	Kernel error data
XM 0504	DFHXMBD	Exc	Invalid format	1	Invalid parameter list
XM 0505	DFHXMBD	Exc	Invalid function	1	XMBD parameter list
XM 0506	DFHXMBD	Exc	DDBR Start_Browse error	1	XMBD parameter list
				2	DDBR parameter list
XM 0507	DFHXMBD	Exc	DDBR Get_Next error	1	XMBD parameter list
				2	DDBR parameter list
XM 0508	DFHXMBD	Exc	DDBR End_Browse error	1	XMBD parameter list
				2	DDBR parameter list
XM 0509	DFHXMBD	Exc	XMXD Inquire_Trandef error	1	XMBD parameter list
				2	XMXD parameter list
XM 050A	DFHXMBD	Exc	Directory name mismatch	1	XMBD parameter list
				2	DDBR parameter list
				3	Trandef static
				4	Directory entry name
XM 050B	DFHXMBD	Exc	LMLM Lock error	1	XMBD parameter list
				2	LMLM parameter list
XM 050C	DFHXMBD	Exc	LMLM Unlock error	1	XMBD parameter list
				2	LMLM parameter list

Table 139. Transaction manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data
XM 050D	DFHXMBD	Exc	Invalid browse token	1 XMBD parameter list 2 Invalid token
XM 050E	DFHXMBD	Exc	Lock held on exit	1 XMBD parameter list
XM 0601	DFHXMDD	XM 1	Entry	1 XMDD parameter list
XM 0602	DFHXMDD	XM 1	Exit	1 XMDD parameter list
XM 0603	DFHXMDD	Exc	Recovery	1 XMDD parameter list 2 Kernel error data
XM 0604	DFHXMDD	Exc	Invalid format	1 Invalid parameter list
XM 0605	DFHXMDD	Exc	Invalid function	1 XMDD parameter list
XM 0606	DFHXMDD	Exc	DDDI Delete_entry error	1 XMDD parameter list 2 DDDI parameter list
XM 0607	DFHXMDD	Exc	LMLM Lock error	1 XMDD parameter list 2 LMLM parameter list
XM 0608	DFHXMDD	Exc	LMLM Unlock error	1 XMDD parameter list 2 LMLM parameter list
XM 0609	DFHXMDD	Exc	DDLO Locate error	1 XMDD parameter list 2 DDLO parameter list
XM 060A	DFHXMDD	Exc	Update lock error	1 XMDD parameter list 2 DSSR or LMLM parameter list
XM 060B	DFHXMDD	Exc	Update unlock error	1 XMDD parameter list 2 DSSR parameter list
XM 060C	DFHXMDD	XM 2	Trandef on exit	1 Trandef instance 2 Trandef static
XM 060D	DFHXMDD	Exc	Lock held on exit	1 XMDD parameter list
XM 0701	DFHXMFD	XM 1	Entry	1 XMFD parameter list
XM 0702	DFHXMFD	XM 1	Exit	1 XMFD parameter list
XM 0703	DFHXMFD	Exc	Recovery	1 XMFD parameter list 2 Kernel error data
XM 0704	DFHXMFD	Exc	Invalid format	1 Invalid parameter list
XM 0705	DFHXMFD	Exc	Invalid function	1 XMFD parameter list
XM 0706	DFHXMFD	Exc	LMLM Lock error	1 XMFD parameter list 2 LMLM parameter list
XM 0707	DFHXMFD	Exc	LMLM Unlock error	1 XMFD parameter list 2 LMLM parameter list

Table 139. Transaction manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
XM 0708	DFHXMFD	Exc	Lock held on exit	1	XMGD parameter list
XM 0801	DFHXMSR	XM 1	Entry	1	XMSR parameter list
XM 0802	DFHXMSR	XM 1	Exit	1	XMSR parameter list
XM 0803	DFHXMSR	Exc	Recovery	1 2	XMSR parameter list Kernel error data
XM 0804	DFHXMSR	Exc	Invalid format	1	Invalid parameter list
XM 0805	DFHXMSR	Exc	Invalid function	1	XMSR parameter list
XM 0806	DFHXMSR	Exc	XMCL Set_Tclass error	1 2	XMSR parameter list XMCL parameter list
XM 0807	DFHXMSR	Exc	XMNT MXT_Change_Notify error	1 2	XMSR parameter list XMNT parameter list
XM 0808	DFHXMSR	Exc	LMLM Lock error	1 2	XMSR parameter list LMLM parameter list
XM 0809	DFHXMSR	Exc	LMLM Unlock error	1 2	XMSR parameter list LMLM parameter list
XM 080A	DFHXMSR	Exc	LMLM Lock error	1 2	XMSR parameter list LMLM parameter list
XM 080B	DFHXMSR	Exc	LMLM Unlock error	1 2	XMSR parameter list LMLM parameter list
XM 080C	DFHXMSR	Exc	Scheduler error	1 2	XMSR parameter list XMQC or DSAT parameter list
XM 0901	DFHXMQD	XM 1	Entry	1	XMQD parameter list
XM 0902	DFHXMQD	XM 1	Exit	1	XMQD parameter list
XM 0903	DFHXMQD	Exc	Recovery	1 2	XMQD parameter list Kernel error data
XM 0904	DFHXMQD	Exc	Invalid format	1	Invalid parameter list
XM 0905	DFHXMQD	Exc	Invalid function	1	XMQD parameter list
XM 0906	DFHXMQD	Exc	DDDI Delete_Entry error	1 2	XMQD parameter list DDDI parameter list
XM 0907	DFHXMQD	Exc	DDDI Delete_Entry error	1 2	XMQD parameter list DDDI parameter list
XM 0908	DFHXMQD	Exc	DDDI Delete_Entry error	1 2	XMQD parameter list DDDI parameter list

Table 139. Transaction manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data
XM 0909	DFHXMQD	Exc	DDDI Replace_Data error	1 XMQD parameter list 2 DDDI parameter list
XM 090A	DFHXMQD	Exc	LMLM Lock error	1 XMQD parameter list 2 LMLM parameter list
XM 090B	DFHXMQD	Exc	LMLM Unlock error	1 XMQD parameter list 2 LMLM parameter list
XM 090C	DFHXMQD	Exc	Update lock error	1 XMQD parameter list 2 DSSR or LMLM parameter list
XM 090D	DFHXMQD	Exc	Update unlock error	1 XMQD parameter list 2 DSSR parameter list
XM 090E	DFHXMQD	XM 2	Trandef on exit	1 Trandef instance 2 Trandef static
XM 090F	DFHXMQD	Exc	Directory name mismatch	1 XMQD parameter list 2 Trandef static
XM 0910	DFHXMQD	Exc	Lock held on exit	1 XMQD parameter list
XM 0A01	DFHXMCL	XM 1	Entry	1 XMCL parameter list
XM 0A02	DFHXMCL	XM 1	Exit	1 XMCL parameter list
XM 0A03	DFHXMCL	Exc	Recovery	1 XMCL parameter list 2 Kernel error data
XM 0A04	DFHXMCL	Exc	Invalid format	1 Invalid parameter list
XM 0A05	DFHXMCL	Exc	Invalid function	1 XMCL parameter list
XM 0A06	DFHXMCL	Exc	DDDI Add_Entry error	1 XMCL parameter list 2 DDDI parameter list
XM 0A07	DFHXMCL	Exc	DDLO Locate error	1 XMCL parameter list 2 DDLO parameter list
XM 0A08	DFHXMCL	Exc	Directory name mismatch	1 XMCL parameter list 2 DDLO parameter list 3 Located tclass entry
XM 0A09	DFHXMCL	Exc	SMGF Getmain error	1 XMCL parameter list 2 SMGF parameter list
XM 0A0A	DFHXMCL	Exc	Update lock error	1 XMCL parameter list 2 DSSR or LMLM parameter list
XM 0A0B	DFHXMCL	Exc	Update unlock error	1 XMCL parameter list 2 DSSR parameter list
XM 0A0C	DFHXMCL	Exc	Internal logic error	1 XMCL parameter list 2 Tclass entry

Table 139. Transaction manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
XM 0A0D	DFHXMCL	Exc	LMLM Lock error	1	XMCL parameter list
				2	LMLM parameter list
XM 0A0E	DFHXMCL	Exc	LMLM Unlock error	1	XMCL parameter list
				2	LMLM parameter list
XM 0A0F	DFHXMCL	Exc	Lock held on exit	1	XMCL parameter list
XM 0A10	DFHXMCL	Exc	Invalid tclass token	1	XMCL parameter list
				2	Tclass entry
XM 0A11	DFHXMCL	Exc	Invalid call to XMCL	1	XMCL parameter list
				2	Tclass entry
XM 0A12	DFHXMCL	Exc	DDDI Delete_Entry error	1	XMCL parameter list
				2	DDDI parameter list
XM 0A13	DFHXMCL	Exc	Invalid call to XMCL	1	XMCL parameter list
				2	Tclass entry
XM 0A14	DFHXMCL	Exc	Internal logic error	1	XMCL parameter list
				2	Tclass entry
XM 0A15	DFHXMCL	Exc	Invalid call to XMCL	1	XMCL parameter list
				2	Tclass entry
XM 0A16	DFHXMCL	Exc	Invalid call to XMCL	1	XMCL parameter list
				2	Tclass entry
XM 0A17	DFHXMCL	Exc	Scheduler error	1	XMCL parameter list
				2	XMQC or DSAT parameter list
XM 0A18	DFHXMCL	Exc	DDBR Start_Browse error	1	XMCL parameter list
				2	DDBR parameter list
XM 0A19	DFHXMCL	Exc	DDBR Get_Next error	1	XMCL parameter list
				2	DDBR parameter list
XM 0A1A	DFHXMCL	Exc	Directory name mismatch	1	XMCL parameter list
				2	DDBR parameter list
				3	Tclass entry
				4	Directory entry name
XM 0A1B	DFHXMCL	Exc	DDBR End_Browse error	1	XMCL parameter list
				2	DDBR parameter list
XM 0A1C	DFHXMCL	Exc	Invalid browse token	1	XMCL parameter list
				2	Browse token
XM 0B01	DFHXMQC	XM 1	Entry	1	XMQC parameter list
XM 0B02	DFHXMQC	XM 1	Exit	1	XMQC parameter list
XM 0B03	DFHXMQC	Exc	Recovery	1	XMQC parameter list
				2	Kernel error data

Table 139. Transaction manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
XM 0B04	DFHXMQC	Exc	Invalid format	1	Invalid parameter list
XM 0B05	DFHXMQC	Exc	Invalid function	1	XMQC parameter list
XM 0B06	DFHXMQC	Exc	Invalid tclass token	1 2	XMQC parameter list Tclass entry
XM 0B07	DFHXMQC	Exc	Invalid call to XMQC	1 2 3	XMQC parameter list Tclass entry Transaction entry
XM 0B08	DFHXMQC	Exc	Invalid call to XMQC	1 2 3	XMQC parameter list Tclass entry Transaction entry
XM 0B09	DFHXMQC	XM 2	Tclass on exit	1	Tclass entry
XM 0C01	DFHXMST	XM 1	Entry	1	STST parameter list
XM 0C02	DFHXMST	XM 1	Exit	1	STST parameter list
XM 0C03	DFHXMST	Exc	Recovery	1 2	STST parameter list Kernel error data
XM 0C04	DFHXMST	Exc	Invalid format	1	Invalid parameter list
XM 0C05	DFHXMST	Exc	Invalid function	1	STST parameter list
XM 0C06	DFHXMST	Exc	Invalid resource	1 2	Module's parameter list STST parameter list
XM 0C07	DFHXMST	Exc	Invalid parameters	1 2	Module's parameter list STST parameter list
XM 0C08	DFHXMST	Exc	LMLM Lock error	1 2	LMLM parameter list STST parameter list
XM 0C09	DFHXMST	Exc	LMLM Unlock error	1 2	LMLM parameter list STST parameter list
XM 0E01	DFHXMCS	XM 1	Entry	1	XMCS parameter list
XM 0E02	DFHXMCS	XM 1	Exit	1	XMCS parameter list
XM 0E03	DFHXMCS	Exc	Recovery	1 2	XMCS parameter list Kernel error data
XM 0E04	DFHXMCS	Exc	Invalid format	1	Invalid parameter list
XM 0E05	DFHXMCS	Exc	Invalid function	1	XMCS parameter list
XM 0E06	DFHXMCS	Exc	Lock error	1 2	XMCS parameter list LMLM parameter list

Table 139. Transaction manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data
XM 0E07	DFHXMCS	Exc	Unlock error	1 XMCS parameter list 2 LMLM parameter list
XM 0E08	DFHXMCS	Exc	Unknown kernel error	1 XMCS parameter list 2 Kernel error data
XM 0E09	DFHXMCS	Exc	No bridge environment	1 XMCS parameter list
XM 0F01	DFHXMBR	XM 1	Entry	1 XMBR parameter list
XM 0F02	DFHXMBR	XM 1	Exit	1 XMBR parameter list
XM 0F03	DFHXMBR	Exc	Recovery	1 XMBR parameter list 2 Kernel error data
XM 0F04	DFHXMBR	Exc	Invalid format	1 Invalid parameter list
XM 0F05	DFHXMBR	Exc	Invalid function	1 XMBR parameter list
XM 0F06	DFHXMBR	XM 2	Call user exit	1 BRXA transaction area 2 BRXA command area
XM 0F07	DFHXMBR	XM 2	Return from user exit	1 BRXA transaction area 2 BRXA command area
XM 0F08	DFHXMBR	Exc	URM failed	1 XMBR parameter list
XM 1001	DFHXMIQ	XM 1	Entry	1 XMIQ parameter list
XM 1002	DFHXMIQ	XM 1	Exit	1 XMIQ parameter list
XM 1003	DFHXMIQ	Exc	Recovery	1 XMIQ parameter list 2 Kernel error data
XM 1004	DFHXMIQ	Exc	Invalid format	1 Invalid parameter list
XM 1005	DFHXMIQ	Exc	Invalid function	1 XMIQ parameter list
XM 1006	DFHXMIQ	Exc	APRM Inquire error	1 XMIQ parameter list 2 APRM parameter list
XM 1007	DFHXMIQ	Exc	DSBR Inquire_Task error	1 XMIQ parameter list 2 DSBR parameter list
XM 1008	DFHXMIQ	Exc	ICXM Inquire_Facility error	1 XMIQ parameter list 2 ICXM parameter list
XM 1009	DFHXMIQ	Exc	TDXM Inquire_Facility error	1 XMIQ parameter list 2 TDXM parameter list
XM 100A	DFHXMIQ	Exc	TFIQ Inquire_Term_Facility error	1 XMIQ parameter list 2 TFIQ parameter list
XM 100B	DFHXMIQ	Exc	TFIQ Inquire_Term_Facility error	1 XMIQ parameter list 2 TFIQ parameter list

Table 139. Transaction manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
XM 100C	DFHXMIQ	Exc	LMLM Lock error	1	XMIQ parameter list
				2	LMLM parameter list
XM 100D	DFHXMIQ	Exc	LMLM Unlock error	1	XMIQ parameter list
				2	LMLM parameter list
XM 100E	DFHXMIQ	Exc	Invalid browse token	1	XMIQ parameter list
XM 100F	DFHXMIQ	Exc	Invalid call to XMIQ	1	XMIQ parameter list
XM 1010	DFHXMIQ	Exc	Internal logic error	1	XMIQ parameter list
XM 1011	DFHXMIQ	Exc	Internal logic error	1	XMIQ parameter list
XM 1012	DFHXMIQ	Exc	Internal logic error	1	XMIQ parameter list
XM 1013	DFHXMIQ	Exc	DSAT Cancel_Task error	1	XMIQ parameter list
				2	DSAT parameter list
XM 1101	DFHXMAT	XM 1	Entry	1	XMAT parameter list
XM 1102	DFHXMAT	XM 1	Exit	1	XMAT parameter list
XM 1103	DFHXMAT	Exc	Recovery	1	XMAT parameter list
				2	Kernel error data
XM 1104	DFHXMAT	Exc	Invalid format	1	Invalid parameter list
XM 1105	DFHXMAT	Exc	Invalid function	1	XMAT parameter list
XM 110C	DFHXMAT	Exc	LMLM Lock error	1	XMAT parameter list
				2	LMLM parameter list
XM 110D	DFHXMAT	Exc	LMLM Unlock error	1	XMAT parameter list
				2	DSBR parameter list
XM 110E	DFHXMAT	Exc	Internal logic error	1	XMAT parameter list
XM 110F	DFHXMAT	Exc	Internal logic error	1	XMAT parameter list
XM 1110	DFHXMAT	Exc	XMLD Locate&Lock_Trandef error	1	XMAT parameter list
				2	XMLD parameter list
XM 1111	DFHXMAT	Exc	Invalid XXMATT return code	1	XMAT parameter list
XM 1112	DFHXMAT	Exc	Internal logic error	1	XMAT parameter list
XM 1114	DFHXMAT	Exc	Scheduler error	1	XMAT parameter list
				2	XMQC or DSAT parameter list
XM 1201	DFHXMER	Exc	Invalid call to XMER	1	XMER parameter list
XM 1202	DFHXMER	Exc	Invalid call to XMER	1	XMER parameter list
XM 1203	DFHXMER	Exc	Invalid call to XMER	1	XMER parameter list

Table 139. Transaction manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data
XM 1204	DFHXMER	XM 1	Entry	1 XMER parameter list
XM 1205	DFHXMER	XM 1	Exit	1 XMER parameter list
XM 1206	DFHXMER	Exc	Invalid call to XMER	1 XMER parameter list
XM 1207	DFHXMER	Exc	Invalid format	1 Invalid parameter list
XM 1208	DFHXMER	Exc	Invalid function	1 XMER parameter list
XM 1209	DFHXMER	Exc	No transaction	1 XMER parameter list
XM 120A	DFHXMER	Exc	Invalid call to XMER	1 XMER parameter list
XM 120B	DFHXMER	Exc	Recovery	1 XMER parameter list 2 Kernel error data
XM 120C	DFHXMER	Exc	PGPG Initial_Link error	1 XMER parameter list 2 PGPG parameter list
XM 1301	DFHXMTA	Exc	APRM Transaction_Init error	1 DSAT parameter list 2 APRM parameter list
XM 1302	DFHXMTA	Exc	APRM Transaction_Term error	1 DSAT parameter list 2 APRM parameter list
XM 1303	DFHXMTA	Exc	APXM Transaction_Init error	1 DSAT parameter list 2 APXM parameter list
XM 1304	DFHXMTA	Exc	APXM Transaction_Term error	1 DSAT parameter list 2 APXM parameter list
XM 1305	DFHXMTA	XM 1	Entry	1 DSAT parameter list
XM 1306	DFHXMTA	XM 1	Exit	1 DSAT parameter list
XM 1307	DFHXMTA	Exc	ICXM Bind_Facility error	1 DSAT parameter list 2 ICXM parameter list
XM 1308	DFHXMTA	Exc	ICXM Release_Facility error	1 DSAT parameter list 2 ICXM parameter list
XM 1309	DFHXMTA	Exc	Invalid format	1 Invalid parameter list
XM 130A	DFHXMTA	Exc	Invalid function	1 DSAT parameter list
XM 130B	DFHXMTA	Exc	LMLM Lock error	1 DSAT parameter list 2 LMLM parameter list
XM 130C	DFHXMTA	Exc	Internal logic error	1 DSAT parameter list
XM 130D	DFHXMTA	Exc	MNMN Transaction_Term error	1 DSAT parameter list 2 LMLM parameter list

Table 139. Transaction manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
XM 130E	DFHXMTA	Exc	PGXM Init_Transaction error	1	DSAT parameter list
				2	PGXM parameter list
XM 130F	XMTA	Exc	PGXM Term_Transaction error	1	DSAT parameter list
				2	PGXM parameter list
XM 1310	DFHXMTA	Exc	Recovery	1	DSAT parameter list
				2	Kernel error data
XM 1311	DFHXMTA	Exc	APXM RMI_Start_Of_Task error	1	DSAT parameter list
				2	APXM parameter list
XM 1312	DFHXMTA	Exc	SMAR Allocate_Tran_Stg error	1	DSAT parameter list
				2	SMAR parameter list
XM 1313	DFHXMTA	Exc	SMAR Release_Tran_Stg error	1	DSAT parameter list
				2	SMAR parameter list
XM 1314	DFHXMTA	Exc	TDXM Bind_Facility error	1	DSAT parameter list
				2	TDXM parameter list
XM 1315	DFHXMTA	Exc	TDXM Release_Facility error	1	DSAT parameter list
				2	TDXM parameter list
XM 1316	DFHXMTA	Exc	TFBF Bind_Facility error	1	DSAT parameter list
				2	TFBF parameter list
XM 1317	DFHXMTA	Exc	TFRF Release_Facility error	1	DSAT parameter list
				2	TFRF parameter list
XM 1318	DFHXMTA	Exc	Internal logic error	1	DSAT parameter list
XM 1319	DFHXMTA	Exc	LMLM Unlock error	1	DSAT parameter list
				2	LMLM parameter list
XM 131A	DFHXMTA	Exc	USXM End_Transaction error	1	DSAT parameter list
				2	USXM parameter list
XM 131B	DFHXMTA	Exc	XSRC Check_CICS_Resource error	r	or1 DSAT parameter list
				2	XSRC parameter list
XM 131C	DFHXMTA	Exc	Scheduler error	1	DSAT parameter list
				2	XMQC or DSAT parameter list
XM 131D	DFHXMTA	Exc	KEXM Transaction_Init error	1	DSAT parameter list
				2	KEXM parameter list
XM 131E	DFHXMTA	XM 2	TXN control block	1	TXN control block
XM 1401	DFHXMxE	XM 1	Entry	1	XMxE parameter list
XM 1402	DFHXMxE	XM 1	Exit	1	XMxE parameter list
XM 1403	DFHXMxE	Exc	Invalid format	1	Invalid parameter list
XM 1404	DFHXMxE	Exc	Invalid function	1	XMxE parameter list

Table 139. Transaction manager domain trace entries (continued)

Point ID	Module	Lvl	Type	Data	
XM 1405	DFHXMXE	Exc	LMLM Lock error	1	XMXE parameter list
				2	LMLM parameter list
XM 1406	DFHXMXE	Exc	Recovery	1	XMXE parameter list
				2	Kernel error data
XM 1407	DFHXMXE	Exc	Internal logic error	1	XMXE parameter list
XM 1408	DFHXMXE	Exc	Internal logic error	1	XMXE parameter list
XM 1409	DFHXMXE	Exc	LMLM Unlock error	1	XMXE parameter list
				2	LMLM parameter list

Security manager trace points

Table 140. Security manager trace entries

Point ID	Module	Lvl	Type	Data	
XS 0101	DFHXSDM	XS 1	Entry	1 DFHXSDM parameter list	
XS 0102	DFHXSDM	XS 1	Exit	1 DFHXSDM parameter list	
XS 0103	DFHXSDM	Exc	Recovery	1	DFHXSDM parameter list
				2	Kernel error data
XS 0104	DFHXSDM	Exc	Invalid format	1 DFHXSDM parameter list	
XS 0105	DFHXSDM	Exc	Invalid function	1 DFHXSDM parameter list	
XS 0106	DFHXSDM	Exc	Lock error	1 DFHXSDM parameter list	
XS 0107	DFHXSDM	Exc	Unlock error	1 DFHXSDM parameter list	
XS 0108	DFHXSDM	Exc	No storage for security domain anchor block	1 DFHXSDM parameter list	
XS 0109	DFHXSDM	Exc	Initialization did not find SIT parms for security domain	1 DFHXSDM parameter list	
XS 010A	DFHXSDM	Exc	Initialization did not find CICS SVC	1 DFHXSDM parameter list	
XS 0201	DFHXSAD	XS 1	Entry	1 DFHXSAD parameter list	
XS 0202	DFHXSAD	XS 1	Exit	1 DFHXSAD parameter list	
XS 0203	DFHXSAD	Exc	Recovery	1 DFHXSAD parameter list	
XS 0204	DFHXSAD	Exc	Invalid format	1 DFHXSAD parameter list	
XS 0205	DFHXSAD	Exc	Invalid function	1 DFHXSAD parameter list	
XS 0206	DFHXSAD	Exc	DFHXSSA failure	1 DFHXSAD parameter list	
XS 0207	DFHXSAD	Exc	DFHXSSB failure	1 DFHXSAD parameter list	
XS 0301	DFHXSIS	XS 1	Entry	1 DFHXSIS parameter list	

Table 140. Security manager trace entries (continued)

Point ID	Module	Lvl	Type	Data	
XS 0302	DFHXSIS	XS 1	Exit	1	DFHXSIS parameter list
XS 0303	DFHXSIS	Exc	Recovery	1 2	DFHXSIS parameter list Kernel error data
XS 0304	DFHXSIS	Exc	Invalid format	1	DFHXSIS parameter list
XS 0305	DFHXSIS	Exc	Invalid function	1	DFHXSIS parameter list
XS 0306	DFHXSIS	Exc	DFHXSSC failure	1	DFHXSIS parameter list
XS 0307	DFHXSIS	Exc	DFHXSSI failure	1	DFHXSIS parameter list
XS 0308	DFHXSIS	Exc	Extract lock error	1	DFHXSIS parameter list
XS 0309	DFHXSIS	Exc	Extract unlock error	1	DFHXSIS parameter list
XS 030A	DFHXSIS	Exc	Rebuild lock error	1	DFHXSIS parameter list
XS 030B	DFHXSIS	Exc	Rebuild unlock error	1	DFHXSIS parameter list
XS 0401	DFHXSXM	XS 1	Entry	1	DFHXSXM parameter list
XS 0402	DFHXSXM	XS 1	Exit	1	DFHXSXM parameter list
XS 0403	DFHXSXM	Exc	Recovery	1 2	DFHXSXM parameter list Kernel error data
XS 0404	DFHXSXM	Exc	Invalid format	1	DFHXSXM parameter list
XS 0405	DFHXSXM	Exc	Invalid function	1	DFHXSXM parameter list
XS 0406	DFHXSXM	Exc	GETMAIN failure	1	DFHXSXM parameter list
XS 0501	DFHXSFL	XS 1	Entry	1	DFHXSFL parameter list
XS 0502	DFHXSFL	XS 1	Exit	1	DFHXSFL parameter list
XS 0503	DFHXSFL	Exc	Recovery	1	DFHXSFL parameter list
XS 0504	DFHXSFL	Exc	Invalid format	1	DFHXSFL parameter list
XS 0505	DFHXSFL	Exc	Invalid function	1	DFHXSFL parameter list
XS 0506	DFHXSFL	Exc	Invalid security token	1	DFHXSFL parameter list
XS 0507	DFHXSFL	Exc	Invalid format passed to DFHXSSA	1	DFHXSFL parameter list
XS 0508	DFHXSFL	Exc	Invalid function passed to DFHXSSA	1	DFHXSFL parameter list
XS 0509	DFHXSFL	Exc	Invalid flattened buffer	1	DFHXSFL parameter list
XS 050A	DFHXSFL	Exc	Disastrous error in DFHXSSA	1	DFHXSFL parameter list
XS 0601	DFHXSPW	XS 1	Entry	1	DFHXSPW parameter list

Table 140. Security manager trace entries (continued)

Point ID	Module	Lvl	Type	Data	
XS 0602	DFHXSPW	XS 1	Exit	1	DFHXSPW parameter list
XS 0603	DFHXSPW	Exc	Recovery	1 2	DFHXSPW parameter list Kernel error data
XS 0604	DFHXSPW	Exc	Invalid format	1	DFHXSPW parameter list
XS 0605	DFHXSPW	Exc	Invalid function	1	DFHXSPW parameter list
XS 0606	DFHXSPW	Exc	CICS SVC failure	1	DFHXSPW parameter list
XS 0607	DFHXSPW	Exc	DFHXSSD failure	1	DFHXSPW parameter list
XS 0701	DFHXSRC	XS 1	Entry	1	DFHXSRC parameter list
XS 0702	DFHXSRC	XS 1	Exit	1	DFHXSRC parameter list
XS 0703	DFHXSRC	Exc	Recovery	1 2	DFHXSRC parameter list Kernel error data
XS 0704	DFHXSRC	Exc	Invalid format	1	DFHXSRC parameter list
XS 0705	DFHXSRC	Exc	Invalid function	1	DFHXSRC parameter list
XS 0706	DFHXSRC	Exc	Lock error	1	DFHXSRC parameter list
XS 0707	DFHXSRC	Exc	Unlock error	1	DFHXSRC parameter list
XS 0708	DFHXSRC	Exc	Dispatcher error	1	DFHXSRC parameter list
XS 0709	DFHXSRC	Exc	Resource check entry	1	DFHXSRC parameter list
XS 070A	DFHXSRC	Exc	Resource check exit	1	DFHXSRC parameter list
XS 070B	DFHXSRC	Exc	Resource check error	1	DFHXSRC parameter list
XS 070D	DFHXSRC	Exc	Invalid access	1	DFHXSRC parameter list
XS 070E	DFHXSRC	Exc	DFHXSSC failure	1	DFHXSRC parameter list
XS 0801	DFHXSLU	XS 1	Entry	1	DFHXSLU parameter list
XS 0802	DFHXSLU	XS 1	Exit	1	DFHXSLU parameter list
XS 0803	DFHXSLU	Exc	Recovery	1 2	DFHXSLU parameter list Kernel error data
XS 0804	DFHXSLU	Exc	Invalid format	1	DFHXSLU parameter list
XS 0805	DFHXSLU	Exc	Invalid function	1	DFHXSLU parameter list
XS 0806	DFHXSLU	Exc	ESTAE error in CICS SVC	1	DFHXSLU parameter list
XS 0807	DFHXSLU	Exc	EXTRACT error in CICS SVC	1	DFHXSLU parameter list

Table 140. Security manager trace entries (continued)

Point ID	Module	Lvl	Type	Data	
XS 0808	DFHXSLU	Exc	CICS SVC error	1	DFHXSLU parameter list
XS 0809	DFHXSLU	Exc	Lock manager failure	1	DFHXSLU parameter list
XS 080A	DFHXSLU	Exc	Lock manager failure	1	DFHXSLU parameter list
XS FE01	DFHXSS	XS 1	Entry	1	DFHXSS parameter list
XS FE02	DFHXSS	XS 1	Exit	1	DFHXSS parameter list
XS FE03	DFHXSS	Exc	Installation data	1	Installation data
XS FE04	DFHXSS	Exc	Exception exit from CICS SVC	1	DFHXSS parameter list
XS FE05	DFHXSS	Exc	Error exit from CICS SVC	1	DFHXSS parameter list

Sending your comments to IBM

If you especially like or dislike anything about this book, please use one of the methods listed below to send your comments to IBM.

Feel free to comment on what you regard as specific errors or omissions, and on the accuracy, organization, subject matter, or completeness of this book.

Please limit your comments to the information in this book and the way in which the information is presented.

To request additional publications, or to ask questions or make comments about the functions of IBM products or systems, you should talk to your IBM representative or to your IBM authorized remarketer.

When you send comments to IBM, you grant IBM a nonexclusive right to use or distribute your comments in any way it believes appropriate, without incurring any obligation to you.

You can send your comments to IBM in any of the following ways:

- By mail, to this address:

Information Development Department (MP095)
IBM United Kingdom Laboratories
Hursley Park
WINCHESTER,
Hampshire
United Kingdom

- By fax:
 - From outside the U.K., after your international access code use 44-1962-870229
 - From within the U.K., use 01962-870229
- Electronically, use the appropriate network ID:
 - IBM Mail Exchange: GBIBM2Q9 at IBMMAIL
 - IBMLink™ : HURSLEY(IDRCF)
 - Internet: idrcf@hursley.ibm.com

Whichever you use, ensure that you include:

- The publication number and title
- The topic to which your comment applies
- Your name and address/telephone number/fax number/network ID.



Program Number: 5655-147



Printed in the United States of America
on recycled paper containing 10%
recovered post-consumer fiber.

SC34-5446-33



Spine information:



CICS TS for OS/390

CICS Trace Entries

Release 3